

Australia's Top Selling Electronics Magazine

Electronics Australia

NOVEMBER
1986


Aust* \$2.95
NZ \$3.95 incl. GST

Challenger

WHAT REALLY HAPPENED

**Special
Feature:**
What's New
In Display
Technology

Build These Projects:
150W Linear
Amplifier
High-Quality
Microphone



How to beat the high cost of cheap meters.



You get what you pay for.
So get the Fluke 70 Series.

You'll get more meter for your money, whether you choose the affordable 73, the feature-packed 75 or the deluxe 77.

All of them will give you years of performance, long after cheaper meters have pegged their fishhook needles for the last time.

That's because they're built to last, inside and out. So they're tough to break. They don't blow fuses all the time. You don't even have to replace batteries as often.

And they're backed by a 3-year warranty. Not the usual 1-year.

Of course, you may only care that the world-champion 70 Series combines digital and analog displays with more automatic features, greater accuracy and easier operation than any other meters in their class.

You may not care that they have a lower overall cost of ownership than all the other "bargain" meters out there.

But just in case, now you know.

FROM THE WORLD LEADER
IN DIGITAL MULTIMETERS.

FLUKE®



FLUKE 73

Analog/digital display
Volts, ohms, 10A, diode test
Autorange
0.7% basic dc accuracy
2000+ hour battery life
3-year warranty



FLUKE 75

Analog/digital display
Volts, ohms, 10A, mA, diode test
Audible continuity
Autorange/range hold
0.5% basic dc accuracy
2000+ hour battery life
3-year warranty



FLUKE 77

Analog/digital display
Volts, ohms, 10A, mA, diode test
Audible continuity
"Touch Hold" function
Autorange/range hold
0.3% basic dc accuracy
2000+ hour battery life
3-year warranty
Multipurpose holster

ELMEASCO

Instruments Pty. Ltd.

N.S.W. 15 McDonald St, Mortlake. Tel: (02) 736 2888
VIC. 12 Maroondah Hwy, Ringwood. Tel: (03) 879 2322
QLD. 192 Evans Rd, Salisbury. Tel: (07) 875 1444
S.A. 241 Churchill Rd, Prospect. Tel: (08) 344 9000
W.A. 46-48 Kings Pk Rd, West Perth. Tel: (09) 481 1500

Talk to your local distributor about Fluke

• A.C.T. Actec Pty Ltd (062) 80 6576 • George Brown 80 4355 • N.S.W. Ames Agency 699 4524 • George Brown (02) 519 5855 Newcastle 69 6399 • Bryan Catt Industries 526 2222 • D.G.E. Systems (049) 69 1625 • David Reid 267 1385 • W.F. Dixon (049) 61 5628 • Macelec (042) 29 1455 Ebon 707 2111 • Selectro Parts 708 3244 • Geoff Wood 427 1676 • N. TERRITORY Thew & McCann (089) 84 4999 • QUEENSLAND L.E. Boughen 369 1277 • Colourview Wholesale 275 3188 • Fred Hoe & Sons 277 4311 • Nortek (077) 79 8600 • St Lucia Electronics 52 7466 • Electro Parts (Qld) 394 2422 • S. AUSTRALIA Protronics 212 3111 • Trio Electrix 212 6235 • A.W.M. Wholesale • TASMANIA George Harvey (003) 31 6533, (002) 34 2233 • VICTORIA A.W.M. Electrical Wholesale • Radio Parts 329 7888 • G.B. Telespares 328 3371 • Browntronic 419 3986 • R.K.B. Agency 82 7704 • A.J. Ferguson 347 6688 • SIRS Sales (052) 78 1251 • Mektronics 690 4593 • W. AUSTRALIA Atkins Carlisle 321 0101 • Dobbie Instruments 276 8888 • Cairns Instrument Services 325 3144 • Willis Trading 470 1118

THIS MONTH'S COVER

This month, we bring you a special report on what happened to the Challenger space shuttle (see page 36).

Painting by John Berkey,
© Discover Magazine
4/86, Time Inc.

Electronics Australia

Volume 48, No.11

November
1986

Features

- 10 HIGH CURRENT AMPLIFIERS *Do we need them?*
- 36 SPECIAL REPORT: THE SPACE SHUTTLE TRAGEDY *What really happened*
- 80 THE LATEST IN DISPLAY TECHNOLOGY *We survey the field*
- 92 DIGITAL SIGNAL PROCESSING PT.2 *Another nail in the analog coffin*
- 104 EPSON'S EX-800 DOT MATRIX PRINTER *For graphics and colour*

Entertainment Electronics

- 74 AN INTRODUCTION TO HI-FI PT.9 *More on digital technology*
- 122 COMPACT DISC REVIEWS *Tchaikovsky, Beethoven, Stravinsky*

Projects and Technical

- 26 BUILD THE MICROPHONE *Pick it up and it turns on*
- 34 CIRCUIT & DESIGN IDEAS *TV-derived frequency standard*
- 44 THE SERVICEMAN *A wink is as good as a nod*
- 50 HIGH-POWER HF LINEAR AMPLIFIER *Build it from a kit*
- 63 A LOW-COST DUMMY LOAD *Put six light bulbs in a box*
- 64 INFRARED REMOTE CONTROL PREAMPLIFIER PT.2 *Construction details*
- 70 SOLAR-POWERED BILGE PUMP *Don't let the boat sink*
- 90 DX RECEPTION *Increase the stations you receive*

News and Comment


- 4 LETTERS TO THE EDITOR *Fake grass and static electricity*
- 5 EDITORIAL *Should radar detectors be banned?*
- 6 NEWS HIGHLIGHTS *Aussie-made robots for industry*
- 124 INFORMATION CENTRE *Answers to reader queries*

Departments

- 110 NEW PRODUCTS
- 120 50 AND 25 YEARS AGO
- 121 EA CROSSWORD PUZZLE

- 128 MARKETPLACE
- 126 NOTES AND ERRATA

Do-it-yourself microphone




This high-quality microphone can be built for half the cost of comparable commercial units and boasts several novel features. Details page 26.

What's coming

Don't miss next month's issue. In addition to a big feature on marine electronics, you'll find articles describing a low-distortion audio oscillator, a digital audio storage device and a UHF keyswitch for use in burglar alarms.

Solar-powered bilge pump



Don't let the yacht sink. This new automatic bilge pump is low in cost and easy to build. Best of all, it's powered by the Sun.

MANAGING EDITOR

Leo Simpson, B.Bus. (NSWIT)

EDITOR

Greg Swain, B.Sc. (Hons. Sydney)

EDITORIAL CONSULTANTNeville Williams, F.I.R.E.E.
(Aust.) (VK2XV)**TECHNICAL STAFF**John Clarke, B.E. (Elec. NSWIT)
Colin Dawson
Louise Upton**GRAPHIC DESIGNER**

Brian Jones

ART PRODUCTION

Alana Horak

PRODUCTION

Mark Moes

SECRETARIAL

Carmel Triulcio

ADVERTISING PRODUCTIONBrett Baker
Vikki Patching (Vic)**ADVERTISING MANAGER**

Selwyn Sayers

PUBLISHER

Michael Hannan

HEAD OFFICEThe Federal Publishing Company
Proprietary Limited, 180 Bourke Road,
Alexandria, NSW 2015. Phone:
(02) 693-6666. Fax Number:
(02) 693-2842. Telex: AA74488. Postal
Address: PO Box 227, Waterloo 2017.
Representative: Norman Palmer.**INTERSTATE****ADVERTISING OFFICES****Melbourne:** 23rd Floor, 150 Lonsdale
Street, Melbourne, Vic 3000. Phone:
(03) 662 1222.
Representative: John Oliver, B.A. (Hons.
Essex).**Adelaide:** John Fairfax & Sons Ltd, 101
Weymouth Street, Adelaide 5000. Phone:
(08) 212 1212.
Representative: Dane Hanson.**Brisbane:** 26 Chermiside Street, Newstead,
Old 4006. Phone: (07) 854 1119.
Representative: Bernie Summers.**Perth:** John Fairfax & Sons, 454 Murray
St, Perth, WA 6000. (09) 481-3171.
Representative: Jim Wells.**New Zealand:** 3rd Floor, Communications
House, 12 Heather Street, Parnell,
Auckland, New Zealand, PO Box 37-291.
Telex: NZ63122. Telephone: 79 6648.
Representative: John Easton.**ELECTRONICS AUSTRALIA** is
published monthly by the Federal
Publishing Company Pty Limited, under
licence from Double Bay Newspapers Pty
Limited, General Newspapers Pty Limited
and Suburban Publications Pty Limited.Typeset and printed by Hannanprint,
Bourke Road, Alexandria, NSW, for The
Federal Publishing Company Pty Ltd.Distributed by Magazine Promotions Pty
Ltd, Sydney.Registered by Australia Post —
publication No. NBP0240. ISSN
0313-0150.©Double Bay Newspapers Pty Limited,
General Newspapers Pty Limited and
Suburban Publications Pty Limited
(trading as "Eastern Suburbs
Newspapers"), 1985.*Recommended and maximum Australian
retail price only.

Letters to the editor

Fake grass and shocked gardeners

Neville Williams' comments about the hazards of static charges (Forum, June 1986) reminded me of an experience in the UK about 20 years ago.

At the time I worked at the Engineering Centre of a big conglomerate electronics company, founded and built up by a then venerable entrepreneur, who had just received a knighthood in recognition of his efforts. Let us preserve this gentleman's anonymity by giving him the invented name of Sir Les North.

For his retirement, Sir Les had purchased a very plush unit in one of the best areas of North London. TV outlets were required in most rooms, so it was

natural to call in his own engineering staff to design and install the system.

A small mast carrying the antenna was bolted to a convenient steel hand-rail which surrounded the unit's flat roof and a mains powered amplifier gave the signals a boost before distribution. The system was tested and to the relief of all concerned, Sir Les indicated his approval.

About a week later the cataclysm occurred. We had a phone call from a very icy Lady N to let us know our antenna system must be faulty as it had given the gardener a nasty electric shock. Good jobs were not easy to get at that time and I must admit we all panicked a bit before unanimously electing one of our colleagues, who had

Three reasons for not purchasing kits

In response to your article on projects only being available in kit form from suppliers, I would like to voice my agreement with your contributors.

You mentioned in "Forum" that many overseas magazines are having enormous problems with falling circulations, and I can't help but wonder if this is due to the trend of publishing kit projects. I have dropped my subscription to two overseas magazines because of this.

As your magazine is Australian, I am at least able to purchase kits locally. However, I have three objections to having to do this:

Firstly, I agree with the letters published. The cost of many of the kits is such that I cannot afford to purchase the project in one hit, although I would be able to purchase the parts spread over a period.

Secondly, like many people, I have purchased standard parts in bulk packs over the years and fail to see why I should have to buy these parts a second time.

Finally, maybe it is just my bad luck, but I have had some lousy experiences with kits. This has ranged from incorrect or missing parts to defective components, and makes me wonder if some

firms are using seconds to make up kits.

I would also agree with I.G. of Victoria that a proper kit should have decent instructions. I have no objection to photostats of your article, but I do object when the photostat quality is very poor and they do not include the "Notes and Errata" that has been published since the original article.

Over the years your magazine has published some excellent projects, but in recent times the value of these for me has dropped due to this kit problem. I would be more than happy to see the supply situation revert to being able to purchase individual parts, or projects not being published if components are not available individually.

G. Parrant,
Castle Hill, NSW.

Kit suppliers losing sales

I am writing in response to your request for "... a wad of letters that we can wave under the noses of kit suppliers."

I wholeheartedly agree with the comments in your Forum of July 1986. I am also in complete agreement with J.M. (Seven Hills, NSW) regarding the construction of the larger (both in terms of parts and money) kits.

a superb bedside manner, to go and investigate.

He found that following our antenna work on the flat roof, a very nice little garden had been installed, complete with flowers in pots, trees in tubs and a lush green plastic lawn. The gardener had been sweeping the lawn with a traditional birch broom and after some vigorous exertion had decided to take a rest by leaning on the handrail. His extended hand never quite reached the rail however, as whilst it was still a short distance off, a juicy spark jumped the gap, giving him a hefty zap, a small burn and some instant rejuvenation.

A 50kV electrostatic voltmeter was brought in and we found that a few strokes with the broom on the lawn would generate enough static to put it off the end of its scale. All was explained to Lady N, we kept our jobs and the plastic lawn went back to a company which mines and manufactures in Minnesota for antistatic treatment.

T. N. Ayscough,
Beacon Hill, NSW.

I would dearly love to build the Tele-text Decoder, and both the Playmaster amplifier and tuner, but could not even begin to consider the financial outlay in one hit. This means that there is a considerable (my own definition) amount of money that a kit supplier will not be getting from me.

Granted that a supplier has to outlay the cost of both purchasing and storing the components if he was to sell them separately, but at least he would eventually get a return for these components, rather than nothing at all if he was to market them as a complete kit which a lot of people could not possibly afford.

This is really a two-edged sword. By not supplying the components of a kit as separate entities, not only are the suppliers losing money from prospective sales, but they also risk driving the electronics enthusiast, particularly the beginner, into another hobby.

In fact, you could almost call it a three-edged weapon if you consider that an electronics enthusiast who is driven to another hobby may even stop reading *Electronics Australia*. And if enough people do that . . .!

I shudder to think of the consequences!

D. Cunningham,
Geelong West, Vic.



Editorial Viewpoint

Should radar detectors be banned?

The recent announcement by the New South Wales Minister for Police, Mr Paciullo, that radar detectors and jammers would henceforth be banned has caused consternation amongst motorists and manufacturers alike. Should this action have been taken?

From a strictly legalistic point of view, you could argue that anyone who fits a radar detector or jammer to their vehicle is intent on breaking the law. Further, those people who go to great lengths to conceal their detectors or jammers are compounding the offence.

That point of view would be unlikely to be disputed if the rules of the road were uniformly and fairly enforced. But in the State of New South Wales the rules of the road are not fairly and uniformly enforced and on past history, are never likely to be.

The fact is that on many roads in Metropolitan areas motorists consistently exceed the speed limits, often by 20km/h or more. In peak periods, any motorist who did not keep up with the traffic would be a severe hazard. So everyone exceeds the speed limit. Ergo, the speed limits are a joke. That is point number one.

Point number two is that where radar traps are set up by the police they invariably are at places where it is safe to travel at speed; ie, on a wide freeway or on a straight downhill stretch of road where the speed of the vehicle tends to naturally increase. Radar traps are almost never set up on the suburban back-streets where some lunatics drive cars at speeds which really are a hazard to life and limb.

So the average motorist can be forgiven for being cynical about the views of officialdom on radar detectors. Radar traps have been no more than revenue-earners in the past. The police will have to use them much more fairly in the future if the radar detector ban is to mean anything.

Perhaps the police have correctly realised that past radar speed measuring systems could not reliably be used on heavily trafficked arterial roads or on narrow winding suburban streets. New radar systems are claimed to be effective in pinpointing particular vehicles in traffic so that obvious offenders can be singled out.

But unless the police use radar sensibly and fairly to weed out the dangerous motorists they should not use it at all. Until the police demonstrate that they will enforce the speed regulations fairly, motorists have some justification for feeling that the radar detector ban is just official posturing.

LEO SIMPSON

News Highlights

IBM expands operations at Wangaratta

Underlining its commitment to its Australian operations, IBM has begun manufacturing PC planar boards at its Wangaratta, Victoria, plant and has announced plans to manufacture telecommunication products.


The planar boards are used in IBM Personal Computers, PC XT's and PC AT's which are also assembled at Wangaratta. The decision to manufacture the boards for these computers represents a further \$3.7 million investment by IBM in local manufacturing.

During 1985, the Wangaratta plant produced over 30,000 IBM personal computers. These are used to supply the Australian market and are also exported to New Zealand and to South East Asia.

The decision by IBM to manufacture telecommunications products in Australia is in line with a Telecom agreement requiring telecommunications suppliers to include local content in their products.

Two communications controllers, the CBX-11 and VSCBX, will be produced at the plant and the first models are expected to be rolling off the production line later this year. These controllers are the computer-based section of a ROLM business communications system.

The ROLM CBX-11 8000 system supports up to 840 voice and/or data lines and/or associated Telecom trunks. The VSCBX is designed for smaller systems with 16 to 140 users.



Dishing out Aussat!

Want fast access to Aussat from anywhere in Australia? An Australian company, Network Technologies Pty Ltd, has developed a mobile 3.7-metre dish that can be towed to the desired location and set up within a few minutes.

The company says it can transport the new dishes to any site in Australia accessible by vehicle, be it a city hotel, a country office or a private home. The 3.7 metre antenna works in conjunction with any of the video transmission standards of the various broadcasters in Australia, and is ideal for satellite videoconferencing.

Australia in strong position with optical fibres

Australian industry could be in a strong position to capitalise on the growth opportunities being offered by the \$2 billion undersea fibre optic communications cable planned for the Pacific basin, according to the Australian Electronics Industry Association.

According to Mr Bill Page-Hanify, the President of AEIA, "the basic technologies for submarine optical fibre

cable systems are already in place in this country and Australian companies are now hard at work developing these technologies even further."

The Pacific network project will involve laying the world's largest underwater fibre optic network and will link Australia with other countries on the Pacific rim — New Zealand, Japan and North America. Tenders for the first

phase, Tasman 2, linking Australia and New Zealand, will be called later this year and already a number of leading overseas communications companies have expressed interest.

The need for local technology, manpower and skill to become involved in the project is also very much a part of OTC's strategy. Five Australian companies have already been contracted to carry out developmental work on the project. These companies are AWA, STC, Austral Standard Cables, Olex Cable and Optical Fibre Research.


Asteroids named for Challenger astronauts

Seven asteroids have been named after the members of the Challenger Space Shuttle crew who perished on January 28. The asteroids were all discovered from Lowell Observatory by astronomers Dr Edward Bowell and Mr Norman Thomas, and are named for Francis R. Scobee, Michael J. Smith, Christa McAuliffe, Gregory B. Jarvis, Ronald E. McNair, Ellison S. Onizuka, and Judith A. Resnik.

Asteroids are small rocky bodies left over from the time of formation of the solar system some 4.6 billion years ago and which failed to coalesce into a major planet. Most orbit the Sun between Mars and Jupiter.

A small number of asteroids have orbits that cross the orbits of the planets, such as Mars or Earth, but there is very little danger of collision as their orbits are inclined to those of the planets. The largest asteroid is about 850 km across, but those being discovered these days are usually only a few miles across.



The seven Challenger asteroids were discovered between 1980 and 1984, during the course of a survey funded by NASA's Planetary Astronomy Program.



Aussie-made robots for industry

Four specialised single arm machine loading robots, designed and constructed by Machine Dynamics in Victoria, have joined the workforce of one of Australia's leading toolmaking companies, Sutton's Tools of Thomastown, Victoria.

The Machine Dynamics' robots can be set up for a new line in about three minutes and are fed by a tube conveyer system. The robots have dramatically increased productivity at Sutton's, thus ensuring that the company's products remain competitive.



SEALED LEAD-ACID STATIONARY BATTERY

UXL SERIES

10 YEARS LIFE

Conventional vented type stationary batteries require water replenishment due to water decomposition during charge. The "UXL Type" battery introduced herein incorporates further the maintenance-free design which eliminates such troublesome maintenances as electrolyte level check, water topping-up, specific gravity measurement and equalizing charge, making the battery truly maintenance free. This is a sealed type stationary lead-acid battery of long life, high reliability and high performance, which has been developed based on the technologies of the small size sealed batteries.


UXL Saves up to
Half on Space

Ex. UXL220-2

AMTEX
ELECTRONICS

A DIVISION OF TLE ELECTRICAL PTY LIMITED
(Incorporated in New South Wales)

TELEPHONE (02) 728-2121, 727-5444 36 LISBON STREET
TELEX AA27922 ATTN AMTEX FAIRFIELD, NSW 2165
FACSIMILE (02) 728-2837 AUSTRALIA



GENERAL SPECIFICATIONS

Battery Model	Nominal Voltage (V)	10HR Nominal Capacity (AH)	Dimensions (mm)			Overall Height	Approx. Weight (kgs)
			Length	Width	Height		
UXL33-12	12	30	235	128	190	217	16
UXL44-12	12	40	299	128	190	217	20
UXL55-12	12	50	363	128	190	217	24
UXL66-6	6	60	217	128	190	217	15.5
UXL88-6	6	80	281.2	128	190	217	19.5
UXL110-6	6	100	345.4	128	190	217	23.5
UXL220-2	2	200	170	106	330	362	16
UXL330-2	2	300	170	150	330	362	24
UXL550-2	2	500	241	171	330	362	39

News Highlights

Hetero-junction bipolar transistor

Toshiba researchers have developed a hetero-junction bipolar transistor (HBT) with a switching time of 35 picoseconds.

The transistor uses compound semiconductor materials of aluminium gallium arsenide (AlGaAs) and gallium arsenide (GaAs), according to Toshiba. It is suitable for use in central processing units (CPUs) for next generation supercomputers, and in transceivers for optical communications.

In conventional transistors, the emitter and the base are formed respectively by using different masks, which means extra space is needed to ensure enough isolation between each electrode. This, in turn, increases the overall size of the transistor.

Toshiba's new transistor overcomes this problem by shrinking the gap between the emitter and base electrodes using a process called the "self-alignment" method. In this method, the emitter is formed first and a thin layer

Holiday camps

Each Christmas, vacation camps for high school students interested in electronics, computing and photography are held at Mount Victoria, NSW.

Known as Camp Technology, they are an interdenominational Christian organisation project.

Participants can construct electronic projects, try their hand at computer programming, operate amateur radio station VK2BCT, shoot, develop and print photographs, and learn video production.

Two camps are planned for this summer — one for boys years 7 to 9 (in 1986) and the other for boys and girls years 10 to 12. Dates are the 6th to 13th and 14th to 21st January, 1987 and the cost is \$95.


For further information contact Scripture Union, 120 Chalmers Street, Surry Hills 2010. Telephone (02) 690 1777.

Subscription winner

The winner of the Sony Digital Audio/Video system, from an EA subscription is:

G. Somerville, Punchbowl, NSW

The competition appeared in EA during May, June and July.



of silicon dioxide is then introduced as an insulator to completely cover the emitter region. The base electrodes (in the case of an IC) are then formed directly next to this SiO₂ layer.

As a result of the new technology, the

width of the emitter is halved from four to two microns and the gap between the emitter and base electrodes is down from one micron to 0.25 microns. This, in turn, significantly reduces the size of the transistor.

The colder the clock the better

Researchers at the University of British Columbia in Vancouver, Canada, have made a step towards developing the most accurate clock in the world.

At present the hydrogen maser operating at room temperature has the most accurate atomic clock — it loses about one second every 30 million years. The new Canadian design is a liquid-hydrogen maser that works at just 0.5°K — or -272.5°C in everyday language. It is said to be 10 times more accurate than existing masers, losing just one second every 300 million years, and in theory could be made 100 times more accurate again.

The greater accuracy results from the

stability achieved at the very low temperature at which the clock functions. Up until the Canadian work, Teflon has always been used to coat the inner wall of a hydrogen maser and at very low temperatures this becomes useless. The hydrogen atoms can no longer bounce off the Teflon walls, the frequency of the microwaves that this creates defining the basic unit of time.


The Canadians have overcome this problem by using walls coated with a thin layer of liquid helium.

Possible applications for the new clock include helping to track deep space probes, and detecting gravity waves.

WANT A NEW CHALLENGE? EXPLORE THE UNIVERSE THROUGH A MEADE TELESCOPE

Discovers planets, moons, suns, nebulae, starclusters, comets, galaxies, supernovae, and if you like take a photograph of what you see!


MEADE SCHMIDT CASSEGRAIN SERIES ▶ So technically advanced they're warranted for life. Available with three different apertures - 100mm, 200mm and 254mm. These telescopes are the ultimate combination of performance and portability. Laser tested, hand matched optics with Quartz electronic drive systems make these the most sought after telescopes in the world today. Prices start at \$1630 for model 2045 (100mm apertures f10, f/L1000mm) complete with new quartz electronic drive system.



◀ **MEADE NEWTONIAN REFLECTOR SERIES** Meade reflector combine optical performance second to none with rock solid motorised mountings so necessary for successful viewing and photography. This series starts with Model 618F (150mm aperture f8, f/L 1200mm) complete with motor drive for \$1967. They have excellent deep space photographic capability while at the same time permitting superb planetary and lunar resolution. Sizes range up to the marine 312mm. Research series which is already used in many schools and college observatories around the world.

MEADE GIANT DEEPSPACE SERIES ▶ This series provides "Big Aperture" at an affordable price. The DS16 (406mm aperture f4.5) is still the biggest commercially available telescope "off the shelf" in Australia. Motor drive is included but all other accessories are left to your choice. DS16 owners all rave about unbelievable deep space viewing. DS16 \$4794.

Also available is the smaller DS10 \$2510.



◀ MEADE SPOTTING SCOPES, TELEPHOTO LENSES

Compact, light and powerful. If you have a camera, a casual interest in astronomy and enjoy nature then owning one of these instruments will be lots of fun. Observe wildlife, enjoy the view from your home, see the craters on the moon or the rings around Saturn. Attach your camera in a matter of seconds and you have a 1000mm telephoto lens. By inserting various eye pieces visual and photographic power of up to 200 times can be obtained. Models start at 97D (90mm aperture f11 f/L 1000mm) \$895



CONTACT YOUR NEAREST STATE DEALER . . .

- **PRECISION OPTICS AUSTRALIA**
138 Railway Pde. Leederville 6007. 008-99 9832
- **YORK OPTICAL**
7th Floor, 270 Flinders St. Melbourne 3000. 03-654 3938
- **BINOCULAR & TELESCOPE SHOP**
Shop F9, The Hunter Connection
310 George St. Sydney 2000. 02-235 3190
- **AUDIO OPTICS**
2 Central Stn. Cnr. Edward and Turbot St. Brisbane. QLD. 4000. 07-221 6398.
- **CAPITAL COLOUR**
43 Northbourne Ave. Canberra City 2601. 062-47 4030

Authorized



Dealer

NAME:

ADDRESS:

MEADE INSTRUMENT CORPORATION U.S.A.

THE LEADERS IN QUALITY TELESCOPE DESIGN
SEND FOR FURTHER DETAILS:-

High current amplifiers

Do we need them?

How important is the current-sourcing ability of amplifiers? Does it need to be specified separately, in addition to power ratings or is it a new marketing ploy dreamed up by the amplifier manufacturers?

by LEO SIMPSON

One of the parameters we read more of in amplifier advertisements these days is current capability. According to some audiophiles and designers, current capability is one of the most important characteristics of an amplifier. Hence, typical amplifiers today, as well as having power ratings into 8-ohm and 4-ohm loads, also have a figure quoted for instantaneous current capability.

For example, a current model (sorry about that) from the USA has a rated power of 70 watts per channel into 8 ohms and an instantaneous current capability of 50 amps. This is said to make it suitable for use with low impedance speakers.

Well, just how important is current sourcing ability? And just how much current should an amplifier be able to deliver, for a given power rating. A few moments' work with a calculator will quickly show the answers to these questions.

For example, let us consider the recent Playmaster Sixty/Sixty amplifier which had a nominal rating of sixty watts per channel. As the spec panel published in the May 1986 issue of EA showed, the amplifier was able to deliver about 74 watts into an 8-ohm load with one channel driven and about 88 watts into a 4-ohm load, again with one channel driven. This means, that on a steady-state basis, the amplifier could deliver about 3 amps into an 8-ohm

load and about 4.7 amps into a 4-ohm load.

That does not sound like very much when compared to the figure of 50 amps quoted above, does it? But the figure was quoted as an instantaneous capability, so perhaps we should use the dynamic power figures as a guide. For the Playmaster Sixty/Sixty, these figures were 105 watts into 8 ohms and 153 watts into 4 ohms, both for a single channel being driven.

These figures are obtained using the IHF procedure which involves using a pulsed sinewave signal with a pulse duration of 20 milliseconds and a pulse repetition rate of 2Hz; ie, two pulses per second.

Again, you can calculate the equivalent current figures at about 3.6 amps for the 8-ohm load condition and about 6.2 amps for the 4-ohm load condition. These are RMS figures (root mean square) which are the effective or DC equivalent values for an AC sinewave signal. To get the instantaneous figure, we have to multiply the RMS value by 1.414. This gives instantaneous values of just over 5 amps for the 8-ohm condition and 8.75 amps for the 4-ohm condition.

And while we did not quote the performance of the Playmaster amplifier into 2-ohm loads, it will deliver a peak current of about 11.5 amps. This corresponds to an IHF power output of

about 130 watts. Even if we take the highest possible figure of 11.5 amps, it is still paltry compared with the 50 amps figure for the American designed amplifier. So why did they need it?

The note about suitability for low impedance speakers gives the clue. These high current requirements are based on the fact that loudspeakers do not present a simple resistive load to the amplifier terminals. Instead, they are a complex impedance. On some speaker systems, the actual impedance value at a particular frequency may plummet to below two ohms.

This can happen if the loudspeaker system is transformer-coupled, as in the case of an electrostatic system, or has a badly designed crossover network. With these sorts of loudspeakers, the amplifier must be able to deliver very high currents if it is to avoid distorting the signal waveform, for a given volume setting. This will not be a problem for the amplifier at low volume settings but at high settings, where the amplifier is close to clipping, it can cause a serious reduction in power output.

So would it be possible to produce an amplifier with a nominal rating of 70 watts per channel into 8-ohm loads, able to deliver an instantaneous current of 50 amps? Quite simply, yes. But there are a number of big ifs.

Rugged output stage required

First, the output stage must have sufficiently highly rated power transistors to be able to deliver 50 amps peak. To do it safely, the transistors would probably have to be capable of delivering up to 100 amps on a pulsed basis. Surprising though it may seem, such a requirement is not too difficult these days. The designer could even obtain such an output stage capacity with single transistors

(or Darlington) without the need to parallel transistors.

It is a lot more difficult to obtain such a high capacity with power Mosfets though, since they are transconductance devices, ie, they require so many volts into the gate to obtain so many amps of drain current. (Typically, at least three Mosfets would have to be paralleled to obtain a 50 amp capacity, giving an output stage of six transistors.)

Of course, as well as having high current capacity, the output transistors would require adequate voltage and power ratings. A typical device might have a collector rating 120 volts and a power rating of 300 watts. At the same time, it would need very good "second breakdown" characteristics if it was to be able to safely handle reactive loads. Be under no illusions, all loudspeakers are highly reactive somewhere within the audible spectrum.

And it is the reactive load condition which rejects most high current transistors as being unsuitable for high power amplifier design. "Second breakdown" is the bugbear. This is the process by which bipolar transistors develop hot spots at the higher voltage and high current conditions. The higher voltages cause current crowding which then causes the hot spots. It is the hot spots on the chip surface which can cause failure of the device.

Because of the second breakdown effect, all bipolar transistors have to be derated to some extent at the higher voltages. And paradoxically, the tendency is for the very high current devices to be derated the most.

So even if you could obtain sufficient current capacity (ie, 50A) with a pair of complementary output transistors, the chances are that a viable output stage would require at least four output transistors if it was to be a reliable design. To be a really conservative design, capable of handling the most difficult, low value, reactive loads, you might need as many as six output devices in each channel.


How to calculate maximum amplifier output current

To calculate the maximum instantaneous output current of an amplifier, you need to know how much power it can deliver from one channel into the specified minimum load. For example, if it will deliver 100 watts on a short term basis into a 4Ω load, we calculate the RMS voltage across the load as:


$$V_L = P \times R_L = \sqrt{100 \times 4} = 20 \text{ volts}$$

We then calculate the peak voltage by multiplying V_L by 1.414 to obtain 28.28 volts. We then calculate the peak current:

$$I_p = \frac{V_p}{R} = \frac{28.28}{4} = 7.07 \text{ amps}$$



A rugged amplifier if ever there was one, this Perreux PM3150 is capable of delivering 10 amps on a short term continuous basis.




This massive Perreux 5150B amplifier was rated at 800 watts per channel and had a total power supply capacitance of 80,000μF.

As well as making sure that the output transistors have sufficient current sourcing ability, the designer must make sure that the driver stages can also deliver enough current to the output transistors, without any danger of damage to the devices if the loads are short circuit.

Power supply

Having taken care of the amplifier output stage, the next requirement is for sufficient current capacity from the power supply. Since the current only has to be delivered for a very short time, less than 50 milliseconds, say, it is possible to build in this order of current capacity merely by specifying very large filter capacitors in the power supply. So, while the Playmaster Sixty-Sixty used a value of 5000μF for the total filter capacitance for both the positive and negative supply rails, the value probably may have to be increased to around 15,000μF or more, depending on the quality of the capacitors.

At the same time, all the conductors within the amplifier would have to be of sufficient cross-section to ensure that resistive losses did not become excessive



The power amplifier of the Playmaster Sixty-Sixty. This has very rugged power transistors in the output stage but these would need to be paralleled up to increase the output current capability.

High current amplifiers

at these high output currents. At 50 amps, a resistance of only 0.1 ohms between the commoned-emitters of the power transistors and the loudspeaker would mean a loss of 5V. That would not be easily achieved.

It goes without saying that a 70 watt/channel amplifier with a 50 amp instantaneous current capability would cost a lot more than an equivalently rated amplifier such as the Playmaster Sixty-Sixty. And having paid for such an

amplifier, what are the circumstances in which it would be required to deliver its all?

The conditions under which 50 amps peak would be required are simply these: (a) the amplifier is driven to deliver its full output voltage swing. For an output capability of 70 watts into an 8-ohm load, this amounts to 23.7 volts RMS or 33.5 volts peak; and (b) the loudspeaker impedance for the signal being delivered by the amplifier must be


0.67Ω or less.

The first condition could occur quite often, particularly if the volume setting is high. The second condition would be very rare, if it is ever likely to happen at all.

Having come this far though, let us look at a more-likely worst case condition. Consider for example, if we have two sets of loudspeakers connected, both of which have a nominal impedance of 4Ω. For a typical loudspeaker system, you can expect that the minimum impedance will be at least two-thirds of the nominal impedance, or 2.68Ω. With two such loudspeakers in parallel, the load impedance is therefore 1.34Ω which is getting pretty low. For the same maximum output condition as listed above, the amplifier will now have to deliver 25 amps.

Frankly, the likelihood of having two sets of loudspeakers which have a minimum impedance of 1.34Ω (to obtain a parallel combination of 0.67Ω) is stretching credibility. And the likelihood of having any loudspeaker with a nominal impedance of 8Ω with such a minimum impedance is zero. Such a loudspeaker would cause so many problems with ordinary amplifiers that it would quickly be withdrawn from sale. No self-respecting loudspeaker designer would produce such a system.

So what conclusion are we left with?



This is the B&W DM110 which has an impedance characteristic typical of many well-designed loudspeakers. Notice that it does not dip below 5 ohms at any point in the audible frequency range.

We have to consider that it is possible to have a situation where a user may have two sets of loudspeakers which, when connected in parallel, will have a minimum impedance of 1.34Ω . And therefore, if the amplifier is not to clip prematurely when driven to full output, it needs to be able to deliver 25 amps peak.

More realistically, a typical user may have two pairs of 8-ohm loudspeakers (or one pair of 4-ohm loudspeakers) which can be expected to have a minimum impedance, when connected in parallel, of no less than 2.5Ω . The amplifier now has to deliver 13.4 amps peak.

Or if we use the example cited at the start of this article, where the minimum loudspeaker impedance is 2Ω , the maximum peak output current, for a peak output voltage of 33.5V, is 16.75 amps. Note that this current capability is only required when the amplifier is being driven flat out. The consequence of using a less well endowed amplifier (as far as current capability is concerned) is that difficult loudspeakers would not be able to be driven quite as hard before severe distortion became apparent.

So you could argue that a 70 watt per channel amplifier with an output current of say, 20 amps, is desirable, for the best quality sound, and you would be right, as far as technical considerations are concerned. But to argue that a 70 watt per channel amplifier needs a 50 amp instantaneous current capability is ridiculous.

So where does that leave the Playmaster Sixty-Sixty which we have used as the basis for comparison in this article? Plainly, it is not intended to drive very low impedance loads although it will safely drive a 2-ohm load for short periods. If driven hard into such a low value load, it will blow the fuses. In other words, it is designed to survive being connected to low impedance loads and short circuits, not to drive them.

With typical 8-ohm loudspeakers though, whose impedance values fall into the expected range, it would be extremely hard to better the performance of the Playmaster Sixty-Sixty, at any price.

It would be possible to beef up the output stages of the Playmaster amplifier, but that would require the addition of more output transistors, larger heat-sinks and bigger filter capacitors in the power supply. It would add up to a considerably more costly amplifier with no audible improvement to the performance, except on "difficult" loudspeakers.


LIKE TO GET AN AMATEUR RADIO CERTIFICATE? IT'S MUCH EASIER WITH PROFESSIONAL HELP.




If something's worth doing, it's worth doing well. So don't waste your valuable spare time finding your own way through the Amateur Radio maze. Ask Stott's instead. We have top professional instructors, who'll make sure your time is well spent on your way to an operator's certificate. You'll have individual attention, working at your own speed, in the comfort of your own home. Any queries will be answered personally, and promptly.

So don't delay. Mail the coupon for full details.
Over and out.

Stotts



CORRESPONDENCE COLLEGE



The name to trust in correspondence education.

Please send me free, and without obligation, full details of the following courses:

_____ (PLEASE PRINT)

MR MRS MISS _____ AGE _____

ADDRESS _____

_____ POSTCODE _____

Stott's undertake that no sales counsellor will visit you

The Stott's range of courses in Amateur Radio is:

- Novice Amateur Operator's Certificate of Proficiency.
- Amateur Operator's Certificate of Proficiency.
- Amateur Operator's Limited Certificate of Proficiency.
- Radio for Amateurs.

Melbourne, 140 Flinders Street, 3000. Tel. 63 6212

Sydney, 383 George Street, 2000. Tel. 29 2445

Brisbane, 65 Mary Street, 4000. Tel. 221 3972

Adelaide, 226 Pulteney Street, 5000. Tel. 223 3700

W. Perth, 25 Richardson Street, 6005. Tel. 322 5481

Hobart, 150 Collins Street, 7000. Tel. 34 2399


New Zealand, Box No 30 990, Lower Hutt. Tel. 676 592

ALA/ST5285/EA786

FM & WIRELESS ELECTRET MICROPHONE

No more cords! This incredibly clear microphone has a built-in FM transmitter that can be picked up by any FM receiver. The signal can be amplified for PA etc. Range is up to 30 metres. Frequency response is wide and flat. Also usable as a conventional microphone with the supplied cable (saves power). Includes windshield. Cat. AM-4070


ONLY \$32.50



PIONEER 12" GUITAR 422

Our most popular guitar speaker ever - still!! About 1/2 the price of most others of the same quality. 100 watts RMS; frequency response 80 - 6kHz; resonance 80Hz; SPL 100dB/1/2 metre; huge 4,002 gram magnet! Cat. CG-2380

ONLY \$89.50



10 AMP DIGITAL MULTIMETER

WITH TRANSISTOR TEST FACILITY
Superb features and specifications. Includes 0.5" high digits, single function range switch, long battery life etc. Size 170(h) x 90(w) x 35(d)mm. SEE THE JAYCAR 1986 CATALOGUE FOR MORE DETAILS.
Cat. QM-1530

ONLY \$89.95

10 AMP DIGITAL MULTIMETER + TRANSISTOR TESTER &

The big daddy - this superb unit features 0.5" high digits, CMOS logic, auto polarity etc.
Cat. QM-1540

**A BARGAIN AT
\$129.00**

4 1/2 DIGIT ACCURACY

**3 1/2 DIGIT PRICE!!
AND DIGITAL HOLD TO BOOT!**

Just think a multimeter with 0.15% accuracy on most ohms ranges. 0.05% on DC volts and 0.5% MAX on DC current! STAGGERING. Plus, continuity buzzer and LED symbol, auto polarity, auto zero, vinyl case and DATA HOLD as well!! NOT TO MENTION the transistor and diode tester!!


SPECIFICATIONS:

• 0 - 1kV DC 0.05% • 0 - 750V AC 0.8% (max) • 10A DC 0.5% (max) • 0 - 10A AC 1% (max) • 20M ohm 0.5% (max)

FEATURES:


• All ranges fully protected • Auto zero • 0.5" high LCD • Diode test (1mA fixed current) • LCD display feature • Functional annunciators • Extremely accurate • 20 page instruction manual included.
Cat. QM-1550

ONLY \$159.00



SILLY PRICES ON SEMIS

6821 \$2.00 ZZ-8061
6809E \$4.00 ZZ-8055



BARGAIN ELECTRO


We have a quantity of distress purchased electros to clear. Quality RELSIC European brand with axial leads.

680µF 63V

Cat. RE-5909

**ONLY 50¢ each
10 up 40¢ each**

NEW



TELEMAIL PHONE NUMBERS




**(008) 022 888
TOLL FREE
FOR ORDERS ONLY
(02) 747 1888
HOTLINE**

TEFLON COAX RG 178 - 50 OHM

Sensational Price Deal!

Due to a huge scoop purchase we can pass this normally expensive coax on to you at an ENORMOUS saving! Normally around \$4/metre, this month you can save up to 62% - AND A FURTHER 50% ON THESE PRICES - WOW!!! Buy a pack of 4 metres for \$10 (i.e. \$2.50/metre)
Cat. WB-2302
Buy a pack of 10 metres for \$20 (i.e. \$2/metre)
Buy a pack of 50 metres for \$75 (i.e. \$1.50/metre)



**SAVE UP TO
62%**

**TAKE A
FURTHER 50% OFF
THESE PRICES**

ARLEC SUPERTOOL

You've probably heard about this great product. Now you can get one from Jaycar. It drills, grinds, sands, engraves, cuts, polishes, mills and erasers. Two year warranty. 240V operation. 10,000 rpm.
Cat. TH-1900

ONLY \$59.95

NEW

ATTACHMENTS:

Wire Brushes:	TH-1902	\$15.95
Drill Bits:	TH-1904	\$ 7.95
Grinding Bits:	TH-1906	\$11.50
Diamond Engraving Bit:	TH-1908	\$15.95
Cutting Discs:	TH-1910	\$11.95
Engraving Bits:	TH-1912	\$ 9.95

**BUY NOW FOR
CHRISTMAS**



PENLIGHT NiCads

Don't keep wasting money buying throwaway batteries - step up to rechargeable NiCads.

SUPERB "ROCKET" BRAND AA PENLIGHT 450mAh

Cat. SB-2452


**\$2.95 each
SPECIAL 4 for \$10**



MAGGY LAMP

DESK MOUNTED
LAMP/MAGNIFIER
Cat. SL-2700

**ONLY
\$185.00**



IT'S HERE ULTRASONIC AIR HUMIDIFIER

CREATE YOUR OWN CLIMATE
This unit re-humidifies air automatically by an ultrasonic mist evaporator. You can adjust the humidity in your environment in the range 30-90% R.H.!! It has a large water container (4.15 litres) and switches off automatically when dry.
Cat. YH-5510

ONLY \$149.00



SEC APPROVED FUSE HOLDERS


Quality M205 panel mount fuseholders made by Schurtor of Switzerland. To import these today they would cost a small fortune. We have a quantity to sacrifice at:

**ONLY \$1.25 ea
10 up \$1.00 each**
Cat. SZ-2028



**NEW
EXIT**

[illegible]



AM/FM STEREO TUNER SYNTHESISED

Ref: EA December '85 - Feb '86
Cat. KA-1635
\$499.00

REMOTE CONTROL

Ref: EA April 1986
Cat. KA-1636
\$89.50



ETI5000 PRE-AMP "BLUE PRINT"

Cat. KE-4202
\$339.00




ETI5000 POWER AMP "BLACK MONOLITH"

Cat. KE-4200
\$399.00




PLAYMASTER SERIES 200 HI FI MOSFET AMP

Ref: EA Jan - March 1985
100 WATTS RMS (CHANNEL)
Cat. KA-1500
\$499.00




ETI5000 1/3rd OCTAVE EQUALISER

Cat. KE-4204
\$209.00




"ULTRA FIDELITY" PREAMPLIFIER

Ref: AEM Oct - Dec 1985
Cat. KM-3030
\$289.00



2010 10 BAND STEREO EQUALISER

Cat. KJ-6535
\$159.00



2801 1/3rd OCTAVE EQUALISER

• 240V operated • Cannon sockets • Pro
quality
Cat. KJ-6531
\$225.00



MUSICOLOR IV

Ref: EA August 1981
Cat. KA-1010
\$109.90



ELECTRIC FENCE CONTROLLER

Ref: EA December 1985
Cat. KA-1660
\$45.00



30 VOLT - 1A BENCH POWER SUPPLY


Ref: EA January 1985
Cat. KA-1574
\$74.50



JAYCAR No.1 FOR NEW PRODUCTS

The 'LISTENING POST'

Ref: AEM July 1986
Cat. KM-3015
\$37.50



AEM4600 DUAL SPEED MODEM

Ref: AEM December 1985
Cat. KM-3040
\$169.00



VIFA SPEAKERS

EA 60/60 2 WAY


SPEAKERS & CROSSOVERS
Cat. CS-2471

\$369.00

SPEAKERS, CROSSOVERS &
CABINETS

Cat. CS-2470

\$449.00




NEW

AEM 6102 - 2 WAY COMPLETE

\$799 pr


Commercial units cost about \$1,800
Cat. CS-2461



AEM 6103 3 WAY COMPLETE

\$1199 pr

NOW WITH NEW IMPROVED CROS-
SOVERS



JAYCAR No.1 FOR SPEAKERS



**BUY NOW FOR CHRISTMAS
FROM JAYCAR**



FORUM

Conducted by Neville Williams

Video recorders: new battle looms

If you thought that all was now sweetness and light in the world of video cassette recorders, there may be good reason to think again. JVC and Sony, the principals in the long-running VHS/Beta battle, seem poised for another confrontation, this time involving the new 8mm video format.

The original battle of the formats, involving VHS, Beta and V2000, is now history and scarcely warrants recounting at length.

It is sufficient to recall that Philips demonstrated the potential of domestic VCRs in the early '70s, beginning with their N1500 (1972) and culminating in the technically impressive V2000 (1979).

To the rapidly expanding Japanese electronics industry, domestic VCRs presented a golden opportunity and, by-passing the European initiative, they set about developing their own designs, primarily for the Japanese and American (NTSC) markets but with the PAL and SECAM areas in longer view.

As it turned out, two dominant Japanese formats emerged: Beta, sponsored by Sony, and VHS sponsored by JVC (Japanese Victor Company) — basically similar but mechanically incompatible. Together, they invaded world markets although, at the same time, exploiting every trick in the book to assert their own individual superiority.

It became an emotive, as well as a technical and marketing issue but, leaving aside the "leap-frogging" that marked successive refinements, there was really very little to choose between the two formats in terms of the end result.

VHS finally prevailed, mainly because of majority support by big-name manufacturers, headed up by JVC's powerful parent company Matsushita (National, Panasonic, Technics).

Locally, the emotive aspect of the contest was highlighted by a segment in Leo Simpson's editorial in the July '84 issue entitled: "VHS has won the marketing battle against Beta."

It raised a chorus of protest from Beta distributors and owners, who variously saw the editorial as blind prejudice, part of a deliberate conspiracy or a potentially self-fulfilling prophecy.

In fact, it was an objective observation based on analysis of video cassette sales and rentals, on covert moves towards VHS being made by major Beta manufacturers, and a not-so-covert run-out of Beta models — evidence discounted by correspondents in subsequent issues.

But the editorial was spot-on. Within less than twelve months, Sony was the sole remaining manufacturer of Beta format VCRs while, elsewhere, the Philips group had also transferred their support from V2000 to VHS.

According to JVC, as at June 30 last, VHS had chalked up around 100 million sales worldwide — roughly four times the figure for all other domestic formats combined.

A new "standard"?

At about the time when the format furore was at its peak, it became known that video manufacturers had reached agreement on a new video format using 8mm wide tape (compared with the existing 12.7mm standard) accommodated in a cassette broadly similar in size to an audio compact cassette.

The parameters were debated and determined with a particular eye to the needs of video photographers. Apart from being a technically appropriate figure, 8mm offered the marketing advantage of an automatic association with 8mm home movie film.

The new format incorporated desirable technology from the established sys-

tems and, having been endorsed by no less than 127 major companies worldwide, provided some assurance that those who chose to enter the compact video field would not end up with another set of conflicting standards.

Commonsense, it seemed, had prevailed, although Kodak did cause some concern by announcing that they planned to launch the new format forthwith — without awaiting the convenience of the electronics industry.

But perhaps it didn't matter; Kodak was primarily a photographic supplier faced with an inevitable changeover from photographic film to magnetic tape. Why complain if they took upon themselves the task of pioneering the new format?

By and large, the video industry settled back to take advantage of the continuing prosperity of VHS, now becoming available with hifi FM-stereo sound, enhanced picture quality and compatible VHS-C for video photographers who wanted something smaller than was possible with a full 3- to 4-hour cassette.

The original VHS suppliers were content and so, apparently, were companies like Toshiba, Sanyo, NEC and Philips, who had joined them.

Sony's counter move . . .

But that left Sony out on a limb, the sole major supplier of Beta format equipment and certainly not about to abandon it in favour of VHS. Their most obvious course was to move straight into the new 8mm format, with the idea of establishing a trend which other manufacturers would ultimately have to follow.

This they have done, releasing a range of NTSC and PAL camcorders, domestic decks and a PCM processor — backed by what has been termed "extremely aggressive promotion". While Sony has undertaken to support Beta for as long as is necessary, the clear implication is that they are looking to the future (8mm) not dwelling on the past (12.7mm).

And JVC's reaction:

JVC's response has been to accuse Sony of grossly over-selling 8mm around the world as the format for the future. While JVC admits to being one of the 127 signatories, the basic purpose of the agreement, they say, was to "enable compatibility among 8mm products that may appear in the future." I quote:

"Agreement on the standard itself in no way constitutes a move by the industry or the participating companies to

standardise the world market with the 8mm video format."

By its nature, they say, the 8mm format is "isolated to the portable camera recorder market". It "offers no significant advantage over VHS".

"8mm is definitely not the next generation format", according to JVC, because it makes no adequate provision for recording video technologies of the future — a limitation that could even see it as "inhibiting the progress of the industry as a whole".

Pros and cons

As against some of the speculative reporting on the intriguingly compact 8mm format, comparisons drawn by JVC are sobering. The comparative figures are for the PAL format, applicable in Australia:

Max. Playing Time: VHS offers up to 3 hours on thick tape, 4 hours on thin tape, and 6 or 8 hours at half speed. For 8mm the figures are 1 to 1.5 and 2 to 3 hours respectively, with 8mm heavily dependent on half-speed thin tape for timer recording and movies.

Tape Dimensions: 12.7mm wide: 19 or 15.6 μ thick. 8mm wide: 13 or 10 μ thick. The durability of 8mm thin tape for repetitive use (rental movies) is questionable.

Track Pitch: VHS, normal speed, 49 μ , half speed 24 μ . For 8mm, 34.4 μ and 17 μ respectively.

Picture Quality: For general domestic use, the comparison would be between VHS at normal speed, and 8mm at half speed. For a given quality of tape and electronics, VHS will always have the advantage.

Stationary Head Sound: A normal mono or stereo provision with VHS. Optional with 8mm but of dubious value, especially at half speed.

FM Sound: VHS uses depth multiplex stereo, avoiding prejudice to picture quality. 8mm uses frequency multiplex (FM), limited to mono to minimise inevitable interaction with the video signal.

PCM Audio: Although impressive enough at demonstrations, the 8-bit 31.5kHz system specified for 8mm video is actually the lowest specified PCM system in the quality audio field and unlikely to be accepted in lieu of newly developed digital audio tape equipment.

Video cameras

As for video camera equipment, JVC appear to be well satisfied with their own VHS-C option — "a little brother" to the full-scale VHS cassette, which can be used in any VHS deck with the

help of an adaptor. While somewhat thicker than an 8mm video cassette, it has much the same profile dimensions and, in a camcorder, involves a video drum and associated mechanism of similar size.

One possible objection is a recording time limit of 30 minutes at standard speed, although JVC suggest that, in practical video photographic situations, 30-minute cassettes often prove to be more manageable.

It might well be argued that all this is what one would expect JVC to say but it does make sense and it does fit the current pattern in the industry.

Some major companies, including Matsushita, are manufacturing 8mm equipment to order for photographic companies, but there is no haste, and presumably no present inclination, to promote the format in the home video market under their own name.

Looking ahead

There is substance also in JVC's claim that a VCR format for the future should make provision for the next generation of video equipment — in short, for HDTV (high definition television).

The most recent issue of "Monitor" (from the Institution of Radio & Electronics Engineers, Australia) reports on

discussion of HDTV leading up to and at the 16th Plenary Assembly of the CCIR at Dubrovnik (Yugoslavia) during May last.

Clearly, technology is moving towards a standard of video presentation comparable to that offered by modern 35mm photographic film. The technology is available and the problem is not a matter of "if" but of when and by what strategy.

The NTSC block is keen to move quickly; the PAL block is more cautious and anxious to ensure that the course adopted will culminate not only in HDTV, as such, but in common, worldwide video standards.

How long it will take HDTV to reach consumer level is not clear but the possibility exists that it could happen in about the same time frame as would be needed to change over to 8mm. On this reckoning, the supposed "format of the future" would reach maturity in the nick of time to become obsolete!

From what I can gather, the purveyors of VHS VCRs are presently confident that 8mm won't make it to the top; that there won't be another format war — not over 8mm anyway.

But, if there isn't, Sony will have to be content for a while with a couple of minority formats — Beta & Son (?) —

What do you really do for a living?

A few weeks ago I had to write a short piece for a careers booklet on what electronic engineers did. It covered the usual activities of designing, evaluating, inventing and advising, but afterwards I realised that it was written more in hope than in truth.

There have not, to my knowledge, been any recent studies here on how electronic engineers practice their profession and how this relates to their education. (Perhaps such a study may be worth conducting by our Institution.)

But from the reasonable range of people I know in the profession only a few work according to the traditional model of engineers.

While technological change has had visible effects on the lives of clerical and production workers, the less visible changes in engineering have had as large an effect behind the scenes.

Designers who once worked at the discrete component level either do not design at all now or

work at a higher level in which functions are provided by integrated circuits.

Engineers whose responsibility once was to ensure that the components of a system would work together electrically have now become software engineers.

Computers, it sometimes seems, are the new breadboards, the medium that provides the greatest opportunity for creativity and challenge. Our older readers will see many parallels between the role which computers play now — as a source of challenge — and radio systems of 20 or 30 years ago.

I am not sure therefore that we have as clear an idea today of what our profession really means as when our Royal Charter was written. Accordingly, there is a responsibility for the IREE to help define this role and provide a focus for it.

Please give this some thought. You may be asked for your ideas.

Graham Rigby

"WHICH RADIO DO I NEED?"


...THE ANSWER IS IN THE PALM OF YOUR HAND

Whatever task you have to do the ICOM IC-40 is the one that can handle it.

It's ideally suited for farming, transport, sports, bushwalking & boating.

Whatever the communication problem you need to solve this is the radio that's being proven every day in a million different uses.

Contact your local dealer for a demonstration of the most advanced CRS portable available in Australia.



Please post to:

ICOM AUSTRALIA PTY. LTD.
7 DUKE STREET WINDSOR 3182.
VICTORIA.

Name _____

Address _____

City _____

Postcode _____

or phone ICOM on (03) 51 2284



The World System

IC0014

FORUM — continued

plus, of course, a hefty slice of the professional audio and video markets!

Which brings us up to the question as to what will take over from the now universal VHS format, plus embellishments? What will be the true "next generation" VCR? One with thin-film heads and vertical particle recording?

Or will it be a VDR — a video disc recorder, with VMBs — video memory banks — further down the track?

Sorry, but my crystal ball has misted over!

What do engineers do?

Hard on the heels of his controversial "VHS has won the battle" editorial, Leo Simpson did some further stirring in the August '84 issue with a leader entitled "So you think you're an engineer, mate!"

Perhaps he was in a stirring mood at the time but he certainly was exasperated after a series of job interviews with engineer applicants who proved to have a remarkably scant practical knowledge of everyday electronic devices.

Leo just couldn't understand how people who had studied and worked at electronics for years could have generated so little interest in, and remained so aloof from the intriguing technology around them.

In the ensuing debate, some agreed with his sentiments but others tended to the view that a hands-on interest in electronic devices was for technicians and hobbyists. Engineers had to concentrate on broad principles, so that they could make intelligent decisions and issue perceptive directions in any engineering task in which they might become involved.

It sounds most impressive but what does it really mean, and to what extent does it exempt engineers from the need for a broad awareness of the practicalities of their profession?

I was reminded of all this when I came across the "President's Column" in the same June/July issue of the IREE "Monitor", as mentioned earlier. In it, Professor Graham Rigby asks his fellow engineer-members the question: "What do you really do for a living?" If you haven't read it already, I suggest you read it now.

I noted, in particular, his remarks about the migration of engineers from component and system design to the manipulation of IC functions and computer software. How very true.

When I first became involved in the

IREE, the executive and the monthly meetings alike were dominated by engineers responsible for the design and production of a wide range of components and equipment, along with others connected with communications, radio (later TV) broadcasting, audio and recording, film production and so on.

They were a deeply committed, hands-on group, who managed not only to communicate to their peers what they were about, but to enthuse them as well. Rarely did anyone need to ask what they did for a living.

But times have changed and so has the Australian technological environment.

On a relative basis, our involvement in component design and manufacture is but a shadow of what it once was. We may shrug it off as an economic necessity of transitory importance but it has removed a complete strata — maybe two generations — of intensely "practical" engineers, plus the people and the facilities under their direction.

Much the same is true of those involved in designing and manufacturing radio and TV receivers and transmitters, along with sundry other items including (remember?) test equipment.

By today's standards, the formal qualifications of yesterday's "practical" engineers might appear modest but, in a continuing situation, qualifications would assuredly have expanded to match the technology. Increasingly, that kind of expertise has moved "off-shore" — certainly from Australia but also, in varying degrees, from other "western" countries.

What we have left is a distorted technological structure: a top and a bottom but no middle:

- Academically orientated engineers, largely isolated from the challenge, the subtleties and the skills of producing bits, pieces and things; and
- Technicians, servicemen and trainees, looking up a ladder from which the middle rungs have been removed.

I would hope that the President's column will motivate IREE members to think his question through and to respond with information which can be sorted and tabulated.

Analysis of such information might well show that, if modern-day electronics engineers are indeed academically over-biased in attitude and occupation, the present, distorted structure of the industry may be at least partly to blame.

EA



JACK O'DONNEL
DIRECTOR

ALTRONICS
COMPONENTS

It's Now Official Altronics Prices Save You Up To 30% Off Our Nearest Competitor

The reproductive purity of these speakers simply amazed us. The secret, of course is the DANISH VIFA Drivers. VIFA drivers are used in many top selling imported systems such as Bang & Olufsen, Rogers, Mission, Jamo, DCM Timewindow etc.

**Build These Fantastic New
Playmaster HiFi Loudspeakers** **\$449**
See Electronics Australia Sept '86 full kit K 5090

If your budget won't run to the \$600 to \$800 needed for a fully imported pair of equivalent speakers, these are the ones to go for.

Some extracts from Electronics Australia Magazine — Each woofer has a foam roll surround and a doped paper cone with an effective (piston) diameter of about 155mm. The Tweeters "the Tweeters are exotic little beasts" (Editor EA Magazine) each is a 19mm soft dome unit with a ferro-fluid damped voice coil for high power handling and a very smooth frequency response. Its resonant frequency is around 1.7kHz.

Power Handling (60 watts plus RMS!) In an average sized lounge room and driven by the Playmaster Sixty-Sixty or an equivalently rated amplifier, these speakers will deliver enough sound volume to satisfy the most power crazed enthusiast.

Construction Only the most basic of tools are required to assemble these loudspeakers. Even if you are a rank amateur at carpentry you will have no problems putting them together. You don't need special clamps or jigs and all timberwork has been precisely machined. You do have to be able to use a soldering iron though, to connect the loudspeakers to the crossover network.




**Why Risk Unnecessary
Heart Attack?**

Heart disease strikes down many people in their early 40's (or even 30's). The tragedy remains that had such victims been alerted, remedial medical, physical and dietary action could have been prescribed to avoid illness and in many cases restore full bodily health. X 3055

**Blood Pressure and Heart
Rate Monitor**

- Features:**
- Non-Microphone Measurement System
 - LCD Readout
 - Blood Pressure Monitor
 - Pulse Rate Monitor



Why Pay \$150?

X 3055 **Only \$110**


\$189 Next Month



**Desk Mounted
Lamp Magnifier**
\$169

If you have trouble with fine PCB work or component identification but still want both hands free, this is for you. We thoroughly recommend this quality Australian made product.

TECHNICAL INFORMATION Illumination: 22W Fluorescent **Weight:** 8.16kg **Lateral Extension:** 254mm **Vertical Extension:** 254mm **Fixing:** Heavy table base (grey & ivory) with two chrome plated flexible arms. Cat A 0980



**100 Amp
Jumper Leads**
Superb Quality

A 3011 **\$17.50**

Up to Incredible 1KM Range

**Professional
Megaphone PA**
**20 Watts Max. Power with
In-Built Whistle**

A new product for 1986, our A 1990 Megaphone PA is quite simply one of the finest around irrespective of price. This is an extremely sturdy unit with a quality in-built 20 watt (max) low distortion amplifier. Another **Secret** of the fine performance is the incorporation of a noise cancelling microphone - the result is a surprising level of gain available without feedback even when used indoors in relatively confined spaces.

Why Pay \$150 or more?



A 1990

\$109.50

**'Sixty-Sixty'
Integrated Amplifier Kit**
(EA May, June, July '86)

Features:

- 60 watts per channel into 8 ohm loads • Very low noise on all inputs - better than CD performance • Very low distortion • Excellent headroom • Tape monitor loop • Tone controls with centre detent and defeat switch • Mono/stereo switch • Toroidal power transformer • Easy-to-build construction • Very little wiring.

Performance Specification

Power Output — 8 ohms 62W **Distortion** - Less than .0% at 1kHz. **Frequency Response** - Phono Inputs - RIAA/IEC equalisation within + - 0.5db from 40Hz to 20kHz. **Line Level Inputs** — -0.5db at 20Hz and -1db at 20kHz **Input Sensitivity** - Phono 1kHz -4.3mV • Line Level - 270mV. **Hum & Noise** - Phono - 89db • High Level Inputs - 103db. **Tone Control** - Bass - + -12db at 50Hz **Treble** - + -12db at 10kHz. **Damping factor** - At 1kHz and 30Hz - greater than 80 **Stability** — Unconditional.



K 5060 **\$299**

"This New Amplifier offers a standard of performance far ahead of anything we have previously published and ahead of most commercial Integrated Stereo Amplifiers".

"It is half to one third of the cost of an imported Amplifier with equivalent power output and performance". Says Leo Simpson Managing Editor Electronics Australia Magazine.

Beginner constructors can Build this Amplifier Kit — It looks terrific and will last you a lifetime.

Save \$200 or more on comparable performance commercial units

Altronics Deliver Next Day With Jetservice Phone Your Order Now

Sensational Labtech

Full 12 Months Warranty

Dual Trace 20MHz CRO With Component Tester Under \$800

Definitely Australia's Best Value in Quality Oscilloscope Test Equipment — Just Look at the Facilities

The Inbuilt Component Tester Alone is Over \$300 Value. **Why Pay \$1000?**

DESCRIPTION:

This model is a dual-trace 20MHz Oscilloscope using high brightness CRT. The vertical amplifiers have high sensitivity of 5mV/Div and the frequency characteristic response with the smooth roll off exceeding 20MHz. The highest triggering sweep speed is 0.2 usec/Div. For component test, special circuit is designed, with which a single component or components in or out of actual circuit designed, with which a single component or components in or out of actual circuit board can be easily tested, requiring no power to drive the circuit. The display shows fault of components, size of a component value, characteristics of component, and half-dead components under dynamic test.

FEATURES:

- Component Tester • Wide bandwidth & high sensitivity • Very low power consumption • High sensitivity X-Y mode • Z axis (intensity modulation) • Front panel electrical trace Rotator • Regulated power supply circuit for Accuracy

ALTRONICS FAMOUS SATISFACTION GUARANTEE

We are delighted with our new Labtech Q 0155 Oscilloscope and Component Tester and naturally we are confident you will be too — However, if for any reason you are less than 100% satisfied with your new Labtech CRO you may of course return it to us (in original condition with all instructions, packaging etc.) within 14 days for a full refund less transport costs.

Q 0155 Value **\$799**

Highly Recommended For:
Service Workbench, Design Laboratory, Manufacturers, Universities and the dedicated Enthusiast.

Labtech Test Equipment for Life

Just Arrived - The Superb Micron Soldering Station

No more changing tips to obtain correct working temperature — simply select between 320 and 440 deg.C with the flick of a switch.

Excellent for
Production Work

Excellent for
Delicate PCB Work

Quality
Iron Clad Tips

At last! A true temperature controlled temperature selectable soldering station with all the parameters one would expect from a professional soldering iron without the high price slug some of our competitors ask.

Temperature Selectable to 5 settings 320, 350, 380, 410 and 440 degrees C.

Temperature Readout via led barograph instantly visible.

Temperature Stability to within 4% of selected mean temperature at normal ambient temperatures i.e. 20-25 deg. C.

Heat Capacity Full 48 watts of heat energy available for heavy duty work.

Earthed Tip/Element Tip is earthed as a protective measure for work on microprocessor circuitry etc.

Low Voltage Element 24V element for added safety especially with CMOS and microprocessor soldering in situ.

Silicon rubber iron lead used providing a comfortable, flexible connection to station and durability against accidental burn damage.


Chrome Plated Iron Plated Tips Regardless of the excellence of the station and iron element, it is absolutely imperative the iron tips be of a high standard, easily cleaned and long life. The Micron tips are "State of the Art" chrome plated, iron clad ultra long life, very resistive to over heating, clean easily and what's more are **very reasonably priced!**

* * * * *



Replacement Tips All \$3.95

Micro Chisel	1mm Tip	T 2423
Mini Chisel	1.5mm Tip	T 2424
Standard Chisel	3mm Tip	T 2425

Free Bonus set of 3 tips (\$12 value) this month



TYPICAL COMPONENT TEST STATUS PATTERNS



Probe Sets

1:1 or 10:1 Attenuation

Q 0175

\$47.50



T 2440

\$99.50

Save Up To 30% With These Prices

NATIONAL SEMICONDUCTOR DATA MANUALS

Sold Separately or by the set

Million Diode Sellout! From 1.5¢ each


Altronics have just purchased around 1 Million (yes million) factory fresh, premium quality IN914/IN4148 diodes. These became surplus to Fairchild Australia as the factory supplied bulk, loose pack diodes instead of the tape/reel diodes ordered. So unless you are a manufacturer with automatic component insertion equipment, these fine quality diodes represent the diode bargain of all time!! Cat. Z 0101

1-99	3¢ ea
100-499	2.5¢ ea
500 plus	1.5¢ ea

RACKS

Rack Frames for the Home Stereo System
Rack Cabinets for Equipment Manufacturers

New For '86



Supplied in Flat Pack Format
Easily Assembled in Minutes

The all new Altronics racking system is available in 2 formats.

1. Racking Frame Only Fantastic for neatly housing your home HiFi system. Looks fine as is with your various sound system modules bolted in place, however, should the little woman disagree, then it is dead simple to obtain some low cost timber panels from your local cabinet shop to fill the side and top recesses. Edging of the timber is not required due to the 15mm recesses.

2. Complete Equipment Cabinet with the simple addition of the panel sets you now have a series of professional equipment cabinets of appearance and ruggedness second to none - and just look at the savings!


Assembly Each Frame System is supplied complete with 12 Custom extruded Natural Anodised Aluminium sections, 8 ABS corner connector pieces, 6 clip in MM6 captive nuts and 6 M6 mounting screws. The sections and corner pieces simply push-fit together. A rubber or wooden mallet is recommended to fit together the self aligning pieces. Further strength can be obtained by pop rivetting the various overlapping extruded sections if desired, although we hardly feel this is necessary.

Side and Top Panels Tough powder coat medium grey gives a pleasing contrast with the natural anodised frame. The resultant product is extremely professional in appearance and well and truly strong enough for the heaviest of electronic equipment.

H 0365 Rack 6 unit (370mm)	89.50	H 0382 Panel set for H 0380	149.00
H 0367 Panel Set for H 0365	49.00	H 0385 Rack screw M6 PK 12 Nat.	2.95
H 0370 Rack 18 unit (907mm)	119.50	H 0386 Rack " M6 PK 100 Nat.	19.95
H 0372 Panel Set for H 0370	89.00	H 0390 Rack " M6 PK 12 black	2.95
H 0375 Rack 30 unit (1450mm)	149.50	H 0391 Rack " M6 PK 100 black	19.95
H 0377 Panel Set for H 0375	129.00	H 0395 captive nuts M6 PK 12	3.95
H 0380 Rack 38 unit (180mm)	189.50	H 0396 captive nuts M6 PK 100	25.00

Rack Panel Screws

Low. Low prices on Nickel Plated and Black finish Rack Screws
Dome Head, M6 Thread, 25mm overall length.



INTERFACE

This data book provides complete specifications for a variety of transmission line drivers/receivers, peripheral power drivers and level translators/buffers. Product selection guides list applications information and operating features. Memory, dynamic memory, micro-processor, data communications and disk support products are also covered in the data book. The interface appendix section contains cross reference guides, the programmable logic section describes the technology, design and gives application suggestions.

Pages: 1520 Year: 1983

B 1005 ... \$13.50

DATA CONVERSION ACQUISITION DATA BOOK

The 1984 edition of the Data Conversion/Acquisition Data book is one the most comprehensive in the industry. It contains specifications for high technology conversion products in the analog signal path, both preceding and following the conversion process. Combining high volume production capability with leading edge technology such as thin film resistors, laser trimming and advanced micro CMOS and bipolar processing, has helped develop products best suited to your design needs.

Pages: 1232 Year: 1984

B 1007 ... \$13.50

HYBRID PRODUCTS DATA BOOK

The Hybrid Products Data book is the only National Semiconductor publication that contains complete information on all our hybrid semiconductor products. Included are precision thin film and thick film products which provide the user with standard functions from operational amplifiers to converters with capabilities beyond those of current monolithic technology. Product selection guides and an application section are also included.

Pages: 792

Year: 1982

B 1045 ... \$9.95

LINEAR DATA BOOK

The 1982 edition of the National Semiconductor Linear Data book is the most comprehensive available. It presents approximately 2000 pages of specifications for our high-technology linear products. Applications, descriptions, features and diagrams in this data book include detailed sections for Voltage Regulators, Op Amps, Voltage Comparators, A to D, D to A Converters, Industrial Blocks and Audio and TV Circuits. The data book also features advanced telecommunications devices and speech synthesis (DIGITALER). Plus other non state-of-the-art linear products offering performance, economy, quality and reliability.

Pages: 1952

Year: 1982

B 1010 ... \$21.50

LINEAR APPLICATIONS HANDBOOK

Provides an indexed & cross reference collection of linear integrated circuit applications using both monolithic & hybrid circuits. Individual application notes written to explain the operation & use of one particular device or to detail various methods of accomplishing a given function. Each section includes, applications, descriptions, features, diagrams & specifications.

B 1012 ... \$15.00

LINEAR SUPPLEMENT

The 1984 Linear supplement provides the most recent information on National's new linear products. This supplement also provides a comprehensive index published in the Master Data book. New products designed are indicated by an Asterisk and in bold type. Revised data sheets are listed in bold type. National's supplement data book system allows you to make product selections of their latest product offerings.

Pages: 566

Year: 1984

B 1011 ... \$7.50

MOS MEMORY DATA BOOK

The 1984 MOS Memory Data book is a comprehensive collection of information advanced, high-density memory products covering the spectrum of this mainstream semiconductor component category. National Semiconductor has an array of advanced technology processes to apply to memory design and development. These range from high-density triply poly process used in the most advanced RAMs, the small-geometry, silicon gate, oxide-isolated micro-CMOS technology which is now being applied to high performance memory devices for the first time.

Page: 256

Year: 1984

B 1025 ... \$7.50

TRANSISTOR DATA BOOK

National Semiconductor has added many new transistors and product families since publication of the last data book. Many have already been widely acclaimed by users. In addition to small-signal, power-pipolar and field effect transistors that have been the mainstay of our catalogue, there is a section for multiple-field-effect transistors. More part numbers will be added as market needs expand. To keep current on all new National transistors, please contact your National sales representative or franchised distributor and ask to be placed on the customer mailing list.

Pages: 558

Year: 1982

B 1050 ... \$9.95

The first 30 customers also receive NATIONAL'S BRILLIANT VOLT-AGE REGULATOR HANDBOOK absolutely free - that's a further \$10 value

Free Bonus offer for the first 30 Customers Phone order reserve yours now!

VOLTAGE REGULATOR HANDBOOK

The 336 page Voltage Regulator Handbook becomes a must for the selection of three terminal and dual tracking components that meet the system requirements while utilizing the most cost effective approach. Beginning with product selection procedure and a data sheet summary, the text continues with easily accessible information about booster circuitry, power transformer and filter specifications, test methods, manufacturers' cross reference and extended use applications for National's regulators. B 1055

SERVICE DELIVERY

FOR NEXT DAY

PHONE 008 999 007

BANKCARD HOLDERS — PHONE ALTRONICS TOLL FREE 008 999 007

FOR NEXT DAY JETSERVICE DELIVERY

PHONE 008 999 007

BANKCARD HOLDERS — PHONE ALTRONICS TOLL FREE 008 999 007

Ultrasonic Pest Repeller

Build EA's new "Pest-Off" and save a small fortune on insect sprays.

The "Pest-Off" generates frequencies between 23KHz and 64KHz. Claimed to be the best for driving off most vermin.

Altronics Kit Includes: • Strong "ABS" Case • Efficient Piezo Tweeter • Screened Front Panel. **K 1600**

\$39.95



Make Your Next Party Swing with the Fantastic Musicolour IV

Ideal for Parties, Shop Signs, Display Windows, special lighting effects etc. Combination Colour Organ and Light Chaser. Four channel colour organ. Internal microphone or connect to speakers for colour organ operation. Four chaser modes forward and reverse. Output lamp load capacity a massive 2400 watts—that's 100 party globes. Full instructions and every last nut and bolt included. **K 5800**



\$115.00

Car Security System The Ultimate in Vehicle Protection

Uses Microphone Sensing to Guard Against Tampering and Vandalism.

The latest 'State of the Art' Vehicle Security System. This ETI design provides protection that could save you a fortune. Strategically placed resonance microphones detect any tampering with your vehicle e.g. Lifting of a door handle, scratching of a coin etc.


Temperature Controlled Soldering Station

(EA Sept. '86)


Controls the temperature of your standard soldering iron. Suitable for Irons rated from 20W—75W — Standard soldering iron plugs straight in no need for modification.

The Altronics Kit comes complete - pre-punched and silk screened. **Cat. K 6400**

\$35.00



- Auto Arming with Exit and Entry delays
- Dash Mount status indicator
- Remove Protection of bolt-on accessories
- Inc. circuitry to monitor any failure of dash warning lights.
- Normally closed and normally open circuits available.
- Supplied in high quality "ABS" Case with drilled and screened front panel.
- **Protect your expensive stereo** — Simply run a wire from the alarm system normally closed terminal to any earth screw on your stereo.



K 4340 **\$59.50**



105 STIRLING STREET, PERTH
**FOR INSTANT SERVICE
PHONE ORDER
TOLL FREE**

008 999 007

**PERTH METRO
AND AFTER HOURS
ORDERING SERVICE**

(09) 328 1599

ALL MAIL ORDERS

Box 8280, Stirling St. Perth W.A. 6000

**PACKING AND
DELIVERY CHARGES**

\$3.00 DELIVERY AUSTRALIA WIDE

We process your order the day received and despatch via. Australia Post. Allow approx. 7 days from day you post order to when you receive goods. Weight limited 1Kg.

\$6.00 OVERNIGHT JETSERVICE We process your order the day received and despatch via. overnight jetservice Courier for delivery next day. Country areas please allow additional 24-48 hours. Weight limit 3Kgs.

\$6.00 HEAVY MAIL SERVICE For deliveries exceeding 3Kgs and less than 10Kgs - allow 7 days for delivery

\$10.00 HEAVY HEAVY SERVICE All orders of 10Kgs. or more must travel Express Road - Please allow 7 days for delivery.

INSURANCE — As with virtually every other Australian supplier, we send goods at consignee's risk. Should you require comprehensive insurance cover against loss or damage please add 1% order value (Minimum charge \$1). When phone ordering please request "Insurance"

TOLL FREE PHONE ORDER - Bankcard Holders can phone order toll free up to 6pm Eastern Standard Time. Remember with our **Overnight Jetservice** we deliver next day.

Altronics Resellers

Chances are there is an Altronics Reseller right near you — check this list or phone us for details of the nearest dealer.

Blue Ribbon Dealers are highlighted with a ■. These dealers, generally carry a comprehensive range of Altronics products and kits or will order any required item for you.

Don't forget our Express Mail and Phone Order Service—for the cost of a local call, Bankcard, Visa or Mastercard holders can phone order for same day despatch.

Please Note: Resellers have to pay the cost of freight and insurance and therefore the prices charged by individual dealers may vary slightly from this Catalogue — in many cases, however, Dealer prices will still represent a significant cost saving from prices charged by Altronics Competitors.

WA

COUNTRY

ALBANY

BP Electronics ■ ... 41 2681

ESPERANCE

Esperance Communications 71 3344

GERALDTON

K.B. Electronics & Marine ... 21 2176

KALGOORLIE

Todays Electronics ■ ... 21 2777

NEWMAN

Watronics ... 751734

WYALKATCHAM

D & J Pease ... 81 1132

NT

DARWIN

Ventronics ... 81 3491

ALICE SPRINGS

Ascom Electronics ... 52 1713

FARMER

Electronics ... 52 2967

ACT

CITY

Bennett Commercial Electronics ... 80 5359

Scientronics ... 54 8334

NSW

CITY

David Reid Electronics ■ ... 267 1385

Jaycar ... 267 1614

SUBURBAN

CARINGHAH Hicom

Unitronics ... 5247878

CARLINGFORD Jaycar ... 872 4444

CONCORD Jaycar ... 745 3077

GORE HILL Jaycar ... 439 4799

HURSTVILLE Jaycar ... 570 7000

LEWISHAM PrePak

Electronics ... 569 9770

COUNTRY

ALBURY Webb's

Electronics ■ ... 25 4066

BATHURST

The Electronics Shop ... 31 4421

BROKEN HILL Crystal TV ... 4803

COFFS HARBOUR Coffs Harbour

Electronics ... 52 5684

GOSFORD

Tomorrows Electronics ■ ... 24 7246

KURRI KURRI Kurri Electronics 37 2141

NEWCASTLE

D.G.E. Systems ... 69 1625

George Brown & Company ... 69 6399

Novacastrian Elect. Supplies ... 616055

NOWRA

Ewing Electronics ... 218412

Southern Communications 21 4011

EAST MAITLAND East Maitland

Electronics ... 337327

ORANGE

Fyfe Electronics ... 626 491

RAYMOND TERRACE Albark

Electronics ... 87 3419

RICHMOND

Vector Electronics ... 773 174

TENTERFIELD Nathan Ross ... 36 2204

TOUKLEY TES Electronics . 96 4144

WINDSOR M & E Electronics ■

Communications 77 5935

WOLLONGONG Newtek

Electronics ■ ... 27 1620

Madjen Electronics ... 74 3061

Vimcom Electronics ... 28 4400

VICTORIA

CITY

Active Electronics ■ ... 602 3499

All Electronic Components ... 662 3506

Ellistronics ■ ... 6023499

MaGraths Electronics ... 347 1122

SUBURBAN ASPENDALE

Gilronics ... 5809839

BENTLEIGH Absolute

Electronics ... 557 3971

BOX HILL SOUTH Eastern

Communications 288 3107

CHELTENHAM Talking

Electronics ... 550 2386

CROYDON Truscott

Electronics ■ ... 723 3860

MULGRAVE Ellistronics ■ ... 5615844

PRESTON Preston

Electronics ... 48 40191

SPRINGVALE Active

Electronics ■ ... 547 1046

COUNTRY BENDIGO

KCJohnson ■ ... 41 1411

MORWELL Morwell

Electronics ... 34 6133

SALE Gippstech ■

Communications 447402

SHEPPARTON GV Electronics ■ 21 8866

SWAN HILL Cornish Radio

Services ... 32 1427

QUEENSLAND

CITY

Delsound P/L ... 2296155

Jaycar ... 393 0777

SUBURBAN FORTITUDE VALLEY

McGraths Electronics ... 832 3944

Economic Electronics ... 523 762

PADDINGTON Jacques

Electronics ... 369 8594

SLACKS CREEK David Hall

Electronics ... 2088808

TOOWONG Techniparts ... 3710879

COUNTRY CAIRNS

Thompson Instrument

Services ... 512404

BUNDABERG Bob Elkins

Electronics ... 721 785

GLADSTONE Supertronics ... 724321

NAMBOUR Nambour

Electronics ... 411604

PALM BEACH The Electronic

Centre ... 341248

ROCKHAMPTON Electron

World ... 278 988

Purely Electronics (East St.) ... 21058

Purely Electronics (Shopping Fair) 280 100

TOOWOOMBA Hunts

Electronics ■ ... 329677

TOWNSVILLE Solex ■ ... 722015

SA

CITY

Electronic Comp & Equip. 212 5999

Force Electronic ■ ... 212 2672

Protronics ... 2123111

SUBURBAN BRIGHTON

Electronics ■ ... 296 3531

CHRISTIES BEACH Force

Electronics ■ ... 382 3366

ENFIELD Force

Electronics ■ ... 3496340

PROSPECT Jensen

Electronics ■ ... 269 4744

COUNTRY MT. GAMBIER

South East Electronics ... 250 034

PT. LINCOLN West Coast

Elect Supplies ... 82 5802

WHYALLA Eyre

Electronics ■ ... 45 4764

TASMANIA HOBART

D & I Electrical Electronics ... 34 8244

George Harvey ■ ... 342233

LAUNCESTON Advanced

Electronics ... 315688

George Harvey ■ 31 6533

Nichols Radio TV ... 316171


LEGANA Frank Beech

Electronics ... 301379

MORE ALTRONICS DEALERS WANTED

If you have a Retail Shop, you could increase your income significantly by becoming an Altronics Dealer. Phone Steve Wroblewski 09 3817233 for Details

Books & Literature



Complete Guide to Car Audio

The Complete Guide to Car Audio: by Martin Clifford. Published by Howard W. Sams & Co, Indianapolis, 1981. Soft covers, 135 x 216mm, 232mm, illustrated with photographs and diagrams. ISBN 0-672-21820-8. Price \$19.95

In addition to the practical considerations of installing car audio equipment, this book offers a brief background to the subject and some useful tips of safeguarding the gear once it is installed.

Solid state electronics has benefitted car audio more than just about any type of consumer equipment. Imagine the days when car radios were so large and cumbersome that they actually had to be mounted on the running board. Sensitivity was so poor that a wire mesh antenna as large as the roof had to be used — not to mention the inconvenience of three different sets of batteries. Reading through "The Story of Car Audio" chapter certainly stimulates an awareness of the progress that has been made.

Most of the audio gear offered as standard equipment in cars is mediocre at best. Some expensive models have available equipment with the desirable

features - but at a surcharge which far exceeds the value of the equipment. For motorists who want better sound than can be had with the standard equipment, but are unfamiliar with the relevant terminology and specifications, there is an apparently bewildering assortment of equipment on the market.

This book could be most helpful in explaining some of the more common terms. The prospective buyer would be in a much better position to independently evaluate the equipment on offer instead of depending entirely on the salesman's suggestions.

From the purely technical point of view, the book does not have a great deal to offer. The explanations of terms like "multipath distortion" and "image rejection" are most elementary. But considering the non-technical nature of the book's readership, this is quite appropriate.

The book is also a little dated in some respects - particularly with regard AM transmissions. No mention is made of stereo, and this medium is only credited with having a bandwidth of 5kHz. This latter figure may have been true at the time, and may still be true in USA, but Australian AM transmissions have a claimed bandwidth of over 10kHz pre-

and the training needs of computer-related personnel.

Over 2,500 organisations, public and private, were sampled by questionnaire and a number of very interesting facts relating to employment and computerisation have been brought to light by the study.

The belief that there is a correlation between the influx of computers in the workforce and rising unemployment is firmly disputed.

The final chapters (6 & 7) investigate the demand and supply of computer related personnel now and in the future. In particular, chapter 7 considers how to avoid over supply in one area to the detriment of another.

It is a concise and well documented report on data processing in Australia, that takes a look at future trends. Our review copy came from the publishers, Allen Unwin Australia Pty Ltd, PO Box 764, North Sydney, NSW 2060. (L.U.)



sently. The receivers are a different story, though. The 5kHz figure would be more than generous for most.

Our review copy was supplied by Jaycar Electronics, PO Box 185, Concord, NSW 2137. (C.R.D.).

How to Build Speaker Enclosures

How To Build Speaker Enclosures: by A. Badmaieff and D. Davis. Published by Howard W. Sams & Co, Indianapolis, 1985. Soft covers, 136 x 216mm, 144 pages. Illustrated with photographs and diagrams. ISBN 0-672-20520-3. Price \$14.95.

Here's a loudspeaker system that you'll surely want to build: each enclosure has internal dimensions of 1.2 x 1.2 x 5.5m, a volume of over 72,000 litres and weighs around 25 tonnes. Perhaps a little too ambitious? Not to worry - there are some more modest systems described in the book.

The emphasis here is on designing your own enclosure to suit whatever drivers you may have on hand. Loudspeaker types are grouped under five headings: (1) Finite Baffle; (2) Infinite Baffle; (3) Bass Reflex; (4) Horn Projectors; (5) Combinations. The respective merits and disadvantages of each type are discussed.

Consider, for example, that a loudspeaker with an efficiency of 0.1% (which is representative of some infinite baffle types), would require a power input of 40,000 watts to recreate the full dynamic range of an orchestral performance. Obviously, various practical considerations would deter any rational person from even wanting to recreate this range in the living room, but the argument leads to some interesting comparisons of efficiency for various types of enclosures.

The book is a balance of theory and practice. The relevant formulae are provided so that the constructor can decide on the type and number of drivers, the enclosure volume and type, the crossover requirements, etc. Techniques for construction are also discussed. Overall, the book is an interesting read and seems to be reasonably complete.

Our review copy was supplied by Jaycar Electronics, PO Box 185, Concord, NSW 2137. (C.R.D.).

Data Processing Skills and Usage

Data Processing in Australia by Roy J. Krieger et. al. Published 1986 by Allen & Unwin Australia Pty Ltd. Soft cover 136 x 212mm, 70 pages, with appendices, tabled statistics and references. ISBN 0 86861 655 9. Retail price \$14.95.

This text is for anyone interested in a statistical and historical analysis of the impact of computers on Australian business and employment. It has been written with the researcher in mind and attempts to trace the how, why and where of computer growth in this country, and the special needs it creates in training and employing personnel.

Chapters 2 to 5 set out to determine the extent of computer penetration into the workplace and also estimates the number of personnel employed in this type of work. The section goes on to provide information on the demand for employees

Build it yourself and save money

The microphone: for stage & PA

Pick it up and it automatically switches on. Put it down and it switches off. This high-quality microphone can be built for half the cost of comparable commercial units and boasts several novel features.

by BRANCO JUSTIC

Build a microphone you say? You've got to be kidding. You don't make microphones, you buy them ready made. Perhaps this is some kind of joke?

Well, we're not kidding. The microphone to be described here offers a performance that can only be equalled by expensive commercial units. It is very easy to build, you can buy all the parts for less than \$20, and it boasts a list of impressive features:

- Automatic switch on/switch off: pick "The Microphone" up, and it switches on automatically. Put it down, and it switches off automatically after a couple of minutes (can be extended to 20 minutes if required).

- Inbuilt battery check: if you touch one of the metal screws on the base of the unit, a LED will light up to indicate that the battery voltage is OK.

- Omnidirectional or unidirectional pickup: you can build the unit to suit your requirement simply by ordering the appropriate electret insert.

- Output level selection: during construction, you can set the output level from a few millivolts all the way up to line level. Thus, the microphone can drive the sensitive inputs of stage and audio mixers, the auxiliary inputs of hifi amplifiers, and instrument amplifiers (ie, it can drive any amplifier).

- Inbuilt equalisation: the internal circuitry is equalised to compensate for the

usual lack of bass which is apparent with most electret inserts. This equalisation, or bass boost circuit, can easily be disabled if not required.

- Low power consumption: the microphone consumes approximately one milliampere when it's on and an unmeasurably low current when it's off. The internal (alkaline) battery should last the length of its shelf life.


Electret microphone inserts

Electret microphone inserts have been available from electronic parts retailers for some years now. Most fall into the omnidirectional category which means that they pick-up sound equally from all directions.

They also offer good frequency response and sensitivity and are suitable for 'general purpose' and recording situations. However, they are not generally used in public address and live entertainment situations because they are prone to acoustic feedback.

Recently, at least one type of unidirectional microphone insert has become available from component dealers. These are more suitable for stage and PA work because they pick-up sound predominantly from one direction; ie. directly in front of the microphone insert.

It should be noted that these units also



The Microphone — pick it up and it automatically switches on.




Fig.1: Q1 and Q2 form the microphone preamplifier while IC1 makes up the touch-controlled logic circuit.

fall into the close working category. They exhibit good sensitivity only when the sound source is very close to the microphone (around 20cm or less).

This brief description will help you to decide which type of electret insert is the most suitable for your application. Either type may be specified when you order the parts for this project.

How it works

Fig.1 shows the circuit diagram. It can be broken into two sections: a two-stage microphone preamplifier based on Q1 and Q2, and a touch-controlled logic circuit based on hex Schmitt inverter IC1. We'll begin with the microphone preamplifier.

The action starts at the electret insert at the extreme left of the circuit. R10 provides biasing for the FET buffer stage inside the electret, the output of which is coupled to an equalisation circuit consisting of R11, C5 and R12. This provides approximately 8dB of bass boost.

If, however, a flat frequency response is desired, the bass boost feature can be

disabled by replacing C5 with a 0.1uF monolithic capacitor.

The output of the equaliser is coupled to common emitter amplifier stage Q1 via capacitor C6. This stage has a fixed gain of approximately 20dB and its output is directly coupled to the base of Q2 which, with its associated components, serves as an emitter-follower.

The addition of this latter stage gives the microphone a low output impedance. This is to ensure that high frequency components are not attenuated when the preamplifier output is connected to very long coaxial cables (50 metres or more). C8 rolls off the low frequency response of the common emitter stage (Q1) below 20Hz.

Finally, the signal at the emitter of Q2 is coupled via C10 to an attenuator network (R20, R21 and R22). This attenuator enables the constructor to select one of three different output levels: 25mV for low impedance microphone inputs on public address amplifiers and mixers; 120mV for high impedance inputs on PA

amplifiers and instrument amplifiers; or 500mV for line inputs of hifi amplifiers etc.


Touch control circuitry

The touch control circuitry switches the supply to the microphone preamplifier, and provides the battery check function. Here's how it works:

With no hand contact, pin 9 of IC1a is pulled high via R2 and R3. This means that pin 8 will be low and, since pin 11 of IC1b is pulled low by R5, pin 12 of IC1c will also be low. Thus, no power will be supplied to the microphone preamplifier.

When the microphone is picked up, the user's hand bridges two electrodes. One of these electrodes is formed by the metal case of the microphone, while the other consists of a 1cm-wide collar which is wrapped around the case but insulated from it with plastic tape.

The hand resistance between the 'on' terminal (metallic strip) and the case pulls pin 9 of IC1a low via R4 and thus pin 8 switches high. Capacitor C3 now quickly charges via D2 and so pin 10 of



This view shows the completed PCB prior to installation in the metal tube.

IC1b switches low and pin 12 of IC1c switches high. This then supplies power to the preamplifier stage via current limiting resistor R6.

Thus, the output of IC1c provides the switched supply to the preamplifier circuitry. This is quite in order, as it can quite easily supply the necessary current of less than 1mA.

Switch off

When the microphone is subsequently put down, IC1a's input is pulled high again and its output goes low, reverse biasing D2. C3 now discharges via R5 and, after about 100 seconds (as set by the RC time constant), pin 10 switches high and pin 12 of IC1c goes low.

Result: the microphone stays on for approximately 100 seconds after the removal of hand contact. This time constant can easily be extended to around 20 minutes by using a higher value for C3. This will allow the microphone to be used in a stand for quite long periods of time between hand contacts.

Note that C3 should be either a low leakage aluminium or tantalum electrolytic.

Battery check

Let's now take a look at the battery check function. This works in similar fashion to the supply switching circuitry.

As before, the case forms one electrode while the second electrode consists of either of two nuts which are located on a small PCB just inside the base of the unit.

Normally, the battery check electrode is held high by R1 and there is no forward bias across D1. However, when body resistance is present between the two electrodes, D1's cathode is pulled low. This low activates two circuits.

First, D1 is now forward biased and pulls pin 9 of IC1a low. This switches the microphone on for 100 seconds (if it isn't already on) as outlined above. During this time, pin 12 of IC1c is high and so pin 2 of IC1d is also high.

Second, the output of IC1f (pin 6) switches high and quickly charges C4 via D3. Pin 4 of IC1e thus switches low and the full battery voltage is applied across R7, LED 1 and zener diode ZD1. The LED will light to indicate that the battery is OK as long as the supply voltage is

greater than $V_Z + V_{LED} = 5V$.

When the resistive contact between the battery check terminals is removed, the LED remains on for the time constant determined by C4 and R8. With the values shown, this is about one second. The remainder of the circuit then switches off after about 100 seconds as outlined previously.

Construction

Virtually all the parts are mounted on a printed circuit board coded 86mp10 and measuring 170 x 29mm. To simplify construction, the PCB design includes the rear cover plate for the microphone and this accommodates the indicator LED and the battery check terminals.

The battery check terminals simply consist of two nuts which secure the cover PCB to two 70mm-long threaded rods. These rods, in turn, are soldered to large copper pads at one end of the main board.

Begin construction by enlarging several holes in the PCB to the diameters indicated in Fig.2. This done, cut along the required line to separate the main PCB and rear cover. The rear cover PCB can




Fig.2: enlarge the holes in the PCB as shown, then separate the main section from the rear cover.






Fig. 3 shows the parts layout on the two PCBs. No special procedure need be followed when installing the parts but watch the orientation of the semiconductors and

the electrolytic and tantalum capacitors. Also, push the transistors down onto the board as far as they will comfortably go before soldering the leads. An IC socket was used for the prototype but this can be considered optional.

The electret insert is supported on two stout pieces of tinned copper wire. These, in turn, are soldered directly to the copper side of the PCB. Bend the leads at right angles so that the insert is centrally located as shown in Fig.6.


The next step is to mount the LED and the threaded rod assemblies on the cover PCB as shown in Figs.3 and 4. This done, slide two 53mm x 3mm-dia. plastic sleeves over the threaded rods. The rods can then soldered to the pads provided on the main PCB (note: tin the PCB pads first).

The remainder of the wiring can now

be completed as shown in Fig.5 but don't connect the battery at this stage. The large holes in the main PCB act as a clamp for the shielded output cable (see Fig.6). We connected the inner conductor to the high level output terminal but you can also choose either the low or medium level outputs to suit your particular requirements.

Note that the lead to the metal collar for the switch-on function is soldered to a PC stake on the copper side of the PCB, and should be about 250mm long. Terminate the free end of this lead with a solder lug.

The other external lead is the earth lead. This should be about 115mm long and is routed through the hole in the centre of the cover plate PCB, along with the microphone cable. It should also be terminated with a solder lug.



Microphone for stage & PA

Final assembly

A 235mm x 32mm-dia. aluminium tube is used to house the circuitry. This aluminium tube will be supplied pre-cut with the kit, but the constructor will have to drill the necessary holes.

To simplify the drilling of the microphone case, a template has been prepared (Fig.8). This should be affixed to the tube using double-sided sticky tape. The holes can then be centre-punched and drilled to the diameters indicated.

A suitable piece of dowel can be used to stop the tube from collapsing during centre punching.

It is a good idea to leave the template in position during this operation, as this will help protect the case from accidental damage. Deburr all holes after drilling, then wrap a couple of layers of insulation tape around the tube where the metallic strip is to be mounted (ie, so that it covers the single hole located about 80mm from




Fig.7: this diagram shows how the metal collar is connected to the 'on' terminal on the PCB.


one end). This done, pierce the tape where it covers the hole in the tube.

The next step is to drill holes in both ends of the metallic strip. To do this, drill a 3.2mm hole about 6mm from one end, then wrap the strip tightly around the tube insulation so that the end with the hole is in the overlapping position. The location of the second hole can then be marked and drilled to size.


You can now install the metal collar and terminate the lead to the PCB as

shown in Figs.6 and 7. This operation is a little tricky but can be accomplished with the aid of a pair of longnose pliers. Use your multimeter to confirm that the metal collar has been correctly insulated from the case.


At this stage, you should go back over your work and carefully check the assembly against the wiring diagram. If everything checks out, the battery can be wired into circuit and wedged between the two threaded rod assemblies.




This photo shows how the PCB assembly is slid into the metal tube.



The "business" end of The Microphone. The electret insert is clearly visible.



Above: view showing the cover plate PCB.



The completed unit prior to installation of the windsock. Note that the metal collar must be correctly insulated from the case (see Fig.7).

The PCB assembly can now be slid into the aluminium tube (see Fig.6) and the earth/stop screw assembly installed. Be careful not to short out any of the PCB tracks during this procedure. We used a couple of small pieces of foam rubber as an anti-rattle measure.

Finally, install the windsock and check that the LED on the cover plate PCB lights when you touch one of the adjacent nuts. After that, it's simply a matter of plugging it in and trying it out.

PARTS LIST

- 1 PCB, code 86mp10, 170 x 29mm
- 1 electret microphone insert (see text)
- 1 235mm x 32mm-dia. aluminium tube
- 1 piece of metallic strip, 120 x 12mm
- 1 windsock
- 2 70mm x 3mm threaded rods
- 4 3mm nuts
- 2 53mm lengths of plastic sleeving
- 2 solder lugs
- 1 insulating washer
- 2 machine screws, nuts and washers to suit
- 1 length of shielded microphone cable plus plug to suit

Semiconductors

- 2 BC549 NPN transistors
- 3 1N4148 silicon diodes
- 1 3.3V 400mW zener diode
- 1 red LED (5mm)
- 1 74C14 or 40106 hex inverting Schmitt trigger

Capacitors

- 1 220uF 16VW axial electrolytic
- 2 4.7uF 16VW tantalums
- 1 10uF 16VW tantalum
- 4 0.1uF monolithics
- 1 0.022uF greencap
- 2 0.001uF disc ceramics
- 1 18pF disc ceramic

Resistors (0.25W, 5%)

- 5 x 10M, 1 x 330k, 3 x 82k, 1 x 15k,
- 2 x 10k, 2 x 6.8k, 1 x 4.7k,
- 1 x 3.3k, 1 x 2.2k, 1 x 1.5k,
- 3 x 470 ohm, 1 x 47 ohm

Where to buy the parts: a kit of parts for this project is available from Oatley Electronics, 5 Landsdowne Pde (PO Box 89), Oatley, NSW 2223. Telephone (02) 579 4985. Price: \$19.95 with omnidirectional electret insert; \$21.95 with unidirectional electret insert. These prices include pack and post. Note: microphone cable not supplied.





Fig. 8: Use this actual size template to drill the holes in the metal case.

12 months warranty!



HUNG CHANG (RITRON) 20 MHz DUAL TRACE OSCILLOSCOPE

- Wide bandwidth and high sensitivity
- Internal graticule rectangular bright CRT
- Built in component tester
- Front panel trace rotator
- TV video sync filter
- Z axis (Intensity modulation)
- High sensitivity X-Y mode
- Very low power consumption
- Regulated power supply circuit

COMPONENT TESTER is the special circuit with which a single component or components in circuit can be easily tested. The display shows faults of components, size of a component value, and characteristics of components. This feature is ideal to troubleshoot solid state circuits and components with no circuit power. Testing signal (AC Max 2 mA) is supplied from the COMPONENT TEST IN terminal and the result of the test is fed back to the scope through the same test lead wire at the same time.

CRT

CRT: 6" (150mm) Flat-faced high brightness CRT with Internal Graticule.
Effective display area: 8 x 10 div (1 div = 10 mm)
Acceleration potential: 2KV

VERTICAL

Operating Modes: CH-A, CH-B, DUAL, ADD (CH-B can be inverted.)
Dual modes: Alter: 0.2u/s - 0.5ms/div. Chop: 1ms - 0.5s/div.
CHOP frequency 200KHz approximately.
Deflection factor: 5mV/div 20V/div +/- 3%, 12 ranges in 1-2-5 step with fine control.
Bandwidth: DC; DC - 20MHz (-3dB). AC; 10Hz - 20MHz (-3dB).
Rise Time: Less than 17ns.
Overshoot: Less than 3%.
Input Impedance: 1M ohm +/- 5%, 20pF +/- 3pF.
Maximum Input Voltage: 600Vp-p or 300V (DC+AC Peak).
Channel Isolation: Better than 60 dB at 1KHz.

HORIZONTAL

Sweep Modes: NORMAL, and AUTO
Time Base: 0.2u/s - 0.5s/div +/- 3%, 20 ranges in 1-2-5 step with fine control.
Sweep Magnifier: 5 times (5X MAG).
Linearity: 3%.

TRIGGERING

Sensitivity: INTERNAL: 1 div or better for 20Hz - 20MHz (Triggerable to more than 30MHz); EXTERNAL: 1Vp-p or better for DC - 20MHz (Triggerable to more than 30MHz).
Source: INT, CH-A, CH-B, LINE and EXT.
Slope: Positive and Negative, continuously variable with level control PULL AUTO for free-run.
Coupling: AC, HF-REJ and TV. TV SYNC Vertical and Horizontal Sync Separator Circuitry allows any portion of complex TV video waveform to be synchronized and expanded for viewing TV-H (Line) and TV-V (Frame) are switched automatically by SWEEP TIME/DIV switch.
TV-V: 0.5s/div to 0.1ms/div. TV-H: 50u/s/div to 0.2u/s/div.

X-Y OPERATIONS

X-Y Operations: CH-A: Y axis. CH-B: X axis Highest Sensitivity: 5mV/div.

COMPONENT TESTER



Component Tester: Max AC 9V at the terminal with no load. Max current 2mA when the terminal is shorted. (Internal resistance is 4.7K ohm)

OTHER SPECIFICATIONS

Intensity Modulation: TTL LEVEL (3Vp-p); Positive brighter.
BANDWIDTH: DC - 1MHz MAXIMUM INPUT VOLTAGE: 50V (DC+AC Peak)
Calibration Voltage: 0.5Vp-p +/- 5%, 1KHz +/- 5% Square wave.
Trace Rotation: Electrically adjustable on the front panel.
Power Requirements: AC: 100, 120, 220, 240V 20W
Weight: 7kg approximately.
Size: 162(H) x 294(W) x 352(D)mm.

Cat. Q12105 **only \$849**
(tax exempt only \$695)


Bulk orders, schools, please phone (03) 543 2166 for special low pricing



605 3 1/2 DIGIT MULTIMETER

As reviewed in March EA!
See specification tables below for details.

Cat. Q11035 **\$79.95**



705A 3 1/2 DIGIT MULTI/CAPACITANCE METER

See specification table below for details.

Cat. Q11040 **\$119**

605 & 705A SPECIFICATIONS

DC Voltage				
Range	Resolution	Accuracy	Input Impedance	Overload Protection
200mV	100uV			
2V	1mV	0.5% -1	10MΩ on all ranges	1000V DC/peak AC on all ranges
20V	10mV			
200V	100mV			
1000V	1V	0.8% -1		

AC Voltage				
Range	Resolution	Accuracy	Input Impedance	Overload Protection
200mV	100uV			
2V	1mV	1% -4	10MΩ on all ranges	750V rms on all ranges except 200mV AC ranges
20V	10mV			15 seconds max. above 250V rms AC
200V	100mV			
750V	1V	2% -4		

DC Current				
Range	Resolution	Accuracy	Burden Voltage	Overload Protection
200uA	100nA	NC		
2mA	1uA			
20mA	10uA	1% -1	0.3V max	705A: 0.2A fuse up to 250V
200mA	100uA			605: 2A fuse up to 250V
2000mA	1mA	1.5% -1		10A range not fused
10A	10mA	1% -1	0.7V max	

Resistance				
Range	Resolution	Accuracy	Open Voltage	Overload Protection
200Ω	100mΩ	1% -2		
2kΩ	1Ω			
20kΩ	10Ω			
200kΩ	100Ω	0.8% -2	HiV < 3.5V LoV < 0.25V	250V DC/rms on all ranges
2000kΩ	1kΩ			
20MΩ	10kΩ	2% -4		

AC Current				
Range	Resolution	Accuracy	Burden Voltage	Overload Protection
200uA	100nA	NC		
2mA	1uA			
20mA	10uA	1.2% -4	0.3V max	705A: 0.2A fuse up to 250V
200mA	100uA			605: 2A fuse up to 250V
2000mA	1mA	2% -4		10A range not fused
10A	10mA	1.5% -4	0.7V max	

Capacitance				
Range	Resolution	Accuracy	Test Signal	Max Input
2nF	1pF		400mV rms	
2uF	10pF			
200nF	100pF	NC	512 Hz	3V DC/peak AC on all ranges
2000uF	1uF		40mV rms	
20uF	10nF			

METEX MULTIMETERS

These instruments are compact, rugged, battery operated, hand held 3 1/2 digit multimeters. Dual-slope A-D converters use C-MOS technology for auto-zeroing, polarity selection and over-range indication. Full overload is provided.



METEX 3800 MULTIMETER

This instrument is a compact, rugged, battery operated, hand held 3 1/2 digit multimeter for measuring DC and AC voltage, DC and AC current, Resistance and Diode, for testing Audible continuity and transistor hFE. The Dual-slope A-D Converter uses C-MOS technology for auto-zeroing, polarity selection and over-range indication. Full overload is provided. It is an ideal instrument for use in the field, laboratory, workshop, hobby and home applications.

- Features...**
- Push-button ON/OFF power switch.
 - Single 30 position easy to use rotary switch for FUNCTION and RANGE selection.
 - 1 1/2" high contrast LCD.
 - Automatic over-range indication with the "1" displayed.
 - Automatic polarity indication on DC ranges.
 - All ranges fully protected plus Automatic "ZERO" of all ranges without short circuit except 200 ohm Range which shows "000 or 001".
 - High Surge Voltage protection 1.5 KV-3 KV.
 - Diode testing with 1 mA fixed current.
 - Audible Continuity Test.
 - Transistor hFE Test.

SPECIFICATIONS
Maximum Display: 1999 counts
3 1/2 digit type with automatic polarity indication.

Indication Method: LCD display.
Measuring Method: Dual-slope in A-D converter system.
Over-range Indication: "1" Figure only in the display.

Temperature Ranges: Operating 0°C to +40°C
Power Supply: one 9 volt battery (006P or FC-1 type of equivalent)
Cat. Q91530 **Normally \$99.95**
SPECIAL \$89.95



METEX 3530 MULTIMETER

This instrument is a compact, rugged, battery operated, hand held 3 1/2 digit multimeter for measuring DC and AC voltage, DC and AC current, Resistance and Diode, Capacitance, Transistor hFE and Continuity Test. The Dual-slope A-D Converter uses C-MOS technology for auto-zeroing, polarity selection and over-range indication. Full overload is provided. It is an ideal instrument for use in the field, laboratory, workshop, hobby and home applications.


- Features...**
- Push-button ON/OFF power switch.
 - Single 30 position easy to use rotary switch for FUNCTION and RANGE selection.
 - 1 1/2" high contrast LCD.
 - Automatic over-range indication with the "1" displayed.
 - Automatic polarity indication on DC ranges.
 - All ranges fully protected plus Automatic "ZERO" of all ranges without short circuit except 200 ohm Range which shows "000 or 001".
 - High Surge Voltage protection 1.5 KV-3 KV.
 - Capacitance measurements to 1pF
 - Diode testing with 1 mA fixed current.
 - Audible Continuity Test.
 - Transistor hFE Test.

SPECIFICATIONS
Maximum Display: 1999 counts
3 1/2 digit type with automatic polarity indication.

Indication Method: LCD display.
Measuring Method: Dual-slope in A-D converter system.

Over-range Indication: "1" Figure only in the display.
Temperature Ranges: Operating 0°C to +40°C

Power Supply: one 9 volt battery (006P or FC-1 type of equivalent)
Cat. Q91540 **Normally \$129**
SPECIAL \$119



CORDLESS RECHARGEABLE SOLDERING IRON

- Built in solder point illumination
- Easy replacement of solder tip
- Protective stand which also functions as charging unit
- Sponge pad attach to stand
- Plug pack power adaptor
- Includes Nicad battery
- Instruction manual
- 12 months warranty


Cat. T12480 **Normally \$79.95**
SPECIAL, \$69.95



WELLER WTCNP SOLDERING STATION

- The WTCNP Features:
- Power Unit 240 V AC
 - Temperature controlled iron, 24 V AC
 - Flexible silicon lead for ease of use
 - Can be left on without fear of damaged tips!
 - The best is always worth having.

Cat. T12500 **R.R.P. \$149**
SPECIAL, ONLY \$119



SCOPE 60W SOLDERING SYSTEM

- Infinitely adjustable temp. 200°C to 470°C. Sliding control selects desired tip temperature (LED readout monitors tip temp.)
- Safety holder features ceramic burn-proof bush and can be converted to left-hand-side.
- Soft and cool hand grip in pliable rubber.
- Screw type connector prevents accidental plug removal and guarantees solid contacts.
- Temperature lock allows production supervisors to control soldering temperatures.
- Anti seize tip retention design reduces risk of thread seizure by removing locking nut to cooler end of barrel.
- Optional 30W soldering pencil is available for finer work.

Cat. T12900 **Normally \$159**
NOW \$149

DIRECT IMPORT SOLDER SUCKERS!

Rod Irving Electronics
has done it again!
Quality solder suckers at
incredibly low prices!!



REGULAR SOLDER SUCKER

- Light weight
- Sturdy construction
- Easy to remove tip
- Excellent value for money!


Cat. T11271 **\$9.95**



ANTISTATIC SOLDER SUCKER

- Light weight
- Sturdy construction
- Easy to remove tip
- Excellent value for money!

Cat. T11281 **\$11.95**



ARLEC SUPER TOOL

A versatile 12V electric tool for...

- Sanding
- Engraving
- Grinding
- Polishing
- Cutting
- Drilling
- Milling
- Erasing, etc.

Features:

Operates on safe, low 12 volts from mains electricity via AC adaptor (supplied). Light and easy to handle with touch switch and lock for continuous running. High torque motor. 10,000 R.P.M. Can drill 2mm holes in steel. 2 year guarantee

Contents:

- 12V Super Tool
- Plugback AC adaptor
- spherical milling cutter
- 1 wire brush
- 1 grinding wheel
- 4 drill bits, 0.6, 0.8, 1.0, 1.2mm
- Set of 5 chuck collets
- 6 eraser sticks
- Instruction sheets


Cat. T12300 \$59.95



FREE STANDING, FOLD UP MAGNIFIER

An economically priced "hands free" magnifier, lets you take care of all those tricky fine detailed jobs so often encountered in electronics, or any of many other practical uses such as home, work, hobbies etc.

Cat. T12083 \$14.95



BELL WIRE

Red and white twisted conductors: 2 x 1 strand 0.17mm Sheath: O.D. 2 x 1.35mm

Cat. W 10+ rolls \$19.00/m
10+ rolls \$17.50/m




COMPUTER CABLE

CIC6 6 conductor computer interface cable. Colour coded with braided shield. (to IE422 specifications). Copper conductor 6 x 7/0.16mm. 1-9 metres \$1.90/m
10+ metres \$1.70/m

CIC9.100 9 conductor computer interface cable. Colour coded with mylar shielding. 9 x 7/0.16mm. 1-9 metres \$2.50/m
10+ metres \$1.95/m

CIC12 12 conductor computer interface cable. Colour coded with mylar shielding. 12 x 7/0.16mm. 1-9 metres \$2.70/m
10+ metres \$2.50/m

CIC16 16 conductor computer interface cable. Colour coded with mylar shielding. 16 x 7/0.16mm. 1-9 metres \$3.90/m
10+ metres \$3.40/m




PASSIVE INFRA RED DETECTOR

Compact P.I.R. with adjustable corner or wall mounting bracket, dual pyroelectric infra red sensing element gives a coverage 2 x 14 zones 2m high and 10m wide

- Sensitivity adjustment control
- Detecting range 12-15 metres at 90 degrees
- Detecting zones 9 long (up), 5 short (down)
- LED indicator for walk test. (can be disabled)
- Shielded against RF interference
- Relay output NC or NO at 30V (AC-DC) 0.5A max.
- Integral NC tamper switch
- Operating voltage 10.5 - 16V DC
- Current 20mA at LED 25mA

Cat. S77777 \$145



RECHARGEABLE LANTERN

- Up to 1,000 recharges
- No more expensive batteries
- Beam length 1,050 feet
- Cannot be over charged
- Shoulder strap included
- 240V charge lead connects direct
- 12V Car lighter recharging lead (ideal for camping, travel, boating etc)
- Red safety shade cover

Cat. A15053 only \$29.95



RECHARGEABLE FLASH LIGHT

- Up to 1,000 recharges
- No more expensive batteries
- Beam range 150 metres
- Size: 160(L) x 60(W) x 60(H)mm
- Weight: 140 gram
- Shoulder strap included
- To recharge simply unclip the handle which contains the power pack and plug directly into a 240V power point.
- Charging time: approx. 10 hours (when fully discharged)
- Operating time approx. 80 minutes (when fully charged)
- Output/Bulb: 2.4V


Cat. A15052 only \$15.95



RECHARGEABLE POCKET LIGHT

- Compact and very convenient!
- No more expensive batteries
- Up to 1,000 recharges
- To recharge, simply remove the rear cover and plug directly into a 240V power point.
- Charging time: approx. 15 hours (when fully discharged)

Cat. A15051 only \$13.95



FLUORESCENT WORK & EMERGENCY LIGHT

- Suits cars, boating, caravan, camping etc.
- Shatterproof, glare free
- Cigarette lighter plug and alligator clips
- 12V DC, 8 watt, transistorised

Cat. A15052 \$25.95



FULLY AUTOMATIC EMERGENCY LIGHTS

In the event of a power failure these lamps will automatically come on. A very handy service, particularly where natural light is not available. The power meter is used to indicate recharging.

Cat. A15049 \$109



DC/DC CONVERTER

- Fail safe circuit protects against short circuit or wrong polarity
- Under dash mounting
- 13.8V DC input
- 7.5V/12V DC output
- Current: 7.5V (900mA); 9V (1.2 amp); 12V (1.2 amp)
- 2 metres cord with 4 plug adaptor

Cat. A15054 \$21.95

LIGHTER TO LIGHTER CAR STARTER

The simple, cleaner solution to flat car batteries! Simply plug in to the cigarette lighter positions and presto! Features 5 metre long lead, and LED indicates correct connection

Cat. A15062 \$10.95



DIGITAL SPEEDO/DIGITAL TACHO/SPEED ALERT

- Digital readout (LED) for both tach and speed.
- Alarm with sound at variable preset speed.
- Audible beeper and visual indicator.
- In built light indicator for night illumination.
- Designed for 12 volt negative earth electrical systems.
- Speed: 0 - 199kph
- Tachometer: 0 - 9900kph
- Speed alert: 40 - 120kph
- Complete with mounting hardware.

Cat. A15064 Normally \$69.50

SPECIAL, ONLY \$59.50



CODE KEY PAD

- Telephone type digital keypad.
- Four digit, changeable code.
- Over 5000 possible combinations.
- Power consumption: 5mA standby, 50mA alarm.
- Two sector LED and 1 arm LED.
- Wrong number lockout.
- 12V DC operation.
- Relay output.
- Panic button.
- Normally open tamper switch.
- Dimensions: 145 x 100 x 37mm
- ACP3 compatible.

Cat. A13014 Normally \$69.50

SPECIAL, ONLY \$55.60



ECONOMY TRANSFORMERS

- | 1-9 | 10+ |
|----------------------------|-----------------|
| 2155 240V 6-15V 1A | |
| Cat. M12155 | \$9.95 \$8.95 |
| 2156 240V 6-15V 2A | |
| Cat. M12156 | \$14.95 \$13.95 |
| 2840 240V 9V CT | |
| Cat. M12840 | \$5.95 \$4.95 |
| 2851 240V 12-6V CT 150mA | |
| Cat. M12851 | \$6.95 \$5.50 |
| 2860 240V 15V CT 250mA | |
| Cat. M12860 | \$5.95 \$4.95 |
| 6672 240V 15-30V 1A tapped | |
| Cat. M16672 | \$14.95 \$13.95 |

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11260 14/20 RED
W11261 14/20 BLACK
W11265 14/20 BLUE
W11268 14/20 WHITE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11270 24/20 RED
W11272 24/20 GREEN
W11274 24/20 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL


1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80



DIECAST BOXES

Diecast boxes are excellent for RF shielding, and strength. Screws are provided with each box.

H11451 100 x 50 x 25mm	\$ 5.95
H11452 110 x 60 x 35mm	\$ 6.50
H11453 120 x 65 x 40mm	\$ 6.95
H11461 120 x 94 x 53mm	\$11.50
H11462 188 x 120 x 78mm	\$13.50
H11464 188 x 188 x 64mm	\$29.50



"SNAP TOGETHER" PLASTIC CASE

Top and bottom simply snap together (no screws required), removable front and back panels.

Size: 186(W) x 125(D) x 50(H)mm

Cat. H10116 \$7.95



HOOK UP WIRE

Cat. No. Description

W11251 13/12 TND BLK	
W11252 13/12 TLD BROWN	
W11253 13/12 TLD ORANGE	
W11254 13/12 TLD YELLOW	
W11255 13/12 TLD GREEN	
W11256 13/12 TLD BLUE	
W11257 13/12 TLD WHITE	

PRICES PER 100 METRE ROLL

1-9	10+
\$6.95	\$5.00
\$5.35	\$4.50

W11260 14/20 RED
W11261 14/20 BLACK
W11265 14/20 BLUE
W11268 14/20 WHITE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$10.80	\$9.00

W11270 24/20 RED
W11272 24/20 GREEN
W11274 24/20 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$12.60	\$10.80

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$18.00	\$16.20

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$18.00	\$16.20

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$18.00	\$16.20

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$18.00	\$16.20

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$18.00	\$16.20

W11280 32/2 BROWN
W11282 32/2 BLUE

PRICES PER 100 METRE ROLL

1-9	10+
\$24.00	\$12.00
\$18.00	\$16.20

W11280 32/2 BROWN
W11282 32/2 BLUE



ALWAYS CHECK OUR MEMORY PRICES BEFORE YOU BUY!

(If you find a cheaper price let us know!)

IC SPECIALS!

1-9	10+	100+
5558pin 0.50	0.40	0.35
4116	\$3.75	\$3.50
4164	\$3.95	\$3.75
2716	\$8.90	\$8.50
2732	\$8.25	\$7.95
2764	\$6.25	\$5.95
27128	\$6.95	\$6.50
6116	\$2.95	\$2.75
41256	\$5.95	\$5.50
6264	\$6.50	\$5.50
27256	\$11.50	\$10.50

WORLD MODEM CHIP

Cat. U21614 Normally \$49.50

Save \$20, SPECIAL \$29.95

MEL9501

Have you blown up your Apple drive by plugging it in backwards or not turning off the power while changing bauds? We have the MEL9501 chip!

SPECIAL, ONLY \$29.95



SPEECH SYNTHESISER CHIPS!


SP0256A-AL2: Speech synthesiser chip, needs programming to work.

..... \$16.95

CTS256-AL2: Contains the code recognition circuit to enable the project to plug directly on the printer port, or into an IBM PC.

..... \$29.95

A SET OF EACH \$44.95



POT CORES

FX2242 Assembly.

2 halves, 36mm diameter

L12100 \$6.95

Former to suit FX2242

L12101 \$0.95

FX2243 Assembly.

2 halves, 24mm diameter

L12110 \$7.95

Former to suit FX2243

L12111 \$1.00

E Core. 2 halves

L12115 \$6.95


Former to suit E Core

L12116 \$3.95

Complete E Core assembly.

(including end plates and bolts)

L12117 \$12.95



HIGH INTENSITY RED LED BAR GRAPH

Dimensions:

Overall: 63mm across, 5mm high.

LEDs: 10 x 5mm x 1mm

Cat. L210180

1-9 \$2.95

10+ \$2.75

100+ \$2.50



ULTRASONIC TRANSDUCERS

Designed to transmit at 40kHz


(L19990) and receive at 40kHz

(L19991) with up to 20V I/P on the

transmitter. These

Circuit & Design Ideas

Interesting circuit ideas from readers and technical literature. While this material has been checked as far as possible for feasibility, the circuits have not been built and tested by us. As a consequence, we cannot accept responsibility, enter into correspondence or provide constructional details.



TV based frequency standard

It is possible to derive a highly stable frequency standard from a TV receiver. Indeed, some stations stabilise their line synchronising pulses with a rubidium standard which can have an accuracy of about one part in 100,000,000,000. Other stations use oven-stabilised crystal oscillators which are not quite as accurate but are nevertheless quite good.

In Sydney, both the ABC and TCN9 use the rubidium standard and thus their line synchronising pulses are highly accurate and stable. This circuit shows how to derive a jitter-free 1MHz reference frequency from these pulses.

Q1 and its associated parts form a 2MHz crystal oscillator. The output of this oscillator is fed via Q2, Q3 and IC1a to IC2 which is a 4024 7-stage binary counter. This divides the signal by two to give the 1MHz reference output at pin 12, and by 128 to give the TV line synchronising frequency of 15.625kHz at pin 3. The

pin 12 output is buffered by IC1b to give the 1MHz reference output, while the pin 3 output is fed to pin 2 of IC3.

The remainder of the circuit provides feedback control for the crystal oscillator (Q1). It uses a ferrite rod loopstick to pick up the 15.625kHz line synchronising pulses from the TV receiver. This signal is then amplified by Q4 and applied via buffer stage IC1c to pin 10 of IC3.

IC3 is a 4518 dual 4-bit binary counter and is used here to divide the signals on its inputs by two. The resulting outputs have a 50% duty cycle at pins 11 and 3 and are fed into the IC4, a phase lock loop IC which is used simply as a phase comparator. The resultant error voltage appears at pin 2 and is fed via a filter circuit to voltage-follower IC5.

The output at pin 6 of IC5 is then fed back to the BA102 varicap diode in the crystal oscillator to phase lock it with the TV line sync pulses. Q5 turns on and lights LED 1 when the lock condition is achieved.

Before putting the frequency standard

into service, the **following** steps need to be taken. After **switching** on:

1. Adjust the 100k trimpot in series with the meter so that it reads exactly centre-scale.
2. Adjust the frequency of the crystal oscillator to zero-beat against WWV, VNG or some other suitable reference.
3. Adjust the resonant frequency of the pickup loop to 15.625kHz. Whilst not critical, this will improve the sensitivity.

The unit is now ready to be synchronised with the TV receiver. Note that sufficient pick up must be obtained to light the "phase-lock" LED. The meter will then come to rest after several seconds, at or near to centre scale.

If necessary, centre scale may be obtained by fine tuning of the crystal oscillator trimmer. The 1MHz output will now be virtually as stable as the rubidium standard at the station.

I. Pogson,
Epping, NSW.

Extra decimal points for EA DFM

The EA Digital Frequency Meter described in December 1981 had no decimal point included in the display. Switching between ranges thus often gave a confusing readout. This was largely overcome by the addition of a decimal point driving circuit, published in EA, July 1982. However, there were still two ranges which did not have the decimal point included in the display.

This simple modification provides the decimal point display for the remaining two ranges. One of the decimal points could not normally be displayed because it would have been located to the left of the most significant digit, and the FND507 displays have right hand decimal

points only. However, the decoded output for this decimal point is actually available from the decimal point driver at pin 3 of IC2.

In this circuit, an NPN driver transistor is used to drive a discrete LED positioned at the left hand extreme of the display. The anode is connected to pin 15 of IC1 on the main board — this will become DP7.

The second missing decimal point (DP1) is between the two least significant digits. The decoded output for this is available from pin 7 of IC2 of the DP driver — again through an NPN driver transistor. The track to DP0 must be cut to prevent it from lighting as well.

Eric Rodda,
Marion, SA.

\$15

Modified audio generator

Several readers have contacted the designer of the high performance audio generator circuit published in the May 1986 CDI pages. Apparently, there is no source for the R54 thermistor used in that circuit, although the RA53 type is available from Radiospares Components (Part No. 151-114), 6c Durdans Ave, Rosebery, NSW 2018. Telephone (02) 669 3666.


The RA53 type can be directly substituted in the original circuit but the output level will be reduced to half its previous value. This problem can be overcome by modifying the output stage to provide a

gain of two as shown in the diagram.

Readers are also advised that a standard dual-gang 10k potentiometer can be used in the circuit but try to find one where the maximum resistances of the two sections are within 10% of each other. Note also that if NE5534s are used, 22pF compensation capacitors between pins 5 and 8 are necessary. Finally, TL072 or RC4558 op amps can be substituted but with a slight increase in noise and distortion.

Phil Allison,
Summer Hill, NSW.

\$10



Basic program for vented box enclosures

This short BASIC program for VZ computers will design the size of the vent needed in a bass reflex enclosure to tune it to a given frequency. It calculates the length of the vent from the given diameter, box volume and box frequency. Also the tuned frequency of an existing enclosure can be found from the cabinet volume and vent dimensions.

Surprising though it may be, the woofer size or type does not affect the tuned frequency; this means that you won't need any speaker data.

If the program gives a vent length of about 20mm then just a hole in the baffle is needed. Remember, however, that any vent should have a diameter not less than one quarter of the woofer diameter to prevent excessive air velocity.

For checking an existing design press RETURN when "BOX FREQ. HZ..." appears. This frequency is then calculated using the other data. If "NEW VENT DIAMETER MM." appears, enter a new larger diameter and try again since the desired frequency cannot be achieved with the previous value.

Phil Allison,
Summer Hill, NSW.

\$20

```

10 CLS:PRINT
30 PRINT " PROGRAM TO CALCULATE VENTED"
35 PRINT " BOX PARAMETERS"
40 PRINT " *****":PRINT:PRINT
50 INPUT " BOX VOLUME LITRES ":(VB:PRINT:IFVB=0 THEN 50
60 INPUT " VENT DIAMETER MM. ":(D:PRINT:IFD=0 THEN 60
61 IFFB=0 THEN 100
70 INPUT " BOX FREQ. HZ ":(FB:PRINT:IFFB=0 THEN 70
71 IFFB=0 THEN 100
80 INPUT " VENT LENGTH MM. ":(L:PRINT:IFL=0 THEN 80
90 IF FB=0 THEN 130
100 L=2360*D^2/(VB*FB^2)-.8*D:IFL=0 THEN PRINT " NEW":GOTO 60
101 PRINT:PRINT
110 PRINT " VENT LENGTH MM. ":(L:PRINT USING "###.###":L
111 PRINT " VENT AREA SQ.CM. ":(A:PRINT USING "###.###":A:7.85E-3*D^2
112 GOTO 150
130 FB=((2360*D^2)/(L+.8*D*VB))^0.5:PRINT:PRINT
140 PRINT " BOX FREQ. HZ ":(FB:PRINT USING "###.###":FB
150 PRINT " *****":PRINT:PRINT:FB=0
160 PRINT:PRINT:GOTO 50

```


WHAT DESTROYED

There were many factors behind the destruction of the space shuttle "Challenger". This article provides a fresh insight into the disaster. It probes the causes and describes how NASA might have better assessed the risks.

NASA, progenitor of American icons and keeper of the faith that man's destiny lies in the stars, is in trouble. It's not so much that, 73.621 seconds after launch on Jan. 28, the shuttle *Challenger* was destroyed by an horrific explosion that killed the spacecraft's seven occupants. Or that one of the victims was NASA's first "civilian" passenger, Christa McAuliffe, 37, a high school social studies teacher from Concord, N.H. As distressing as those facts are, even more damaging for NASA, which over the past 25 years has established an unmatched reputation for technical excellence, is that the explosion happened by surprise. All mechanics understand that machines aren't perfect; that's why good ones pride themselves on taking special care with things that might break.

And although other kinds of accidents involving machines — airplane crashes, for example — may result in more fatalities, the shuttle catastrophe had far greater significance. In the short term it resulted in a national upwelling of grief. In the long term it has broad political implications for the agency — and the space program. For some members of Congress, NASA offers the same satisfaction of buying exotic equipment that the Pentagon does, but without the bloody implications. For a president, NASA is a public relations mother lode; in Ronald Reagan's case, it allowed him, for example, to stake out a pro-education position by announcing that a teacher would be the first "civilian" in space, even while he slashed allocations for schooling. Although the public tends to ignore these less than noble relationships, they're potent. And if they sour, Washington will react in the traditional manner: cutting its losses in a way that could turn NASA into a second-class bureaucracy.

In assessing the damage, the engineering ques-

tions must come first, because it's in the answers to them that both the causes of the accident and NASA's level of responsibility for it will be found.

"Whenever a rocket goes up successfully, it's a miracle," says Robert Cooper, an engineer and businessman who until last summer directed the Pentagon's Defense Advanced Research Projects Agency. "I've been involved with launching hundreds of them — something always happens that makes you think they'll never work again."

That Cooper should still speak in religious terms about a process that most Americans have come to regard as the embodiment of high-tech maturity is an indication of how far out on a limb NASA went — or was driven — with a dangerous machine.

The presidential commission investigating the *Challenger* disaster hadn't reported its findings by this writing, but speculation, both before the committee and among engineers, on the cause of the accident had become focussed on the failure of the seal between the two aftmost sections of the shuttle's right solid-fuel booster. This 45.4 metre-long rocket, one of two that produce 1.5 million kilograms of thrust each, is an assemblage of eleven weld-free, circular steel casings about 3.7 metres in diameter that are joined into four segments. The 1.3cm thick segments are connected to one another by tongue-and-groove joints that are secured by 177 steel pins. If these joints aren't sealed properly, then gases from the propellant burning at 3,000 degrees C inside the booster can escape and cause catastrophic damage.

WHY build the booster in segments, which would seem to be a plumber's nightmare? "All big solid rocket boosters are done this way," says Cooper. "It's not possible to grow a propellant grain that's larger than a certain size and still


SPECIAL REPORT

The immediate cause of the disaster may have been a faulty seal, but a deeper reason may be that, because of economic and political pressures, NASA sacrificed safety standards

by WAYNE BIDDLE

CHALLENGER?


11:38:59.259



In this depiction of how the accident may have unfolded, fire erupts by the right booster's aft seal and burns away the attachment between the booster and the fuel tank.

11:39:12.8

The fire now encircling the booster burns away the attachment between the booster and the fuel tank.



11:39:13.631

Perhaps because the booster nose is now free to pivot into the tank, a vast explosion is set off in the tank.



11:39:14.0

The explosion, fueled by the highly volatile mix of hydrogen and oxygen in the tank, destroys the orbiter.




11:39:25.0

The wrecked *Challenger* disappears behind a ball of fire and a cloud of vapour, as the boosters fly on.

Paintings by John Berkey © "Discover Magazine" 4/86, Time Inc.


CHALLENGER'S FATAL FLAW



THE SPACE SHUTTLE

Challenger was propelled aloft by two solid-fuel booster rockets and the orbiter's three main engines, which were fuelled from a vast external tank. By the time the explosion occurred, the craft had completed its "roll sequence", so the crew in the two-deck cockpit were flying upside down.

Joseph Milioto (c) "Discover Magazine" 4/86, Time Inc.



HOW THE EXPLOSION MAY HAVE BEGUN

Under the stresses of ignition (1), putty protecting the aft seal of the right booster may have failed, opening a passage to the seal. Then hot gases from solid-fuel combustion could have breached the O-rings and burst through other seal components (2 and enlargement), with the seal failure continuing until flame circled the booster (3). Heat from this fire may have caused the fuel tank to explode.

Fluke. First Family of DMMs.



When accuracy, performance and value are important, professionals the world over look to Fluke — the first family of DMMs.

Reliable Fluke-quality 3½- or 4½-digit DMMs fit every need — from design engineering to industrial troubleshooting.

There's the low-cost 70 Series — the most DMM you can get for the money. The tough 20 Series — totally sealed and built to survive the dirtiest, grimeiest, roughest jobs. The reliable 8020B Series — made to withstand the rigors of the field service environment. The precise 8060A Series — the most powerful and complete test and measurement system available in a handheld package. And, of course, the versatile Bench/Portables that carry on the Fluke tradition for precision and durability in lab-quality bench instruments.

Fluke comes in first again with the world's largest selection of quality accessories to help extend the capabilities of your DMM even further.

There's no need to look anywhere else. Uncompromising Fluke design and leading edge technology are the reasons why attempts at imitation will never fool the millions of professionals that accept nothing less than a Fluke.

FROM THE WORLD LEADER
IN DIGITAL MULTIMETERS.



ELMEASCO **Instruments Pty. Ltd.**

N.S.W. 15 McDonald St, Mortlake. Tel: (02) 736 2888
VIC. 12 Maroondah Hwy, Ringwood. Tel: (03) 879 2322
QLD. 192 Evans Rd, Salisbury. Tel: (07) 875 1444
S.A. 241 Churchill Rd, Prospect. Tel: (08) 344 9000
W.A. 46-48 Kings Pk Rd, West Perth. Tel: (09) 481 1500

Talk to your local distributor about Fluke

• A.C.T. Actlec Pty Ltd (062) 80 6576 • George Brown 80 4355 • N.S.W. Ames Agency 699 4524 • George Brown (02) 519 5855 Newcastle 69 6399 • Bryan Catt Industries 526 2222 • D.G.E. Systems (049) 69 1625 • David Reid 267 1385 • W.F. Dixon (049) 61 5628 • Macelec (042) 29 1455 Ebsen 707 2111 • Selectro Parts 708 3244 • Geoff Wood 427 1676 • N. TERRITORY Thew & McCann (089) 84 4999 • QUEENSLAND L.E. Boughen 369 1277 • Colourview Wholesale 275 3188 • Fred Hoe & Sons 277 4311 • Nortek (077) 79 8600 • St Lucia Electronics 52 7466 • Selectro Parts (Qld) 394 2422 • S. AUSTRALIA Protronics 212 3111 • Trio Electrix 212 6235 • A.W.M. Wholesale • TASMANIA George Harvey (003) 31 6533, (002) 34 2233 • VICTORIA A.W.M. Electrical Wholesale • Radio Parts 329 7888 • G.B. Telespares 328 3371 • Browntronic 419 3986 • R.K.B. Agency 82 7704 • A.J. Ferguson 347 6688 • SIRS Sales (052) 78 1251 • Mektronics 690 4593 • W. AUSTRALIA Atkins Carlisle 321 0101 • Dobbie Instruments 276 8888 • Cairns Instrument Services 325 3144 • Willis Trading 470 1118

WHAT DESTROYED CHALLENGER?

guarantee uniformity." "Grow a propellant grain" is engineer-talk for the manufacturing process whereby chemicals — in this case a mixture of 70% ammonium perchlorate, 16% powdered aluminum, a binder called polybutadiene acrylic acid acrylonitrile terpolymer (12%), an epoxy curing agent (2%) and a trace of iron oxide — are poured into the steel segments. In the case of the shuttle's boosters, this propellant load is built up in about 40 pourings, then cured and groomed for uniformity. The segments are then stacked.

At least since 1980, NASA has recognised that the integrity of the seals between casing sections is a troublesome safety issue. For example, on a "critical items list" compiled by an agency analyst and dated Dec. 17, 1982 — after five successful shuttle missions — the potential effect of a seal failure was described with chilling terseness as "loss of mission, vehicle and crew due to metal erosion, burn-through, and probable case burst resulting in fire and deflagration." By April 1984 there was enough concern that NASA managers ordered a formal review of the sealing procedures.

There were good reasons for such scrutiny. Out of the first twelve shuttle flights, inspection of retrieved boosters had revealed four instances in which the first of two rubber gaskets, or O-rings, which are major components of these seals, had been partly burned away by propellant gases in the joint between the nozzle and the aft segment. After NASA began using a new type of putty to protect the joint, such O-ring erosion happened even more frequently — seven burnings occurred in the first four flights of 1985. More troubling was the discovery of damage to a secondary O-ring in a nozzle joint on flight 51-B, which was launched on April 29 last year.

NASA officials have also observed at least half a dozen damaged primary O-rings on seals between the booster segments. These gaskets are meant to be "dual redundant" to ensure the utmost safety — damage to both meant that the double barrier was being breached. NASA realised that redundancy couldn't be guaranteed, and it waived its fail-safe rule for the O-rings in 1983. This is the sort of seal that may have failed on *Challenger*.

Test data submitted on August 19, 1985 to NASA by Morton Thiokol Inc., the manufacturer of the boosters, indicated that from 330 to 600 milliseconds after the fuel was ignited at launch, there was a "high probability of no secondary seal capability." During the next two minutes, while the fuel burned itself out as the shuttle hurtled upward, "if erosion penetrates the primary O-ring seal, (there is) high probability of no secondary seal capability," Morton Thiokol warned.

Nonetheless, NASA's top engineers and managers judged that this flaw wasn't serious enough to halt or delay shuttle flights. "The current design must be improved," a NASA engineer advised

NASA's chief of propulsion systems in July 1985. "The long-term steps will require design and procedure changes that will require expensive qualification."

A launch chronology released by NASA showed that *Challenger's* right-hand booster emitted a puff of dark smoke from the vicinity of its aft casing joint at 0.445 seconds after ignition, indicating that the seal had failed. By the 2.147 second mark the smoke had billowed halfway across the booster and remained visible until about twelve seconds into launch. For the next 45 seconds or so, the shuttle system operated smoothly despite the presumably blown seal. The ascent into orbit is totally automated, with the shuttle "pilots" available for limited duty only in dire emergencies.

In this case, although the shuttle's sensors were recording information of relevance to the impending disaster, it was being stored as usual for later reference and not relayed directly to the crew or ground controllers. Even if someone had known about the blown seal, however, there's no escape from the shuttle while the solid-fuel rockets are firing.

At 58.774 seconds came the first sign that the right booster was about to fail — smoke from the casing just above its aft attachment to the vast liquid-fuel tank. This was about the time when pressure inside the booster began its normal rise after having fallen from the peak that occurs at ignition. At 59 seconds the shuttle experienced the maximum level of aerodynamic stress. At 59.249 seconds, an intense tongue of hot gas appeared on the booster casing, indicating that the seal had cracked wide open.

With propellant gas roiling from the side of the booster as well as out of its nozzle, internal pressure started to fall to below that of the left solid rocket, which was running properly. Sensors noticed this mismatch at 60.164 seconds, but it wasn't great enough yet to cause alarm. The boosters are never precisely alike, and some thrust deviation is expected.

BUT now the flow of gases through the seal crack was thrusting in a direction the spacecraft's structure couldn't tolerate. At 62.484 seconds, onboard computers commanded *Challenger's* right wing elevon to move as part of a vain effort to correct this imbalance. Another attempt to keep the flight path true came at 63.924 seconds, when the computers ordered the orbiter's right engine nozzle to pivot.

At about 66 seconds, other hot spots began to appear on the forward casings. At 67.684 seconds, sensors noticed a pressure glitch in the line feeding liquid oxygen from the external fuel tank to the orbiter's engines, suggesting that the tank was coming apart. At 73.175, a gas cloud suddenly appeared beside the tank, and then there was a flash between the orbiter and the tank's liquid hydrogen

Ominous data being recorded by the sensors wasn't being relayed to the shuttle's crew

WHAT DESTROYED CHALLENGER?

Budget and performance pressures may be more than NASA can withstand

chamber. The vehicle started to break up, with an explosion near the booster's forward attachment strut to the tank occurring at 73.226.

One theory about the cause of this explosion was propounded by *Aviation Week & Space Technology*, which hypothesized that heat from the fire had destroyed the aft attachment between the booster and the tank. The nose of the booster then pivoted to the left, piercing the thin skin of the tank.

At this point, as the shuttle stood on the edge of eternity, two poignant events took place — one demonstrating the durability of a machine, the other the instinct of a man. At 73.534 seconds, 87 hundredths of a second before all data ceased in a fireball, computers began to shut down the orbiter's engines because of overheated fuel pumps. A voice tape of the flight carries the sound of an explosion just before the end of transmissions at 73.621 seconds, meaning that Shuttle Commander Dick Scobee had probably turned on his microphone to ask controllers why the shuttle was jolting left and right.

The implications of a design change in a machine as complex as the shuttle are profound. There's no such thing as tinkering. Putting the system together took a decade of tests to certify not only every component but also the interplay among them. According to Richard Cook, a NASA budget analyst, it would take 13 months just to get redesigned casings back from the manufacturer once a new seal had been approved. Lawrence Mulloy, the shuttle project manager for solid-fuel boosters, says modification of the O-ring joint could take anywhere from four months to three years. "Merely qualifying a new putty for the joint — something that was under way before the *Challenger* accident because of the seal erosion and because the existing caulking contains asbestos and is hazardous to workers — would cost \$50 million", says Cook.

ACCORDING to documents released by the presidential commission, NASA had long been aware of how the case seal could fail. At the moment of booster ignition, rapid internal pressure build-up causes tiny blowholes through the zinc chromate putty that protects the joint from hot propellant gases. These holes permit unwanted pressurization of the empty cavity between the spot where the putty ends and the first O-ring, as well as direct erosion of that O-ring by the gases. Rotational stress at the joint during launch can unseat the gaskets.

The O-rings are made from a fluorocarbon elastomer, which has good resistance to high temperatures but not as much sealing resilience as other types of rubber. This lack of resilience worried members of the commission, because the cold at the time of *Challenger's* launch — 3.3 degrees C

versus 11 degrees for the previous coldest launch — could make the rubber stiffen. There were reports that during one of the commission's closed hearings, a high-level Morton Thiokol engineer had testified that he'd argued strenuously with company and NASA officials that *Challenger* shouldn't be launched because of the effects of cold on the O-rings. His views, however, weren't made known to those with the authority to scrub the lift-off. The commission also heard that on the morning of the launch temperature-sensing devices, which are of questionable reliability, had recorded surface readings on the right booster as low as -14 degrees C. The head of the shuttle program was never told of these readings.

More alarming than NASA's decision to send *Challenger* aloft in the cold was its failure to ensure that the above information reached its top officials. Though at this writing there was still substantial dispute among technical experts about what, if anything, the cold may have done to the O-rings, there was no doubt that the seals had long been a source of concern, and any information about them should have been given top priority. But NASA treated these warnings no more seriously than it had earlier ones from its engineers and Morton Thiokol.

In reaction to the evidence of seal erosion, Morton Thiokol submitted 43 design revisions for NASA's consideration last August. The company warned then that the joint that apparently led to *Challenger's* destruction "poses the greatest potential risk in that its secondary seal may not maintain metal contact". NASA was to have begun testing a modification of the backup seal this year, but decided to keep flying the shuttle in the meantime.

"If you fix something like this, you've got quite a range of cost implications," Cook told the commission, calling the process a "major budget hit".

That money was apparently a consideration in a safety debate is the most unsettling revelation of the aftermath of the *Challenger* disaster. Budget pressures have been a fact of life for the shuttle program since its birth in the early 1970s. Throughout the 1980s allocations for NASA have remained flat; as a result, the ever-rising costs of the shuttle program squeezed out much of the science and engineering research that's supposed to be the agency's main function. In 1984 NASA's Aerospace Safety Advisory Panel warned: "It is essential that the important objective of achieving a more cost-effective operation ... not be permitted to introduce unacceptable risks to the shuttle crew".

The panel's latest report, released on Feb. 12, contains no mention of the booster seals. Staff director Gilbert Roth says panel members heard testimony on the issue, but "must have been satisfied with agency work on the problem". The report does raise questions about whether proposed

lightweight boosters made from so-called composite materials, or plastics, would be able to withstand the stress of launch.

The prospective move to plastic casings reflects another pressure on the shuttle system — greater payload obtained by lowering the vehicle's weight — that the safety panel has repeatedly warned about. Before the sixth shuttle mission, each booster weighed about 83,915 kilograms when empty. Shaving the thickness of the steel casings by 0.5 to 1 millimetre brought the weight down to 82,100 kilograms. Since higher-performance rocket motors were also added beginning with the eighth mission, the net effect was to increase the amount of cargo the shuttle can haul.

The same dictum — less weight, more cargo — has been applied to the other two primary shuttle components, the external liquid-fuel tank and the orbiter. With its sixth mission, the shuttle began to use a tank that, at 30,300 kilograms, was 4,128 kilograms lighter than its predecessors. The reduction was accomplished by getting rid of structural stiffeners, modifying internal frames and milling the tank walls thinner. Also, a lighter and cheaper titanium alloy was used in the tank's aft attachment struts to the solid-fuel boosters.

As for the orbiter, stresses in early flights were higher than predicted. In the first five missions the predicted limit of strain on the orbiter wings was exceeded 63 times during ascent and 41 during descent. NASA therefore had to reinforce the lighter wings of the third and fourth orbiters (*Discovery* and *Atlantis*) in 1984.

PUT simply, budget and performance pressures on the shuttle may have added up to more than the program could stand and still maintain adequate margins of flight safety. If so, then failure of a booster was just one of several catastrophes waiting to happen.

The NASA safety panel reports point to the strongest candidates. Last year, for example, the panel was especially critical of the orbiter's three liquid-fuel rocket engines. They've fallen short of the power levels they were expected to provide, and they have a voracious appetite for spare parts.

Still, the engines represent a considerable accomplishment; their most glorious feature is that they can be ignited, throttled up and down, extinguished, and restarted. No other rocket has ever been capable of this. Each engine produces 178,625 kilograms of thrust at 104 percent of rated power, the peak level during each mission so far. The two turbopumps that make it possible to get so much power out of such small engines are each the size of a trash can, yet each delivers the equivalent of 3.3 million kilowatts (five million horsepower).

The engines were supposed to last for 55 missions without extensive refurbishment. But the turbopumps have been far less durable than planned,



NASA's hubris may have been exposed by its decision to take "civilians" on the shuttle


and have sometimes had to be replaced after just two flights. Moreover, the engines haven't been cleared for routine use at 109 per cent of rated power, which is badly needed for carrying some military payloads into polar orbit. "The accumulated data on turbomachinery has made it amply clear that the engine is being operated near the upper limits tolerable to the design", the panel warned.

The proceedings of the safety panel, along with the internal documents released since the *Challenger* investigation began, seem to show that NASA was aware of how dangerous its spacecraft was. The outstanding question is why the program kept accelerating in the face of this information — more flights, less turnaround time, fewer dollars for engineering development. Small wonder the commission said the decision to launch *Challenger* may have been "flawed", and ordered that any NASA official involved in that decision not be allowed to participate in the post-mortem.


"I just hope that people realise that these things are all judgment issues," says Cooper in NASA's defense. "Every one of them has to be judged on its merit and with the knowledge the engineers have about how things fail. You do it every time you launch, every time you design a new system. It's a risky business".

RISKY business is what test pilots thrive on. But NASA's fatal hubris may have been most clearly exposed in the decision — or in acquiescence to a presidential suggestion — to take members of Congress, teachers, and journalists aboard. The image of Christa McAuliffe in orbit, teaching rapt children on earth, somehow became stronger to NASA than the engineers' knowledge of how things fail. What's left is an equation between imagery and substance that NASA will struggle to balance for years to come.

Reprinted by arrangement © "Discover Magazine" 4/86, Time Inc.



The Serviceman



A wink is as good as a nod...

A serviceman's problems are not always purely technical. Particularly where warranty jobs are concerned, one often has to make a decision as to whether a claim can be justified. And, while most such cases are fairly clear cut, there is always the odd one about which there is an element of doubt. These can cause a certain amount of worry, especially where a substantial sum of money is involved.

My main story this month concerns just such a decision and, even now, there may be some doubt as to whether I made the right one. On the other hand, the customer is delighted and the company concerned has accepted the situation, so it is only my conscience that seems to be worried. And no nasty remarks about servicemen having no conscience!

The appliance involved was an AWA/Mitsubishi colour TV set type C6334, fitted with an MV100 series chassis. It was nearly four years old when this latest incident occurred — a matter of some importance, as we shall see — but I had made one previous service call to it, under warranty, when it was about two years old.

On that occasion the customer had complained of poor colour and a visit to his home confirmed that all was not well. More specifically, turning down the colour revealed a distinct greenish tinge. I pulled the back off and went through the colour balance/grey scale procedure, and this produced a first class picture. This point is of some importance in regard to later events, but it should be noted that both the customer, who is quite fussy about picture quality, and myself examined the picture most carefully before mutually agreeing that it was virtually perfect.

When the customer complained more recently it was in somewhat similar terms, ie, poor picture quality, but he went on to say that he thought the picture tube might be on the way out. Re-

calling the previous problem I was more inclined to think that it might be nothing more than another shift in colour, and which could be fixed in the same way.

Different symptoms

In fact, the symptoms turned out to be quite different. The first thing I noticed, as the tube warmed up and for several seconds afterwards, was that the overall picture quality, or definition, was extremely poor. Even though this cleared fairly rapidly, my first reaction was that the tube might be gassy. Thermionic devices in general may suffer in this way, in that the gas which has seeped in during the off period will affect performance at turn-on and until it has been burnt off by the heat of the cathode, and at some cost to cathode life.

On the other hand, I considered that it could be simply weakened cathodes which were taking more time than usual to reach full emission. Or it could be both, one being the fault of the other. But this was incidental to the customer's complaint. As he pointed out, wherever the picture contained a substantial area of red, particularly if it was saturated, the colour would smear to the right. The customer agreed that it had not been in evidence when I serviced the set previously, but went on to say that it had first been noticed some time after that, in a very mild degree, and had become progressively worse.

So everything pointed to a picture tube which was on the way out, and with only a few months warranty left. Nevertheless, I wasn't prepared to rush in and claim a new tube until I had exhausted any other likely possibilities. The Christmas break intervened at that stage, so I left the set with the customer for the time being. With the Christmas rush over and as soon as I could organise a loan set, I brought the faulty set back to the shop.

It produced the same symptoms on the bench as I had already observed, including the sluggish behaviour at warm-up. I gave the tube and associated drive circuits a thorough voltage check, determined to make sure that there was nothing wrong with the tube operating conditions which would contribute to either symptom. This included the tube heater voltage which, being derived from a winding on the EHT transformer, cannot be measured accurately with an ordinary multimeter.

But I could find nothing wrong. I let the set run on the bench for several days, mainly to convince myself that the red smear was really serious enough to justify a claim, if it came to that. The point was that, subjectively, the effect varied with picture content. On dilute colours, such as light studio flesh tones — news readers etc — it was possible to find an acceptable compromise colour control setting, whereby the effect was hardly noticeable.

But if such a scene was followed by one containing a highly saturated red, the smear effect was quite objectionable. Again, it could be minimised by resetting the colour control, but only at the expense of adequate colour saturation, which would become most evident when the picture reverted to the studio news reader scene. In broader terms, any aberration which calls for that kind of control juggling cannot be tolerated.

Finally, after I had tried every trick I could think of, and drawn a complete blank, I decided it was time to call for help. I rang the AWA service department and spoke to a staff member who had proved most helpful in the past. Having outlined the problem my first question was whether they had ever en-

countered anything like this smear problem and, if so, whether it was likely to be a picture tube fault.

The answer was quite definite; they had never seen anything like the problem as I described it and were quite unable to say whether it was likely to be a tube problem or not. Next question: in view of my suspicions about the tube, in regard to both the red smear and the sluggish warm-up characteristic, would they consider replacing the tube under warranty?

The reply was a little more subtle this time. "From what you tell me, the warranty on the tube has almost expired. If you want to make a claim, you ought to make it without too much delay."

Well, I reckon I'm old enough to recognise that a twitch of the eyelid is as good as a slight inclination of the cranium in the direction of an equine quadruped devoid of its visionary capacity*. I took the hint and ordered a replacement tube under warranty.

This duly arrived and I set about fitting it to the set. That done, the next thing was convergence and colour balance adjustment. I concentrated on the convergence first, and deliberately avoided touching any of the colour balance adjustments. The convergence routine is rather tricky on this model set, being essentially mechanical, and involves juggling the scan coils around the tube neck and wedging them in place.

That done, I was able to confirm what I had already begun to suspect; with the colour turned off there was a marked colour cast in the picture. This was unusual in the circumstances or, at any rate, it would have been unusual had the original tube been in first class condition. On the other hand, it is quite common in cases where a tube has been flogged as long as possible with repeated colour balance adjustments. All of which seemed to confirm that, red smear aside, there was something suspicious about the original tube.

But that was somewhat academic at this stage because, after I had completed all the adjustments, and was able to take a long hard look at the end result, I was forced to the realisation that the red smear was still in evidence. I couldn't be sure, on a purely subjective basis, whether it was as bad as before, and rather imagined that it wasn't. However, that was probably wishful thinking because, after living with the set for a few days, I concluded that it was much the same as before.

So where did we go from here? My only previous experience with a colour smear problem anything like this in-

volved a Philips model for which a modification had been issued for the red driver stage. While this was a design problem, rather than a fault, recalling it set me wondering as to whether there could be a fault in this red driver stage, such as the transistor, Q651, a 2SC2688.

I had no spare of this type in stock but, fortunately, it was a simple matter to swap the red unit with one of the others. The only good point about this exercise was that the result was completely conclusive; no difference to the red performance whatsoever. So that squashed that theory. After that I spent a lot of time with the colour bar generator and the CRO trying to analyse where and how the effect was occurring. Unfortunately, it all proved fruitless.

In desperation I rang the AWA service department again, re-stated the problem, detailed all the things I had tried so far, and asked for any suggestions. They had no specific suggestions to offer, but we chewed the fat over the problem for some time, discussing and discarding several possibilities. The upshot was that we moved our thinking back to chip LC601, an M51393P. This is a 30 pin unit which performs a variety of functions, including sync separator, R-Y, B-Y demodulator, various amplifying and clamping functions, plus the matrix providing the signals to the red, green, and blue driver stages.

In particular, I was anxious to find out whether there was any history of trouble with this chip, either in general terms or in regard to this specific fault. The answer was no; it had been a particularly reliable device. So that was that, except that I promised to let them know when, and if, I found the fault.

A long shot

I went back to the circuit, thought about all the things I had tried, and finally admitted that I would have to change the chip, if only to prove the point one way or the other. The truth is I had skirted around this idea for as long as possible, if only because unsoldering a 30-pin IC is not something I undertake lightly. This the more so because, judging by its history, it seemed like a long shot.

Nevertheless, I ordered a replacement and, when it arrived, set to with the solder sucker and removed the existing one. Then I fitted the new one, crossed my fingers, and switched on. And lo and behold, that was the answer. The set produced a perfect picture, with all signs of red smear completely eliminated. In fact, it was only then that I rea-

Looking to purchase instruments

We are stockists of Hitachi, Fluke, Trio, Goodwill, Meguro, Aaron and Kikusui: so if you're in the market for an oscilloscope, think of David Reid.

ESCORT MULTIMETERS

EDM 1105 \$75.00

- 3 1/2 digits. • Six functions: DCV, ACV, DCA, ACA, OHM, Diode Testing.
- 0.8% basic DC accuracy.

EDM 1116 \$100.00

- New model complete with transistor and capacitor tester.

EDM 1118 \$119.00

- 3 1/2 digits with DB range

EDM 1125 \$108.00

- 3 1/2 digits. • Seven functions: DCV, ACV, DCA, ACA, OHM, Diode Testing, Audible Continuity.
- 0.25% basic DC accuracy.

EDM 1135 \$140.00

- 3 1/2 digits. • Eight functions: DCV, ACV, DCA, ACA, OHM, Diode Testing, Audible Continuity.
- 0.1% basic DC accuracy.

EDM 1346 \$225.00

- 4 1/2 digits. • Eight functions: DCV, ACV, DCA, ACA, OHM, Audible Continuity Testing, Diode Testing, Data Hold.
- 0.05% basic DC accuracy.

All multimeters + 20% Sales Tax

Ring us first for your 20 Meg. Oscilloscope enquiries!

NEW GOS-522

1 YEAR

WARRANTY!

FEATURES

- * Large 6 inch rectangular internal graticule CRT
 - * CH1 & CH2 ALT Triggering (Alternate triggering function)
 - * High Sensitivity 1mV/div
 - * Hold-off function
 - * TV Sync. Separation circuit
 - * CH1 Signal output
- Plus 2 probes included in this deal.

\$730.00

+ 20% TAX

Check out our kit range!

Here's two to have a go at —

Megohm Meter

It uses a transistor inverter to produce a regulated 1000V DC supply which is applied to the insulation under test. Insulation resistances between 20M Ohm and more than 2000 Ohm can be measured. K 2500 (See EA July '85).

\$59.00

8 SECTOR ALARM SYSTEM KIT

Features:

- Alarm has 8 separate input circuits — 8 sectors can be monitored independently.
- Each input circuit is provided with an indicator LED and a sector On/Off switch.
- Individual sector isolation allows the user to have some areas of the premises habited while others remain protected e.g. Inside Off/Outside On.
- Inputs accept both normally closed and normally open sensors.
- Two inputs provided with an entry delay between 10-75 seconds).
- Internal trip warning buzzer — alerts owner/occupant of pending alarm operation — great for the "forgetful" amongst us. This buzzer is pre-settable between 5 and 55 seconds prior to Alarm.
- Unique circuit detects automatically when any N/O or N/C loops are either open circuit or dead short. e.g. someone trying to bridge reed switches etc.
- Switched output can be used to send a silent alarm through an auto-dialler circuit or similar.

K 1900 (without Back up Battery) \$139.50
S 5065 (12V 1.2AH Backup Battery) \$22.95


These are just a few of the many 100's of up-to-date Electronic items on display at:



DAVID REID ELECTRONICS LIMITED

127 York Street, Sydney, 2000
or Telephone (02) 267 1385

Twelve months in
and you could still b



some other career fetching the coffees.

In many careers, being an enthusiastic young man can be a liability.

Before you're given any responsibility, you're asked to prove yourself responsible.

You have to acquit yourself on complex tasks such as remembering that Mr Brown now takes his cuppa black with one sugar. (It used to be two with milk, but now he's on a diet.)

In the Royal Australian Air Force, however, we look at bright young men in quite a different light.

The very fact that you're young means your reaction times should be quicker.

You should be fitter. And your concentration is less likely to be impaired by things like mortgages.

In short, if you meet our selection requirements, we consider you're ready to start right at the very top.

Aircrew.

Granted, those requirements are tough.

For Pilots and Navigators, they're good passes in English, Maths and Physics at Year 12. You must also be between 17 and 27.

To be an Airborne Electronics Analyst, you must be at least 17 and have completed Year 11 with good passes in similar subjects.

Naturally, you must also be an Australian citizen, or eligible to become one.

From here on, the selection process gets a little harder.

We put you through several rounds of tests which rate both your physical and psychological fitness.

Your aptitude for flying and so forth.

Pass them and you'll land yourself in possibly one of the most exciting and rewarding careers imaginable.

There are new FA-18 Hornets that need Fighter Pilots.

Strike/reconnaissance F111s that require Navigators. And P3C Orion maritime surveillance squadrons that are short on AEAs.

And they're just three of the 17 types of aircraft currently in service with the RAAF that need men. Men like yourself.

After around 52 weeks of flying training, you'll be posted to an operational squadron.

And you'll be flying.

While most of your contemporaries have probably only just graduated to fetching Mr Brown's lunches.



To: RAAF Careers, GPO Box XYZ (in the Capital City nearest you).

Name _____

Address _____

Postcode _____

Telephone _____

Date of Birth _____

Highest Educ. level attained or being studied _____

Or phone an RAAF Careers Adviser on Adelaide 2121455. Albury 218277. Bendigo 43 8008. Brisbane 226 2626. Canberra 57 2311. Geelong 211588. Hobart 34 7077. Launceston 311005. Melbourne 697 9755. Newcastle 26 3011. Parramatta 635 1511. Perth 325 6222. Sydney 219 5555. Townsville 72 4566. Wollongong 28 1855.

AIRCREW.  RAAF

The Serviceman

lised just how irritating the original condition had been.

So that was that as far as the job itself was concerned, but not quite the end of the story. One of the first things I did was contact the technician in the AWA service department and tell him what I had found. He was just as surprised as I was, but thankful for the advice which, hopefully, may help someone else with a similar problem.

The next question, in my own mind, concerned the kind of fault in the IC which would cause this effect. The best suggestion I can offer is that, whatever the actual defect, it resulted in poor frequency response and/or phase shift in the red channel out of the matrix. Unfortunately, it would probably take a fairly elaborate laboratory set-up to confirm this theory. Suffice it to say that we now know that this fault can occur in this chip.

And finally, there is the question I raised at the beginning; was I justified in replacing the tube under warranty? While granting that the smear turned out to be a red herring — Ouch! Sorry about that — I am still convinced that the tube was sick; either gassy and/or suffering from falling emission. Maybe, assuming the smear fault had been fixed first, we could have flogged it along for a while longer, but I seriously doubt whether it would have enjoyed a typical life span.

So, all things considered, I feel that the customer was entitled to a new tube. On the other hand I didn't make the decision lightly and, if faced with a similar situation again, I would be just as cautious.

And now, if all the foregoing seems rather profound, here is something in a lighter vein. It is from one of my regular contributors, J.L. of Tasmania, and he calls it:

The things people do

From time to time the Serviceman has related some of the crazy things his customers have done to various pieces of equipment. Each of us has his own favourite twit; one that keeps us in jam money, but not everyone is game enough to write about them. I'm game, so here are some of the zany tales from my patch.

Like the one about the HMV 12613 colour TV set that came in this morning. It had a small red raster and distorted sound. The owner said "It just

went like that last night", but I wondered.

Once inside the cabinet, I found that the horizontal adjustment slug had been screwed right out of the horizontal coil and the adjustment rod twisted until it broke. Then Mr Somebody had similarly broken the rod from the vertical hold trimpot.

Unable to get any more adjustment from the vertical hold, he put a screwdriver into the trimpot and twisted that until it broke. The height and linearity trim pots were accessible from outside the set, so they got the same treatment.

When none of his brutality produced any useful results, Mr Somebody must have removed the back cover and had a go at the screen adjusting pots on the tube base and the drive and sub-brightness trim pots on the chrome board.

When he had reduced an otherwise normal picture to the small red raster mentioned earlier, he decided that maybe I would be better able to fix whatever had started him on his destructive rampage.

After I had replaced the broken trim pots and put everything back to where it should have been, the set gave quite a good picture and seems not to have needed any real repairs in the first place. Like I said, money for jam!

Little glass valves

Something similar befell an AWA video recorder, model AV20. The owner arrived at tea time one Sunday evening and asked if I had one of those "little glass valves" for a VCR. The little glass valve turned out to be a fuse, a

1A delay type to be exact.

Now, fuses are not considered a user replaceable part in modern video recorders so I questioned him as to what had happened. You won't believe this!

It seems that his son was watching a rock'n'roll video and decided that the music was playing slow. From that, he deduced that the tape must be running slow, because the motor wasn't getting enough power. So he would give it some more.

He unscrewed the cover over the mains voltage adjustment and repositioned the plug at 110V. When he switched on there was a 'phutt' from inside the machine and "it didn't go any more". I can't imagine by what logic he arrived at the idea to readjust the mains voltage, but he sure gave the motor more power.

Anyway, Dad somehow decided that a fuse had gone so he took the cover off the machine and started poking around inside. He must have pretty sharp eyes because he spotted the blown fuse and tried to replace it with a 20A variety from his car. Fortunately, it wouldn't fit so that's when he came round to me. I had a suitable fuse, charged him for it, and he went off quite happily.


He was back next morning with the recorder wrapped in a blanket under his arm. When he unfolded the blanket I nearly cried. He had not bothered to put the cover back before wrapping it up and there were bits of blanket fluff all over the machine. This bloke was more than one sandwich short of a picnic.

Well, to shorten a long story, I decided that the job was really beyond me so I took it into town, to one of my more expert colleagues. It took him some time to find the fault which turned out to be one of those new fangled "solid state fuses" in one of the 12V supply rails. (It's a pity those things couldn't be made to change colour when they blow. They would then be a lot easier to find.)

Once the machine was running again, it was given a good going over and it was found to be running slow. So the young fellow had been right all along. A complete alignment of the capstan and drum servos put the machine back into first class order. But it cost the owner a lot more than one fuse to get it back again.

Vintage Jaguar

Another videorecorder story was less expensive for the owner but goes to show where some people place their pri-



orities. This time an old but beautifully restored vintage Jaguar rolled up to the workshop. The owner unfolded himself from under the wheel and lifted an early model National top-loading VCR from the seat beside him.

In the workshop he showed me that the machine would accept a cassette, but then would do nothing with it. It wouldn't play, nor would it fast forward or rewind. It was even reluctant to give back the cassette. It would only open up after some gentle prodding with a screwdriver.

On the bench, I first removed the cassette holder cover, then the rest of the cabinet top. Once this was clear, the cause of the trouble was revealed. It was a beautifully detailed model vintage Jaguar car, about 10cm long.

It had fallen, or been pushed, in through the cassette carrier opening, and had lain among the works in such a position that it would stop things working without damaging them. It was the work of a moment to remove the model and check that the machine was now fully functional.

The surprising thing about this whole episode was the reaction of the owner. He seemed to care nothing about the recorder and the fact that it was undamaged. He was more distressed that his now recovered model car might have been scratched among the rods and levers in the VCR.

He seemed to value a plastic model car more highly than an expensive videorecorder and what he was going to do to that (expletive deleted) son of his when he got home was nobody's business.

I don't know! It takes all kinds . . .

The insurance fraud

Then there was something very funny (peculiar) about another job that came my way some months ago. It was a late model Pye stereogram and came in after a week of very heavy rain that flooded many homes in low lying areas.

The story that went with the Pye was that the basement rumpus room had been flooded and in the rush to move as much as possible upstairs the stereo had been dropped. The plate glass doors had been broken, the turntable had come loose and there were sundry other minor problems. The main worry was that the unit would not work at all now.

I was to give an estimate of the cost of repairs so that a claim could be made on insurance. This wasn't unreasonable at the time because we had been through a pretty harrowing period. But

I changed my mind once I got inside the cabinet.

First up, there was no power in the set. I checked the fuse and found this OK so next I tried to check the transformer primary winding resistance from the power plug. There was no continuity because the transformer was wired between the neutral and earth pins. And yes, the active pin went to chassis.

Now there was no way this could have happened during a panic rescue from a flood, so I rang the owner and said, "What's goin' on?" "Oh, it's all right," he said. "When it wouldn't work after the flood, my mate had a look at it and fixed the plug for me."

I then asked if they had tried to use it after his mate's "fix" and, so help me, he said "Yes, the wife tried to play a cassette and it threw her across the room. That's when I decided that perhaps you had better have a look at it."

I told him there'd be no insurance claim on my reading of the facts and that if he wanted it repaired it would be at his own expense. In fact, the power transformer has an open circuit primary and the stereo output chip is shorted. I really wonder if it was in danger of being flooded. Or was the flood being used to get a cheap repair?

The four oddballs featured here are four out of many hundreds of regular customers. Fortunately, most people are perfectly normal and treat their audio gear, TV sets, and VCRs with respect. But somehow, they don't make such interesting reading.

Thank you J.L. for a most interesting contribution. I reckon those four will take some beating. As you suggest, the percentage of weirdos is small but, by crikey, what they lack in numbers they make up for in eccentricity. **EA**

**Translation: a wink is as good as a nod to a blind horse.*

TETIA Fault of the Month Philips K9 Chassis


Symptom: Two or three retrace lines at top of screen. No change when the height or linearity controls are adjusted.

Cure: C572 (100uF, 40V electro) open circuit. This cap forms part of the blanking network rather than the linearity circuit.

This information is supplied by courtesy of the Tasmanian branch of The Electronic Technicians' Institute of Australia. Contributions should be sent to J. Lawler, 16 Adina St, Geilston Bay, Tas. 7015.


Cash More Sound

☆ ☆ ☆ ☆
**SOUND SYSTEMS
DISCOTHEQUE'S & LIGHTING**



pin spots

12"-18"-20" + oval mirror balls



STAGE CONTROLLER
4 x 1000 watt sound to light chaser inbuilt mic



SOUNDCENTRE DISCOTHEQUE CONSOLE
200 x 200 watt inbuilt amplifiers
JVC — National D/Drive T/Tables —
cassette deck — 2 mic inputs W/V/oride
tape & aux in-out carpet covered.



4 arm spinners

cosmo balls



Strobes

Ropelights 30ft 4 colours

- * 18-lamp bar rotator
- * projectors * fuzz lites
- * fog machines * scanners
- * colourer par 30 lamps
- * light boxes * mics-stands

Manufacturers of speaker cabinets discotheque consoles — rope lights chasers etc.

For your entertainment needs contact: —

CASH-MORE SOUND

or visit the showrooms:

354 LIVERPOOL RD, ASHFIELD, NSW 2131
TELEPHONE: (02) 798 6782 TLX: AA74549

**REHERSAL STUDIOS AVAILABLE
HIRE — SALES — INST — SERVICE**

Build this:

High-power HF Linear Amplifier

Most high-power HF linear amplifiers cost an arm and a leg. This one costs around \$300, boasts a power output of up to 150W PEP, and includes switchable output filters.

by GREG SWAIN

If you've having trouble making some of those distant QSOs (contacts) or just want more power for your HF rig, this new HF Linear Amplifier is the answer. Installed between your rig and the antenna, it will boost your power output by 10-14dB — up to a maximum of 150W PEP (peak envelope power) in fact!

This unit can be used on any HF amateur band between 1.8 and 30MHz and will pump out a good clean signal with better than 30dB rejection of unwanted harmonics. That's made possible by the use of switchable low pass filters, a feature often missing from commercial linear amplifiers.



The completed HF linear amplifier —150W PEP and switchable output filters.

In fact, some commercial units deliver a third harmonic content that's almost as strong as the primary frequency. Such units represent a significant potential source of radio frequency interference (RFI).

How much input power can you feed into the new linear amplifier? Answer: you can use any HF transceiver with a power output of up to 15W CW (30W PEP). The only proviso is that a 2:1 attenuator must be included during construction for transceivers in the 10-15W range.

Figs.1 and 2 plot the performance of the unit. As can be seen from Fig.1, the output power is generally better than 110W for an input of 10W from 1.8 to 24MHz. Above that figure, the power output drops due to the ferrite material used in the input and output transformers.

Even so, a power output of about 50W is still available at 28MHz for 10W input.

Let's now take a look at the front panel. There are just three operating controls: an on/off switch; a switch to select between AM and SSB operating modes; and the band filter switch. A power LED, an on-air LED and a power meter complete the front panel line-up.

The rear panel carries the input and output sockets.

Inside the amplifier are two relays which switch the unit in and out of circuit. When power is applied (ie, the on/off switch is in the 'on' position), the amplifier is switched into circuit by the relays whenever the press-to-talk (PTT) button on the transceiver is pressed.

When the PTT button is subsequently released, the amplifier is switched out of circuit and the relay contacts now connect the transceiver output "straight through"




Fig.1: output power vs. frequency (10W drive).




Fig.2: power out vs. power in for 7MHz and 24.8MHz.

to the antenna socket (on the back of the amplifier).

Finally, in addition to all of the above features, the unit is virtually "bullet-proof". It is protected against reverse battery connection and battery overvoltage; it automatically shuts down in the event of RF overdrive; and it shuts down if the antenna SWR becomes excessive (eg, if the antenna lead goes open circuit).

How it works

Fig.3 shows the circuit diagram. It looks complicated but can be broken down into four easily understood sections: a power booster (Q101 and Q102); a low-pass filter circuit; a VSWR-cum-power indicator circuit; and a carrier operated relay circuit.

The booster is based on two 2SC2290 RF power transistors arranged in a standard push-pull design and operating in class B mode.

Starting at the input, the RF signal from the transceiver is fed via relay contacts RL2a to the 2:1 attenuator network and thence to transformer T1. This scales the input impedance down by 16:1, from 50 ohms to around three ohms, to drive the power transistors (Q101 and Q102).

Base bias for the power transistors is provided by Q103 which is configured as a diode. Because it is thermally coupled to the heatsink, this arrangement also prevents thermal runaway of the power devices. The hotter the heatsink becomes due to dissipation in Q101 and Q102, the hotter Q103 becomes.

And the hotter Q103 becomes, the lower the voltage across it and therefore the lower the bias on the power transistors. Q101 and Q102 are thus automati-

cally throttled back as the heatsink temperature rises.

Resistor R7 limits the bias current to about 100mA per device, while capacitors C107-C113 provide supply decoupling. Inductor L101 is designed to filter out RF in the bias supply to Q101 and Q102.

The collector outputs of the power transistors drive output transformer T2. This transformer steps up the output voltage and, in turn, drives the following low-pass filter stage. Trimmer capacitor TC101 and parallel capacitor C106 tune the output transformer primary to give maximum power transfer and to guard against output stage oscillation.

Negative feedback for the booster is derived from a single winding on the output transformer secondary and is applied to the bases of Q101 and Q102 via series RC networks. This helps maintain a low VSWR across the input transformer and also helps compensate for gain variations over the 1.8-30MHz range.

The low-pass filter stage consists of six independent sections arranged in stand-

ard Chebyshev configuration (L2-L13 and C14 to C41). The -3dB cutoff frequencies are listed in Table 1. Double-pole switch S3 selects the required filter and couples the RF energy to the following VSWR-cum-power indicator stage.

VSWR/power indicator

The VSWR/power meter is fairly conventional. It employs a current transformer consisting of a centre-tapped secondary wound on a toroid, with the primary being a heavy gauge conductor through the middle. Diodes D10 and D11 rectify the voltage developed across L1 due to the forward power. The resultant DC signal is then applied to the meter movement via calibration trimpot VR1.

Trimmer capacitor TC1 is used to peak the circuit for a maximum reading on the meter.


Similarly, D12 and D13 rectify the voltage developed across L1 due to the reflected power. This signal is then applied via VR2 and R17 to the gate of SCR1 in the carrier operated relay circuit. More on this later.

TABLE 1

Band	-3dB Fc	Suitable For:
160 metres	2.5MHz	1.8 - 1.86MHz
80 metres	5MHz	3.5 - 3.8MHz
40 metres	10MHz	7 - 7.3MHz
20-30 metres	17MHz	10.1 - 14.35MHz
14-16 metres	26MHz	18 - 21.45MHz
10 metres	31MHz	28 - 29.7MHz

Table 1: 3dB cutoff frequencies for the filter switch settings.

HF Linear Amplifier



View inside the prototype. The RF transistors are bolted directly to the heatsink.

Carrier operated relay

Q1, Q3 and Q4 form the relay switching circuit. This switches the amplifier into circuit on transmit, and switches the amplifier out of circuit during receive. Ignore Q2 and the two SCRs for the time being — they're in the protection business.

Here's how the circuit works: During receive, Q1 and Q3 are off. Thus, relay driver transistor Q4 is also off and the transceiver is connected directly to the output socket via relay contacts RL2a and RL2b.

When the transmit button is pressed, part of the signal passes via C1 to a diode pump consisting of D1 and D2. This charges C2 and provides base bias for Q1 which turns on. Thus, Q3 and relay driver Q4 also turn on and so power is applied to the amplifier circuit and to the on-air LED (D15) via relay contacts RL1a.

At the same time, power is also applied to RL2 which turns on and switches the amplifier into circuit.

When the transmit button is released, the relays remain on for a short time until C3 charges sufficiently to turn Q3 (and thus Q4) off. Switch S2 considerably extends the relay dropout time for SSB and CW by switching out R3. This is necessary to prevent relay chatter since there is no carrier in SSB mode and only an intermittent carrier in CW mode.

Protection

The remaining components shut the circuit down if there is excessive VSWR, RF overdrive or excessive supply voltage. Let's look at the VSWR protection circuit first. This consists of Q2 and SCR1.

As described previously, the output from the reverse side of the VSWR circuit is connected via R17 to the gate of SCR1. Normally, both Q2 and SCR1 are off but if the VSWR signal becomes excessive, the SCR turns on and provides base current for Q2. This turns Q2 on and Q3, Q4 and the relays off, thereby switching the booster out of circuit.

Q2 and SCR2 work in exactly the same


way to protect the booster from RF overdrive. In this case, RF energy from the transceiver is first applied to a voltage divider consisting of R11 and R12. D9 then rectifies the divider output and charges C6. The higher the RF drive, the higher the voltage across C6.

This voltage is sampled by VR3 and applied to the gate of SCR2. If the RF drives becomes excessive, the voltage across C6 rises and the SCR is triggered into conduction. As before, this turns Q2 on and the relays off.

Trimpot VR3 sets the drive level at which the circuit trips. It can be set to any desired level up to a maximum of 15W. Note that the SCR1 and SCR2 protection circuits can only be reset by turning the power switch off for several seconds and then on again.

Zener diode D3 provides protection against excessive supply voltage. Because the supply voltage is usually around

Fig.3: the circuit uses two RF transistors, Q101 and Q102, operating a standard class B push-pull mode.



HF LINEAR AMPLIFIER

PARTS LIST Booster PCB

Semiconductors

Q101, Q102 — 2SC2290 RF power transistors
Q103 — TIP31B NPN power transistor

Capacitors

C101 — 270pF dipped mica DM-15 series, 500V
C102, C103 — 560pF dipped mica DM-15 series, 500V
C104, C105 — 390pF dipped mica DM-15 series, 500V
C106 — 750pF
C107 — 1uF metallised polyester
C108 — .001uF dipped mica DM-16 series, 500V
C109 — 470uF 25VW axial mounting electrolytic
C110 — .01uF dipped mica DM-15 series, 500V
C111, C112 — 0.1uF ceramic
C113 — 10uF 25VW PC-mounting electrolytic
TC101 — 450pF trimmer, GMC31000 Sprague

Resistors (5%, non-inductive)

R101, R102, R103, R104 — 10 ohms 2W
R105, R106, R108, R109 — 10 ohms 5W
R107 — 33 ohms 5W
R110, R111 — 220 ohms 2W

Miscellaneous

2 ferrite beads
6 F16 ferrite cores
1 PCB, ZA-1500
1 5-lug tag strip
1 600mm x 2mm insulated hookup wire
1 300mm x 1.6mm tinned copper wire
4 PCB transformer end pieces
4 3mm spacers
4 3mm x 12mm bolts
5 3mm x 7mm bolts
1 150mm x 2mm spaghetti insulation

1 TOP-66 mica insulating washer
1 3mm bush insulator
1 10 x 10cm copper shim
1 heatsink compound

Carrier operated relay PCB

Semiconductor

Q1, Q4 — BC337 NPN transistor
Q2, Q3 — DS557 PNP transistor
D1, D2, D9, D10, D11, D12, D13 — 1N914 diode

D3 — 15V zener diode
D4 — 3.3V zener diode
D5, D6, D7, D8 — 1N4002 diode
D14 — large red LED plus mounting bezel
D15 — large green LED plus mounting bezel

SCR1, SCR2 — C103B SCR

Capacitors

C1 — 39pF ceramic
C2 — 0.1uF ceramic
C3 — 10uF 25VW tantalum
C4 — .001uF ceramic
C5 — 220uF 25VW PC-mounting electrolytic
C6 — 10uF 25VW tantalum
C7, C8, C10, C11, C12, C13 — .01uF ceramic
C9 — 560pF ceramic

Dipped mica capacitors, DM-15 series, 5%, 500V

C14, C17 — 100pF
C15, C22, C25 — 180pF
C16 — 27pF
C18, C21, C37, C41 — 150pF
C19 — 270pF
C20 — 56pF
C23, C26 — 82pF
C24, C27, C29, C33 — 560pF
C28 — 820pF
C30, C31, C34, C35, C39 — 390pF
C32, C36, C40 — .001uF (1000pF)
C38 — .0022uF (2200pF)

Resistors (0.25W, 5% unless stated)

R1, R3, R8, R16 — 10k
R2 — 56k
R4 — 100 ohms

R5 — 150 ohms
R6, R9 — 1.5k
R7 — 270 ohms
R10 — 820 ohms
R11 — 4.7k 1W
R12 — 1k 1W
R13 — 1k
R14 — 3.3k
R15 — 68 ohms
R17 — 2.2k
VR1, VR2 — 47k large vertical trimpot
VR3 — 4.7k large vertical trimpot

Inductors (see Table 2)

L1 — 10 turns bifilar, 0.6mm enamelled copper wire on Amidon yellow core
L2, L3 — 0.4uH
L4, L5 — 0.5uH
L6, L7 — 0.7uH
L8, L9 — 1uH
L10, L11 — 3uH
L12, L13 — 5uH

Miscellaneous

1 PCB, code ZA-1501
S1, S2 — SPDT toggle switch
S3 — 2 pole, 6 way rotary switch
RL1, RL2 — DPDT relays
M1 — 250uA FSD meter
1 2.3-metre length RG-178 coax
1 30A fuse and fuseholder
1 1-metre length red/black power cable
1 cable clamp grommet
1 knob
4 6mm spacers
4 rubber feet
4 3mm bolts, 13-16mm long
4 3mm nuts and star washers
46 PCB pins
1 275mm x 6-way ribbon cable
2 SO239 sockets
4 Philips 3mm x 8mm self-tapping screws
4 3.5mm x 9mm self-tapping screws
6 3mm x 12mm bolts
1 finned heatsink, 220 x 136 x 38mm
1 case with front and rear panels

Where to buy the kit

This project was developed in the Research and Development Department at Dick Smith Electronics Pty Ltd. It is available as a kit of parts only and can be purchased by mail order or from your nearest Dick Smith Electronics Store.


The kit comes complete and includes fibreglass PCBs, predrilled metalwork, and prepunched front and rear panels with screened lettering.

Mail orders should be addressed to: Dick Smith Electronics Pty Ltd, PO Box 321, North Ryde 2113. Phone (02) 888 2105.

Note: all PCB artwork material copyright Dick Smith Electronics Pty Ltd.

+13.8V, D3 is normally non-conducting. But if the supply rises above about 17V, D3 conducts and provides base current for Q2. Once again, Q2 turns on and the relays switch the booster out of circuit.

Finally, diodes D5 and D8 provide protection against reverse connection of the battery, while D6 and D7 protect Q4 from voltage spikes when the relays turn off.

Next month, we shall give the full construction and alignment details. In the meantime, you can order your kit from Dick Smith Electronics (see box). 

PRE CHRISTMAS BARGAINS

Get-Ready-For-Xmas Bargains!



Great Time With FunWay

Gifts that are fun, educational and affordable. Occupies young minds with hours of constructive entertainment which is educational. FunWay books tell you how and the project kits supply all the materials.

FunWay 1 Project Kits 1-10 Cat K-2600

10 Exciting projects to build in this one inexpensive kit. Fantastic value! **\$8⁹⁵**

FunWay 1 Project Kits 11-20 Cat K-2610

Another 10 projects. Build a beer powered radio, transmitter. (Needs K-2600 Kit) **\$9⁹⁵**

FunWay 1 Gift Box

All parts to build up to 20 projects plus FunWay 1 book. Cat K-2605 **\$24⁵⁰**

FunWay 2 Gift Box

Value! Includes FunWay book 2, soldering iron, wireless mic kit and more. Cat K-2620 **\$26⁹⁵**

FunWay 3 Bonus Pack

Includes FREE FunWay book 3, Electronic Cricket & Mini Amp kits (Worth \$31.10) Cat K-2670 **\$29⁹⁵**

FunWay 1, 2 & 3 Gift Box

Combination of kits to build 24 projects. Unlimited value! Cat K-2680 **\$54⁹⁵**

Jumbo FunWay Box Cat K-2690

Crammed with 30 projects, soldering iron, PCBs - the lot! **\$98⁹⁵**


Deluxe Car Alarm

Delayed and instant alarm inputs • entry/exit delay • siren output • flashing dash light. 9 out of 10 features recommended by the NRMA. Add ignition killer for 10 out of 10 security.

As described in May '84 EA

\$76⁴⁵


Cat K-3252



Stereo Decoder...

Turns your old AM tuner into a brilliant entertainment centre by taking AM IF output, decoding the C-QUAM signal and providing left/right channel audio outputs. Cat K-3415

As described in Oct '84 EA



\$32⁴⁵

Sound value..

BOOKSHELF SPEAKER KIT

Build your own 80W bookshelf stereo speakers and save! Stylish, acoustically well designed with 45-20000Hz frequency response and 89dB sensitivity.

FANTASTIC \$249 PAIR

Cat K-4000



As described in Nov '85 EA

Marine Radio-VHF Marine Transceiver

Value for money VHF handheld with 12 programmable channels to cater for coastal cruises. • 0.5/2.5W switchable power output • Sensitivity better than 0.25uV (12dB SINAD)

DOC approved. **\$399**

Cat D-1404

5W 6Ch Transceiver

Don't leave shore without this beauty! 5W with all 6 channels fitted.

Connects to boat antenna for maximum performance.

Take it home after docking. **\$199**

DOC approved

Cat D-1125

1W 3Ch Safety Transceiver

Here's a popular communicator! 1W, 3-Ch 'safety' transceiver that's compact enough for bushwalkers, etc. Fitted with 27.620 frequency with remaining 2 frequencies open for your choice. DOC approval:

242H0108

Cat D-1102

\$99

Uniden MC-480 Marine Radio Telephone

ONLY

\$449



The best of both worlds: Access to 55 international VHF marine channels PLUS OTC's Seaphone facility for contacting land phone network. Immediate Ch.-16 access. switchable 1W/25W output. DOC approved. Cat D-1400

Economy Marine

10 Channel, 27MHz transceiver that won't sink the budget! Yet provides max. legal output on all channels, auto noise limiter and ceramic filter. LED freq. display and squelch. Doubles as PA amp with optional power horn.

DOC Approval:

2440040

Cat D-1717

\$139



* Stingray - No 1 In Marine Communications

HF Marine Transceiver

Powerful 100W SSB rig for all HF marine frequencies... handles emergency, club and chatter over 2-30MHz range. Plug-in frequency cards for simple single knob frequency selection. DOC approved. Excellent value for a fine unit!

\$1795

ONLY THE BEST

BONUS 2182kHz Emergency channel Card included!



Cat D-1410

AUSTRALIAN MADE

Forget Antenna Tuning Hassles!

Stingray tuning unit matches antenna to transceiver quickly and easily for maximum performance and minimum risk of high SWR damage. Covers 2-23MHz range. Cat D-1412

\$429

Noise Blanking Mute Cord

Fitted in your transceiver to prevent ignition noise and other forms of pulse type interference. D-1414

\$139

2182kHz Whip (emergency frequency)

Just the thing for those smaller craft going off shore. Complete with base and lead.

D-1418

\$129

There's a bigger, better choice at...

DICK SMITH ELECTRONICS

PTY LTD

* These products available at selected stores on the coast — please phone your store for availability.

Be Santa's Helper with a great DSE gift!


Handy Gifts For Handymen!



Mini Multimeter. Budget price, pocket-size 11 range 2000 ohm/volt tester that goes anywhere. Great value! Cat Q-1010

\$16⁹⁵

Economy 2000 ohm/volt meter with bonus features! Buzzer continuity, 10A DC range, battery checker and banana plugs. Cat Q-1022




\$32⁹⁵




2-in-1 bargain! A 100,000 ohms/volt multimeter PLUS transistor capacitance checker and diode tester tool! Cat Q-1140

\$125

New multimeter and transistor/diode checker. 33 ranges, 200-200M ohms (in 7 ranges). Current: 200uA-10A AC/DC. With buzzer continuity. Cat. Q-1445



\$79⁹⁵




Digital Lux Meter. Takes accurate light source measurement quickly: 0-50,000 LUX over 3 ranges. Zero adjustment. Cat Q-1400

\$169

Build It Yourself & Save!


Teletext Decoder. Access to FREE information transmitted by TV stations (news, sports, etc.). Uses your VCR to reduce costs. Cat K-6315

\$259



TV Stereo Decoder. Transforms old mono set into a modern stereo entertainer - why buy a new TV! Features built-in VHF/UHF tuner. Line outputs and 1 watt stereo audio amp. Cat K-6325

\$199




Musicolor Mk IV. Connect to stereo for a brilliant light show at your next party. 4 Chase patterns plus auto and reverse. Controls up to 2400 watts (600W per channel). Cat K-3134



\$129

Beat Triggered Strobe. Professional lightshow at any party. Synchronises strobe light to the music. Cat K-3153

\$64⁹⁵



Measure the value of these beauties...


Feature packed! 3.5 LCD meter with memory, rotary auto ranging and 2 user selectable current ranges: 20mA or 10A. Cat Q-1515



\$99

4.5 digit LCD meter (24 range) with buzzer continuity, battery checker and overrange indication. Red/black test leads included. Cat Q-1510

\$249



Economy 3.5 wide-angled LCD meter (in 10 ranges) with RF shielding, overload protection. Handles 250V or 350V indefinitely, over 350V or 500V DC for up to 30 seconds. Cat Q-1520

\$64⁹⁵

Affordable 4.5 digit bench top that's versatile enough to take with you! Extremely accurate with high resolution. Cat Q-1550

\$289



3.5 Digit meter only 10mm thick! Features super fast auto ranging, buzzer continuity, polarity indication with minus sign, 2x/second sampling and more. Cat Q-1555

\$59⁹⁵


Kits

Enjoy the latest & the best at affordable prices!

Reduce soundtrack noise on video tape. DSE DNR Kit improves signal-to-noise ratio up to 18dB...includes stereo simulation circuit for mono VCR's.

Cat K-3423

\$99




'Anywhere Amp' kit. Compact, battery powered... connect guitars, organs for musical action anywhere! Treble, bass and volume controls. High/low level inputs. Cat K-3447



\$87⁹⁵

Radio Direction Finder. Used with an FM receiver it quickly indicates RF signal direction - ideal for marine use, amateurs. Electronically rotated antenna system produces frequency modulation by Doppler shift. Usable frequency range 50-500MHz if suitable antennae used. Cat K-6345

\$149



DICK SMITH ELECTRONICS

Before You Know It Christmas Will Be Here. Shop At DSE Now & Save!

THE BEST KITS IN THE WORLD!

Ask any "old timer" in electronics who makes the best kits in the world and the answer would be, without fear of contradiction, "Heathkit."

And they'd be right.

For the past fifty years, Heath Company has earned its reputation as the world's leading electronic kit manufacturer.

Heath kits are the best in the world. Not only are they outstanding in design and function, they look good! In fact, most people find it impossible to tell apart a Heathkit product and a commercial equivalent.

Of course, the builder can tell them apart: not only has he/she saved money by building it themselves, they also have the satisfaction of **knowing** they've built it themselves! And, along the way, probably learnt a little more about the fascinating hobby of electronics, and developed new skills in construction techniques.

But Heathkits are much, much more than just a collection of electronic bits and pieces.

As anyone who has ever built a Heathkit will tell you, it's the manuals that set Heathkits apart from the rest.

Some idea of the importance that Heath places on the manual can be gained from the time it takes to prepare them: on average, Heath spends **four times** as long writing, editing, re-writing and drawing the manual as it does in actual kit design.

That's right, four times as long. Heath know that any competent engineer can design a circuit that works... they also know that the kits are normally built by hobbyists without the degrees or even the experience. They know that nothing is more frustrating than not being able to identify a component, or not knowing how to align or adjust a project.

Therefore nothing is left out. Every piece of information even the most novice constructor could need — even things like how to bend

resistor pigtails.

Not only that, but everything you need to know to get the product to work — including comprehensive trouble-shooting and service notes.

And even then, Heath has a technical help service: in the unlikely event that your project doesn't work, there's always help available.

Hence Heath's motto: "We Won't Let You Fail"

HEATHKITS IN AUSTRALIA

Despite their international reputation, Heathkits have not been easily obtainable in Australia.

They've been around — but not so you could walk into a store and buy them.

Until now.

Dick Smith Electronics have, for many years, recognised the potential of Heathkits if made freely available.

As the leading kit supplier in this country for nearly two decades, DSE has had many requests for Heathkits. When the opportunity arose for DSE to import and sell Heathkits, we naturally said "Yes!"

Sure, we recognised that Heathkits were more expensive than most other kits. **But they were worth it!**

We also knew that there was a demand for the quality of Heathkits — particularly from retired people who had time on their hands — and knew of Heathkit's reputation.

DSE's dedication to the electronics hobbyists and enthusiasts of Australia and New Zealand meant that Heathkits would be one more service we could offer. And a top-of-the-line service at that.

So a selected range of Heathkits has been chosen and will become available through DSE almost immediately.

We've picked almost twenty kits which we have had demand for in the past. These will be available "off the shelf", many of them through your local DSE store.

Some may need to be ordered through the central computerised DSXpress Centre in Sydney (24 hour

despatch to anywhere in Australia.)

We're deliberately not trying to stock the whole range in Australia or New Zealand: look at the Heathkit catalogue and you'll see it's immense! It's simply not possible to hold this amount of stock in a small market such as Australia/New Zealand.

This doesn't mean, however, you cannot get other Heathkits: we will order **any** kit in the Heathkit range against a firm deposit, with the exception of computer kits or learning/training aids.

You should keep in mind that some kits are specifically American in nature — such as NTSC colour TV's. Of course, if you specifically **want** an NTSC colour TV, we can order one for you.

Because of the rapidly fluctuating dollar, we cannot print firm prices on these kits: however, one phone call to our Heathkit Information Line will get you the current price.

SPECIAL INSTRUCTION MANUAL OFFER:

It's difficult to order from a catalogue, sight unseen. So here's our special deal:

If you're interested in a particular kit, you can buy the instruction manual alone. It tells you all about the kit, how to put it together, how to adjust/align it, and so on.

You'll be able to judge whether or not it's the kit for you.

Then, if you go ahead and buy the kit, we'll refund 50% of the price you paid for the manual. What could be fairer than that?

You can't lose — no outlay for a kit you might not want — and you'll be assured it's the right one when you order it!

THEY LOOK SO GOOD...

DSE takes pride in the kits we produce. Remember our slogan: They look so good your friends won't believe you built them...

We admit it! Heathkit does it better.

They look so good you won't believe you built them...

Heathkit — available from

**DICK SMITH
ELECTRONICS**
PTY. LTD.

Just a few of the Heathkits you'll find at Dick Smith Electronics. (Not all these kits will be stocked in all stores, but should be available same day in all capital cities).

Deluxe Antenna Tuner

Exactly match your antenna system to your transceiver: minimise losses, maximise efficiency. The Heathkit Antenna Tuner features very high power handling (1kW CW) over the full HF bands, with roller inductor, dual wattmeters and built-in 4:1 balun.

Cat G-3000

\$799

Active Antenna

Just right for the SWL with no room! HF preamplifier with its own inbuilt whip antenna and provision for external 50 ohm antenna. Operates from 300kHz to 30MHz.

Cat G-3005

\$199

Ultrasonic Cleaner

At last! Clean virtually anything (up to 150mm x 100mm) ultrasonically: it actually vibrates dirt, stains and undissolved solids away! Use on components, jewellery, coins... even dentures! Uses ordinary laundry soap or softener.

Cat G-2010

\$299

FM Deviation Meter

Work with FM? You need this one. Deluxe deviation meter accurately and quickly checks deviation from 2 to 75kHz, over the range of 25 to 1000MHz. No more reports of "over deviation, om!" — you can even leave this in line for continuous checks.

Cat G-4000

RF Generator

Economical test gear — that really works well! Modulated and unmodulated signals from 310kHz to 110MHz — with calibrated harmonics to 220MHz. A must for every service shop — or for the serious hobbyist

Cat G-4005

\$149

Signal Tracer for easy repairs

Check out RF, IF even audio circuitry quickly and easily. Trace through until you find the fault. A must for the work bench.

Cat G-4015

\$149

Digital Readout of Unknown Components

Imagine: just plug in any unknown L or C and get an instant readout. Why throw away components? Also ideal for tolerance sorting, checking losses & dissipation, and so on. Range is massive: 1pF to 2000uF; 1uH to 2000H.

Cat G-4020

\$699

The Laser'll Amaze ya!

Schools, colleges, clubs: here's the perfect way to find out all about the laser. The laser trainer includes a HeNe gas laser with modulator, also includes a receiver for detecting the beam and amplifying sound.

Cat G-2020

\$799

(Tax Free price for schools, etc only \$649)

Amateur CW Transceiver

QRP transceiver just right for the novice or avid CW enthusiast. CW coverage on 80, 40, 20 and 15 metres with RF output up to 4 watts. Ideal for portable/battery operation too.

Cat G-3020

\$499

Accessory Band Pack for QRP transceiver

Allows operation on WARC bands — 30, 17 and 12 metres plus 10 metres.

Cat G-3021

\$75

NBS Clock

"The most accurate clock" you'll ever own. Tunes into WWV or WWVH for time signals accurate to 10mS; displays in digital form down to 0.1 second. Can display any of the world's 24 standard time zones. Outdoor antenna recommended.

Cat G-2005

\$629

Cantenna

1kW dummy load in a 4 litre can. Less than 1.5:1 VSWR up to 450MHz; ideal for on-air testing or alignment without any RF getting out. Needs 4 litres transformer oil (not supplied).

Cat G-3015

\$49⁹⁵

The Ultimate Weather Station

Get better weather information than the weather bureau gives! Famous world-wide, the Heathkit computerised weather station gives wind speed and direction, wind chill factor, temperature, barometric pressure (and whether its rising or falling)... everything! If your business is knowing the weather, the Heathkit weather computer is for you! Everything supplied — including sensors and cable.

Cat G-2000

\$999

Everybody's HERO!

The robot of the future is here today. It's Hero Jr — from Heathkit, of course. More than just a robot, Hero Jr will become a real member of your family. He (she?) is pre-programmed: Hero Jr will wake you up (even listen to make sure you're awake!), remember dates and anniversaries, walk, talk, protect you and your home (even activate your security system for you!) and much, much more. You can re-program Hero Jr via its own keypad or with your home computer (needs RS232C link). Of course, Hero Jr is battery operated and comes with an AC recharger.

Cat G-1005

\$1395

(Also available built up: Cat G-1000 @ \$1995)

Accessories:

Infra Red Motion Detector (for security applications)

Cat G-1010

\$399

RS232 interface

(re-program hero from your own computer)

Cat G-1030

\$179

Cartridge Adaptor

(for plug-in command cartridges)

Cat G-1050

\$179

Special Occasions cartridge

Cat G-1045

\$69

BASIC Cartridge

(Robotics Oriented BASIC Language — use when reprogramming with your own computer).

Cat G-1080

\$179

Spare Batteries

(set of 2 rechargeable)

Cat G-1040

\$69

Terms and conditions of sale:

For items stocked in DSE stores or the DSXpress centre, normal DSE terms and conditions apply.

For items from the Heathkit catalogue other than those normally stocked, DSE will order these for you on the following conditions:

- (1) Price must be confirmed via the Heathkit Information Line — Sydney (02) 888 2105.
- (2) A 25% non-refundable deposit must be made on any order (this can be done with your credit card as per normal sales).
- (3) Normally delivery time from the US via seafreight is 8 to 10 weeks from order. Air freight is available (approx 10% extra) and this reduces the delivery time to approximately 4 weeks.
- (4) Items ordered from the US do not qualify for our normal 14 day satisfaction guarantee or for refund: if in doubt about the kit you would like, take advantage of our special assembly manual offer.
- (5) Quotations given for Heathkit products, whether written or verbal, are valid for 7 days only. This is because of the volatile nature of international currencies.
- (6) Orders may be made by phone (toll free 008 226610), mail, fax, telex or any other of our normal order methods. If using phone, we suggest the order form overleaf be filled out to confirm the details of your order and retained by you.

Did you miss out on a Heathkit Catalog?

Some issues of this magazine did not contain the Heathkit Catalogue (it is in very short supply world-wide!)

Or it may be that some light-fingered larrikin has lifted, purloined or pinched it before you saw it...

Don't panic: send this coupon to The Heathkit Information Service, Dick Smith Electronics, PO Box 321, North Ryde — and we'll send you one free of charge.

Or if you talk nicely to your local DSE store manager he/she might be able to find one for you (just give them this coupon).

Name

Address

..... Postcode.....





Heathkit®

ORDER FORM

Phone your order through from
anywhere in Australia for the cost
of a local call.

FREE freight on all Heathkits.

(008) 22 6610

Sydney (02) area phone 888 2105

OR POST TO P.O. BOX 321,
NORTH RYDE NSW 2113

Name Customer No. Date

Address Postcode Phone

Have you bought from DSXpress before? ☐ YES ☐ NO

If you have changed your address, print previous address:

CAT NO	HEATHKIT	PRICE EA	QTY REQ	TOTAL PRICE
G-1005	Hero Jr Robot	\$1395		
G-1010	Hero Jr I/R Detector	\$399		
G-1030	Hero Jr RS232 Interface	\$170		
G-1040	Hero Jr Spare Battery Set	\$69		
G-1045	Hero Jr Special Occasions Cartridge	\$69		
G-1050	Hero Jr Cartridge Adaptor	\$179		
G-1080	Hero Jr BASIC Cartridge	\$179		
G-2000	Computerised Weather Station	\$999		
G-2005	The Most Accurate Clock	\$629		
G-2010	Ultrasonics Cleaner	\$299		
G-2020	Laser Trainer	\$799		
G-3000	Deluxe Antenna Tuner	\$799		
G-3005	Active Antenna	\$199		
G-3015	Cantenna Dummy Load	\$49.95		
G-3020	Amateur CW Transceiver	\$499		
G-3021	Accessory Band Pack G-3020	\$75		
G-4000	FM Deviation Meter	\$435		
G-4005	RF Generator	\$149		
G-4015	Signal Tracer	\$149		
G-4020	Digital L/C Bridge	\$699		

METHOD OF PAYMENT

☐ Cheque ☐ Money Order

Credit Card Expiry Date

☐ Bankcard ☐ Visa ☐ Mastercard ☐ Amex

Card No.

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

Signature

.....

FREIGHT/INSURANCE

Heathkit orders are sent freight free within
Australia by road or post.

Please nominate choice:

☐ Road Freight ☐ Post
(Not to PO Box)

Air freight is available up to 10kg at extra cost
(\$12.50)

☐ Please tick if air freight is required

Insurance is recommended. Cost is only \$1 for every \$100 of order value.

☐ Please tick if insurance is required (goods otherwise sent at owner's — your — risk)

MERCHANDISE TOTAL

INSURANCE

AIR FREIGHT LESS ANY CREDIT

TOTAL \$

NZ CUSTOMERS — PHONE (09) 392 997: STOCKS AVAILABLE EARLY 1987

★ CHRISTMAS ★ IS JUST AROUND THE CORNER

TOOLS

Value plus! 9-Pc Tool Kit

All the basics in a handy zip-up carry wallet. Perfect for hobbyists (PCB work, etc.), jewellers and modellers. Includes: • Micro cutter • Snap-off mini knife with safety lock • Fine tip tweezers • 6 Assorted screwdrivers. Cat T-4836

\$13⁹⁵



Varitemp Iron

At last an affordable variable temp soldering iron to handle the heat. Temperature control is conveniently located on the handle for easy adjustment. 25W 240V operation. Cat T-1350

\$22⁹⁵



Multipurpose Repair Kits

68 piece

Already own a multimeter? This set has everything else — and then some! Auto electric checker (6-12-24V), heavy duty pliers, crimp terminal set... with 60 assorted crimp lugs, insulation tape, even connecting wire!

\$21⁹⁵

Cat T-4834



38 piece Deluxe

Everything for quick and easy wiring repairs — with no soldering! Ideal for automotive and hobby use. Includes multimeter. Cat T-4832


\$37⁹⁵



12 volt Iron

Budget priced, ultra slim iron... ideal for delicate soldering where "precision" is a must! Requires 12V/1A AC/DC power supply. Cat T-1910

\$6⁵⁰



Precision Mini Iron

Don't make a mess of it! Our ultra slim iron is perfect for precision soldering on computers, PCBs and auto repairs. 6W output, 12VAC or DC operated. Cat T-1920

\$16⁹⁵



Pro-Feature Soldering Station

Variable Temp Control

\$99

Cat T-2000



A soldering station with variable temperature control for under \$100! Adjust temp between 200° to 500°C. Includes lightweight iron, holder and cleaning sponge.

Desoldering Iron

A 'must' for any serviceman's or hobbyist's tool kit! A self-contained, fully portable 240V, 30W desoldering tool that operates quickly and efficiently. Cat T-1340

\$75⁹⁵



Easiest Screw Driver around!

Tackle all those handyman jobs quickly and easily with this Turbo Driver. Battery operated and pistol shaped, it includes 4 head sizes and types. Reversible tool!

FOR EVERY HANDYMAN

\$69⁹⁵



Cat T-4750

Arlec Supertool

The mini work centre for the hobbyist or workshop. Contoured handpiece for comfort. Performs drilling, grinding, milling, sanding, polishing, erasing... and more. New model includes carry case. Cat T-4754

*** BONUS \$21 FREE ACCESSORIES**

\$62⁷⁵

FANTASTIC

Accessories:

- Drill Bits
- Grinding Bits
- * Ink Erasers
- * Pencil Erasers
- * Engraving/Milling Bits
- Grinding Bits
- Wire Brush Pack 3

Cat T-4756	\$9.45
Cat T-4758	\$12.55
Cat T-4760	\$5.15
Cat T-4762	\$4.85
Cat T-4764	\$10.95
Cat T-4766	\$12.65
Cat T-4768	\$16.45



Rechargeable Soldering Iron/Station

Versatile, quick heating cordless iron that's perfect for circuit and general purpose soldering... on the workbench or away. Built-in bulb for better viewing, safety cap for on-site jobs. Dual purpose soldering station is a stand and recharger. Complete with long-life tip, solder, sponge and AC adaptor. Cat T-2020

\$54⁹⁵

Spare tip and sponge kit Cat T-2021 **\$8.75**



Electric Glue Gun

What a fantastic idea. This electric glue gun will bond any porous surface instantly. Quick warm up and ergonomic design makes it a must for any workshop. Cat T-4840

\$19⁹⁵

Glue sticks — pack of 12 Cat T-4841 **\$5.45**



The One-Stop Shop for hobbyists needs!

DICK SMITH ELECTRONICS

PTY LTD


Scanning & Marine Bonanza! The best value in communication around.

Note: Marine equipment limited to our coastal stores - please phone ahead.

New! Uniden Bearcat 16-Ch. Scanner

UBC-175XL

Here's what scanning is all about! 16 Channels over 11 ranges - including aircraft and weather. 8-Digit display: freq., Lockout and Priority. Direct channel with manual up/down scanning or auto search ... and much more.



\$499

Cat D-2812

Frequencies Covered

• 29-54MHz • 118-136MHz
• 136-174MHz • 406-512MHz

...Prefer A 16-Ch. Hand-Held?

UBC-100XL



\$399

Frequencies Covered

• 66-88MHz
• 118-135-975MHz
• 136-174MHz
• 406-512MHz

Packs all the best features into a compact, go-anywhere unit just 74x35x179mm. Covers 9 freq. bands with direct channel access and auto search. Enjoy selective scan delay, priority and auto lockout. Includes carry case, ear plug, (AC adaptor and battery optional). Cat D-2813

... And There's A 10-Ch. Hand-Held Too!

BC-50XL



\$299

Frequencies Covered

• 29-54MHz
• 136-174MHz
• 406-512MHz

Economy price and size! Yet it's big on performance... covering 10 bands with direct channel access, manual or scan plus lockout and review buttons. Cat D-2814

Marine Antennas 27MHz Helical

Superb whip for all hull types ... wood, cement, fibreglass ... and it doesn't require a ground plane! Complete with mounting base, cable and simulated ground plane.

Cat D-4070

\$59⁹⁵

27MHz Swordfish 1/2 Wave Antenna

Resilient fibreglass 1/2 wave for all hull types and NO metal ground plane required! Includes coax cable, tuning box and handy 'any-which-way' mounting base with emergency quick release lever.

Cat D-4071

\$74⁵⁰

Marine Crystal Bargains!

All just **\$9⁹⁰** pair

27.620 D-6062 27.910 D-6091
27.860 D-6086 27.940 D-6094
27.880 D-6088 27.960 D-6096
27.900 D-6090

STORE LOCATIONS

NSW

Swift & Young Sts.
T55 Terrace Level
Shop 1, 65-75 Main St
613 Princess Hwy
Oxford & Adelaide Sts
Shop 2, 1B Cross St.
Warringah Mall
Campbelltown Mall Queen St
Shop 235, Archer St Entrance
147 Hume Hwy
164 Pacific Hwy
315 Mann St
4 Florence St
Elizabeth Dr & Bathurst St
450 High Street
621-627 The Kingsway
173 Maitland Rd, Tighes Hill
Lane Cove & Waterloo Rds
George & Smith Sts
The Gateway, High & Henry Sts
818 George St
125 York St
Treloar's Bldg, Brisbane St
263 Keira St

Albury
Bankstown Sq
Blacktown
Blakehurst
Bondi Junction

(060) 21 8399
(02) 707 4888
(02) 671 7722
(02) 546 7744
(02) 387 1444

Brookvale
Campbelltown
Chatswood Chase
Chullora
Gore Hill
Gosford
Hornaby
Liverpool
Maitland
Miranda
Newcastle
North Ryde
Parramatta
Penrith
Railway Square
Sydney City
Tamworth
Wollongong

(02) 93 0441
(046) 27 2199
(02) 411 1955
(02) 642 8922
(02) 439 5311
(043) 25 0235
(02) 477 8633
(02) 600 8888
(049) 33 7866
(02) 525 2722
(049) 61 1896
(02) 88 3855
(02) 889 2188
(047) 32 3400
(02) 211 3777
(02) 267 9111
(067) 66 1711
(042) 28 3800

ACT

96 Gladstone St
VIC
Creswick Rd & Webster St
145 McCrae St
Shop 46, Box Hill Central, Main St
Hawthorn Rd & Nepean Hwy
260 Sydney Rd
1150 Mt Alexander Rd
Nepean Hwy & Ross Smith Ave
Shop 9, 110 High St
291-293 Elizabeth St
Bridge Rd & The Boulevard
Springvale & Dandenong Rds
QLD
157-159 Elizabeth St
166 Logan Rd
Gympie & Hamilton Rds
Queen Elizabeth Dr & Bernard St
2nd Level Western Entrance
Redbank Shopping Plaza
Gold Coast Hwy & Welch St
Bowen & Ruthven Sts
Kings Rd & Woolcock St
Cnr Pacific Hwy & Kingston Rd

Fyshwick

Ballaarat
Bendigo
Box Hill
East Brighton
Coburg
Essendon
Frankston
Geelong
Melbourne City
Richmond
Springvale

(062) 80 4944
(053) 31 5433
(054) 43 0388
(03) 890 0699
(03) 592 2366
(03) 383 4455
(03) 379 7444
(03) 783 9144
(052) 43 8522
(03) 67 9834
(03) 428 1614
(03) 547 0522

Brisbane City
Buranda
Chermside
Rockhampton

(07) 229 9377
(07) 391 6233
(07) 359 6255
(079) 27 9844

Redbank
Southport
Toowoomba
Townsville
Underwood

(07) 288 5599
(075) 32 9863
(076) 38 4300
(077) 72 5722
(07) 341 0844

SA

77 Grenfell St
Main South & Flagstaff Rds
Main North Rd & Darlington St
24 Park Terrace
WA
Wharf St & Albany Hwy
66 Adelaide St
William St & Robinson Ave
Raine Square, 125 William St
TAS
Shop 40A, Lower Level
Cat & Fiddle Arcade
NT
17 Stuart Hwy

Adelaide
Darlington
Enfield
Salisbury

(08) 232 1200
(08) 288 8977
(08) 280 6088
(08) 281 1593

Cannington
Freemantle
North Perth
Perth City

(09) 451 8886
(09) 335 9733
(09) 328 6944
(09) 481 3261

Hobart
Stuart Park

(002) 31 0800
(089) 81 1977

Dear Customers,

Quite often, the products we advertise are so popular they run out within a few days, or unforeseen circumstances might hold up shipments so that advertised lines are not in the stores by the time the advert appears. And very occasionally, an error might slip through our checks and appear in the advert (after all, we're human too!) Please don't blame the store manager or staff: they cannot solve a dock strike on the other side of the world, nor fix an error that's appeared in print. If you're about to drive across town to pick up an advertised line, why not play it safe and give them a call first ... just in case! Thanks. Dick Smith Electronics.

MAJOR DICK SMITH ELECTRONICS AUTHORISED RESELLERS

NSW: • **Ballina:** A. Cummings & Co. 91-93 River St 86 2284 • **Ulladulla:** Pauls Electronics, 10 Wason Street, 55 3989 • **Bowral:** F.R.H. Electrical, 28 Station St 61 1861 • **Broken Hill:** Hobbies & Electronics, 31 Oxide St 88 4098 • **Charlestown:** Newtronics 131 Pacific Hwy 43 9600 • **Coffs Harbour:** Coffs Harbour Electronics, 220 Cressy St, 81 3672 • **Dubbo:** Mavina Electronics, 35 Talbragar St, 82 8500 • **Gosford:** Tomorrow's Electronics & HIFI, 68 William St, 24 7246 • **Lismore:** Decro 3A/6-18 Carrington St, 21 4137 • **Port Macquarie:** Hall of Electronics, Horton Centre, Horton St, 83 7440 • **Orange:** Fyfe Electronics 173 Summer St, 62 6491 • **Springwood:** Wellington's Electrical Discounts 115 Macquarie Rd, 51 4886 • **Taree:** Brad's Electronics Shop 6, Civic Cinema Centre, Pulteney St, 52 8603 • **Tumut:** Tumut Electronics Wynyard St, 47 1631 • **Tweed Heads:** Stuart Street Electronic Sales, Stuart St, 36 5744 • **Wagga:** Phillips Electronics 60 Forsyth St, 21 6558 • **Windsor:** M & E Electronics, Sh 7, Mc Ewans Arcade, 206 George St, 77 5935 • **Young:** Keith Dinges Electronics 186 Boorowa St 82 1279 VIC: • **Echuca:** Webster Electronics, 220 Packham St 82 2956 • **Mildura:** McWilliams Electronics 110A Langtree Ave, 23 6410 • **Morwell:** Morwell Electronics, 95 George St, 34 6133 • **Shepparton:** GV Electronics Centre 100 High St, 21 8866 QLD: • **Bundaberg:** Bob Elkin Electronics, 81 Bourbong St, 72 1785 • **Calmar:** Electronic World Shop 27 K-mart Westcourt Plaza, 51 8555 • **Caloundra:** Hume's Electro-Mart, 9 Tay Ave, 91 4270 • **Gladstone:** Supertronics, 9 Tank St, 72 4321 • **Macquarie:** Stevens Electronics, 42 Victoria St, 51 1723 • **Maryborough:** Keller Electronics, 218 Adelaide St, 41 4559 • **Mt Isa:** Outback Electronics Shop 71 Barkley Hwy 43 3331 • **Nambour:** Nambour Electronics Shop 4, Lower House, Ann St, 41 1804 • **Rockhampton:** Access Electronics, 15 East St, 21 058 SA: • **Mt Gambier:** Hutchessons Communications, 5 Elizabeth St, 25 0400 • **Whyalla:** Eyre Electronics Shop 2 Forsyth St, 45 4784 WA: • **Albany:** Micro Electronics 133 Lockyer Ave 41 3432 TAS: • **Launceston:** Wills Electronics 5A The Quadrant, 31 5688



ORDER SERVICE

ORDERS OVER \$75
FREE DELIVERY

	Order Value	Charge	Order Value	Charge
POST & PACKING CHARGES	\$5.00 — \$9.99	\$2.00	\$50.00 - \$75.00	\$6.50
	\$10.00 - \$24.99	\$3.50	\$75.00 or more	N.A.
	\$25.00 - \$49.99	\$4.50		



PTY LTD

P.O. Box 321, North Ryde N.S.W. 2113

Tel: 888 3200

Terms available to approved applicants

SA Customers: Credit facilities available through Adelaide: 10 Pulteney St, Adelaide

Offer concludes 31/11/86 or until stocks last. Prices can be increased without notice due to fluctuations in currency, high interest rates, government taxes and imports.

Low cost dummy load

*Put six light bulbs in a screened box, fit a six-way switch and what have you got?
Answer: a low-cost dummy load that's just the shot for service work.*

by JIM LAWLER (MTETIA)

When servicing TV sets we often require some means of loading the power supply without risking damage to expensive transistors or other components in the line output stage.

Then again, although most TV power supplies incorporate current limiting, it is often an advantage to have some kind of backstop current limiter in series with the output transistor during line output stage troubleshooting.

There is one common, cheap, easy-to-use component that is ideal for both of these jobs, and in other places as well. This is the ubiquitous light bulb or incandescent lamp.

I usually keep a 100 watt lamp in the workshop for this kind of testing, but recently, while adjusting the output of the EA 300 Watt Inverter, I had need for both low and high value loads. I "pinched" enough 100 watt lamps from the lounge and dining rooms to solve the high value problem but low wattage lamps are not so common.

I solved my immediate problem by borrowing a 45 watt lamp from the little room but later, while sitting in the dark, I decided that I had to build up a proper dummy load with a wide range of wattages instantly available.

To use a lamp as a service aid in TV work, I had used a bayonet socket from an old lamp fitting with a short length of flex and two alligator clips. I sometimes added an old double adapter if it was necessary to increase the load beyond that offered by one lamp.

This system worked well enough, although an awful lot of lamps met a premature end when bashed against the bench, or squashed under TVs. My new setup would have to be rugged enough

to protect the lamps from workshop perils.


The final design suggested itself one day when I was picking up some stores from one of my suppliers. On his wall was a display of HPM electrical fittings, including a switch plate holding six rocker switches. This plus six batten holders, a few scraps of particle board, some short lengths of power cord and a metal screen allowed me to put together the "ultimate" dummy load.

My contraption is fitted with six

lamps, one each of 15, 45, 60, 75, 100, and 150 watts. These are all readily available and quite cheap. Used singly or in combination, they can offer a wide variety of loads up to 445 watts at 240 volts.

The photograph shows how I arranged these parts, but any arrangement would be suitable, provided the lamps are protected from physical damage and are well ventilated. This unit has been fitted with a three pin plug for testing the 300 watt inverter mentioned earlier but it could be fitted with alligator clips, or adapters made up to fit any type of plug or socket that might be required.

When using lamps like this as dummy loads, it is wise to remember that they will dissipate their rated power only when fed from 240 volts. Their consumption is all over the place at lower voltages because of their different temperature coefficients. EA



The light bulbs and switches are all wired in parallel.

An infrared remote control preamplifier

This second and final article on the IR Remote Control Preamplifier describes the construction and setting up procedure. The Dick Smith kit will include prepunched metalwork, moulded remote control case and all hardware down to the last screw and nut.

by JOHN CLARKE

Construction of the IR Remote Control Preamplifier involves assembling five printed circuit boards (PCBs), plus a small amount of wiring and mechanical assembly. Overall it should take only a few nights work to have the system operational.

IR Transmitter

Two PCBs for the remote transmitter are designed to insert into the moulded plastic case. The keypad PCB (coded ZA-1599) is secured with screws to the case lid which retains the keypad switches in position. The ZA-1598 PCB circuit clips into the base of the case. It is shaped like a chunky "T" in order that it can use the integral plastic clips to secure the PCB in position.

Beginning with the keypad PCB, there are ten wire links required and these should be mounted on the top of the PCB as shown on the overlay diagram. After soldering, crop the wires short on the copper side so that they will not foul the plastic membrane switch when assembled.

A 9cm length of 12-way rainbow cable connects to the bus at the edge of the PCB. This is labelled from R1 to R8. Separate each wire from the end of the cable for about 2mm and strip the insulation about 1mm back from the ends. Twist the strands of each wire together and insert the wires into the holes from the top side of the PCB. They can now be soldered.

Assembly of the ZA-1598 circuit PCB

requires that the high profile components (L1 and C1 to C3) be placed side-on so that the PCB will fit within the case. Take care with the polarised components such as the IC, transistors and C3. The transistors should be inserted and pushed down close to the PCB. Note that there is provision for a second 470µF/16VW capacitor below C3. This should be used to obtain better transmitter range if a standard 9V battery is used rather than an alkaline type.

The IR LEDs are mounted proud of the PCB so that when the PCB is clipped in position, the LEDs rest on the integral plastic supports within the case. To do this, bend the anode (longer) lead at 90 degrees 10mm from the LED base and the cathode (k) lead

7mm from the LED base. Insert each LED so that it is raised above the PCB by 8mm.

The rainbow cable also connects to the R1 to R8 bus on this PCB. Make sure that this cable is oriented so that R1 on the keypad PCB also connects to R1 on the main PCB. Finally, the battery wires connect to the PCB with the red wire going to the plus (+) terminal.


Clip the main PCB onto the base of the case and insert the battery clip through into the battery compartment.


The keypad label can be affixed to the front of the case lid and the rectangular holes for the switches trimmed out with a sharp knife. Place the switch tops into the holes and place the membrane switch matrix inside the lid. The keypad PCB screws to the lid and is oriented so that the rainbow cable exits from the window end of the lid.

Finally, place the red plastic window into the front of the case and clip the whole case assembly together. It is secured with a screw near the battery compartment.

Power Supply PCB


Work can now begin on the power supply PCB. This is coded ZA-1597.





View inside the prototype. The two RCA socket assemblies are soldered directly to the analog and logic PCB.

Remote control preamplifier




Here is the parts layout for the power supply PCB. Take care with the mains wiring.

switches are mounted hard against the PCB with the "flat" side oriented as shown on the overaly. Note that the left-most locations for the switches are not used.


Once the switches have been installed, the LEDs can be placed in position. Note that the long lead of the LED is the anode and the short lead the cathode (k). They are installed so that the top of the LED shoulder is at the same height as the shoulder on the switches. Solder only one lead at this time to allow adjustment in the front panel, as necessary.

Note also that LD9 is red and LD8 is green while the remainder from LD1 to LD6 are orange. The level display LEDs from LD10 to LD18 are all green except for LD14 (centre LED) which is red.

The photodiode PH1 is mounted proud of the PCB to the same level as the switch shoulders. Note that the



The control board carries the switches and LED displays and is mounted on standoffs behind the front panel.



Most of the work involves assembly of the analog and logic board. See text for on-board wiring details.

chamfered edge is located toward the top edge of the PCB.

This completes the PCB construction. The remaining work consists of wiring and assembly.

Assembly and Wiring

Bolt the mains socket to the rear and the transformer to the base using machine screws and nuts. The earth lug is


bolted to the baseplate as shown on the wiring diagram. It uses two nuts with spring washers.

Follow the wiring diagram for the mains and transformer connections. Secure the mains cord using the cord clamp grommet and terminate the mains wiring directly onto the power supply PCB. They are soldered quickly to avoid melting the insulation. Be certain


that the earth wires (green/yellow) are soldered to the earth lug and connected to the earth on the mains socket.

Holes are provided in the PCB to accommodate tying the wires down with cable ties.

Temporarily support the power supply PCB using the 4 × 15mm standoffs in readiness to test the power supply PCB. Recheck the wiring and switch on the



Remote control preamplifier



This photo shows the layout of the sub-assemblies inside the chassis.

mains power. Check the voltage at the output of the regulator using a multimeter. It should be about 15V. The relay operation can be checked by connecting a jumper lead between the (-) and (on) terminals of CN5. The 15V supply should now appear at the (+) output of CN4.

Now the rainbow cable for the inter-board wiring can be prepared.

Temporarily locate the main analog/digital PCB on 6 × 15mm standoffs and position the front display PCB on the supplied standoffs. This will allow the lengths for each cable to be determined. The wiring diagram shows the interconnections and the number of wires required for each cable. Note that wiring from the CN6 and CN5 terminals of the main analog/digital PCB goes to the CN4 and CN3 terminals of the control board respectively. The CN7 terminals of the main PCB go to the CN5 terminals of the control board.

Cut each cable to length, strip back the insulation and twist the strands of each wire.

You will need to gain access to the base of the PCBs before attempting to solder the wires in place. For the power supply and main PCB, the wires are inserted into the PCB from the top of the PCB and soldered on the copper side. The control board wiring is done from the copper side of the PCB. For these the wire is inserted into the holes leaving sufficient stripped wire to allow soldering. Make sure that the polarity is correct for each cable.

Reinstall the PCBs on the standoffs and screw the RCA sockets on the main analog/digital PCB to the rear panel using 4 × 8mm self tapping screws. Now the front panel can be secured to the front of the case with spacers. Carefully place this in position, making sure that the switches and LEDs protrude through the holes. Check operation of the switches for binding and solder the LEDs in position. If necessary, the front panel may require slight repositioning to free the switch operation. A square red bezel inserts into the infrared detector hole position and is glued in place.

Setting-up

Initially, set all the preset pots to centre position. Now connect up the mains supply. The green "off" indicator should light. Press the "on" switch and the red LED should light as well as the Tuner and Source selection LEDs. By pressing the other selections, the indicator LEDs above them should light.

Pressing the balance, bass, treble and volume controls should cause the bar

graph display to display in the dot mode. The level should progress up or down the display for the up or down pushbutton switches of each function.

If any of these functions do not operate, check the PCBs for faults such as incorrect component placement and wiring errors. Also check power supplies and trace through the circuit operation to locate the fault. Most faults are not due to faulty ICs since they are very rugged and reliable unless incorrectly connected to the power supply. Look for other problems before suspecting an IC.

Test the remote control unit to check that its controls all operate correctly.

Calibration

To calibrate the level set display, it will be necessary to have access to the VR1 trim pot on the control board by removing the front panel. Press the normal switch and adjust VR1 until the display has three LEDs lit. Now press a balance control switch to check that the red centre LED initially lights before the display moves off centre. Press the normal switch again and press the opposite balance switch. The centre LED should again light before the display moves off centre. If not readjust VR1.

Setting up the analog control presets from VR2 to VR5 requires a high impedance meter such as a digital multimeter. Press the volume up switch until maximum volume is obtained. This is when all the LEDs are extinguished while the switch is pressed. Now measure the voltage on pin 12 of IC6 and adjust VR2 for a reading of 5V DC on the multimeter.

Similarly, the balance, treble and bass controls should be set to a maximum on the level set display. The voltage at pin 9 is set with VR3, pin 4 is set with VR4 and pin 14 is set with VR5 respectively. These should all be set to 5V DC.

Finally, replace the front panel and secure the top lid to the case.


Testing

The unit is now ready to be tested with your sound system. Connect a

continued on page 126

Where to buy the parts

This infrared remote control preamplifier has been developed and produced by the Research and Development Dept. at Dick Smith Electronics Pty Ltd. It is available as a kit of parts only and can be purchased by mail order or from your nearest Dick Smith Electronics store. The cost is \$279 plus postage and packing charges where applicable.



Follow this diagram carefully when wiring up the PCB sub-assemblies. Caution: the power supply board carries mains voltages.

Don't let the boat sink. Build this

Solar-powered bilge pump

Keep the boat afloat when you're not around with this automatic bilge pump. It's easy to make and, best of all, it's powered by sunlight.

by **COLIN DAWSON**

There were many innovative and useful circuit ideas submitted to our recent solar panel contest. One that struck us as being simple, useful and making good use of solar energy was an automatic bilge pump, suggested by Peter Holloway of Perth. We have adopted his idea and designed a low-cost circuit suitable for construction on a printed circuit board (PCB).

The concept of "free" energy from the Sun is an inherently appealing one. Although it is not quite fair to refer to solar panels as free energy, since they have to be bought in the first place, they can be an attractive proposition when there is no easy access to mains power.

In this project, a 12V solar panel is used to top up a battery so that it can power an automatic bilge pump. Without the panel, the battery could quickly go flat, particularly if the boat was leaky and the bilge pump cut in quite frequently. It's obvious what would happen if the battery did go flat — the bilge pump would stop operating and the boat would eventually sink.

Add a solar panel though, and the scenario changes completely. Even the quite modest power of 7W available from a cheap 12V panel is enough to cover a couple of hours pumping per day. The battery is still needed but, except where the boat is inundated, it will not discharge in the long term.

Solar panels with a nominal output of 12V are available from several component retailers. The price for a 700mA unit at the time of writing seems to average about \$90 although Amtex has a higher

power version which is more expensive. Although rated at a nominal 12V, most of them have an open circuit output of up to 18V, depending on the light intensity.

In practice, the battery itself will not allow the solar panel output to rise above about 14.5V.

Naturally, an automatic bilge pump has to have some means of sensing the water level. We envisage that some sort of float and microswitch assembly will do the job in most cases. These level sensors are readily available from boating suppliers.

However, the earth seeking input of our control circuit could easily be adapted to other sensors. It could, for example, be used with a moisture sensing element set up to detect either salt or fresh water, depending on your circumstances (more about this later).

Most boating suppliers will also be able to sell you a bilge pump. Our sample bilge pump from Amtex was rated at 12V DC 3.5A and is capable of pumping around 1800 litres (400 gallons) per hour.

Time delay

One important feature of the circuit is an inbuilt time delay. This holds the pump on for about 30 seconds after the float microswitch opens and so stops the pump from continually cycling on and off as the boat moves on a swell. If the microswitch then closes again inside the timing interval as the boat moves about, the circuit simply retriggers for another 30s.

This low-cost bilge pump is capable of pumping 1800 litres per hour.






Fig.1: IC1 performs level sensing while MOS transistor Q1 switches the pump motor in and out of circuit.

Only when there has been no new trigger for 30s will the circuit switch off.

Note that, with particularly choppy sea, the pump inlet may be uncovered briefly. The same may happen for small boats which can be quickly emptied by the bilge pump. This is nothing to worry about however, as the pump motor is rated for continuous operation with or without water transfer.

How it works

Since every milliwatt counts with a low capacity source such as a solar panel, relay control of the motor was considered unsuitable due to the power wasted in the coil. Instead, we elected to use a MOS transistor to control the motor. This is a voltage controlled device and has negligible gate current.

It is also smaller and more compact than a relay and can be driven directly from a CMOS control IC. So use of a MOS transistor gives us a simpler, more compact circuit.

Refer now to the circuit diagram (Fig.1). It's really very simple. MOS transistor Q1 (BUZ71) is connected in series with the pump motor and functions purely as a switch. When the transistor turns on, the pump turns on and vice versa.

Q1 in turn is controlled by IC1 which is a 4011 CMOS quad NAND gate IC. This is about the cheapest CMOS IC going — around 60 cents seems to be average.

The water level sensor is connected to pins 1 and 2 of IC1a, which acts as a switch/detector. Its input is normally held high by the 10k resistor but is pulled low by the water level sensor. When this happens, its output (pin 3) switches from low to high.

When IC1a's output is high, D1 is forward biased and the 1000uF capacitor

quickly charges. In fact, the capacitor will be held in the fully charged state for as long as the high water condition exists.

During this time, pin 4 of IC1b is held low and thus the outputs of parallel buffer/inverter stages IC1c and IC1d are high. This high is coupled to the gate of Q1 (BUZ71) via a 56 ohm resistor.

When its gate is held high, Q1 is on and thus the pump motor is also on.

Normally, you would expect that a reverse diode would be connected across Q1 to protect the transistor against voltage spikes generated by the back EMF of the motor. This would certainly be the case if Q1 were a bipolar transistor, but the SIPMOS transistor has the diode connected internally. However, we do need to limit the drain to gate voltage and this job is performed by diode D2 and zener diode ZD1.

When the water level subsequently drops below the critical level, the micro-switch (S1) opens and the pin 3 of IC1a switches low. D1 is now reverse biased and so the 1000uF capacitor begins discharging through Rt.

After about 30 seconds, pin 4 of IC1b switches high again and the outputs of IC1c and IC1d switch low. This turns off Q1 and the motor.

Note that the 30s time delay can be easily altered by adjusting the value of Rt. Do not make the time delay too long though, otherwise the pump will continue to run after the bilge has been pumped dry.

Power for the circuit is derived from a 12V auxiliary battery and this is applied direct to the motor. A 27 ohm resistor and 0.1uF capacitor decouple the supply to IC1, while zener diode ZD2 limits the supply to 15V. While this primarily provides protection against inductive kick-back from the motor, it also serves the

secondary function of preventing the solar panel voltage from exceeding 15V. This could otherwise occur if the battery was disconnected.

Finally, the solar panel is connected in parallel with the battery via diode D3. This diode prevents the solar panel from discharging when the output from the solar panel falls below the battery voltage.

Construction

The circuit is built on a small PCB coded 86pc11 and measuring 63 x 45mm.

PARTS LIST

- 1 PCB, code 86pc11, 63 x 44mm
- 1 8-way PC-mounting terminal block
- 1 bilge pump (see text)
- 1 solar panel (12V nominal)
- 1 water level detector (see text)

Semiconductors

- 1 BUZ71 SIPMOS N-channel transistor
- 2 1N4148 diode
- 1 1N4001 diodes
- 1 15V 1W zener diode
- 1 20V 400mW diode
- 1 4011 CMOS quad NAND gate

Capacitors

- 1 1000uF PC-mounting electrolytic
- 1 0.1uF metallised polyester

Resistors (0.25W, 5%)

- 1 x 470k, 1 x 10k, 1 x 56 ohm, 1 x 27 ohm

Where to get the parts: the BUZ71 transistor is available from Jaycar or from Geoff Wood Electronics. An etched PCB can be obtained from RCS Radio Pty Ltd or from Acetronics PCBs.

Fig.2 shows where the parts are mounted on the board. In all, there are just 13 components to be installed. The order is of no consequence although we suggest that the terminal block and the 1000uF capacitor be left till last.


Note that although the PCB has provision for reverse polarity protection diode D3, some solar panels are supplied with a suitable diode mounted internally. If this is the case, D3 should be replaced by a wire link — there is no need for duplication. In fact, if you include D3 in this situation, you're wasting power.

Once the PCB has been completed, it can be given a quick check before installation in the boat. To do this, connect the battery and the motor by referring to Fig.2 and the underside of the PCB. Each of the slots for the terminal block is labelled with a code; eg. "m-" and "m+", meaning motor negative and motor positive respectively.

It's then simply a matter of shorting the i1 and i2 terminals together. The motor should immediately switch on and continue running for approximately 30s after the short is removed.

Installation

The circuit should be mounted in a sealed box to protect it from moisture,



View of the assembled PCB. It should be installed in a waterproof box.

especially if the boat is operating in salt water. Since the PCB is so small, any one of a number of standard project boxes would be suitable. In fact, the smallest zippy box would be ideal and this should be waterproofed using a silicone weather sealant.

Since each boat will present a different case for detecting the water level, we have left this to the constructor's discretion. A float and mercury switch arrangement would probably be the most reliable. The float, however, would have to be quite small for a small V-bottom boat.

As an alternative to the mechanical system, a moisture detector could be used as stated previously. In the simplest case, this would amount to mounting two probes near each other (at a low point in the hull), with one connected to i1 and the other connected to i2. Salt water flowing over the probes would create a low resistance path between them, triggering the circuit.

For fresh water, the 10k pullup resistor may have to be changed to a higher value to ensure reliable triggering.

Using the above method would undoubtedly be successful in the short term, but deposits (especially salt) may lead to false triggering. A more serious limitation is that if this system was set up for salt water, it may not trigger in fresh water. The boat could be at risk during periods of heavy rain.

Irrespective of the water detector used, make sure that the circuit does not trigger the pump for an unrealistically low level of water. Instead, the detector should be arranged so that the pump turns on at a preset level and just manages to pump the water down to the inlet.






Fig.2: parts layout for the PCB. External connections are via an 8-way terminal block.



Here is an actual-size PCB artwork.

PROFESSIONAL P.C.B. DESIGNS from R.C.S. DESIGN PTY. LTD.




the best equipped CAD bureau in Australia
HIGHEST QUALITY □ FAST TURNAROUND
DESIGN PRACTICES TO AUST. STANDARD
PHOTO TOOLS □ DRILL TAPES
CIRCUIT DIAGRAMS □ DOUBLE SIDED
MULTILAYER □ FINE LINE
PROJECT DESIGN AND DOCUMENTATION
PHOTO PLOTTING OF MICRO CAD OUTPUT
DESIGN CONSULTING SERVICE

For details contact:




R.C.S. Design Pty. Ltd.

728 Heidelberg Road
Alphington, Victoria, 3078
(03) 49 6404



Sealed lead acid & nickel cadmium rechargeable batteries

MAINTENANCE FREE




COMPLETE RANGE OF BUTTON CELL STACKS
assembled in Australia to customers specifications.



I.E.I. (AUST.) PTY. LTD.

15-17 Normanby Road, Clayton, Vic. 3149 Phone (03) 544 8411
31 Phillips Street, Thebarton, S.A. 5031 Phone (08) 352 2066
248 Johnston Street, Annandale, N.S.W. 2038 Phone (02) 692 0999

WE ASKED THE WORLD WHAT THEY WANTED IN A SUB-RACK SYSTEM



THEN WE BUILT IT.

The BETACOM UNIRAC has been designed and developed after consultation with users of existing systems throughout the world. Incorporating the widest range of options, allows the BETACOM UNIRAC sub-racks to be assembled to a customer's individual requirements as well as permit TSA to provide very prompt delivery. Constructed of semi-sheared plate, cap screws and tapped extrusions give the BETACOM UNIRAC both positive assembly and rigid construction. Also ask TSA about our custom sub-racks to suit your individual requirements.

BETACOM
UNIRAC

TSA

TEMPLE-SMITH AUSTRALIA PTY. LTD.
2-12 Harp Street, Campsie. PO Box 196, NSW 2194
Telephone (02) 78 3436 FAX (02) 787 2529

VICTORIA
Temple-Smith Australia Pty. Ltd.
459 Collins Street
(moving in January 87)
Melbourne 3000
Telephone (03) 62 5971
FAX: (03) 614 2293

SOUTH AUSTRALIA
Graphic Electronic Industries
Pty. Ltd.
168 Payneham Road,
Evandale 5069
Telephone (08) 363 0277

WEST AUSTRALIA
J. G. Thomas & Associates
5 Durrham Road
Bayswater 6053
Telephone (09) 272 7122

QUEENSLAND
Conwell Trading Company Pty. Ltd.
52 Doggett Street
Fortitude Valley 4006
Telephone (07) 52 7850

HI/TSA/113

Digital technology

Procedures, equipment, terminology

Having discussed the background and the broad principles of digital audio recording and playback, we look now at the procedures and equipment commonly involved and explain some of the relevant terminology — including unfamiliar words like “foldover”, “aliasing”, “granulation noise” and “dither”!

by NEVILLE WILLIAMS

As a first reaction, it might be assumed that the prospect of digital recording would not affect normal analog signal source arrangements involving the performance and acoustics, the type, number and placement of microphones, cabling and preamplifiers, signal control and mixing.

In fact, the exceptional acoustic “transparency” of digital recording and replay systems — the result of very low inherent noise and distortion — tends to expose subtle production faults which have hitherto been masked by the limitations of traditional analog signal sources and methods.

As a result, conductors, producers

and recording engineers have become more sensitive to the intrinsic sound of the orchestra, and to the modifying effects of acoustics, microphone techniques, panel processing, equipment quality, &c. Considerable efforts have thus been made to upgrade the analog equipment in which the multi-channel signals exist prior to digital encoding.

Supersonic filtering

Immediately before the sampling process (Fig.1) the analog signals pass through low-pass filters to remove frequency components beyond the nominated 20kHz passband. The reason for so doing is reminiscent of the “fold-

over” effect, often encountered in conventional analog tape recorders.

In analog tape equipment, if one records and replays a gliding tone signal, passing through and beyond the system high-frequency cut-off, heterodyne whistles may be heard in the background, diminishing in frequency as the gliding tone moves upwards. They result from beats between harmonics of the input signal and the recording bias.

The effect is not directly apparent with normal program input, but spurious intermodulation products must inevitably be present in such recorders.

In the case of digital recording, a different set of circumstances can give rise to a similar effect.

As pointed out in the last article, signal sampling is valid only for frequencies of less than half the sampling rate. For this reason, digital systems intended for signal frequencies up to 20kHz invariably use a sampling rate in excess of 40kHz.

If signal components greater than half




Fig.1: Depicting in block schematic form the signal chain for a digital recording system. In a full-scale studio recorder, sockets on the rear panel accept multiple balanced analog inputs from the central console, all subsequent filtering and processing being an integral part of the recorder.

the sampling frequency are fed into such a system, their sampled resultants will be invalid and liable to be wrongly decoded as spurious signals, including difference frequencies between the sampling rate and its harmonics, and the inadmissible components.

While such "alias" (wrongly identified) components may be very small, they are nevertheless unacceptable in the clinically clean environment of a digital recording. Hence the need for sharp cut-off "anti-aliasing" filters in the analog signal output circuits.

An ideal top-cut (or low pass) filter would exhibit a vertical "brick wall" characteristic, with no phasing or ripple effects on the frequencies which it passes and no trace of those which it rejects. Practical analog filters fall short of the ideal, however, providing grounds for abstract argument by:

- "Golden-eared" hifi buffs who profess to hear filter effects inaudible to others, and
- Engineers who debate filter theory in terms which no one else can comprehend!

Sample and hold

The digitisation process which follows (Fig.1) is often dismissed, rather summarily, as simply involving the acquisition of instantaneous samples of the incoming analog signal — one sample every 25 μ s or so. It is not always appreciated that, during that period, a 20kHz signal would pass through a complete half-cycle, rendering it meaningless to feed such a waveform directly to a quantisation circuit.

The job of acquiring a more valid "instantaneous" sample falls to "sample and hold" (S/H) circuitry, which samples the incoming waveform in something less than 5 μ s (the acquisition time) and holds the determined value until the A/D (analog to digital) converter has matched it to the closest increment in the quantisation ladder.

Essentially, an S/H involves a small capacitor which is electronically switched, by "sample" commands, to a buffered signal source long enough for it to acquire a charge equal to the instantaneous value of the signal. This is then fed to the A/D converter input to permit the acquired signal value to be quantised.

The basic principle is simple enough; the essence of an effective design lies in achieving the fastest possible response to the clock "sample" command, the shortest possible acquisition time, and the minimum "droop" or loss of ac-




Fig.2: A sample and hold circuit must sample the instantaneous amplitude of an analog signal in the shortest possible time and hold it, with a minimum of droop, for the value to be quantised by the A/D converter.

quired charge during the "hold" period. (Fig.2).

Conceptually, a sample and hold circuit transforms an analog signal into unambiguous, readily measurable steps. It remains for the actual A/D converter to relate those steps to discrete voltage increments identifiable by digital words.

Analog-to-digital

A/D conversion is a highly specialised procedure, the finer details of which are frequently secreted within the intricacies of dedicated LSIs (large scale integrated circuits). Most, however, operate on one of two basic principles, the first thing being referred to as SAR (successive approximation register), an ultra high-speed variant of the old "pick a number" routine.

Presented with each new sample, a SAR converter first compares it with the MSB — the most significant bit, representing the largest increments in the reference stack — and decides if the MSB is "too big" or "too small". If too big, the MSB is rejected and the left-hand digit of the 16-bit output word is set to "0". If too small, the MSB is retained and the left-hand digit set to "1".

The SAR then tries the next significant bit, rejecting it or adding it to the first as necessary and setting the equivalent digit accordingly. So the process continues through to the LSB (least significant bit) to optimise the match and complete the 16-bit word.

The main alternative design approach involves the integrating principle where, on receipt of each new sample, a precision capacitor begins to charge at a predetermined rate from a constant current source.

A crystal controlled "clock" circuit

registers the time it takes for the charge to equal the sample signal; it then produces an output reading in binary notation, not as so many microseconds, but in terms of the voltage level that the charge would have attained in the elapsed time, thus providing the output word.

Practical integrating type converters use two charging circuits (described as "dual-slope" or fine and coarse "ramps") each of which outputs 8 bits of the quantising word. The two are merged to provide the full 16-bit word for each sample.

Both SAR and integrating type A/D converters are capable of meeting present day needs. Linearity is very good, as indicated by the very low harmonic and intermodulation distortion levels exhibited by virtually all current digital equipment.

But what is dither?

Digital systems have been open to considerable debate concerning their behaviour when encoding very small signals — especially those which approximate the amplitude of the least significant bit.

We can postulate that, in a noise-free channel, a signal of that magnitude may be treated, somewhat randomly, in various ways:

- (1) It may fall below the quantising threshold and be ignored;
- (2) It may repeatedly cross the quantising threshold and be encoded as if it was actually a low level square-wave signal.

You can argue that, in practical situations, the fate of signals in the -95dB region is academic. On the other hand, critics insist that what happens to very small signals is indicative of a wider problem: one that, in their judgement, produces a "gritty" sound, sometimes referred to as a "granulation" effect or "granulation noise".

Fortunately, there is a simple and almost automatic way around such problems: the addition to the original analog signal of a very small amount of broadband noise — described as "dither" — not simply to mask the quantising errors but, as it transpires, to correct them!

A case can be made for a noise component (or dither) of a particular type but, in practice, ordinary analog "white" noise is adequate.

The effect of dither

With dither present, the quantising errors, responsible for the above problems, are no longer a simple artefact of

An introduction to hifi

the original signal and the quantising process. Errors which would be predictable and cumulative with a smooth input waveform are "randomised" when the waveform is carrying a band of white noise.

The resulting — and similarly randomised — binary quantisation words no longer specify to the decoder predictable, stepped waveshapes with well defined harmonics and intermodulation products; instead, they specify something much less angular — more like the original signal, carrying a quota of broadband noise.

The role of dither is difficult to illustrate graphically but Figs.3 and 4, reproduced from EA for July 1984, show the dramatic effect, at low signal levels, of adding white noise equal to one third of a quantising increment. Harmonic distortion (Fig.3) and intermodulation (Fig.4) subside into the broadband noise at about -27dB relative to the already small signal.

The diagrams come originally from a paper presented to the Canadian AES, in 1982, by J.B. Vanderkooy and S.P. Lipshitz. The authors go on to say: "With sufficient dither, a digital system loses all its digital artefacts."

They further suggest that, whereas early and less pretentious 12-bit and 14-bit systems commonly needed added dither, the increments in a 16-bit system are so small that natural analog noise ahead of the A/D converter is usually

sufficient to provide adequate dithering. Hence our earlier reference to the way around the problem being "almost automatic".

At the same time, it is not something that should be left to chance, which is why a dither source is shown in Fig.1 feeding into the analog system.

Contrary to what you might expect, the addition of dither does not restrict the dynamic range. In effect, optimum dither adds an analog-like "noise floor" below the LSB in which signals can still be subjectively discerned.

Formatting the data

While the binary output from an A/D converter can be handled conveniently enough with logic (computer style) circuit modules, it is not really suitable for storage, recording or transmission in that form.

For one thing, the 16 bits comprising each binary word appear simultaneously as a "parallel" output from the A/D converter; they need to be reorganised into "serial" format — one bit at a time in the desired sequence.

Furthermore, to obviate ambiguity during playback, a synchronising code in the form of a unique bit group must be inserted into the serial data stream, to identify the beginning of each new word and word group. (Synchronising code in a data stream has been likened to punctuation marks in printed text).

As well, check codes and parity bits

are added and the data is "interleaved" or dispersed in the data stream to facilitate error detection and correction during playback. More on this later.

In studio situations involving multiple microphones and multi-channel recorders, the data streams for individual channels are kept separate, for recording in individual tape channels. One or more supplementary information channels may carry timing signals, "address" cues, &c, to facilitate crystal locked playback, along with computer controlled editing, mix-down and dubbing.

If two-channel "stereo" information needs to be merged into a single channel for recording (or transmission), normal practice is to employ time-multiplexing, with formatted bit packages from each channel recorded or transmitted in sequence for later separation and decoding. Time-multiplexing doubles the bit rate, however, and is only practical where the recording or transmission system can accommodate the extra bandwidth.

Modulation codes

Conceptually a data stream is a sequence of on-off states, ie, a rectangular waveform.

In the course of recording or transmission, however, the neat, rectangular waveforms may be degraded so that up/down transitions between the two states become a more reliable feature of the data stream, and the basis on which the original pulses can ultimately be reconstituted.

For this reason most digital systems




Fig.3: In quantising very low level, noise-free signals, the harmonic distortion can be very high. With dither (lower diagram) it subsides into the noise at about -27dB below the already tiny signal.




Fig.4: The prominent spiky pattern shows intermodulation products when two low-level signals are quantised. With dither, the spikes also become part of the noise at about -27dB below the small signal level.

employ so-called "modulation codes", which place emphasis on the transitions rather than the states, to take best advantage of the bandwidth available. The data stream is modified (or modulated) in accordance with the selected code for recording or transmission and, upon replay or reception, demodulated and reconstituted.

Without seeking to discuss the various codes, it may be helpful to list certain ones so that the terms will at least be recognised.

NRZ — Non-return to zero.

NRZI — Non-return to zero inverted.

MFM — Modified frequency modulation.

EFM — Eight-to-fourteen modulation.

HDM-1 — Used in modern studio recorders.

Correction codes

While two-state digital information is "robust" by nature and substantially free from limitations of the analog kind, there is always the possibility that some of the densely packed data bits or groups of bits will be lost due to flaws in the recording medium: eg. coating drop-outs or minute surface particles in the case of tape; scratches or other surface defects in the case of compact discs.

To forestall such problems, and the resulting "clicks" and "plops", digital systems normally include provision for correcting or concealing aberrations during playback — something that has not been practical in analog technology. The effectiveness of such measures contributes in no small degree to the noise-free qualities of digital recordings.

Error correction involves a number of simultaneous measures including parity bits, coding, interleaving, interpolation and muting.

Parity and interleaving

By making provision for extra non-data ("redundant") bits in the data stream it is possible to provide an indication of the accuracy of binary words recovered from the tape.

By increasing redundancy (more check bits) and by more ambitious processing, it becomes possible both to identify and correct most bit errors.

A further measure involves "interleaving" or dispersing individual data bits or words in a structured way, so that their sequence in the data stream is radically changed.

If a "burst" error then creates a major fault in the data stream, the affected bits, after de-interleaving — or

re-distribution — become scattered small errors, subject to individual correction by parity checks, &c.

Using principles such as these, engineers have come up with a range of error correction codes such as CIRC (Cross-interleave Reed-Solomon) code, used for compact discs.

Interpolation, muting

If a "burst" error is of such magnitude that, at best, it is not correctable, the logic circuitry operates to give the missing signal amplitude words interpolated values derived from adjacent valid words.

If interpolation cannot conceal a particularly serious fault, a digital muting circuit cycles the suspect word group through zero amplitude, effectively transforming a click or a pop into brief and hopefully unobtrusive silence.

In practical situations, the muting circuit is very much a last resort. In compact discs, for example, elaborate CIRC encoding can correct burst errors involving up to 4000 bits (2.5mm of track length). This is extended to 12,300 bits (7.7mm of track) by adjacent sample interpolation! (In practice though, no CD player will track a disc with such a surface defect).

Data packing density

While the above figures indicate the effectiveness of digital error correction measures, they also highlight the packing density of digital audio data — of the order of 1500 bits per millimetre — a figure which is valid for both optical and magnetic media.

In terms of frequency bandwidth, and allowing for the bit-rate economy of "modulation" systems referred to earlier, high quality digital recording requires many times the bandwidth of an analog system, for a given audio response — typically Megahertz.

This presents no great difficulty with compact disc because, in the first instance, laser optical technology was developed for video recording. Much the same is true of tape systems using video style helical scanning.

However, for stationery head multi-channel linear recorders, normally preferred for functional reasons in studio situations, a quantum jump in tape, head and circuit technology has been necessary.

To ensure intimate contact with head gaps, for the best possible transfer of densely packed data, digital tape uses a base film little more than half the thickness of ordinary analog tape. This is

possible because residual cross-talk, due to print-through, is normally rejected by a digital system.

The coating too, is different, commonly a cobalt modified gamma ferric formulation, with a coercivity level of between 700 and 1000 Oersteds and able to retain a "robust", saturated pulse pattern.

While the particles must still be needle shaped and positioned lengthwise along the tape, for the normal magnetising format, they must be of the smallest practical dimensions and applied in a thin but dense coating to minimise demagnetisation and the loss of high frequency signal components.

As to magnetic heads, the "thin film" concept, with the essential elements printed on substrate, seems set to take over from the conventionally assembled variety. Also in view is "perpendicular" recording, with super-fine particles positioned vertically in the coating and offering a dramatic potential increase in particle — and bit — density.

Practical recorders

The latest generation of stationary head recorders uses the so-called

ALTRONICS PRODUCTS IN ADELAIDE

All the exciting Altronics Products and advertised specials in the Altronics advertisements in this magazine are available in S.A. from **FORCE ELECTRONICS**, your dynamic Altronics S.A. dealers.

Call in this month for a free
Altronics 1986 Catalogue!

FORCE ELECTRONICS

**203 WRIGHT ST.
ADELAIDE PH: 212 2672**

**ALSO AT CHRISTIES BEACH
PHONE 382 3366**

**AND REYNELLA
PHONE 383 2824**

An introduction to hifi

"DASH" (Digital Audio Stationary Head) format, the Sony PCM-3324, pictured in the last chapter, being an example.

The subject of an agreement between major professional recording equipment manufacturers, the DASH format establishes standards for new and developmental professional digital recorders from 2-track to an ultimate 48-track, using either 12.7 or 6.35mm tape.

An interesting aspect of the DASH format is that, in certain configurations, it provides for the use of one, two or four separate tracks to record individual audio channels. Each track has its own extensive error correction but the use of multiple tracks makes it possible for the playback circuitry to momentarily discard a signal which exhibits an uncorrectable burst error.

So to playback

The steps necessary to reproduce the original analog signals are as indicated in Fig.5, which shows three audio channels only.

Digital signals recovered from the tape are by no means copybook rectangular waveforms but this is of little concern. As long as the signal contains unambiguous up-down transitions, it is possible to readily reconstitute the pulses, as originally recorded, without loss of information.

Following preamplification and waveform re-shaping, the data streams are fed to demodulators which reverse the original modulation and rearrange the data into its wider-band pre-taping format.

At this point, timing signals derived from the tape are fed to a tape drive servo control system, along with refer-




Fig.6: The solid line shows an idealised rectangular output from the final sample & hold stage following the D-A converter. A practical and commonly preferred "integrating" S/H circuit delivers an output to the low pass filter as per the dotted line.

ence pulses from an inbuilt crystal clock. The servo system holds the capstan at the precise speed necessary to maintain synchronisation.

At the same time, the data stream is processed to sort out other information signals, the basic data and the parity bits, and to give effect to error correction procedures. If the data stream has been time-multiplexed to accommodate left/right stereo signals, these are separated and time synchronised by passing the leading signal through a delay line.

At this juncture, the recovered binary words could conceivably be processed into analog but with the possibility that they would introduce timing errors — hence flutter — due to slight "hunting" or jitter from the tape servo control system.

To forestall this possibility, word bits for the respective channels are fed into memory banks, maintained about half-full by the servo system. They are "clocked" out by crystal-derived timing pulses, independently of the input feed. Wow and flutter is thereby eliminated, being typically specified as "unmeasurable".

Back to analog

As part of the D-A (digital to analog conversion) procedure, the serial data streams must again be converted to the required parallel format and then fed to the D-A converter.

Output filtering

An effective low-pass filter, set at or below half the sampling frequency is an essential feature of a digital system, if frequency components are to be removed which represent the difference between a "staircase" waveform from the D-A converter and a "smooth" analog signal.

Once again, a vertical "brickwall" filter, free of phasing effects, would be ideal — if it could be achieved. In general, practical output filters represent a compromise that offers adequate high frequency attenuation, with tolerable phasing effects in the passband.

More ambitious designs use digital filtering to discriminate against the high frequency components while they are still in digital form, thereby reducing the reliance on the analog filter. EA




Fig.5: Illustrating the signal processing sequence involved in recovering the original analog signals, again an integral part of a multi-channel digital studio recorder or, for that matter, of a domestic compact disc player.

Take advantage of Ritronics Wholesale's extensive range and excellent prices!!



MICRODOT 5 1/4" FLOPPY DISKS

Have a look at these prices!
These are 100% certified, prime spec.
disks in labelled jackets.
(not like our oppositions)

Description	1-9	10+	100+
Cat.No. boxes boxes			
S/S/D/D C12440	\$14.50	\$13.90	\$13.00
D/S/D/D C12445	\$16.50	\$14.90	\$13.50

Plus 20% tax where applicable

Attention Schools, Government Depts etc
FREE sample disk available on request!
(Please send \$2 to cover postage)



FANS

Cat.No. Description	1-9	10+	100+
T12461 240V 4 1/2"	10.50	10.00	8.00
T12465 240V 3 1/2"	10.50	10.00	8.00
T12463 115V 4 1/2"	10.50	10.00	8.00
T12467 115V 3 1/2"	10.50	10.00	8.00

(Fan guards to suit also available)
Plus 20% tax where applicable

ELECTROLYTIC SINGLE ENDED PCB MOUNT

Cat.No. Description	10+	100+	1000+
R15405 0.47uF 63V	\$0.07	\$0.06	\$0.05
R15415 1uF 63V	\$0.07	\$0.06	\$0.05
R15422 2.2uF 50V	\$0.07	\$0.06	\$0.05
R15424 2.2uF 50V	\$0.06	\$0.05	\$0.04
R15425 2.2uF 63V	\$0.07	\$0.06	\$0.05
R15432 3.3uF 25V	\$0.07	\$0.06	\$0.05
R15435 3.3uF 63V	\$0.07	\$0.06	\$0.05
R15442 4.7uF 25V	\$0.07	\$0.06	\$0.05
R15443 4.7uF 35V	\$0.08	\$0.07	\$0.06
R15445 4.7uF 63V	\$0.07	\$0.06	\$0.05
R15461 10uF 16V	\$0.07	\$0.06	\$0.05
R15462 10uF 25V	\$0.07	\$0.06	\$0.05
R15463 10uF 35V	\$0.07	\$0.06	\$0.05
R15465 10uF 63V	\$0.07	\$0.06	\$0.05
R15481 22uF 16V	\$0.07	\$0.06	\$0.05
R15482 22uF 25V	\$0.08	\$0.07	\$0.06
R15483 22uF 35V	\$0.08	\$0.07	\$0.06
R15484 22uF 50V	\$0.09	\$0.08	\$0.07
R15502 25uF 25V	\$0.07	\$0.06	\$0.05
R15505 25uF 63V	\$0.10	\$0.08	\$0.07
R15512 33uF 25V	\$0.08	\$0.07	\$0.06
R15521 47uF 16V	\$0.09	\$0.08	\$0.07
R15522 47uF 25V	\$0.09	\$0.08	\$0.07
R15525 47uF 63V	\$0.10	\$0.09	\$0.08
R15531 100uF 16V	\$0.10	\$0.09	\$0.09
R15532 100uF 25V	\$0.08	\$0.07	\$0.06
R15533 100uF 35V	\$0.15	\$0.12	\$0.11
R15535 100uF 63V	\$0.24	\$0.22	\$0.20
R15541 220uF 16V	\$0.09	\$0.08	\$0.07
R15542 220uF 25V	\$0.14	\$0.12	\$0.11
R15543 220uF 35V	\$0.25	\$0.23	\$0.20
R15545 220uF 63V	\$0.26	\$0.24	\$0.22
R15552 330uF 25V	\$0.15	\$0.13	\$0.12
R15555 330uF 63V	\$0.34	\$0.30	\$0.28
R15561 470uF 16V	\$0.16	\$0.13	\$0.12
R15562 470uF 25V	\$0.23	\$0.20	\$0.18
R15563 470uF 35V	\$0.45	\$0.40	\$0.36
R15564 470uF 50V	\$0.00	\$0.00	\$0.00
R15565 470uF 63V	\$0.44	\$0.39	\$0.36
R15581 1000uF 16V	\$0.25	\$0.22	\$0.20
R15582 1000uF 25V	\$0.35	\$0.30	\$0.28
R15583 1000uF 35V	\$0.45	\$0.40	\$0.36
R15591 2200uF 16V	\$0.45	\$0.40	\$0.36
R15592 2200uF 25V	\$0.65	\$0.60	\$0.50
R15593 2200uF 35V	\$1.20	\$0.91	\$0.75
R15601 2500uF 16V	\$0.45	\$0.40	\$0.36
R15602 2500uF 25V	\$0.65	\$0.60	\$0.55

Plus 30% tax where applicable



CRYSTALS

Cat.No. Frequency	Can	10+	100+
Y11000 1MHz	HC33	4.75	4.00
Y11005 2MHz	HC33	1.95	1.70
Y11008 2.4576MHz	HC18	1.95	1.70
Y11015 3.57954MHz	HC18	1.20	.95
Y11020 4.00MHz	HC18	1.20	.95
Y11022 4.194304MHz	HC18	1.20	.95
Y11025 4.75MHz	HC18	1.20	.95
Y11026 4.9152MHz	HC18	1.20	.95
Y11042 6.144MHz	HC18	1.20	.95
Y11050 8.00MHz	HC18	1.20	.95
Y11055 8.867238MHz	HC18	1.20	.95
Y11070 12.00MHz	HC18	1.20	.95
Y11072 14.318MHz	HC18	1.20	.95
Y11080 15.00MHz	HC18	1.20	.95
Y11085 18.432MHz	HC18	1.20	.95
Y11090 20.00MHz	HC18	1.20	.95

Full range of crystals available on indent.
Plus 20% tax where applicable

POLYESTER 100V "GREENCAP" TYPE

Cat.No. Description	1-99	100+	1000+
R15131 .001uF	0.06	0.04	.03 1/2
R15137 .0012uF	0.06	0.04	.03 1/2
R15138 .0015uF	0.06	0.04	.03 1/2
R15140 .0022uF	0.06	0.04	.03 1/2
R15142 .0033uF	0.06	0.04	.03 1/2
R15143 .0039uF	0.06	0.04	.03 1/2
R15145 .0047uF	0.06	0.04	.03 1/2
R15146 .0056uF	0.06	0.04	.03 1/2
R15147 .0082uF	0.06	0.04	.03 1/2
R15148 .01uF	0.07	0.05	.04 1/2
R15150 .015uF	0.07	0.05	.04 1/2
R15152 .022uF	0.07	0.05	.04 1/2
R15154 .033uF	0.07	0.05	.04 1/2
R15155 .039uF	0.07	0.05	.04 1/2
R15156 .047uF	0.08	0.06	.05 1/2
R15157 .056uF	0.08	0.06	.05 1/2
R15158 .068uF	0.08	0.06	.05 1/2
R15159 .082uF	0.08	0.07	.05 1/2
R15160 .1uF	0.09	0.08	.07
R15162 .15uF	0.11	0.10	.09
R15164 .22uF	0.15	0.14	.13
R15165 .27uF	0.16	0.15	.14
R15172 1uF	0.70	0.55	0.50
R15176 2.2uF	1.20	1.10	1.00
R15178 3.3uF	1.50	1.20	

Plus 30% tax where applicable



12V SEALED LEAD ACID BATTERIES

Description/Cat.No.	1-9	10+
1.2 AH S15029	\$12.50	\$11.75
2.6 AH S15031	\$17.70	\$16.50
4.5 AH S15033	\$23.40	\$22.00

Plus 20% tax where applicable

CARD EDGE CONNECTORS

Cat.No. Description	10-24	25-99	100+
P12060 10 Way	2.95	2.50	2.10
P12062 20 Way	3.25	2.75	1.95
P12064 28 Way	3.55	2.95	2.20
P12066 34 Way	3.95	3.50	2.30
P12068 40 Way	4.50	3.90	3.50
P12070 50 Way	5.50	4.50	3.90

Plus 20% Sales Tax where applicable



19" RACK MOUNT CASE

Description	1-9	10+	25+
Tremendous value! Vented top panel.			
Dimensions: 480(W) x 134(H) x 250(D)mm.			
	\$32.00		\$29.50

Plus 20% tax where applicable



500K DISK DRIVE FOR IBM®

Description	1-9	10+	100+
12 months warranty!			
	\$145	\$135	\$125

Plus 20% tax where applicable
(*IBM is a registered trademark)

MITSUBISHI DISK DRIVES

Description	1-9	10+	25+
4851 5 1/4" 500K	\$195	\$185	\$175
4853 5 1/4" 1M/Byte	\$265	\$245	\$215
4854 5 1/4" 1.6M/Byte	\$295	\$260	\$235
2896 8" 1.6M/Byte	\$650	\$625	\$600

Plus 20% tax where applicable

DISK DRIVE FOR APPLE® (6502 SYSTEM)

Description	1-9	10-24	25+
	\$175	\$165	\$155

Plus 20% tax where applicable
(*Apple is a registered trademark)



ECONOMY TOGGLE SWITCHES

Cat.No. Desc.	10-99	100+
S11010 (SPDT)	0.85	0.78
S11020 (DPDT)	0.95	0.88
S11034 (4PDT)	2.95	2.85

Plus 20% Sales Tax where applicable



HORN SPEAKERS


Cat.No.	1-9	10+
C12010 5" Plastic 10W Max	5.80	5.60
C12015 5" Metal 10W Max	5.75	5.50
C12012 12V Siren	9.90	9.60

Plus 20% tax where applicable

ENCLOSED ROTARY SWITCHES

Cat.No. Description	1-9	10+	100+
S13021 1 Pole 12 Position	1.00	.80	.70
S13022 2 Pole 6 Position	1.00	.80	.70
S13023 4 Pole 3 Position	1.00	.80	.70
S13025 3 Pole 4 Position	1.00	.80	.70


Plus 20% Sales Tax where applicable



CANNON TYPE AUDIO CONNECTORS

Cat.No. Desc.	1-9	10+
P10960 Pin Line Male	2.00	1.85
P10962 Pin Chassis Male	1.90	1.70
P10964 Pin Line Female	2.75	2.50
P10966 Pin Chassis Female	2.90	2.75


Plus 20% Sales Tax where applicable



NICADS

Cat.No. Description	1-99	100+	250+
S15020 AA 5AH	\$1.80	\$1.70	\$1.50
S15021 C1.2AH	\$5.55	\$5.45	\$5.15
S15022 D1.2AH	\$5.75	\$5.50	\$5.25

Plus 20% tax where applicable



RITRON II MONITORS

Desc./Cat.No.	1-9	10+	50+
Swivel base monitor in stylish case.			
Green Cat. X14506	\$175	\$165	\$160
Amber Cat. X14508	\$175	\$165	\$160

Plus 20% tax where applicable



TRANSFORMERS

Cat.No. & Desc.	1-99	100+	1000+
M12851 2851	3.00	2.75	2.50
240V 125V CT 150mA			
M12155 2155	5.50	4.95	4.50
240V 6-15V 1A tapped			
M12156 2156	8.50	8.25	7.90
240V 6-15V 2A tapped			
M12840 2840	3.20	3.00	2.70
240V to 9V C.T. at 150mA			
M12860 2860	3.50	3.00	2.80
240V to 15V C.T. at 250mA			
M16672 6672	8.50	7.95	7.70
240V 15-30V 1A tapped			

Plus 20% tax where applicable

75 OHM COAX CABLE IN 100M ROLLS

Cat.No. Description	1-4	5+	10+
W11222 3C2V	25.00	24.00	23.00
W11224 5C2V	30.00	29.00	28.00
(5C2V WHITE OR BLACK)			
LINE LOSS PER 100 FEET (33M 200MHz)			
W11222 3C2V 6.2dB (Approx.)			
W11224 5C2V 3.9dB (Approx.)			

Plus 20% tax where applicable

TELEPHONE CABLE (200 METRE ROLLS)

Cat.No. Description	1-9	10+
W11302 2 Pair	\$34.00	\$30.00
W11303 3 Pair	\$42.00	\$39.00
W11310 10 Pair	\$120.00	\$115.00
Per 200m Roll		

20% Sales tax where applicable

WE HAVE THE BEST MEMORY PRICES!

"Check for the latest memory prices!"

27512	10-99	100+	1000+	10K+
4164-15P	\$24.00	\$22.00	\$22.00	\$22.00
41256	\$2.00	\$1.70	\$1.65	\$1.60
6116P-3	\$4.50	\$4.00	\$3.60	\$3.30
2716	\$3.00	\$2.90	\$2.20	\$2.00
27128	\$7.50	\$7.00	\$6.50	\$6.00
2532	\$5.00	\$4.50	\$4.00	\$3.50
2732	\$7.50	\$6.50	\$6.00	\$5.50
27256	\$9.00	\$8.10	\$7.50	\$7.00
6264	\$5.50	\$5.00	\$4.50	\$4.00
2764	\$6.00	\$5.00	\$4.50	\$4.00

Plus 20% tax where applicable

What's new in display technology?

Display technology is growing rapidly as electronic equipment becomes more and more complex. In this article we review the six major display technologies presently in use and cover recent developments.

by LEO SIMPSON

In October last year we presented a major article on the subject of liquid crystal displays. This time around we shall look at the major display devices presently in use. In addition to LCDs, they include light emitting diodes (LEDs), vacuum fluorescent displays (VFDs), plasma discharge displays, electroluminescent displays and cathode ray tubes (CRTs).

All these devices can be and are used as information displays for computers or for dedicated microprocessors in home and business equipment such as microwave ovens, VCRs and hifi equipment, photocopiers and facsimile machines, electronic tellers, ticket machines, drink dispensers, petrol pumps and so on. It seems as though just about every piece of electronic equipment these days has some sort of digital, alphanumeric or dot matrix display.

The reason why these displays have become virtually mandatory is that equipment is becoming more complex and so needs to give the user more information on how it is functioning. At the same time, as dedicated microprocessors in all this equipment continue to become cheaper and yet ever more powerful, it is becoming much easier to incorporate fancy displays.

In personal computers, there is a drive to produce terminal displays which have

more brightness, greater legibility and higher resolution for text and graphics images. At the same time, there is a continual search to reduce the overall bulk and weight of the visual display unit and to lower its power consumption.

Light emitting diodes

Discounting early display devices such as numerical indicator tubes and cathode ray tubes, the light emitting diode was the first to be widely used in information displays. They were first introduced as single light emitting diodes but then became more specialised as they were incorporated into seven-segment displays and bar graph displays.

In these applications, LED displays have the advantage of being attractive, highly visible and legible in all light conditions except bright sunlight, easily driven by low voltage solid state circuitry and available in a range of colours such as red, orange, green, yellow and yellow/green.

For single lamp devices, all the above

colours are available plus two-colour units (which incorporate two separate LEDs) and just recently, Siemens have introduced blue LEDs.


LEDs are available in a wide range of packages including surface mount. As well there are two broad categories which most manufacturers produce: standard and high-brightness or high efficiency. The latter types can be very bright, with light outputs up to as much as one candela. They can be used in two ways: first to obtain a very bright display and second, to obtain adequate brightness at very low operating currents of only a few milliamps.

As well as producing a wide range of single LEDs, seven segment LED displays and alphanumeric displays, several manufacturers have a range of LED bar-graphs and LED-illuminated legend panels.

Multiplex drive

While single LEDs, bar graphs and legends can be driven with simple circuitry, it is not simple for seven segment displays and alphanumeric displays. Since these are generally used in arrays of four devices or more (as on clock and frequency displays on many appliances), it is customary to use a multiplex system of drive.

In the multiplex method of connection, all the respective segments in the displays are connected together, so that for a four



TEXT LITE MM-300

This moving text display uses LEDs and comes from Text Lite.

digit display there are seven segment lines and four cathode lines (assuming that they are common cathode displays). Thus there are only eleven lines needed to drive the display rather than the 32 lines which would be needed if each digit was separately driven.

The method of multiplex drive is as follows: Each cathode line is turned on separately and when it is energised, the respective segments for that digit are also turned on to illuminate them. The process means that each digit is turned on sequentially very briefly, at a rate of about 3000 times a second. If you were to slow the process down, the digits would each light sequentially with a duty cycle of approximately 25% (ie, each digit is on 25% of the time).

As well as saving on connection lines, multiplex drive of LED displays also results in a brighter-looking display for a given current consumption (compared to direct drive).


Alphanumeric displays are very similar to seven-segment displays except that the former have more segments so that they can show all letters of the alphabet as well as numerals from 0 to 9. They can be multiplexed in a similar way.

A step up in complexity is brought about by dot matrix displays which can display all ASCII characters in a matrix of LEDs consisting of five columns and seven rows. Again, these are multiplexed as direct drive would be impractical.

On an even larger scale there are the moving text displays used in theatres, retail stores and clubs. These may be several metres long and employ thousands of high brightness LEDs. The displays are driven by a small computer which may be programmed by a detachable keyboard. The most "intelligent" of these displays can even show company logos such as those for Ford and Coca-Cola.

Advantages and disadvantages of LEDs

The advantages of LED displays are self-evident. They are bright, easily read and available in a number of different colours, as outlined above. Their disadvantage is that they consume relatively large amounts of current. Hence they are not suitable for very complex displays such as the now standard personal computer 80 column by 25 rows of ASCII text. Such displays are actually large dot matrix arrays with 200 rows and 640 columns or a total of 128,000 picture elements. Clearly, such a large display would be impractical. This is why liquid crystal, plasma and electroluminescent technology has come so far.



Light emitting diodes (LEDs) come in various shapes, sizes and colours and are also available as surface mount packages.





Fig. 1: The twisted nematic effect in an LCD structure with the electric field on and off.



ADILAM
Your reliable direct
distributor of Liton

Products include

Lamps and Light Bars
Numeric Displays
Dot matrix displays
Clock modules
Infrared products
Hybrid modules


—Contact us now for a product summary



Adilam Electronics
Pty Ltd

Melb. - Site 7, 145 Parker St Templestowe P.O. Box 52, Bullen, 3105	(03) 846 2511 Tlx 151369
Syd. - 30 Colson Cres., Monterey, 2217	(02) 587 1554
Adel. - N.S. Electronics	(08) 46 8531
Bris. - F. Hoe & Sons	(07) 277 4311
Canb. - Electronic Components	(062) 80 4654
Perth - Atkins Carlyle Prospec	(09) 481 1233 (09) 362 5011

What's new in display technology



This graphic type plasma display from Oki runs off DC power.

Vacuum fluorescent displays

After LED displays, vacuum fluorescent displays are probably the most popular type. They are and have been used in countless digital clocks, VCRs, AM/FM tuners, microwave ovens and so on. In these cases they are typically four digit alphanumeric or seven-segment displays coupled with annunciators (ie, illuminated legends) to indicate various modes of the particular appliance.

The big reason why they have been so universally popular is that they are so attractive with their soft blue or blue-green lighting. They are actually based on a very old technology, being similar to that used in the much-loved "magic-eye" tun-

ing indicator used in old valve radios and to some extent as a level indicator in early tape recorders.

As such, the vacuum fluorescent technology is based on the thermionic tube and in particular, on the directly heated triode. The typical display has a filament which is in the form of a mesh across the inside of the front glass. Then there are grid lines, one for each display segment or element and finally, the anode lines which actually are fluorescent material deposited on the inside of the back panel of the display.

The filaments are heated by passing current through them and so they emit electrons. The electrons are accelerated to the anodes depending on whether the




Fig.2: the structure of an Electro Luminescent display unit.

associated grids are slightly positive, to enable electron flow, or negative, to stop current flow.

Such vacuum fluorescent displays require an anode supply of around 135 volts DC as well as a filament supply. The driver circuitry need not supply any current though, since it is used to control the grid lines. Again, the multiplex drive method is used to reduce the number of connections.

Recently, the Japanese manufacturer Futaba has developed a high resolution vacuum fluorescent display module which will be able to compete directly with large LCD and plasma displays. The new VFD module has 640 x 400 dots with a dot pitch of 0.28 x 0.28mm. The panel comes with a 32-bit control board which converts standard RGB signals intended for a video monitor into the drive signals for the display.

Liquid crystal displays

By far the most efficient display technology is the liquid crystal display. It uses far less current than any other display technology and only requires a few volts drive. A comprehensive report on liquid crystal displays was featured in the October 1985 issue of EA but for those who did not see that article, we will give a brief summary here.

Liquid crystal displays (LCDs) first made their appearance in watches and calculators but now the list of applications has expanded to embrace virtually every electronic device that has a read-out. Unlike all other displays, LCDs are passive. They do not emit light themselves but modify incident light which may be scattered, reflected or transmitted by the display.

In a typical LCD, the liquid crystal (an organic fluid which can exist in a "mesophase") occupies the space between two parallel glass plates which are separated





Fig.3: A Vacuum Fluorescent Display module structure for a large panel (640 x 400 dot).

by a distance of just a few microns. The inner surfaces of these glass plates have transparent electrodes which define the characters to be displayed. The electrode surfaces are treated to induce the long molecules of the LCD fluid to align in one direction, parallel to the plates.

This is how the common LCD description, "twisted nematic" arises. Nematic means thread-like and so twisted nematic LCDs have the induced direction of the front and back plates at right angles to each other. Hence, the liquid crystal structure is twisted through 90 degrees from the back plate to the front plate.




The Oki character type plasma displays are available in a large range of models, from 64 characters to 1,920.

Choosing the right display for your coins, medals or stamps is easy when you buy a presentation PYX.

This innovative small display cabinet is handcrafted to give your coin, medal or stamp an appropriate resting place. Despite it being totally enclosed you'll have a global view. The content is dustproof, yet you may take it apart anytime.

It comes in a highly polished brass or in 24 carat pure gold plate. There are many models available for you. Send for your obligation free brochure NOW. **Prices from \$39.60**




To: Elja Enterprises
P.O. Box 667
Cheltenham 3192
or Tel: (03) 583 8274

Main Interest is
☐ Coins ☐ Medals ☐ Stamps

Please forward an obligation free brochure to:

Name
Address
Postcode

What's new in display technology



An EL graphics panel from Sharp.

Now, and this is crucial to the whole process, if a voltage is applied between the two plates, the crystal structure of the liquid is broken as the long molecules align themselves parallel to the electric field.

Also crucial to the operation of LCDs are the polarising filters which are usually fitted over the front and back plates. These filters are also arranged at 90 degrees so that no light can pass through them. Hence, when voltage is applied between the plates, light passes through the front polarising filter, through the aligned liquid crystals and thence the rear polarising filter where it is absorbed.

When no voltage is applied, light passes through the front polarising filter, then through the helix crystalline structure of the liquid thereby having its planer of polarisation rotated by 90 de-

grees. This allows it to pass through the rear polarising filter, be reflected from the rear mirror coating and back out the front. Hence, where no voltage is applied, the display appears silvery grey.

The above description applies to the most common LCD, the twisted nematic reflective type. Variations on the use of polarising filters and mirror coating allow other modes to be used such as transmissive (used with back-lighting) and transreflective which is a compromise allowing both reflective and backlit modes.

Colours can also be added to LCDs either by the use of colour-selective polarising filters, coloured filters, coloured back-lighting or dichroic dyes in the liquid itself. The last named are known as guest-host displays and are capable of brilliant colours.

Multiplexing


A comparatively recent development in LCD technology is the use of multiplex drive. At first all LCDs were directly driven but for large complex LCDs as used for personal computer screens this is impractical, as it is with any other large display. The catch with LCDs is that multiplexing reduces the contrast and legibility of the display and it gets worse as the multiplex drive ratio (ie, the duty cycle) increases. For the most complex 640 x 400 pixel (picture element) displays, the multiplex ratio can be as high as 100:1 and the contrast ratio may be less than 3:1 which means that it can be almost unreadable under anything but ideal conditions.

During the last year, the manufacturers have improved this aspect of LCDs with the introduction of the super-twist display. This is a variation on the twisted nematic display whereby the crystalline helix is rotated through 270 degrees instead of 90 degrees. The resulting displays are certainly more legible under a wider range of lighting conditions but they still have a considerable way to go before they can really compete with the CRT (cathode ray tube) for a video display.

Plasma displays

Apart from display contrast, the big problem with LCD screens is the restricted viewing angle. Move just slightly off-axis to the display and its overall visibility diminishes drastically. This is the reason that plasma displays are becoming more widespread even though they are more expensive than CRTs or LCDs.

Interestingly, the plasma display is another example of an old technology dressed up in a new form. In fact, the plasma display is a very refined version of the gas discharge or neon tube. Each dot in a plasma display can be likened to a neon tube. It has an anode and a cathode with a gas in between at low pressure. This gas is a mixture of neon and a small amount of argon or xenon. A high volt-



Above are two LCD modules from Oki.



Do you look for a standard HCMOS supplier or for the one that sets the standard?

Right now, we have a complete range of high-speed CMOS (HCMOS) logic IC's. And we have them in both DIL and in our space-saving SO-package, now a JEDEC world standard. For your HCMOS needs come to us, Philips Elcoma, the Australian source.

Plug our pin and function-compatible 74HCT IC's straight into your LSTTL sockets – often without redesign! LSTTL level compatibility with dramatically reduced power consumption. Without sacrificing system speed, and at the right price.

Using MOS already? Then look at our 74HCT for TTL-level CMOS and NMOS systems, or our 74HC for all-CMOS systems.

Or, design-in HCMOS and enjoy all of its benefits. Like freedom from latch-up and high



Save board space. Our SO-versions are up to 65% smaller than comparable DILs, and are up to 10 times lighter.

reliability (5 FITS). Noise immunity critical? Then think about 74HC.

Space and cost conscious? Then use SO-versions and benefit from Surface-Mounted Device (SMD) technology.

At Philips, we know about CMOS. Ten years as European leader with the

HE4000B family has taught us a thing or two. About quality. And about design. Our patented HCMOS input structure, for example, makes it possible for us to produce 74HC (CMOS input levels) or 74HCT (LSTTL input levels) with a single mask change. So the type range is available in both versions.

Need samples or data? Then call your nearest Philips Electronic Components and Materials office. We're ready with full technical support and documentation. Plus a User Guide, set to become the standard for designing with HCMOS.

HCMOS
HIGH-SPEED LOGIC

The name is Philips
The product is HCMOS

Philips Electronic Components
and Materials
11 Waltham Street,
Artarmon, N.S.W. 2064
Telex AA20165 AUSLCEC +

Sydney
Melbourne
Adelaide
Perth
Brisbane

(02) 439 3322
(03) 542 3333
(08) 243 0155
(09) 277 4199
(07) 44 0191

the UN 279



Electronic
Components
and Materials

PHILIPS

SUBSCRIBE

receive **A FREE PRECISION**
and your chance to **WIN A**



CONDITIONS OF ENTRY

1. Entries close last mail February 27, 1987.
2. Entry to the prize draw is achieved by returning a completed subscription card and payment. Entry is open to both new and renewal subscribers.
3. Entry is open to all residents of Australia other than the employees and immediate families of The Federal Publishing Company Pty. Ltd. and Daihatsu and their associated agencies and publications.
4. The draw will take place on March 4, 1987, and the winner will be notified by mail and the result published in The Australian newspaper date March 13, 1987, and a later issue of the magazine.
5. Prizes must be taken as offered. There is no cash alternative. Prizes are not transferable and cannot be altered in any way.
6. The vehicle prize of a Daihatsu Charade includes all on-road costs, including third party insurance and registration.
7. Federal Publishing will arrange delivery of the vehicle within Australia within one month of the winner being drawn. If delivery is required outside of Australia, this becomes the responsibility of the winner.
8. Permit No.: T.C. 86/2203 issued under the Lotteries and Art Unions act 1901; Raffles and Bingo Permits Board Permit No. 86/1013 issued on 15/9/86; ACT Permit No. TP86/650 issued under the Lotteries Ordinance, 1964.

• The Pace • The Feel • The Space • The Ride

• The Luxury • The Style • The Eco

NOW!

SCREWDRIVER SET

"CHARADE" from "DAIHATSU"

FREE SCREWDRIVER SET

with all new or renewed subscriptions

- ★ Chrome plated and presented in plastic storage case.
- ★ Free running top on each driver gives operator ease of use.
- ★ Consists of 4 blade drivers from 1.4 mm to 2.9 mm and 2 Phillips screwdrivers, No. 0 and No. 1.



LIMITED OFFER, SO POST SUBSCRIPTION CARD TODAY!!
(If card missing, please phone (02) 693-6666 and ask for the Subscriptions Department).



"Daihatsu.
That's who."




*See Subscription
Coupon*


conomy • The Options • The Safety

• The Ride • The Space • The Feel • The Pace


IT'S NO SURPRISE!




Light Bar Modules.



Opto Couplers.



Fibre Optic Components.




LED's and displays.



Bar Code Wands.



Optical Encoding.



Microwave Semiconductors.

H.P. stands for high performance

HP's quality and reliability ensures top performance. You can design in HP products with confidence that they will perform as specified, even in the most demanding environments. Their reliability has been proven over and over in a wide variety of applications, and they

are backed by HP's worldwide reputation.

If you require LEDs, light bar modules, fibre optic devices, bar code wands, optical encoders, microwave semi-conductors or the world's fastest opto couplers – choose Hewlett-Packard, and call VSI, Australia's authorised distributor.

VSI

THE SOURCE OF
 **HEWLETT
PACKARD**
COMPONENTS

VSI Electronics (Aust) Pty. Ltd.,
16 Dickson Avenue, ARTARMON,
NSW 2064, AUSTRALIA.
Telephone (02) 439 8622.
Telex AA22846.

◆ QUEENSLAND (07) 52 5022 ◆ VICTORIA (03) 543 6445 ◆ SOUTH AUSTRALIA (08) 267 4848 ◆ WESTERN AUSTRALIA (09) 328 8499

Meridian VSI 0002

What's new in display technology

age is applied between the anode and cathode which causes the gas to ionise and glow. Thus there is light output while ever voltage is applied.

In practice, practical dot matrix plasma displays are much more complicated than this simple description would indicate. Again, for practical displays, the multiplex drive method is used. For a 640 x 400 dot display there are 640 cathode lines and 400 anode lines (or vice versa). So there are effectively 256,000 plasma cells which are progressively scanned to build up the display. The anodes and cathodes are laid out in a matrix of long thin conductors embedded in glass plates. The gas is contained in tiny cavities at each intersection which are each divided to form three separate cells.

One of these is the main display cell while the other two are auxiliary cells — the constant discharge (or DC pilot) cell and the scanning cell. The constant discharge cell provides a constant stream of ions to neighbouring display cells and auxiliary cells to effectively "bias" them. For their part, the auxiliary cells are used to transfer the discharge across the whole display. They are used because the main display cells would otherwise take too long to turn on from cold, which would result in a flickering display.

As with other large displays, plasma panels are supplied complete with all the interfacing circuitry so that they can be controlled with standard RGB signals intended for a video monitor. While orange is the most frequently seen plasma colour, these displays are also available in green.

Custom made plasma panels are currently available in very large sizes, up to as much as half a metre square in some cases. IBM has a plasma screen unit which will simultaneously display four video screens. And the Australian submarine project envisions a map table based on a large plasma panel.

Apart from its large size, non-critical viewing angle, high brightness, and lack of flicker, the plasma display is attractive because it is relatively compact, with a small front to back dimension of around 50mm or so. Its main drawback is its relatively high power consumption which can range up to 200 watts for a large panel. Even so, their compact size is making them popular for the more expensive portable personal computers such as those made by Toshiba and Panasonic (Matsushita).

Electroluminescent panels

In the early sixties, electroluminescence or "cold light" was expected to be the light source of the future. It seems that as far as that prediction is concerned, the future has yet to arrive but they have been developed into an alternative display medium by companies such as Sharp and IEE.

An electroluminescent (EL) display relies on the property of some substances to give off light when subjected to a sufficiently high voltage. The substance used in today's panels is zinc sulphide doped with manganese which produces an easily readable amber display.

By sandwiching a layer of the luminescent material between sets of horizontal and vertical electrodes, a voltage can be applied across small areas of the panel to make it glow. So whenever a row and column electrode are energised, the material at the intersection glows to produce a dot on the display. As with other panels such as LCD and plasma, EL panels therefore lend themselves to multiplex drive and the manufacturers package the panels complete with all interface and power supply circuitry.

Power consumption is relatively low, with large panels consuming less than 20 watts overall.

Also as with other panel displays, the EL display is based on a glass substrate. But since it does not employ a vacuum, a fluid or a gas at low pressure, it is claimed to be more rugged and able to be used at very high altitudes, making it suitable for use in military aircraft.

The EL panel has additional advantages of even higher brightness than plasma displays, wider viewing angle (vir-

tually the same as this page) and a contrast ratio of up to 100:1 (also comparable with this page). However, the present high cost of EL panels tends to limit their use to very specialised applications, mostly in defence.


And the winner is: the CRT

When all is said and done though, the cathode ray tube is still by far the most popular and efficient display for use with computers. It is capable of much better resolution than competitive displays and is simpler to drive in that it does not require multiplex circuitry. In monochrome form it is available in green or amber and of course, it is the only high resolution display format which is available in colour.

Because the CRT has been evolved over many years and used in such large quantities for television receivers, the technology is now highly refined and very reliable. But whereas all colour television receivers now use self-converging tubes with in-line guns, the higher resolution colour monitors for personal computers still use shadow-mask tubes with the triad gun format. This is somewhat harder to adjust for optimum performance but is capable of the higher resolution needed for today's very detailed computer displays as used in computer-aided design software.

While the CRT still tends to have a big lead in overall performance compared to other display formats, it still has a number of drawbacks. These include weight and bulk of the tube, the tendency to produce electromagnetic interference (from the sweep circuitry), relatively high power consumption and lack of ruggedness (unless a ruggedized version is specified).

Even so, the CRT is likely to remain king for at least the next five years or so, and perhaps for a good time beyond that.



Above is a prototype LCD dashboard module developed by Bosch Engineers in Australia.

For experimenters:

DX reception with small AM radios

DXing is the art of listening to radio stations over long distances. Here's how to increase the number of stations that you can receive.

by STEVE PAYOR

The AM-3 radio (EA, February 1986) used a ZN414 integrated circuit for the "front end". One of the problems with this IC is the lack of a wide range of Automatic Gain Control (AGC), and for this reason the AM-3 has a manual gain control to trim back the gain for strong signals. But what about very weak signals?

With the ZN414, any signal input below $50\mu\text{V}$ will not be heard at all, because it is below the threshold of the

detector. This limits the useful range of the AM-3 to a hundred miles or so under good conditions.

For those constructors of ZN414 radios who live in remote areas, or who just want more signal from their favourite station, the following ideas will bring the signal up to a level which can only be described as "loud".

Furthermore, no modification to the receiver is necessary — you don't even have to open up the case!

Picking up more signal

Firstly, string up 10 to 20 metres of wire as an aerial. Insulated hookup wire will do fine. It should be as high as possible, but the picture rail will usually suffice. Connect one end directly to a good RF earth: a grounded water pipe is best, but the case of an *earthed* mains appliance will do.

The RF currents now flowing up and down the wire should be strong enough to be picked up by simply holding the ferrite rod aerial near the down-lead (Fig.1).

For more signal, wrap the wire once or twice around the radio as shown in Fig.2. Note: in any metropolitan area, two turns will completely saturate the ZN414.




Fig.1: Coupling in a signal from an external aerial can be as simple as putting the radio near the down-lead.




Fig.2: Stronger signal coupling can be obtained by wrapping the down-lead around the radio.

Tuning the aerial

For more selectivity, use an aerial tuning coil. This is the reception technique which allowed early radio receivers to perform so well without any form of electronic amplification.

To make a suitable aerial tuning coil, you will need a piece of cardboard tube which will comfortably slide over a length of ferrite rod. On this tube wind a coil of 120 turns of enamelled copper wire. (Note: Most parts suppliers stock a small rectangular ferrite rod, complete with coil which is ideal for this application; eg. Dick Smith L-0520, Jaycar LF-1015).

By inserting this coil between the aerial and earth, the whole system can be made to resonate at the desired signal frequency by simply sliding the rod in or out of the coil. (At broadcast band frequencies, the aerial itself behaves as a simple capacitor to ground, with a





Fig.3: Aerial tuning and "loose" coupling provides ultimate selectivity and sensitivity.

value of around 100pF to 300pF.)


Putting the AM-3 anywhere near the tuning coil will give you more signal than the ZN414 can use. A spacing of about 100mm can be used as a starting point (Fig.3). Optimum signal transfer will occur with quite "loose" coupling.

If the coupling is too "tight", the two

tuned circuits will interact and form a double-humped response curve, making tuning a frustrating exercise. So start with the coupling loose and simply peak each tuned circuit separately for best reception.

The improvement in reception is quite dramatic: crystal set owners take note! 

BOSE®



Sound Professionals demand high quality loudspeaker systems at home, in the car and at work.

Only Bose hifi speakers produce a combination of reflected and direct sound, similar to what you hear at a live concert. Not to mention stereo throughout your listening room, not just between the speakers!

If you demand quality with lifelike performance you owe it to yourself to check out Bose Direct Reflecting Speaker systems for your home and car very soon.

Please send me further information on Bose Speaker Systems.

- ☐ Professional ☐ Car
☐ HiFi ☐ Commercial

Name

Address

.....Postcode.....

BOSE(Australia) Inc, 11 Muriel Ave,
Rydalmere, 2116 N.S.W. Ph (02) 684-1022

Another nail in the analog coffin

Digital Signal Processing

Last month, we looked at the basic theory behind digital signal processing (DSP). This second article considers digital filters, describes how they are designed, and looks at the algorithms used to implement them.

by MIKE FAULKNER

Lecturer at the Footscray Institute of Technology

Filtering is one of the most important and widely used signal processing operations. Digital filters, like analog filters, are used to reject noise, separate signals of different frequencies, modify signal characteristics, and compensate or equalise previous distortions.

Filter characteristics

Filters are normally characterised by their frequency selective behaviour; ie. low-pass, high-pass, bandpass etc. The frequency selective property of a filter, however, is not its only important characteristic. Transient response problems such as risetime limitations and ringing effects can have detrimental effects on some types of input signals (data, for example).

Filter phase response and group delay can also cause problems. Group delay is a measure of the time required for different frequency components to get through the filter. For minimum distortion the group delay for all frequencies within the passband should be the same. This means that frequencies that start out together will arrive at the filter output together, and will not be dispersed in time.

Filters with a constant group delay have a linear phase characteristic; that is, a phase shift that increases linearly with frequency. The terms "linear phase" and "constant group delay" are synonymous. Unfortunately, for many filter classes the group delay is not constant. An illustration is given in Fig.1.

The design of filters is often a compromise between conflicting requirements, with the emphasis being determined by the application. Data signals, for example, require a good group delay and transient response and so selectivity is often sacrificed. Audio signals on the other hand can exploit the ear's low sensitivity to group delay distortion and so highly selective filters with poor phase characteristics can be used. In many hifi applications, tone control circuits and speaker crossover networks still do not have constant group delay.

Even in this day of computer aided design, the filter designer is still required to have a considerable amount of experience. Not only are there specification trade-offs, but there is also a cost and implementation problem.

Normally a designer will choose a certain class of filter ap-




Fig.1: fourth order elliptic bandpass filter. (a) Frequency response. The specifications are: passband ripple ± 0.1 (1.74dB); stop-band attenuation 0.1 (20dB); passband cutoff frequencies $F_{c1} = 1.5\text{kHz}$, $F_{c2} = 2.2\text{kHz}$; stop-band frequencies $F_{a1} = 1\text{kHz}$, $F_{a2} = 2.2\text{kHz}$. (b) Group delay. Frequencies near the passband edges experience the most delay which is a common occurrence in filters.

Pt.2

proximation (Butterworth, Chebyshev, etc.) based on group delay, transient response, and implementation considerations, and then design the filter to a frequency specification. The list below shows the necessary specifications for a bandpass filter. These apply to both analog and digital filter design.

(1). Passband ripple: ideal filters have a passband gain of unity. The ripple error is a measure of the tolerance the designer is prepared to accept on this passband gain. Values between 0.1dB and 1.0dB are common. Obviously, the lower the ripple specification the more complex the filter.

(2). Cut-off frequencies (F_{c1} and F_{ch}): these define the passband edges.

(3). Stop-band attenuation: the minimum attenuation required throughout the stop-band. The greater this attenuation the more complex the filter. Attenuations between 30dB and 60dB are common.

(4). Stop band frequencies (F_{a1} and F_{ah}) — the stop-band edges: the required minimum attenuation must be reached by these frequencies. The narrower the skirts ($F_{ah}-F_{ch}$ and $F_{c1}-F_{a1}$), the more complex the filter.

These specifications are illustrated diagrammatically in Fig.1. The designer does not normally care about the actual shape of the filter response provided the specifications are met; ie. the response falls within the set limits.

Digital Filters

The constant coefficient difference equation is the most common algorithm for implementing digital filters. It effectively says that the output is a function of the input, previous inputs and

previous outputs.

$$y_n = a_0 x_n + a_1 x_{n-1} + a_2 x_{n-2} + \dots - b_1 y_{n-1} - b_2 y_{n-2} - \dots$$

The coefficients a_0, a_1, b_1, b_2 , etc determine the filter's characteristic; the current input and output are x_n and y_n , and the previous input and output are x_{n-1} and y_{n-1} etc. Fig.2 shows the implementation block diagram. The blocks marked T represent a delay of one sample period. The z transfer function of this equation is shown below, where Z^{-1} represents a delay of one sample period (T seconds).

$$H(z) = \frac{Y(z)}{X(z)} = \frac{a_0 + a_1 Z^{-1} + a_2 Z^{-2} + \dots}{1 + b_1 Z^{-1} + b_2 Z^{-2} + \dots}$$

The order of the filter is given by the highest power of Z^{-1} in the expression. The order of the filter is a measure of its complexity and the number of poles it has. The transfer function of a first order filter is shown below. This filter can have a response similar to that of a simple analog RC low-pass network.

$$H(z) = \frac{Y(z)}{X(z)} = \frac{a_0}{1 + b_1 Z^{-1}}$$

Digital filters may be classified as either recursive, having an infinite impulse response (IIR); or non-recursive, having a finite impulse response (FIR). The FIR digital filter is essentially a delay line in which the output is formed by applying various weighting factors to the delayed input signal. The output is not a function of the previous outputs and so all the b coefficients in the previous two equations are put to zero.

Fig.3 shows an example of a three coefficient digital FIR filter. The coefficients, a_0, a_1 , etc represent the impulse response of the filter.

Given enough coefficients, FIR filters can implement any amplitude and phase characteristic. Normally, however, they are used to implement linear phase (or constant group delay) filters. Their disadvantage is in the number of coefficients, and hence the processing effort, required to get an acceptable frequency response.

On the other hand IIR filters can be made very selective for a given processing effort (number of multiplications and addi-




Fig.2: implementation block diagram — direct form. T represents a delay of one sample period.





Fig.3: implementation block diagram of an FIR filter with three coefficients.



TEXAS TMS320

OVERVIEW

TI's TMS320 family comprises six high-speed digital signal processors (DSPs) — the broadest family of these devices available today. All are capable of implementing complex, numeric-intensive algorithms in real time. Among them you can find the device to meet a wide range of price/performance goals. While family compatibility reduces development costs and speeds time to market.

TI's DSP family is a reliable, flexible replacement for analog systems, and it provides designers with high-performance alternatives to conventional microprocessors and microcontrollers.

The Harvard architecture of TI's TMS320 family increases parallelism for higher throughput; and these economical, programmable, general-purpose DSPs can accomplish many tasks that formerly required expensive custom or bit-slice solutions. As the industry standard, TI's TMS320 family minimizes your design risk.

APPLICATIONS

DSP is finding applications as varied as:

- Telecommunications
- Voice/speech processing
- Graphics/image processing
- Control systems
- Instrumentation

And benefiting users in such fields as:

- Manufacturing
- Consumer goods
- Automotive
- Medical
- Military

DEVELOPMENT SUPPORT

Texas Instruments can also provide an extensive catalog of development tools and support, including:

- Emulators and evaluation modules
- Assemblers, linkers, and simulators
- Applications software
- Training workshops
- Third-party hardware and software
- Local technical support

◀ Setup is as simple as 1-2-3 with Lear Siegler's adaptive telephone repeater using TI's TMS32010 DSP. Whereas manual adjustment of an analog repeater can take many hours, only three simple switch settings are required to assure rock-stable, "sing"-free performance from the digital repeater.

INSTRUMENTS DIGITAL SIGNAL PROCESSORS

SOLUTIONS . . . WITH TI's PROCESSOR OF CHOICE.

Texas Instruments' general-purpose DSPs are cost-effective solutions — not only to realtime communications tasks, but to a wide range of applications involving high-speed, numeric-intensive computations. In telephony, data communications, graphics applications, industrial controls, general signal filtering . . . The possibilities are bounded only by your imagination. TI provides solutions to do your whole job — not just part of it.

Off the drawing board . . . into the hardware of choice

Let Texas Instruments help speed your DSP project to market. Get the TMS320 DSP Design Kit (TMS320DDK). It contains the key building blocks you



Everything you need to prototype your DSP system — from chips to code — is included in TI's TMS320 Design Kit.

need to prototype your system: DSPs, peripherals, more than 700 pages of application notes, and four floppy disks with applications source code. It's a cost-effective way to get started. And you can get it from your nearest TI Field Sales office or authorized distributor now.



In-depth support for TI's TMS320 family of DSPs includes host-independent development systems, an evaluation module, an emulator, and an analog interface board, as well as assembler/linkers and simulators that can run on a variety of host computers and PCs. Documentation and application support are extensive and thorough.

TI's TM320 FAMILY OVERVIEW

	MEMORY				CYCLE-TIME				PACKAGE				I/O		INSTRUCTIONS	TECHNOLOGY	SMJ MILITARY
	ON CHIP		OFF CHIP		ns				DIP		PGA	PLCC	SER	PAR			
	RAM	ROM	PROG	DATA	200	160	125	100	40	68	44	68					
TMS32010	144	1.5K	4K		✓	✓			✓		✓			8x16	60	NMOS	✓
TMS32011	144	1.5K			✓				✓				2	6x16	60	NMOS	
TMS320C10	144	1.5K	4K		✓	✓			✓		✓			8x16	60	CMOS	✓
TMS32020	544		64K	64K	✓					✓			1	16x16	109	NMOS	✓
TMS320C25*	544	4K	64K	64K			✓	✓				✓	1	16x16	133	CMOS	✓

*In development. Contact your nearest TI Field Sales Office for availability or further information.



Texas Instruments Australia, 6 Talavera Rd, North Ryde 2113
Telephone: (02) 887-1122

Please tick selection

- ☐ Rush me a copy of the 700 page "Digital Signal Processing Applications with the TMS320 Family".
- ☐ Place my name on the TMS mailing list.

Name:

Company:

Address:

City: State: Postcode

Telephone: ()

Signal Processing




Fig.4: the major design approaches for IIR digital filters. The bilinear transform is used by most commercial CAD packages.

tions.) The rest of this article will concentrate on the IIR type of digital filter.

IIR digital filters

Because these filters include at least one feedback path their impulse response will, theoretically, never completely die away. In this respect, IIR filters are similar to analog filters and in fact the majority of IIR filters are obtained by designing the analog filter first.

The main steps in the design of IIR filters are shown in Fig.4.




Fig.5: amplitude distortion caused by the impulse invariant transform.





Fig.6: frequency distortion caused by the bilinear transform. This is compensated for by changing (pre-distorting) the original cut-off and stop-band specifications.

MAGNITUDE RESPONSE



Classical Filter Approximations

Many digital filter designs are based on classical analog approximations. In particular, IIR filters are almost wholly based on these approximations. The following table reviews the features of the more important types. Some of these points are illustrated in Fig.7.

- Butterworth
 - flat response in the passband (no ripples)
 - medium selectivity near cut-off
 - attenuation approaches 20dB/decade/pole
 - poor group delay

There are a number of possible approaches. The indirect approach involves designing an analog filter first. This filter is normally one of the classical types; ie. Butterworth, Chebyshev or elliptic, depending on what is appropriate for the application (see Classical Filter Approximations). Analog filters are normally designed from tables which give the pole and zero locations of their transfer function in the s-plane.

There are many transforms for converting an analog filter to a digital filter, three of which are shown in Fig.4. In each case, however, the resultant frequency response is distorted, especially in the vicinity of half the sampling rate. The main features of each transform are listed below.

(1) The impulse invariant transform gives the digital filter an identical impulse response to the analog filter. The frequency response of the resulting digital filter has an amplitude distortion which is illustrated in Fig.5. This distortion can be reduced by using sampling rates which are high compared to the cut-off frequency. This transform is not suitable for high-pass filters.

(2) The matched z transform maps the s-plane poles and zeros into the z-plane (see "Z Transforms, Transfer Functions, Poles and Zeros"). This transform has similar limitations to the impulse invariant transform.

(3) The bilinear transform compresses the frequency axis of the analog filter before mapping the s-plane poles and zeros into the z-plane (Fig.6). This overcomes the problems of the above two transforms, but necessitates a modification of the initial cut-off frequency specifications to compensate for the frequency distortion. Although complex, this is the most popular method for designing digital filters and is used by most commercial CAD programs.

Direct design methods obtain the digital filter transfer function directly from the specification. Design equations exist for the mathematically simpler classical filter types such as the Butterworth response, for which a program is included in the section on CAD of Digital Filters.





Fig.7: three classical approximations to the same filter specification — (a) 6th order Butterworth, (b) 4th order Chebyshev, (c) 3rd order elliptic.

- Chebyshev
 - equal ripple in the passband
 - high selectivity near cut-off (steep skirt)
 - attenuation approaches 20dB/decade/pole
 - very poor group delay
- Elliptic or Cauer
 - ripples in pass-band and stop-band
 - highest selectivity near cut-off
 - very poor group delay
- Bessel
 - flat response in the passband
 - poor selectivity near cut-off
 - constant group delay
- All-pass
 - flat amplitude, unity gain
 - variable phase or delay (often used to equalise the phase response of other filters).

Implementation of IIR filters

Although the structure shown in Fig.2 can be used to implement IIR filters, it is not normally used. This is because coefficient quantisation effects can cause large changes in the filter characteristics. This problem is reduced by splitting the overall transfer function into a cascade of smaller second order (and perhaps one first order) sections as shown in Fig.9. Each of these smaller sections, often called biquadratic sections, account for two poles and up to two zeros of the overall transfer function.

The implementation structure shown is to be preferred to a second order version of Fig.2. It uses fewer delay elements and

therefore less memory. Implementing this section in software first requires the calculation of the variable w_0 , then the calculation of the output.

$$w_0 = x - b_1 w_1 - b_2 w_2$$

$$y = a_0 w_0 + a_1 w_1 + a_2 w_2$$

A computer flow diagram for the implementation of a filter with four second order sections is shown in Fig.10, and a listing




Fig.9: (a) factorising a high order transfer function into second order (with perhaps one first order) biquadratic sections; (b) implementation block diagram of one such section.




Fig.10: flow diagram — implementing an IIR filter.

Signal Processing

of a BASIC program to simulate the response of the filter to a sine wave input is shown in Fig.11. The program is suitable for the IBM-PC and compatibles.

The implementation of the delay block (T) takes some under-

```

10 REM *****PROGRAM TO SIMULATE CASCADED BIQUADRATIC STAGES *****
100 REM READ "NO. OF STAGES", "CONSTANT GAIN FACTOR", "COEFFICIENTS"
110 READ N,CGF
120 FOR M=1 TO N
130   READ A0(M),A1(M),A2(M),B1(M),B2(M)
140 NEXT M
200 REM *****RUN FILTER, SIMULATE INPUT*****
205 INPUT "ENTER INPUT FREQUENCY WRT SAMPLE FREQUENCY (MAX 0.5)",F
210 FOR J= 1 TO 50
215   X0 = SIN(2*3.14159*J*F)
217   REM EXECUTE ALGORITHM
220   X=X0*CGF
230   FOR M=1 TO N
240     GOSUB 300
245     X=Y
250   NEXT M
260   REM DISPLAY ON SCREEN
270   PRINT TAB(INT(19*(1+X0)+1.5)) "*" TAB(INT(41.5+19*(1+Y))) "Y"
280 NEXT J
285 PRINT TAB(15) "INPUT SIGNAL" TAB(55) "OUTPUT SIGNAL"
290 END
300 REM *****BIQUADRATIC SECTION*****
310 W0(M) = X - B1(M)*W1(M) - B2(M)*W2(M)
320 Y = A0(M)*W0(M) + A1(M)*W1(M) + A2(M)*W2(M)
330 W2(M) = W1(M)
340 W1(M) = W0(M)
350 RETURN
1000 DATA 4,.0000001762
1010 DATA 1,2,1,-1.794,0.8863
1020 DATA 1,2,1,-1.623,0.7069
1030 DATA 1,2,1,-1.513,0.5912
1040 DATA 1,2,1,-1.460,0.5348

```

RUN

ENTER INPUT FREQUENCY WRT SAMPLE FREQUENCY (MAX 0.5)? .06




Fig.11: IIR filter simulation program. Input data format is 1000 DATA (no. of biquad. sections), (CGF) 1010 DATA (a_0), (a_1), (a_2), (b_1), (b_2) etc.

Computer Aided Design (CAD) of Digital Filters

Just as VLSI has helped in the implementation of DSP algorithms (to the point where they are serious contenders for signal processing systems handling frequencies up to 20kHz), so has the advent of CAD reduced the design effort in deriving the algorithms in the first place.

For example, programs now exist which can design digital filters and then automatically write the assembly code for their implementation on a DSP microprocessor. Any serious DSP designer should have access to one of these packages. The potential saving in design time is immense. To give an example, the first digital filter designed by the author took three days (before CAD packages were generally available); the same filter designed on one of these packages would probably take 30 minutes.

Unfortunately, these packages are expensive so a small BASIC program is included here for those readers wishing to design their own filters (Fig.8). The program is limited to low-pass even order Butterworth designs. The program will generate coefficients for the second order biquadratic sections, and a constant gain factor (CGF) which is necessary to normalise the DC gain of the filter to unity.

The same program can be used to obtain a high-pass response with the aid of a low-pass to high-pass transformation. In this case, replacing Z^{-1} with $-Z^{-1}$ in the transfer function (by inverting the sign of the a_1 and b_1 coefficients in each biquadratic section) changes a low-pass filter with a 3dB cut-off frequency of F_c to a high-pass filter with a 3dB cut-off frequency of $(F_s/2-F_c)$. Transforms for bandpass and band-stop also exist (see T.J. Terrell, "Introduction to Digital Filters", Macmillan 1980).

```

10 REM  CALCULATION OF BUTTERWORTH LP BIQUADRATIC SECTIONS
20 INPUT "FILTER ORDER (MUST BE EVEN)":N
30 INPUT "SAMPLE FREQUENCY HZ":S
40 INPUT "3DB CUT-OFF FREQUENCY HZ":C
50 F=C/S: PI =3.141593: A = TAN(PI*F): CGF = 1
60 PRINT "A0", "A1", "A2", "B1", "B2"
70 FOR M=0 TO (N/2-1)
80   T = (2*M + N + 1)*PI/(2*N)
90   D = (1 - 2*A*COS(T) + A^2)
100  U = (1-A^2)/D:V = 2*A*SIN(T)/D
110  CGF = CGF*(1-2*U+U^2+V^2)/4
120  PRINT 1,2,1,(-2*U),(V^2+U^2)
130 NEXT M
140 PRINT "CONSTANT GAIN FACTOR = ",CGF
150 END

```

RUN

FILTER ORDER (MUST BE EVEN)? 8

SAMPLE FREQUENCY HZ? 10000

3DB CUT-OFF FREQUENCY HZ? 500

A0	A1	A2	B1	B2
1	2	1	-1.793962	.8862831
1	2	1	-1.623406	.7069499
1	2	1	-1.513291	.5911681
1	2	1	-1.459706	.5348261

CONSTANT GAIN FACTOR = 1.762551E-07

Fig.8: Basic listing of a program to design even order low-pass Butterworth filters. The input requirements are the sample frequency, 3dB cut-off frequency, and the filter order. The output gives the bi-quadratic coefficients and the constant gain factor (CGF).



TEXAS
INSTRUMENTS

THIS

DIGITAL SIGNAL PROCESSOR DEVELOPMENT SYSTEM

**could be
yours!!!**

WIN
TOTAL VALUE
\$10,000




Includes:

Texas Instruments
Professional Computer

- TMS 32020
Evaluation Board
- TMS 32010
Cross Assembler/Simulator
- TMS 32020
Cross Assembler/Simulator
- TMS 320C25
Cross Assembler/Simulator

**GRAND
PRIZE!**

**TOTAL
VALUE
\$10,000**



Entries will be
judged on originality
and presentation.

ENTRIES CLOSE 15th DECEMBER, 1986

HOW TO WIN

*Simply explain in less than 500 words why you
deserve to win this Digital Signal Processing (DSP)
Development System.*

**Entries should include details on at least one DSP
application for which the system will be used.**

**ENTER
NOW!**

Send your entry to
The Editor,
Electronics Australia,
PO Box 227,
Waterloo 2017

The winner will be notified by mail and the result announced in the March 1987 issue of
Electronics Australia.

Signal Processing

standing. In this case, T is the time required for one complete program pass through the loop. In that time, data in variable w_0 becomes the previous data, in which case it is stored in w_1 . Line 340 of the program implements the first delay block, and line 330

the second.

That's all we have space for this month. In the final article, we will consider FIR filters and DSP implementation.

Footnote: in the box headed "The Discrete Fourier Transform (DFT)" on page 94 of last month's issue, reference is made in the second paragraph to equation (4). This should have read equation (3).

Z Transforms, Transfer Functions, Poles and Zeros

Using suitable CAD packages it is possible to design digital filters with little or no knowledge of z transforms. This section, therefore, is for readers interested in a better understanding of DSP theory.

The transfer function relates the output of a linear system to its input. Unfortunately, the transfer function only applies to transformed signals. The Laplace transform is used for analog signals, while the z transform is used for digital signals. In the digital case the transfer function $H(z)$ is the z transform of the impulse response h_n

$$H(z) = \sum_{n=-\infty}^{+\infty} h_n z^{-n}$$

and the output $Y(z)$ is related to the input $X(z)$ by

$$Y(z) = H(z) X(z)$$

The above equations effectively say that the operator, z^{-1} , represents a delay of one sample period (T). For example, the transfer function $H(z)$ of the DSP system with impulse response $h_n = \{0.5, 1.0, 0.5\}$ is

$$H(z) = 0.5 + 1.0 z^{-1} + 0.5 z^{-2}$$

Analysis of the transfer function can give some valuable insights into the behaviour of the network. In particular, the value of the poles and zeros of the expression can be used to determine the system's stability and frequency response.

Poles are the value of z that cause the expression $H(z)$ to go to infinity, and zeros are the values of z that cause the expression to go to zero. In the above expression two poles are located at $z = 0$, and two zeros at $z = -1$.

It is normal to plot the positions of the poles and zeros on a diagram called a z -plane (or s -plane for analog systems). Since poles and zeros can have real and imagi-

nary components, the plane has a real and imaginary axis as shown in Fig.12. Stability is guaranteed if all transfer function poles lie within a circle of radius one from the origin. Zeros have no effect on stability.

The s - and z -planes are related through the unit delay T because the Laplace transform of a fixed delay of T seconds is equal to e^{-sT} and the z transform is equal to z^{-1} and so

$$z^{-1} = e^{-sT} = e^{-(\sigma + j\omega)T}$$

This equation relates any point in the s -plane to a point in the z -plane. Using this expression the stable left hand region of the s -plane maps into a circle of radius 1 (unity).

One of the techniques for designing digital filters is to first obtain the pole and zero positions of the necessary analog filter, and then transfer them into the z -plane by using the above relationship (matched z transform); the digital transfer function $H(z)$ can then be obtained.

If, for example, we take the analog RC network of Fig.13, it has an analog pole at $s = -1/RC$ and a zero at negative infinity. These map into a pole on the z -plane at $z = e^{-T/RC}$ and a zero at the origin. The transfer function is therefore:

$$H(z) = \frac{Y(z)}{X(z)} = \frac{z - 0}{z - e^{-T/RC}} = \frac{1}{1 - e^{-T/RC} z^{-1}}$$

(Note: the DC gain of this function can be obtained by putting z equal to 1). This transfer function can easily be converted into a DSP algorithm by remembering that z^{-1} represents a delay of one sample period (T), or

$$y_n = x_n + e^{-T/RC} y_{n-1}$$

Substituting values for R and C , choosing a sample period $T = 0.1\text{ms}$ ($F_s = 10\text{kHz}$), and then compensating for the DC gain produces the algorithm

$$y_n = 0.01 x_n + 0.99 y_{n-1}$$

where 0.01 provides the gain normalisation.




Fig.12: mapping s -plane poles (zeros) into the z -plane. Z -plane poles outside the unit circle cause instability.

Interpretation of DSP Signals

When testing digital filters using a cathode ray oscilloscope (CRO) it is often difficult to interpret the results. This is because an accurately repeating sweep requires the synchronisation of three independent generators, these being the CRO timebase, the input signal and the DSP sampling rate. The trigger facility on the CRO can only synchronise to one other signal.





The other problem is illustrated in Fig.14. In all cases, the top trace is the analog input signal and the bottom trace the sample data output from the DSP.

Observers of the top photo could be tricked into thinking that their DSP algorithm was not working, the output appearing to be totally unrelated to the input signal. The individual steps, however, can be seen distinctly. This is because the CRO is triggering off the bottom trace.

Changing the trigger to the top (input) trace and then expanding the timebase gives the second photo. The relationship between the input and output can now be seen. The blur on the output trace is caused by the changing position of the output steps for each sweep of the trace. The horizontal width of the blur is equal to the output step size; ie. the sample period.

These effects are especially prevalent when the input signal frequency is close to half the sampling rate ($F_s/2$). Special care must be taken, therefore, when testing high-pass filters.

The last photograph shows the best of both worlds. However, this was obtained using a single sweep of the CRO. The sweep of the trace is normally too fast for the eye to follow, and a storage facility or camera is necessary.



$$H(s) = \frac{1}{s + \frac{1}{RC}}$$






Fig.13: Designing a first order IIR filter to emulate an RC network — (a) RC network and transfer function; (b) Converting the poles and zeros to the z-plane; (c) Implementation block diagram.

Fig.14: CRO traces showing a DSP output from the D/A converter — (a) Triggering off the output (bottom trace); (b) Triggering off the input (top trace); (c) Single sweep.



ECONOMY 4 CHANNEL MICROPHONE MIXER (MM1)


Its size and simplicity makes this mixer very portable and easy to operate.

SPECIFICATIONS:

- 4 low impedance 600 ohm microphone inputs.
- Individual gain control for each microphone.
- Master volume control.
- Power on LED.
- Inputs/Outputs - 6.3mm mono sockets.
- DC operated (9V battery only).
- Input impedance 600 ohm.
- Output impedance 1.5kohm.
- Signal/noise ratio 55dB.
- Frequency response 20Hz to 20kHz plus or minus 2dB.
- Weight 320 grams.
- Dimension 148 x 46 x 86mm.
- Torque variable range 1-22dB.
- Input sensitivity 1mV.
- Output level 90mV (at input 5mV).
- T.H.D. 0.01%.

Cat. A12001

\$44.95



12 CHANNEL STEREO MIXING CONSOLE (MX1210)

Loaded with professional features but simple to operate. A 3 position attenuation switch with -15dB, 0dB, +15dB, together with separate mic. and line inputs allows perfect matching with any input signal. Foldback with the pre-fade send or on stage monitoring. Includes bass and treble controls plus a left and right 5 band graphic equaliser. Other features include effect return panning, P.P.I. overload indicators and stereo headphone monitoring. Ideal for disco's with 2 stereo disc inputs with cross fade. A high quality 12 channel mixer for the professional enthusiast.

SPECIFICATIONS

Inputs:

- 12 x Mic -46dB at 47k ohm
- 12 x Line -20dB at 20k ohm
- 12 x Phono -52dB at 50k ohms (approx 2mV at 1kHz)
- Effect Return -20dB at 50k ohm

Outputs:

- PGM Out 0dB at 10k
- F/B Out 0dB at 10k ohm
- Effect Send 0dB at 10k ohm
- Rec. Out -4dB at 10k ohm
- Headphones +10dB at 600 ohm (100 - 1k ohm)
- Equaliser (Channel): Bass + -12dB (100Hz), Treble + -12dB (10kHz)
- Equaliser (Master): 100/330/1k/3.3k/10kHz, (5 band stereo) + -12dB
- Frequency Response: 20 - 20kHz (+1dB, -3dB)
- S/N Ratio (IHF-A): 120dB
- T.H.D.: 0.15% at 1kHz
- Peak Indicators: 12 x LED
- Power Supply: 240V AC 50Hz
- Power Consumption: 8W
- Dimensions: 662(W) x 356(D) x 105(H)mm
- Weight: 8kg
- RRP \$1,256

OUR PRICE \$1,150

16 CHANNEL STEREO MIXING CONSOLE (MX1610)

The same general description as the MX1210 but with the advantage of more channels.

SPECIFICATIONS

Inputs:

- 16 x Mic -46dB at 47k ohm
- 16 x Line -20dB at 20k ohm
- 16 x Phono -52dB at 50k ohm (approx 2mV at 1 kHz)
- Effects Return -20dB at 50k ohm

Outputs:

- PGM Out 0dB at 10k
- F/B Out 0dB at 10k ohm
- Effect Sound 0dB at 10k ohm
- Rec. Out -4dB at 10k ohm
- Headphones +10dB at 600 ohm (100 - 1k ohm)
- Equaliser (Channel): Bass + -12dB (100Hz), Treble + -12dB (10kHz)
- Equaliser (Master): 100/330/1k/3.3k/10kHz, (5 band stereo) + -12dB
- Frequency Response: 20 - 20kHz (+1dB, -3dB)
- S/N Ratio (IHF-A): 120dB
- T.H.D.: 0.15% at 1kHz
- Peak Indicators: 16 x LED
- Power Supply: AC117/220/240V, 50/60Hz
- Power Consumption: 8W
- Dimensions: 750(W) x 356(D) x 105(H)mm
- Weight: 9kg
- RRP \$2,330


OUR PRICE \$2,095

UNIVERSAL MIXER WITH CUE CONTROL (MM3)

- Microphone inputs 2 high or low impedance.
- Two stereo phono inputs magnetic or ceramic.
- 1 stereo line input for tape or tuner.
- Cue function with LED indicator for each input.
- Tape recorder output connections.
- Dual VU meters to monitor output and cue level.
- Mono/stereo mode selector.
- Battery test button to check their condition.
- DC or AC adaptor operation.

Input Sensitivity: Mic. low 0.7mV at 600 Ohm, Mic High 3.5mV at 50k ohm
Phono Mag. 2.5mV at 50k ohm, Phono Cer. 150mV at 100k Ohms
Tape Tuner: 150mV 50k ohms
S/N Ratio: More than 55dB
T.H.D.: Less than 0.5%
Frequency Response: 20 - 20kHz + -2dB
Output Level: 300mV
Recording Output: 120mV
Power Source: 9V DC (PP100/9)
Dimensions: 265 x 195 x 70mm
Weight: 1.8kg
RRP \$199

OUR PRICE \$179



UNIVERSAL STEREO MIXER WITH GRAPHIC EQUALISER (MM4)

The MM4 is our most flexible mixer. Incorporating the most advanced IC technology for performance and reliability. Built in graphic equaliser virtually eliminates the need for a pre-amplifier. Features 4 stereo program and 2 microphone inputs.


SPECIFICATIONS:

- Input Sensitivity: Mic. 1.5mV at 10k ohm, Phono. 1.5mV at 50k ohm, Line 75mV at 50k ohm
- Rated Output: Amp 1V/600 ohms, Rec. 1V/600 ohms
- T.H.D.: Less than 1% at 1kHz
- Hum and Noise: Mic. -52dB, Phono -62dB, Line -65dB
- Frequency Response: Mic. 30 - 16kHz (-1dB), Phono 30 - 20kHz (RIAA + -dB), Line 20 - 30kHz (-1dB)
- Power Source: 240V AC 50Hz
- Size: 360 x 260 x 85mm
- Weight: 2.9kg

EQUALISER SECTION

- Control of Frequency: 60Hz, 250Hz, 1kHz, 3.5kHz, 12kHz
- Control Range: + -12dB boost or cut - centre detent
- Headphone Output: (Cue) 50mW at 75 ohm at 0.5% T.H.D.
- Talk Switch: -14dB
- R.R.P. \$399

OUR PRICE \$379



MULTITRACK MIXING CONSOLE (MX842)

With balanced and Cannon inputs the MX842 is a complete multitrack mixing console. The four group out with stereo master configuration is designed for both studio and P.A. applications, either with a four track recorder or live P.A. mixing with the advantage of four sub groups. It is well equipped with all functions needed to produce first class results.

FEATURES:

- Balanced line inputs
- Cannon and 6.35mm inputs
- 240V operated, fuse protected
- Comprehensive headphone monitoring

Inputs:

- 8 x Mic: -46dB/18k ohm (Cannon)
- 8 x Line: -20dB/15k ohm (6.35)

Outputs:

- 2 x Master: Max. output +18dBV (Cannon)
- 4 x Group: Max. output +18dBV (6.35mm)
- 1 x Master Effect Send: Gain 18dBV (6.35mm)
- 2 x Record: Gain 18dBV (6.35mm)
- 1 x Headphone Output: 2mV-8kohm, 30mW at 500ohms
- Frequency Response: 20-20kHz + -2dB
- S/N Ratio: 120dB
- T.H.D.: Less than 0.15% at 1kHz
- Peak Indicators: 5 point master level control
- Power Consumption: 15W
- Power Supply: 240V AC 50Hz
- Dimensions: 622(W) x 105(H) x 356(D)mm
- Weight: 6.8kg
- R.R.P. \$1,425

OUR PRICE \$1,275



DISCO MIXER WITH GRAPHIC EQUALISER (MX1)

This stereo mixer is especially designed for discotheques and radio studios. It is a versatile rack or console mounting mixer with varied features which enable high quality broadcasts through its 3 microphone inputs, 3 phono inputs or 3 line inputs.

- 6 channel monitoring system
- 9 point dual LED output level display
- Output panpot
- 3 outputs
- Adjustable talkover with LED display
- Master level control

SPECIFICATIONS

Input:

- Talk Mic. 47k ohms nominal 5mV
- Mic. 2,3 47k ohms nominal 5mV
- Phono 1,2,3 47k ohms nominal 5mV
- Line 1,2,3 37k ohms nominal 300mV
- Output 1k ohm nominal 0.775V
- Rec. Out 1k ohm nominal 250mV
- Line Out 1k ohm nominal 250mV
- Frequency Response: Talk Mic. 150Hz - 7kHz -3dB, Mic. 2,3 15Hz - 30kHz -3dB, Phono 1,2,3 20Hz - 20kHz + -2dB, Line 1,2,3 15Hz - 100kHz -3dB
- S/N Ratio: (IHF-A) input short
- Talk Mic. -73dB/5mV
- Mic. 2,3 -73dB/5mV
- Phono 1,2,3 -76dB/5mV
- Line 1,2,3 -80dB/300mV
- Crosstalk: Better than 60dB/1kHz
- T.H.D.: Less than 0.1%/1kHz
- H.P. Out Level: 55mW/80 ohms - 1k ohm
- Eq. Frequency: 60/250/1k/4k/12kHz + -12dB
- Talk Over Level: -14dB
- Meter Level: 0dB = 0.775V/1.5V
- Power Consumption: 15 watts
- Power Supply: 240V 50Hz
- Dimensions: 482(W)x222(H)x130(D)mm
- Net Weight: 4.5kg
- R.R.P. \$865

OUR PRICE \$765



WIRELESS MICROPHONE RECEIVER WA100

(Waits for 150Hz (VHF) or 40MHz (UHF) this device will turn any microphone fitted with a Cannon Type male socket into a wireless microphone.

The receiver will plug into any 6.35mm microphone input. Both transmitter and receiver can be tuned from 76 - 81MHz.

Freq. Response: 50 - 16kHz
Tunable: 76 - 81MHz

Field Strength: Transmitter 10uV/100 metres

Receiver 15mV (100%)

Battery: Transmitter LR44 (1.5V)

Receiver 3 x UM4 (4.5V)

Instructions: Japanese (English not available)

Cat. A10520 R.R.P. \$199

Our price, only \$189



ARLEC "DISCO LITE" CONTROLLER

Give your parties a professional touch with the Arlec "Disco Lite". Simply plug your light(s) into the "Disco Lite" and you've instant party life!


3 DIFFERENT MODES!

Music Mode: Place the "Disco Lite" in range of the speakers and it flashes the lights to the beat of the music!

Strobe Mode: Simply adjust to desired speed! Great for mime or theatre! The christmas season or advertising!

Dim Mode: Allows you to dim the lights to create moods, effects etc.

Cat. M22003 \$49.50



MICROPHONE ECHO ADAPTER (SM100)

Gives microphones "depth"

Invaluable when using them in "dead" room/halls etc.

• Echo effects may be varied

• Volume control

• Power on LED

• Fits in line

• Standard 6.5mm socket and plug

• Input low impedance

• Output 30mV (max)

• Signal/noise ratio 40dB

• Delay time up to 60m seconds

• Frequency response 50 - 15kHz

• Cord length 75cms

• Weight 220 grams

• Dimensions 115 x 32 x 44mm

Cat. A10530 \$44.95



CRYSTAL LOCKED WIRELESS MICROPHONE

MICROPHONE SPECIFICATIONS:

Transmitting Frequency: 37.1MHz
Transmitting System: crystal oscillation

Microphone: Electret condenser

Power Supply: 9V battery

Range: 300 feet in open field

Dimensions: 185 x 27 x 38mm

Weight: 160 grams

RECEIVER SPECIFICATIONS:

Receiving Freq: 37.1MHz

Output Level: 30mV (maximum)

Receiving System: Super

heterodyne crystal oscillation.

Power Supply: 9V Battery or 9V DC

power adapter.

Volume control

Tuning LED

Dimensions: 115 x 32 x 44mm

Weight: 220 grams

Cat. A10452 R.R.P. \$113

Our price, \$99

Audio Audio Audio Audio Audio



CAR REPLACEMENT SPEAKERS

All are rated at 4 ohm, Nominal 3W, Maximum 5W with 3 inch magnets, and feature dust proof covers

5" x 7" Oval Cat.C10757 \$11.95
 4" x 6" Oval Cat.C10746 \$10.50
 5" Round Cat.C10705 \$8.95
 6" Round Cat.C10706 \$10.95



CAR ANTENNA BOOSTER

• In-line installation
 • 12V boosts 100%
 Cat. A12073 \$7.95




STEREO VOLUME CONTROL

30W RMS, wire wound, ceramic base with heatsink
 Cat. A \$29.95

STEREO VOLUME CONTROL

10W RMS, wire wound, ceramic base with heatsink
 Cat. A \$29.95



CAR ANTENNAS

• 4 section
 • 860mm length
 • Top key lock down
 • 1.2 metre lead
 Cat. A12061 \$5.95

MODEL CA-2

• 3 section
 • 1.4 metres extended
 • 1.2 metre lead
 • Spring based
 Cat. A12062 \$13.95

MODEL CA-3

• Stainless
 • Top cowl
 • 1 section whip
 • 1 metre length
 • 1.2 metre lead
 Cat. A12063 \$7.95

MODEL CA-4

• Pillar mount
 • 3 section
 • Suits Toyota, Nissan, Mazda
 Cat. A12060 \$6.95

MODEL CA-5


• Roof, boot, mount anywhere
 • 830mm length
 • 3 section, tuned for FM
 • 2 metre lead
 Cat. A12065 \$12.95

MODEL CA-6

• Rubber duckie
 • 1 section flexible rubber
 • Flexible spring base
 • Adjustable ball
 • 1.2 metre lead
 Cat. A12066 \$11.95

MODEL CA-7

• Black, 1 section whip
 • Top cowl
 • 1 metre length
 • 1.2 metre lead
 Cat. A12067 \$7.95



CAR ANTENNAS (POWERED)

MODEL ACA-1

• Semi automatic
 • 5 section
 • 1 metre stainless steel
 • 1.2 metre feeder cable
 • 12V DC
 Cat. A12070 \$34.95

MODEL ACA-2


• Fully automatic
 • 5 section
 • 1 metre stainless steel
 • 1.2 metre feeder cable
 • 12V DC
 Cat. A12071 \$49.95

MODEL ACA-3

• Semi automatic, flush head
 • 5 section
 • 1 metre stainless steel
 • 1.2 metre feeder cable
 • 12V DC
 Cat. A12072 \$59.95


CROSSOVER NETWORKS

Crossovers are essential for multiway speaker systems, otherwise your bass will be degraded by inter-modulation distortion and cone break up, and your treble will be distorted by bass components. These crossovers are designed to channel only the frequencies that each driver can properly handle. Read the specifications to choose the correct one for your need.




2 WAY 60 WATT CROSSOVER NETWORK

• 6dB attenuation
 • Cross over point 3,500 Hz
 • Impedance 8 ohms
 Cat. A16001 \$7.95




3 WAY 60 WATT CROSSOVER NETWORK

• 6dB attenuation
 • Cross over point 800 and 5,000 Hz
 • Impedance 8 ohms
 Cat. A16003 \$12.95



3 WAY 100 WATT CROSSOVER NETWORK


• 12dB attenuation
 • Cross over point 800 and 5,000 Hz
 • Impedance 8 ohms
 Cat. A16005 \$28.95



2 WAY MID SIZED SPEAKER SYSTEM

Labyrinth enclosure assures adequate bass at low volume. Polypropylene woofer with aluminium voice coil. Finished in walnut cabinet with removable black grille.

SPECIFICATIONS:
 Speakers: 6 1/2" woofer and 2 1/2" tweeter
 Power input: 30W RMS 86dB/Wm
 Impedance: 8 ohms
 Frequency Response: 60 - 20kHz
 Size: 345(H) x 230(W) x 280(D)mm
 Weight: 3.8kg each
 Cat. C10766 \$179



3 WAY MINI BOOKSHELF SPEAKER SYSTEM

Aluminium diecast cabinet. Superb sound for it's size with polypropylene cone for bass driver. Finished in silver/grey with black mesh grille and comes complete with mounting bracket.

SPECIFICATIONS:
 Speakers: 4 1/2" woofer, 2" midrange, 1" dome tweeter
 Power input: 30W RMS 86dB/Wm
 Impedance: 8 ohms
 Frequency Response: 70 - 20kHz
 Size: 186(H) x 116(W) x 120(D)mm
 Weight: 2kg each
 Cat. C10764 \$169



1" DOME TWEETER SPEAKER

Mylar diaphragm
SPECIFICATIONS:
 Sensitivity: 96dB
 Frequency Response: 2-20 kHz
 Impedance: 8 ohms
 Power RMS: 15 watts RMS
 Magnet Weight: 5.4oz.
 Size: 36mm diameter
 Cat. C10234 \$10.95



2" HORN TWEETER SPEAKER

Mylar diaphragm, aluminium voice coil
SPECIFICATIONS:
 Sensitivity: 95dB
 Frequency Response: 1.5-20 kHz
 Impedance: 8 ohms
 Power RMS: 10 watts RMS
 Magnet Weight: 2.5oz.
 Cat. C10232 \$8.95



4" EXTENDED RANGE SPEAKER

Rubber edge, black cone
SPECIFICATIONS:
 Sensitivity: 90dB
 Frequency Response: 90-8 kHz
 Impedance: 8 ohms
 Power RMS: 8 watts RMS
 Magnet Weight: 5.3oz.
 Cat. C10220 \$13.95




5" MIDRANGE SPEAKER

Sealed back, foam edge, black cone, silver dust cap.
SPECIFICATIONS:
 Sensitivity: 98dB
 Frequency Response: 500-8 kHz
 Impedance: 8 ohms
 Power RMS: 10 watts RMS
 Magnet Weight: 5.4oz.
 Cat. C10230 \$12.95



6 1/2" TWIN CONE FULL RANGE SPEAKER

Foam edge, black cone, black whizzer cone
SPECIFICATIONS:
 Sensitivity: 89dB
 Frequency Response: 60-15 kHz
 Impedance: 8 ohms
 Power RMS: 10 watts RMS
 Magnet Weight: 5.3oz.
 Cat. C10222 \$14.95



UNIVERSAL CAR RADIO/CASSETTE LEAD

Connects stereo unit to battery, speakers switch. Universal plug fits most stereo units. Fuse carrier in red lead with 3A fuse.
 Cat. A12052 \$2.95



8" TWIN CONE FULL RANGE SPEAKER

Foam edge, black cone, black whizzer cone
SPECIFICATIONS:
 Sensitivity: 96dB
 Frequency Response: 45-16 kHz
 Impedance: 8 ohms
 Power RMS: 30 watts RMS
 Magnet Weight: 13oz.
 Cat. C10224 \$23.95



8" WOOFER HIGH POWER SPEAKER

Cloth edge, dark grey cone, rubber mounting seal, cloth dust cap.
SPECIFICATIONS:
 Sensitivity: 90dB
 Frequency Response: 60-4 kHz
 Impedance: 8 ohms
 Power RMS: 50 watts RMS
 Magnet Weight: 20oz.
 Cat. C10226 \$34.95




10" WOOFER HIGH POWER SPEAKER

Cloth edge, dark grey cone, rubber mounting seal, cloth dust cap.
SPECIFICATIONS:
 Sensitivity: 93dB
 Frequency Response: 50-2.5 kHz
 Impedance: 8 ohms
 Power RMS: 100 watts RMS
 Magnet Weight: 30oz.
 Cat. C10228 \$59.95




12" WOOFER HIGH POWER SPEAKER

Cloth edge, dark grey cone, rubber mounting seal, cloth dust cap.
SPECIFICATIONS:
 Sensitivity: 97dB
 Frequency Response: 28-4 kHz
 Impedance: 8 ohms
 Power RMS: 50 watts RMS
 Magnet Weight: 30oz.
 Cat. C10229 \$69.95



DUAL ATTENUATOR

• LED indicator
 • Mid/High range for 3 way systems
 • Impedance 8-10 ohms
 • Power handling 18 watts RMS
 Cat. A16013 \$17.95



EXTENSION SPEAKER 1

Slimline walnut cabinet with mounting holes and volume control.
SPECIFICATIONS:
 Speaker: 5"
 Impedance: 8 ohm
 Magnet: 3oz
 Nominal Power: 3W/5W maximum
 Size: 245(L) x 150(W) x 65(D)mm
 Cat. C17777 \$44.95



PORTABLE MINI P.A. AMPLIFIER

A completely portable system, sets up anywhere in seconds. Inputs for microphone, electronic organ and cassette players. Variable echo makes this an ideal unit for buskers and budding singers.

SPECIFICATIONS:
 Output power: 1W RMS, 2W max.
 Frequency Response: 100-15kHz
 Speaker: 5" full range, 4 ohms
 Echo Time: Variable 5-52m/sec
 Power Source: 6 x "D" size batteries (position for power adaptor also)
 Size: 280(H) x 120(W) x 180(D)mm
 Weight: 1.3kg
 Cat. A12022 \$89.95



MINI HAND HELD MEGAPHONE

Suitable for schools, sports meetings, boats, etc. Portable, lightweight and effective with anti howling dynamic microphone. High power output, low power consumption.

SPECIFICATIONS:
 Size: 150mm diameter
 Power output: 2 1/4 watt maximum
 Effective Distance: 120 metres
 Power source: 6 x "AA" batteries
 Power duration: 6 hours
 Weight: 0.6kg
 Cat. A17777 \$69.95

CLAYTON MAIL ORDER PICK UP!

Simply phone your orders through on our Mail Order Hotline and you can pick them up a few hours later! How convenient!



Rod Irving Electronics

48 A Beckett St, MELBOURNE
 Phone (03) 663 6151
 425 High St, NORTHCOLE
 Phone (03) 489 8866
 Mail Order and Correspondence:
 P.O. Box 620, CLAYTON 3168
 Telex: AA 151938



MAIL ORDER HOTLINE (03) 543 7877 (2 lines)

POSTAGE RATES:
 \$1 - \$9.99 \$2.00
 \$10 - \$24.99 \$3.00
 \$25 - \$49.99 \$4.00
 \$50 - \$99.99 \$5.00
 \$100 - \$199 \$7.50
 \$200 - \$499 \$10.00
 \$500 plus \$12.50

This is for basic postage only. Comet Road Freight, bulky and fragile items will be charged at different rates.

Certified Post for orders over \$100 included free!
 Registered Post for orders over \$200 included free!

All sales tax exempt orders and wholesale inquiries to: RITRONICS WHOLESALE, 56 Renner Rd, Clayton, Ph. (03) 543 2166 (3 lines)

Errors and omissions excepted

*Apple and IBM are registered trade names



For text and graphics with colour . . .

Epson's EX-800 dot matrix printer

There's no doubt about it. Printers are continuing to become more intelligent, easier to use and above all, faster. It used to be that dot matrix printers were used only where print quality was unimportant. Now they are displacing daisy-wheel printers because they can produce good quality print and graphics output too. And the Epson EX800 can also print in colour.

by LEO SIMPSON

NLQ is a term you see more often these days when reading the specs of dot matrix printers. The term stands for "near letter quality" and it means just below the print quality of a daisy-wheel printer or golf ball typewriter.

Some dot matrix printers produce near letter quality by employing a large number of pins in their print head. Instead of using the standard seven, eight or nine pins, some print heads have 24 pins. As they move across the paper these very fine pattern print heads have no difficulty in producing a dot matrix pattern which is almost equivalent to a good daisywheel machine.


The EX800 attacks the problem in a different way. It only has nine pins in its print head but it produces a fine

quality print by passing its print head across the paper twice and moving the paper slightly in between, so each line of print requires two passes of the print head when in NLQ mode. In draft mode, only one pass is used and the dot matrix structure of the printed words is clearly evident. What this means is that

the machine is much faster in draft mode than in NLQ mode. Is that the end of the story? No, not by a long shot.

Where the dot matrix NLQ printer has it all over the daisy-wheel printer is that it can easily change print fonts. With a daisy-wheel printer the only way to change fonts is to change print wheels, a process which can be fiddly and requires stopping the printer. With an NLQ dot matrix printer on the other hand, you have the possibility of changing print fonts in mid-sentence, under software control.

For some years now, most dot matrix printers have offered this feature whether they had pretensions to "letter quality" or not. The way in which the instructions were delivered to the printer was by ESC instructions embed-



The Epson EX-800 dot matrix printer for text and graphics is flexible and fast.

ded into the text or material to be printed.

Now this is all very well if you are printing out a file under Basic or DOS and it consists of ASCII characters. But if you are using a word processing program such as Wordstar, things are not so simple. The ESC sequences don't work unless they are "patched" into the program. And since you can have only a limited number of patches in Wordstar, the number of different print options you can actually use are limited.

With the EX-800 though, you have another way of changing fonts within the one piece of text. You can merely take the printer off-line at any stage during printing, select the desired font and then continue printing. Epson refer to this feature as SelecType and it gives three basic fonts: Draft (which is fast and looks like dot matrix printout), Roman and Sans Serif (which means without the serif, the curly bits on type-faces).

At the same time, you can also select the print width; Pica (10 characters per inch); Elite (12 characters per inch); Proportional which is fairly close to Pica but varies the amount of space depending on each character; and Condensed (about 60% compression) for all three of these modes. If you select both Elite and Condensed you can get up to 160 characters per line which is handy if you want to print out large spreadsheets. Normally this could not be done on a printer of this sort because the maximum paper width is 80 columns (when in the Pica mode).

I should mention that some word processing programs will not let you change fonts using the SelecType feature because they initialise the printer to selected fonts at the start of printing which will effectively cancel some type-styles. There are ways around that though, by re-customising your program to take this into account.

Naturally, you can use subscripts, superscripts, emphasised and double-strike modes and italics. The EX-800 supports the full ASCII set, including Greek symbols. It can also emulate IBM printers and thus give their full graphics character set or, in its own Epson mode, give eight international character sets: USA, English, French, German, Danish, Swedish, Italian and Spanish. These features are selectable by means of two eight-way DIP switches at the rear of the machine.

Graphics

And as with most dot-matrix printers these days, the EX-800 will support dot-

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

These are some of the fonts that can be produced on the Epson EX-800.

Epson's dot matrix printer

addressable graphics in both the IBM mode and Epson mode. These give 240 dots per inch horizontally and 72 dots per inch vertically. In the main graphics mode, the EX-800 uses only the top eight of the nine pins in its print head. To print images or characters taller than eight dots, the machine does one line, advances the paper slightly, and then does another pass. It uses the same technique to fill in the spaces between the dots when printing in the NLQ modes.

Print speed is quoted as 250 cps (characters for second) in Draft Pica mode, 300 cps in Draft Elite and dropping to 50 cps in NLQ mode. I found that actual performance on text was somewhat slower than these figures but the EX-800 still really rips along in Draft mode and is quite a bit faster than typical daisy-wheel printers when in NLQ mode. It is also reasonably quiet for a dot-matrix printer.

In the draft mode, the character structure is formed from a 9 x 9 dot matrix, which gives an easily read type with true descenders (ie, on the letters g, j, p, q and y). In the NLQ mode, the double-pass operation of the print-head combined with paper movement, gives an 18 x 18 dot matrix which is very readable and has little evidence of dot structure, unless you look closely. The print quality is not quite as sharp or as densely black as from a daisy wheel printer but all who saw it agreed that it was satisfactory, especially considering the other attributes of this machine.

Line spacing is 1/6-inch, 1/8-inch or programmable in increments of 1/216-inch, as most dot-matrix printers are.

Paper

You can use either tractor-feed, roll or single sheets of paper in the EX-800 and you can obtain three copies at once, providing the paper thickness does not exceed 0.16mm. Paper width can be from 101 to 254mm wide in the case of tractor-feed while single sheets can be up to 216mm wide.

The ribbon cartridge is Epson's own design and is similar to those used in Diablo daisy-wheel printers. Life expectancy of the ribbon is about three million characters or about 500,000 words. Actual life will no doubt depend on the climatic conditions — printer ribbons tend to fade over a period of time, regardless of whether they are used or not.

Mechanical features

Gaining access to the inside of the EX-800 is quite interesting and shows the amount of ingenuity that Epson have brought to bear in this machine. It involves removing two screws, removing the SelecType panel, reaching in to unfasten two clips and the whole top lifts off to give access to the mechanism and electronics. And as with many dot matrix printers these days, the EX-800 is mechanically absurdly simple, with all the clever functions taken care of by software via its own processors. It has an 8K print buffer too, which is enough to store about two or three quarto pages of text.


Centronics (parallel) and RS232C (serial) interfaces are fitted as standard and a number of other serial interface boards are optional such as IEEE-448 and RS232C current loop.

One feature of the design which we do think could be improved is the mains

wiring. When the top of the case is removed the mains fuse lies fully exposed. It is adjacent to the mains switch and is directly connected to the active line of the mains. Since it is placed exactly where your hand would tend to go when lifting the printer, it presents a risk of very severe electrical shock, if the machine is still connected to the mains.

Sure, the manual tells you to switch off the printer and remove the power cord but those precautions always tend to be ignored and, in any case, the machine would have to be powered during servicing. A small change to the wiring would fix the problem and would make the machine safe to work on, even with power applied. We have suggested this to the local branch of Epson. They have agreed to have the wiring modified.

The EX-800 comes with a very comprehensive manual, by the way, which includes all the ESCape sequences and the technical details of the interfaces. In the manner of the manuals for the Epson PC reviewed last month, the spiral-bound 246-page manual is well-



As well as offering "near letter quality" text, the EX-800 can print graphics images in full colour.

"LEADERSHIP TECHNOLOGY FROM EPSON CAN BE YOUR LEADING EDGE."

JAMES DIBBLE

Leading edge in technology made Epson number one in printers.

And you could take advantage of it.

Epson technology is available to the OEM market in the form of printing mechanisms, LCD's, floppy and hard disc drives.

Printer Mechanisms from the leaders

Epson pioneered the field of dot matrix printing and continues to be the world's leading producer.

The line-up starts with the micro series, ideal for use in POS terminals, ticket printers, measuring devices and portable computers.

The 200 series are compact and fast, with a capacity of up to 31 characters per line at 2.4 lines per second.

The 500 series offer even higher performance and extraordinarily long life, making them ideal for use wherever hard copies of transactions are needed in high volume.

High Resolution LCD's

Epson's high resolution LCD modules rely on a newly developed combination of LCD and semi conductor technology to deliver high reliability and low power consumption.

The Drive for Success

Epson has harnessed its unmatched production engineering capability to produce a range of drivers that are smaller, and run cooler, longer, more reliably, and more accurately on much less energy than competitive products.

The right choice

To stay in front in the OEM business, only the best quality components are good enough.

And in printer mechanisms, LCD's and drives, Epson can give you the leading edge you need.

For more information, phone Epson Sydney (02) 452 5222 or write for free brochure.

EPSON®

Post to Epson Components Division,
P.O. Box 410 FRENCHS FOREST 2086

NAME

ADDRESS

Amplifiers

TD300 \$750.00
Slave Amp (150 watts per channel into 16 ohms) with stereo to mono switching.
ZPE SERIES II \$2200.00
500 Mosfet Output Stages 250W into 8 ohms for bands that want power!

Disco Mixers

CITRONIC SM 350 \$1070.00
6 Channel Input (2 Mikes + 4 aux)
ARISTA \$450.00
6 Channel Input with Equalization.

Jumbo Strobe

JS 10 \$195.00
White Flash Jumbo Strobe with Speed Control. Every performer should have one.

Scanner

S101 \$160
Search Lighting effect

Scanner Bar

S104S \$550
Light bar housing four GE 4515 lamps scanning with individual motors.

All housing complete with front cover and with provision for colour gel.

Rope Lights

FOR BANDS
DISCOS & CLUBS

PRL 803
Rope light. Tubes Red, Blue, Green, Orange, White.
\$135.00(5m)

MULTI COLOURED:

White reinforced spiral tube with MC lamps.
Tred-proof \$135.00(5m)
SRL 801 \$180.00(10m)
Rope Controller
\$195.00

Border Lights

BL104 - \$195
FREE
Gel Filter Frame
Mount Rkts

Mirror Balls

MB 005, 5" \$27
MB 008, 8" \$58
MB 012, 12" \$88
MB 014, 14" \$120
MB 018, 18" \$160
MB 020, 20" \$195
MB 012C Mirror Cylinder (12" length) 6" Dia. - \$52
MB 008H Half Mirror Ball & Motor, 8" - \$54.11
MB 012H

MIRROR BALL MOTORS:
A.C. 240V Heavy Duty - \$100
Battery Motor \$15.00
A.C. 240v - \$39

CONTROLLERS

AUDIO/CHASER (DW 4LC 4000) \$360
Pre-set Programmed Controller 4 Channels each 1000W.

LIGHT COMPUTER (DW 7LC 4200) \$595
Programmable 7 channel with E-prom (16 programmes).
Ideal for Advertising signs and Disco lighting.

VU LIGHT BAR (DW 12 LC 480) \$460
12 channel L.E.D. like display controller.
Triggered by sound signals. Exciting new product!

GAFFER TAPE (Black) per roll \$7
PACKAGING TAPE per roll \$5.00

Special offer till stocks run out: 4 ch. chaser \$80.00

**PLEASE NOTE: ALL DW CONTROLLERS
COME WITH 12 MONTHS WARRANTY.**



Helicopter

A GE 4515 lamp in housing can be swivelled and directed up or down spinning 360° in the one place.

RPS102 2 ARM SPINNER \$275.00
RPS104 4 ARM SPINNER \$495.00
RPS106 6 ARM SPINNER \$550.00

UFO 324 UFO LIGHT (24XGE 4515)\$2200.00

Micro phones

129B 33 cm Flexible Chrome Arm, goose-neck \$5.90

186C Chrome Base Mount \$3.40

SMOKE MACHINE
(Great for Special Effects!) \$395.00
Fluid - 1 litre \$15.00

518C

Arista Mike \$80
UD312 Primo Mike \$120

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80

102 Mike Stand Adjustable \$93.80
HL43U Flexible Arm Mike Holder - \$2.90

518C

Arista

Mike \$80</

written and easy to follow. It also includes a fold-out quick reference card with all the commands and oft-used data.

Apart from one small criticism on the power wiring, we could conclude at this point and state that this new printer from Epson is a fine machine which is certainly worth its purchase price. But it has another attraction which we mentioned at the beginning of this review: colour.


This is an optional kit which comprises a colour ribbon cartridge, a small motor, a Philips-head screwdriver and a small plastic lifting tool. A subsidiary manual explains how to install it. It takes about five minutes to do it. The colour ribbon is wider than the standard black ribbon and has three basic colours, red, blue and green plus black. The small motor in the kit is used to angle the ribbon carriage to bring each colour band of the ribbon into play.

After the installation you can do the self-test routine and get a printout in no less than seven colours: black, red, blue, violet, yellow, orange and green. The colours are vivid and stand out very well on white paper, except for yellow which normally does not contrast well with white.

These colours can be brought into play by using ESCape commands which can be embedded into some word processing programs or used in Basic routines. Where the colour really comes into its own is in the production of coloured bar charts and in complex graphics work. Epson include some examples of these in their manual which must have taken hours to develop on a computer but can be printed out in only a few moments. It is really very impressive.


Interestingly, you can change back to a black ribbon at any time and the printer will recognise this when it is turned on. The colour ribbon has a pin moulded into its underside which opens a microswitch in the ribbon carriage baseplate.

Well, to actually conclude this time, we are impressed with this printer. It is a highly capable, near-letter-quality printer with an excellent bonus option in the form of colour printing. It should be a winner.

Recommended retail price at the time of writing was \$1050 plus tax for the Epson EX-800 while the colour option was expected to be about \$150. For further information contact your Epson dealer or Epson Australia Pty Ltd, Unit 3, 17 Rodborough Rd, Frenchs Forest, NSW 2086. Phone (02) 452 5222. 

He-Ne LASERS

From \$450 plus tax



Helium Neon Lasers

High quality, attractive price

The Lab laser series are economical Helium Neon lasers designed for laboratories, schools or clean workshops. They are ideal for experiments, alignment and demonstrations and can be fitted with a variety of optics.

The hard sealed plasma tubes are rubber mounted for protection and the attractive case is finished in durable epoxy powder coat. All lasers are factory burnt in during a thorough test procedure. Tubes, injection moulded tube mounts and 240V power supplies available separately, in kit form.

Models

LL05

LL1

LL2

LL5 M

LL5 S

Power

0.5mw

1.0mw

2.0mw

5.0mw Multimode

5.0mw Single mode

Beam divergence

1.54 mrad

1.23 mrad

1.23 mrad

8.0 mrad

0.96 mrad

Specifications:

Dimensions: height 75mm, width 75mm, length 405mm.

Power Source: 240V ac.

Wavelength: 632.8nm.

Mode: Tem₀₀ except LL5 which is multimode.

Polarization: Random.

Beam diameter: (1/e²) 0.65mm, LL5M 2.0mm, LL05, 0.52mm.

Output boss 1" x 32 tpi for scope or accessory mounts.

Warm up time full specification: 10 mins.

Operating Temp: -20°C - 50°C.

Options: • 12 volt dc power • key switch.

Designed, serviced and sold in Australia by

Laser Systems Pty. Ltd.



A BWD GROUP COMPANY

5 Dunlop Road, Mulgrave, Vic. 3170

P.O. Box 298, Mulgrave North, 3170, Australia

Telephone: 03 561 2888

Fax: 61-3-560 1164 Telex: AA35115

Ian J. Truscotts ELECTRONIC WORLD

For all your components!
Test gear, data books.
Huge range of active
and passive components.

FLUKE Multimeters
Amidon Ferrite Products

Are you pulling out your
hair trying to find parts
for the PLAYMASTER
AM/FM tuner kits???


Give us a call! We have most
parts (incl. semi's) in stock.

**30 Lacey Street,
CROYDON, VIC. 3136**
Ph: 723-3860/3094

Mail Orders Welcome

MICE IN CIRCUIT EMULATORS

Manufactured by Microtek International Inc.



***MICEII Real-Time
In-Circuit Emulation for:**

Z8	6809/E
ZS8	6502 Family
8051 Family	8086/8088
8048/49/50	80186/80188
Z80B	80286
8085	68000/68010
NSC 800	68008

***Full development/debugging
software for IBM-PC/XT/AT.**

***Source level debugging for
APX-86 compiled code.**

***NOW AVAILABLE MICE-32
for 68020**

MACRO DYNAMICS P/L Australian
Distributor

80 Lewis Rd, Wantirna Sth 3152. Ph.: 220-7260

CONTACT:

Tlx AA30674

VIC (03) 220 7260 QLD (07) 369 5900

NSW (02) 858 5611 SA (08) 243 2107

New Products...

Product reviews, releases & services

Look Mum! — both hands

This gadget is called "Type-Right" and it allows you to learn to accurately speed type without the time and expense of evening classes.

Type-Right is a computerised teaching aid that guides you step-by-step on the path to becoming a proficient typist. First, it familiarises you with the keyboard. Then, with the aid of the manual, you practice finger placement and begin typing simple words, before moving on to complete sentences and paragraphs.

Main features of the machine include four Lesson Keys, a Class Key which offers nine lessons at various skill levels, and a Game Key which introduces you to speed touch typing. In the latter case, a series of letters creep across the built-in liquid crystal display and must be entered into the keyboard.

During each lesson, all relevant information is displayed on screen to gauge



progress. A Speed Key calculates typing speed, while an Error Key determines accuracy and counts the number of mistakes.

Type-Right retails for just \$69.95 and

is available from your nearest Dick Smith Electronics store. For further information contact Dick Smith Electronics Pty Ltd, PO Box 321, North Ryde, NSW 2113. Telephone (02) 888 3200.

Military standard oscilloscope


Parameters Pty Ltd, the marketing arm of BWD Precision Instruments, has announced the release of BWD's Model 835 60MHz oscilloscope.

The Model 835 is a dual-trace oscilloscope suitable for both digital and analog applications. It is lightweight, compact and rugged in construction, and can be operated from 95-264V 48-440Hz power supplies without external switching.

The vertical amplifiers provide a full 60MHz bandwidth from 5mV to 20V per div and 50MHz at 2mV/div. For noisy waveforms or operation in noisy environments, a 20MHz bandwidth limit button is provided.

Sweep speeds range from 1s/div to 50ns/div and the 8 x 10cm CRT operates at 10kV. Other features include TV line and frame lock, low or high frequency reject, power line trigger and external trigger for both A and B time bases.

Function selection is by a pushbutton or a rotary switch. When switched to al-



ternate sweep, four traces can be displayed — CH1 and 2 at the 'A' sweep rate and the CH1 and 2 at the delayed 'B' sweep rate.


The BWD 835 is supplied complete with two dual range 10:1 and 1:1

probes, plus an operation and maintenance handbook.

For further information contact Parameters Pty Ltd, Centrecourt, 25-27 Paul Street, North Ryde, 2113. Telephone (02) 888 8777.

YOUR SCOPE

OS-620



PROBES INCLUDED IN PRICE

only **\$649**

\$735. INCL. TAX

neotronics
FOR HIGH TECHNOLOGY ELECTRONICS

37 Ryedale Road, West Ryde
N.S.W. 2114, Australia
Phone (02) 807 4739



DELIVERED ANYWHERE IN AUSTRALIA FOR \$10


Prices correct and goods in stock at time of going to press.

- Bandwidth 20MHz
- Rise time less than 17n sec
- 5mV/DIV sensitivity
- Channel A, channel B, dual, add, subtract
- Component tester
- X-Y mode
- TV video synch filter

Phone on the Hotline (02) 807 4739. Avoid disappointment. Order your scope by Bankcard on the phone. Just call up, reverse the charges and we'll take your order.

GW THE ALTERNATIVE 20 MHz OSCILLOSCOPE




While other 20MHz CRO's are content to be like the rest, GW offers you the real alternative. The GOS-522 is a 2 Channel, CRO with a unique 'ALTERNATE TRIGGERING' mode between Channels 1 and 2. This allows you to compare test points between good and bad boards simultaneously!



GW Instrument's GOS-522 offers more 'real' facilities for your dollar:

- Fast 20ns/DIV sweep speed – for high precision
- Large 6 inch rectangular, internal graticule CRT
- Trigger Level Lock and Variable Hold-off – for operating ease
- DC Trigger Coupling – for low frequency signals
- AUTO NORMAL and SINGLE SHOT sweep modes

GW's "ALTERNATE TRIGGERING" MODE:



WITH PROBES:		WITHOUT PROBES:	
\$733	excl. tax	\$698	excl. tax
\$855	incl. tax	\$815	incl. tax



EMONA INSTRUMENTS
A division of Emona Enterprises Pty Ltd

1st Floor,
720 George Street, Sydney, 2000
Phone: (02) 212-4599

ALSO AVAILABLE FROM:


NSW David Reid Electronics
Geoff Wood Electronics
QLD Baltec Systems Pty Ltd Brisbane
Nortek Townsville
VIC Radio Parts Group Melbourne

TAS George Harvey Electronics Hobart
George Harvey Electronics Launceston
WA Henco Engineering Pty Ltd Perth
SA Int'l Communication Systems Pty Ltd Port Adelaide

12 MONTH WARRANTY

New Products...

Economic line conditioners



Ferguson's new "ferroresonant" type ELC line conditioners are designed to provide relatively constant output voltage when there are substantial fluctuations in the supply voltage. The basic component of these units is a ferroresonant (constant voltage) transformer.

The line conditioners are used in a number of applications where the following characteristics are required: (1) constant output voltage regardless of supply variations; (2) isolation from electrical noise; (3) modification of waveform from square to sine wave; and a combination of the above factors.

Six models are available with outputs between 160VA and 3500VA. They feature a common mode electrical noise rejection ratio greater than 120dB and are protected against output short circuits. They automatically respond to input voltage fluctuations and provide a sinusoidal output irrespective of electricity supply voltage distortions.

For further information contact Ferguson Transformers Pty Ltd, 7 Moorebank Avenue, Moorebank, NSW 2170. Telephone (02) 602 1222.



TENNYSON GRAPHICS

Tennyson Graphics can do your photoplotting with the speed of light.

Tennyson Graphics are Australia's only company with state of the art laser photoplotting and computer graphics.


So we can photoplot artwork masters of your printed circuit boards with higher speed, higher resolution and higher accuracy than anywhere else in the country.

You can even choose your own non standard apertures on our Scitex Response 280 System. It can also do step-and-repeat and nesting up to 1000 mm x 1850 mm.

And of course we can accept data on tape or floppy disk in industry standard Gerber format.

Tennyson Graphics will be happy to give you the full story if you phone on (03) 579 0424.

TENNYSON GRAPHICS
A DIVISION OF REPROCART PTY LTD
993 NORTH ROAD
MURRUMBEENA VIC 3163
TELEPHONE (03) 579 0424
TELEX 34457



Ultra-fast 10-bit D/A converter


Datel has expanded its line of digital to analog converters (DACs) by introducing the DAC-330 which is a monolithic, video speed, 10-bit, 100MHz DAC, with a 14MHz bandwidth multiplying capability.

Applications include use in industrial and commercial graphic displays, high definition video and high speed signal processing. The chip operates from a -5V power supply, and features a low power consumption, dissipating a maximum of 1.48 watts.


The DAC-330 is supplied in a 28-pin dual-in-line plastic package with an operating temperature range of -20° to +75° C.

For further information contact Elmeasco Pty Ltd, 15 McDonald St, Mortlake, NSW 2137. (02) 736 2888.

ALL YOU NEED TO KNOW IS ON SCREEN



ONLY WITH THE **HITACHI V1100A** 4 CHANNEL 8 TRACE 100MHz DELAYED SWEEP SCOPE



**60 &
150 MHz
VERSIONS
AVAILABLE
NOW!**

- Built-in DVM and Counter
- Measures voltage and time differences and ratios between cursors and phase shifts
- Four independent channels
- User defined 30 character on-screen comments

Check the full spec and
arrange a demonstration

(V1100 A ONLY)

irh
COMPONENTS

IRH COMPONENTS

SYDNEY 32 Parramatta Road,
Lidcombe 2141 Tel (02) 648 5455
TLX AA24949 FAX (02) 647 1545
MELBOURNE 74 Raglan Street,
Preston 3072 Tel (03) 484 5021
TLX AA32422 FAX (03) 480 2772
PERTH 5/59 East Parade
East Perth 6000 Tel (09) 325 9333



**Australian
Maritime College**

ASSOCIATE DIPLOMA IN MARITIME ELECTRONICS ASSOCIATE DIPLOMA IN MARINE RADIOCOMMUNICATION

Switch on to an interesting and challenging career. Successful graduates of the Associate Diploma courses qualify for a wide range of positions in the public and private sector – as engineering assistants, technical officers, design draftsmen and technicians, or as radio officers. Opportunities exist with several Government departments and with private industry in the marine electronics and communications fields.

Entry Requirements: HSC or equivalent level passes in mathematics, a science subject and English.

Course Duration: Two years full time.

There are no tuition fees for Australian residents. The courses are approved under TEAS. Both diplomas are recognised by the Australian Public Service Board and the Australian Institute of Engineering Associates.

Please send me more information on:


- ☐ Associate Diploma in Maritime Electronics
☐ Associate Diploma in Marine Radiocommunication

Name _____

Address _____

Send to: The Admissions Officer,
Australian Maritime College,
PO Box 986,
Launceston, TAS. 7250.
Toll free telephone: (008) 030277


We try to have Australia's cheapest prices, widest range and excellent in-stock availability of computer accessories and compatibles.




RITRON 2 MONITORS
Stylish, swivel base monitor, available in amber or green.
Green Cat. X14506 Normally \$235
Amber Cat. X14512 Normally \$239
SPECIAL, ONLY \$199



TTL MONITORS
Fantastic resolution! Enjoy a crisp, sharp image with the latest Ritron TTL monitor! IBM* compatible, green display, swivel and tilt base.
Green Cat. X14510 Normally \$289
Amber Cat. X14512 Normally \$289
SPECIAL, ONLY \$269



NEW INTRA HIGH RESOLUTION RGB COLOUR MONITOR!
Size: 14 inch
Sync. Horiz. Scan Freq: 15.75 KHz
Sync. Vert. Scan Freq: 50 Hz
Band width: 18 MHz
Dot Pitch: 31mm
Resolution: 640 x 400 dots
Display Format: 80 x 25 Characters
Display Colours: 16 colours.
Input Connector: 9 pin D type
Cat. X14520 **only \$695**




ANTI GLARE SCREEN
Half the price of other brands!!
Relieve eye strain and headaches and increase productivity with these Anti Glare Screens. Suitable for 12" monochrome and colour monitors.
Cat. X99995 **\$24.95**




RITRON MULTI PURPOSE MODEM
The RITRON Multi Purpose Modem has all the features you require.
● CCITT V21 300 Baud Full duplex
● CCITT V23 1200/75
● Bell 103 300 Full duplex
● Bell 202 1200 Half duplex
● Auto answer, auto disconnect
Telecom Approval No. C84/37/1134
Cat. X19103 Normally \$399
SPECIAL \$299

1200/75 BAUD RATE/BIT CONVERTER
For computers not capable of split baud rates. Buffers characters at 1200 and converts to 75 baud
Cat. X19105 **\$99**



IBM* COMPATIBLE DISK DRIVES
Tired of paying up to 100% more for Japanese Disk Drives? We now have "direct import" Taiwanese disk drives at much lower prices!
Cat.No. Description Price
C11801 500K **\$199**
C11803 1 M/Byte **\$219**
C11805 1.6 M/Byte **\$239**



APPLE* COMPATIBLE SLIMLINE DISK DRIVES
Japanese Chinen mechanism, Cat. X19901 Normally \$225
NOW \$195
(*Apple is a registered trade mark.)



20 M/BYTE HARD DISK DRIVE FOR IBM* AND COMPATIBLES
Includes hard disk controller card.
Cat. X20010 **WAS \$1,250**
SPECIAL, ONLY \$995
*IBM is a registered trade mark.



MITSUBISHI DISK DRIVES
MF353 (3 1/2" DRIVE)
Double sided, double density, 1 M/Byte unformatted, 80 track per side.
Cat. C11953 **\$280**


M2896-63
Slimline 8" Disk Drive, Double sided Density No AC power required. 3ms track to track, 1.6 Mbytes unformatted, 77 track side 10s/5u10 bit soft error rate.
Cat. C11916 Case & Power Supply to suit
Cat. X11022 **\$159**

M4854
Slimline 5 1/4" disk drive. Double sided, double density, 96 track/inch, 9621 bit/inch, 1.6 Mbytes unformatted 3ms track to track access, 77 track/side.
Cat. C11904 Case & Power Supply to suit.
Cat. X11011 **\$375**

M4853
Slimline 5 1/4" disk drive. Double sided, double density, 1 Mbyte unformatted, 40 track/side. Steel band drive system.
Cat. C11903 **\$295**

M4851
Slimline 5 1/4" disk drive. Double sided, double density 500K unformatted, 40 track/side. Steel band drive system.
Cat. C11901 Case & Power Supply to suit
Cat. X11011 **\$109**


M4855
Slimline 5 1/4" disk drive, double sided, double density, 96 track/inch, 2.0 Mbytes unformatted.
Cat. C11905 **\$385**




CANON A-40 PRINTER
● Serial Impact Dot Matrix
● 140 C.P.S.
● Near Letter Quality Mode
● 1.4K Buffer
Cat. C20040 **\$525**



PRINTER LEAD FOR IBM*
● To suit IBM* PC XT and clones.
● 25 pin "D" plug on computer end to Centronics 36 pin plug
● Length 2 metres
Cat. P19029 R.R.P. \$44.95
SPECIAL, ONLY \$19.95



COMPUTER PAPER
Quality paper at a low price! 2,500 sheets of 11 x 9 1/2" 60 gsm bond paper.
Cat. C21001 Normally \$44.95
SPECIAL, ONLY \$37.95



PAPER TAMER
● Restores order to the top of your desk or work area
● Made of white plastic coated steel
● Stores up to 900 continuous sheets
● Allows perfect paper feed
● Allows easy examination of print out
Cat. X20010 **\$44.95**
(Printer and paper not included)



RS232 DATA SWITCH WITH TESTER
● 25 pin RS232 "D" connectors 2 in, 1 out or 1 in, 2 out.
● Ideal for 2 computers to one peripheral or 1 computer to 2 peripherals.
● Six dual coloured LED indicators showing certain flow status:
T.D. Transmit Data
R.D. Receive Data
R.T.S. Request To Send
C.T.S. Clear To Send
D.S.R. Data Set Ready
D.T.R. Data Terminal Ready
● Housed in heavy duty metal cabinet.
● Size: 200(W)x68(H)x150(D)mm
Cat. X19110 Normally \$149
SPECIAL, ONLY \$119

CENTRONICS DATA SWITCH
● 36 pin gold plated female Centronics connectors.
● All other specs as for RS232 Data Switch with Tester.
Cat. X19115 Normally \$169
SPECIAL, ONLY \$129




5 1/4" DISK SPECIALS!
All prices 10 disk boxes!
XIDEX
S/S/D/D 1-9 10+
S/S/D/D \$29.95 \$29.95
D/S/D/D \$38.95 \$36.95
High Density \$99 \$90
VERBATIM DATALIFE
S/S/D/D \$27.95 \$26.95
D/S/D/D \$34.95 \$32.95

3 1/2" DISK SPECIALS!
STOP PRESS!
PRICES SLASHED ON 3 1/2" DISKS!
SAVE \$10 PER BOX!!
Verbatim S/S \$54.95
Verbatim D/S \$59.95
Xidex S/S \$55.95
Xidex D/S \$79.95




MICRODOT 5 1/4" DISKS
100% certified and error free guaranteed! Over 300,000 now sold and not one complaint. Where else can you get 100% guaranteed quality disks at these prices?
S/S Cat. C12440 1-9 10+
S/S Cat. C12440 \$17.95 \$16.95
D/S Cat. C12445 \$19.95 \$17.95


SPECIAL OFFER!
During November, Double Sided Microdot Disks 20 boxes or more, \$16.50 each!!!
UNBEATABLE VALUE!!!
Bulk and Dealer inquiries welcome please phone (03) 543 2166



JUMBO 5 1/4" DISK STORAGE
If you've got lots of disks, you'll appreciate the extra capacity of this disk storage unit when it comes to locating "that" disk!
Features:
● 100 disk capacity
● Smoked plastic cover
● Lockable (2 keys supplied)
● 9 Dividers/spacers
Cat. C16027 **only \$24.95**



3 1/2" DISK STORAGE UNIT
● Holds up to 40 x 3 1/2" diskettes.
● Lockable (2 keys supplied)
● High Impact plastic lid and base
Cat. C16035 **only \$19.95**



IBM* COMPATIBLES from \$895*

Assembled & Tested in Australia!
Incredible deals to suit everyone including special package deals!
*256K RAM, single drive, graphics, and disk controller cards. \$895

256K RAM: Colour Graphics, Disk Controller Card, 1 parallel port, 2 disk drives and 3 months warranty. **only \$1,195**
640K RAM: Colour graphics, Multifunction Card, Disk Controller Card, 2 serial and 1 parallel ports, 2 disk drives and 3 months warranty. **only \$1,295**

256K PACKAGE DEAL: Includes Colour Graphics Card, Multifunction Card, Disk Controller Card, 2 serial and 1 parallel ports. A 120 C.P.S. printer and a monochrome monitor and 3 months warranty! **only \$1,995**

640K PACKAGE DEAL: Includes Colour Graphics Card, Multifunction Card, Disk Controller Card, 2 serial and 1 parallel ports. A 120 C.P.S. printer, a monochrome monitor and 3 months warranty! **only \$2,095**
*IBM is a registered trademark.



IBM* AT COMPATIBLE!

Assembled & Tested in Australia!
● 6 MHz
● 80286 CPU
● 8 slots
● 1 M/Byte main board
● 1.2 M/Byte Floppy disk drive
● 20 M/Byte Hard disk
● Colour graphics display card
● Floppy and Hard disk controller card
● Printer card and RS232
● 200W Power supply
● Keyboard
● Manual
All this for just \$3,995
(Monitor not included)



"IBM" AT TYPE KEYBOARD

● 100% IBM* PC, XT compatible
● Low profile keyboard design
● Proper placement of shift keys with large key tops to suit professional typists
● 3 step height-angle adjustment
● Cherry brand TS-Moco 1.9mm low profile switches, meet 30mm ergonomic requirement and provide high performance and maximum reliability.
● Curl lead plugs straight into PC/XT
● 3 Status displays
Just like the "real McCoy" only at fraction of the price!
Cat. X12020 Normally \$249
SPECIAL, ONLY \$149



Rod Irving Electronics
48 A Beckett St, MELBOURNE
Phone (03) 563 6151
425 High St, NORTHCOLE
Phone (03) 489 8866
Mail Order and Correspondence:
P.O. Box 620, CLAYTON 3168
Telex: AA 151938



MAIL ORDER HOTLINE (03) 543 7877 (2 lines)

POSTAGE RATES:
\$1 \$9.99 \$2.00
\$10 \$24.99 \$3.00
\$25 \$49.99 \$4.00
\$50 \$99.99 \$5.00
\$100 \$199.99 \$7.50
\$200 \$499.99 \$10.00
\$500 plus \$12.50

This is for basic postage only. Comet Road Freight, bulky and fragile items will be charged at different rates.
Certified Post for orders over \$100 included free!
Registered Post for orders over \$200 included free!

All sales tax exempt orders and wholesale inquiries to: RITRONICS WHOLESALE, 56 Renner Rd, Clayton, Ph. (03) 543 2166 (3 lines)

Errors and omissions excepted

*Apple and IBM are registered trade names



APPLE* COMPATIBLE CARDS

Printer Card Cat. X17029 \$89
Drive Card Cat. X17019 \$79
80 Column Card Cat. X17025 \$85
Speech Card Cat. X17009 \$69
Music Card Cat. X17011 \$99
Super Serial Cat. X17035 \$129
RGB Card Cat. X17039 \$79
Z80 CP/M Card Cat. X17041 \$59

APPLE IIe COMPATIBLE CARDS
80 Column/64K Card X17061 \$89

New Products...

Bench top multimeters

The new Fluke 367 benchtop multimeter features the combined analog/digital display seen in the Fluke 70 Series and the accuracy and input overload protection found in the Fluke 20 Series.


The front panel features a 15 degree slope for optimum visibility and switch access, and the carrying handle offers greater portability. A large storage compartment built into the rear half of the case allows the user to store test leads and small accessories inside the meter.

Other features include 0.1% basic DC accuracy, wide bandwidth AC response, "Touch Hold", min/max and relative recording modes, autoranging with manual range selection, and a continuity/diode test beeper.

All current ranges, including the 10A range, are protected by fuses. The

resistance function is overload protected by 500V RMS, and both AC and DC voltage functions are protected to 1000V RMS.

For further information contact Elmeasco Instruments Pty Ltd, 15 McDonald Street, Mortlake, 2137. Telephone (02) 736 2888.



Design programs for power transformers

A software package for the computer design of small power transformers has been released by Maneng Pty Ltd. It is suitable for Apple II and IIE computers and is aimed at the educational and hobbyist market.

Input specifications allow for three windings of up to 2000V each, with two taps on each winding and with a maximum 2000VA single phase total rating.

Parameters which may be specified are temperature rise, impedance, copper loss, and core loss. If the design specified is not practical, the program will request modification of the input specification.

For further information contact Maneng Pty Ltd, 64 Brisbane Water Drive, Koolewong, NSW 2256. Telephone (043) 41 1940.

PCB-mounting power relays

The new Fujitsu FRL270 series of miniature PCB mounted power relays are now available from IRH Components.

Measuring only 21.3 x 25.2 x 19.2mm, they are designed for heavy duty, low voltage, printed circuit board applications in automotive and battery oper-

ated equipment.

A wide operating temperature range from -30°C to $+80^{\circ}\text{C}$ is provided and the contacts handle 15A at 12V DC continuous and will handle 30A max overload current. Preferred coil operating voltages are 12V and 24V DC.

Also available from IRH are the Fujitsu FMR 800 series of mercury wetted contact relays. These are now available in total of eight packages.

All relays in this series are designed for PCB mounting and feature epoxy sealed metal cases for immersion cleaning.

Depending on the type selected, a range of coil voltages from 5V DC to

48V DC are available. Contact arrangements include single Form A, Form C, Form C latching and Form D.

Switching capacities up to 100VA (500V or 2A DC max) are standard for the Form C and Form D while the Form A contact is rated at 50VA.

Mercury wetted contacts ensure long mechanical life, stable contact resistance and bounce-free switching suitable for applications such as communications, data processing, measurement and control systems.

For more information contact IRH Components, 32 Parramatta Road, Lidcombe, NSW 2141. Telephone (02) 648 5455.

Quality Assembly?


Leave It In Our Capable Hands

The price is right and deliveries are always on schedule


Duet Electronics

414 St. Georges Rd
Thornbury, 3071
(03) 480-5803 (03) 484-4420
Distributor in N.S.W.
16 Barambah Rd
East Roseville
(02) 406-5762

Duet Electronics



New Products...



Network/communication boards for IBM PC

Novatech Controls has released MetraByte's new COM-485 board which allows IBM PC/XT/AT and compatible computers to be networked over the RS-485 bus.

Unlike the RS-422 bus which allows multiple receivers but only a single transmitter on a bus, the RS-485 allows multiple transmitters and receivers to operate over a 2-wire bus, thus allowing

a 'party line' network to be created.

Applications for the COM-485 include networking instruments, scanning and updating various user input and output devices (such as CRTs and keyboards etc), and any other communication application that requires more than one device to be networked to a personal computer.

For further information contact Novatech Controls Pty Ltd, 429 Graham Street, PO Box 240, Port Melbourne, Vic. 3207. Telephone (03) 645 2377.

General purpose I/O boards


The Mondotronic PIO-6U is a general purpose I/O board for IBM PC/XT/AT or compatibles. Based on the popular 8255A-5 chip, it features 48TTL compatible and programmable I/O ports.

It is a short board and is switch addressable throughout the 10-bit PC-10 addressing range.

Connections are via two 50-pin polarised ribbon connectors fitted with a positive lock/ejection mechanism. Signal connections are designed to allow either standard or twisted-pair ribbon cable to be used.

A 5V supply with a separate ground is also supplied via the connector to power possible external devices such as switching regulators, opto-couplers or pull-up resistors.

For further information contact Mondotronic, 560 Waverley Road, Glen Waverley, Vic. 3150. Telephone (03) 232 4110.



BRIGHT STAR CRYSTALS PTY. LTD.

Wish to announce that with the introduction of New High Tec equipment to our production line B.S.C. now offer a full range of STATE OF THE ART **RESISTANCE WELDED CRYSTAL UNITS**



HC/49u



HC/50u



HC/51u



HC/48u


RESISTANCE WELD the seal of perfection for

*Highset Accuracy *Very Low Ageing Rate

Custom Crystal Units to your specifications, ALSO stock **MICRO-P** Crystals **CUSTOM AND STANDARD** Hybrid Clock Oscillators.


Postal Address: **PO BOX 42 Springvale, 3171.**

Phone: **(03) 546 5076. Telex: AA 36004**



ESCORT EDC-110A CAPACITANCE METER

Check values and match capacitors for critical applications. Covers 200pF to 20,000 microfarads. Three and a half digit LCD display with 0.5% basic accuracy. Maximum resolution is 0.1pF. Fuse protection built-in. Complete with detailed manual and test clips **\$129.72**.




ESCORT ELC-120 L/C/R METER

Measures resistance, capacitance and inductance all in one handy instrument. Three and a half digit LCD display with typical 1% accuracy. Covers capacitance from 200pF to 200microfarads in seven ranges with 1% accuracy and 0.1pF max resolution. Inductance ranges are from 2mH to 200H in 6 ranges with 0.1uH resolution and 2% accuracy. Also covers 20ohms to 20Mohms in seven ranges with 10milliohm resolution and 1% accuracy. Supplied with test clips and detailed manual **\$264.32**.

5V POWERED DUAL RS232 TRANSMITTER/RECEIVER MAX232


Yes it meets all RS232C specs but only needs a 5V supply because it has built-in converters for the +10V and -10V power supplies. Can also be used as a voltage quadrupler for input voltages up to 5.5V.

Also contains 2 drivers and receivers. Uses low power CMOS. Handles 30V input levels and provides a +9V output swing. Ideal for battery powered systems. **\$12.96**



ADJUSTABLE VOLTAGE & CURRENT REGULATOR L200C

Handles output currents up to 2A and voltages in the range 32V down to 2.85V. Thermal overload and short circuit protected. Input over-voltage protected to 60V. **Only \$3.16**



Programmable voltage regulator with current limiting

CONVERT YOUR MULTIMETER INTO A THERMOMETER

See ETI June 83 which features a project using the AD590JH (ETI-153). The AD590JH produces an output current proportional to absolute temperature. It's ideal for remote sensing as long cable runs have negligible effect on accuracy over a hundred metres or more! The simplest circuit requires one resistor and one pot and a battery, but better to build the proper circuit and get an accurate 10mV/degree centigrade output to put into your DMM. The AD590JH is only **\$7.14**

CONNECTORS

9-Way "D"	
DE9P	\$2.30
DE9S	\$2.40
Backshell	\$2.20
15-Way "D"	
DA15P	\$2.80
DA15S	\$3.00
Backshell	\$2.20
25-Way "D"	
DB25P	\$3.05
DB25S	\$3.20
Backshell	\$2.20
37-Way "D"	
DC37P	\$8.00
DC37S	\$8.70
50-Way "D"	
DD50P	\$9.00
DD50S	\$9.80
Centronics 36 Solder Male	\$6.45
Centronics 36 Solder Female	\$9.50
Centronics 36 IDC Male	\$10.50
Centronics 36 IDC Female	\$11.85

Eddystone Die Cast Boxes



The original die cast box!! Ideal for r.f. shielding and heavy duty applications. Sizes given are outside dimensions -

ED7969P	92.1 x 38.1 x 27.0mm
ED6809P	119.1 x 93.6 x 52.4mm
ED9830P	119.1 x 93.6 x 30.0mm
ED6827P	187.1 x 119.5 x 52.4mm
ED6357P	187.7 x 119.5 x 77.8mm

CRYSTALS

Most popular crystals are available ex-stock. Call us for latest pricing.


32 kHz	2.4576 MHz	3.6864 MHz	4.9152 MHz	9.8304 MHz	16 MHz
1 MHz	2.5 MHz	4 MHz	5.068 MHz	10 MHz	20 MHz
1.8432 MHz	3.2768 MHz	4.194304 MHz	6 MHz	12 MHz	
2 MHz	3.579545 MHz	4.433 MHz	8 MHz	14.318 MHz	

8.30 to 5 Monday to Friday, 8.30 to 12 Sat.
Mail Orders add \$5.00 to cover postal charges.

All prices INCLUDE sales tax.

Tax exemption certificates accepted if line value exceeds \$10.00.

BANKCARD, MASTERCARD, VISA, CHEQUES



GEOFF WOOD ELECTRONICS P/L (02) 427 1676

INC IN NSW

229 BURNS BAY RD.
(CORNER BEATRICE ST.)
LANE COVE WEST N.S.W.

TXW 71996
P.O. BOX 671
LANE COVE N.S.W. 2066

OR CASH CHEERFULLY ACCEPTED

specialising in electronic components for the professional and hobbyist.



New Products...

Funway Into Electronics — the movie

school students, the videomovie is ideal for any novice wanting to get started in electronics. It introduces the viewer to the most common electronic components, explains how each part works, and concludes with the construction of a few simple projects. These projects are all taken from the Funway book and include a simple moisture detector and the now famous 'beer-powered' radio.

Of course, the videomovie won't turn you into an instant electronic expert. That's not its purpose. Instead, the aim is to provide the absolute beginner with an entertaining introduction to electronics so that the book may be tackled with confidence.

All the projects described in the Funway book can be built without lifting a soldering iron. Instead, the various parts are connected together by simply screwing their leads to a special plastic base (or breadboard). Special cut-out plans show where the parts actually go and all the projects are battery-powered to ensure complete safety.

In all, there are some 20 projects described in "Funway Into Electronics, Vol.1". The book also includes a section which outlines the operation of

each component (in greater detail than the videomovie), shows what its circuit symbol looks like, and describes marking codes.

In short, Dick Smith Electronics have come up with a well thought out package that should appeal to schools and to would-be electronics enthusiasts alike. And because the two are designed to marry together — the videomovie and the book — *Electronics Australia* and Dick Smith Electronics have combined to bring you the special offer shown on the facing page.

Here's what you get:


- a two-year subscription to *Electronics Australia*;
- the Funway Into Electronics videomovie (available in VHS and Beta);
- a project kit which includes the Funway Into Electronics book plus all the necessary components to make up the 20 projects described in the book.

The above package costs just \$99, which represents a saving of just over \$26 off the regular retail price. It makes an ideal Christmas gift and can be ordered from your nearest Dick Smith Electronics store or via the DSE hotline: (008) 22 6610.

Electronics is a fascinating and potentially rewarding hobby — for those who know the basics. The problem is, how does one get started? For the novice, finding out about the various parts and discovering what they do can seem a daunting prospect.

Well, Dick Smith Electronics have thought about the problem and have come up with what would seem to be the ideal answer: a half-hour videomovie entitled "Funway Into Electronics". This has been specially produced as an adjunct to DSE's enormously popular book "Funway Into Electronics, Vol.1".

Although aimed mainly at secondary



If your Transceiver uses Micro Logic Components, then we recommend

PRIMARY POWER PROTECTION

... protects your transceivers memory against spikes, glitches, lightning, on-off switches, electric motors etc. Max. peak surge current up to 4500 amps; transient energy absorption up to 75 joules.



Westinghouse Systems

80-86 Douglas Pde., Williamstown, Vic. 3016. Tel: (03) 397 1033. Tlx: 37477.

Ask for Fred — VK3AFR

N.S.W.: Bryan Catt Industries P/L. Tel: (02) 526 2222.

QLD: Colourview Wholesale, Tel: (07) 275 3188. S.A.: F.R. Mayfield P/L. Tel: (08) 212 3161.

W.A.: Geo. Moss P/L. Tel: (09) 446 8844.



PIF3-1A 1AMP 2STAGE +E.L.C. \$88
PIF3-3A 3AMPS 2STAGE +E.L.C. \$91
PIF3-6A 6AMPS 2STAGE +E.L.C. \$96
PIF3-10A 10AMPS 2STAGE +E.L.C. \$102
Plus Sales Tax if applicable Add pack/post
Bankcard and Visacard. Vic & NSW only.

WS25

Start in a Hobby



**Your Complete
Kit!**

20% OFF

- 2 YEARS Subscription to Electronics Australia.
- 20 Electronics Projects in a box. (Cat K-2605)
- Video — Introduction into Electronics
VHS/BETA

\$70⁸⁰

\$24⁵⁰

\$29⁹⁵

~~\$125²⁵~~

Wow — your price only \$99

LIMITED STOCK — Hurry, beat the Xmas rush!

**Electronics
Australia**

FUNWAY

Order through Hotline (008)22 6610 or any DSE Store.

**DICK SMITH
ELECTRONICS**

• NSW • Albury 21 8399 • Bankstown Square 707 4888 • Blacktown 671 7722 • Blakehurst 546 7744 • Bondi Junction 387 1444 • Brookvale (Warringah Mall) 93 0441 • Campbelltown 27 2199 • Chatswood Chase 411 1955 • Chullora 642 8922 • Gore Hill 439 5311 • Gosford 25 0235 • Hornsby 477 6633 • Liverpool 600 9888 • Maitland 33 7866 • Miranda 525 2722 • Newcastle 61 1896 • North Ryde 88 3855 • Parramatta 689 2188 • Penrith 32 3400 • Railway Square 211 3777 • Sydney City 267 9111 • Tamworth 66 1711 • Wollongong 28 3800 • ACT • Fyshwick 80 4944 • VIC • Ballarat 31 5433 • Bendigo 43 0388 • Box Hill 890 0699 • East Brighton 592 2366 • Coburg 383 4455 • Essendon 379 7444 • Frankston 783 9144 • Geelong 43 8522 • Melbourne City 67 9834 • Richmond 428 1614 • Springvale 547 0522 • QLD • Brisbane City 229 9377 • Buranda 391 6233 • Chermiside 359 6255 • Redbank 288 5599 • Rockhampton 27 9644 • Southport 32 9863 • Toowoomba 38 4300 • Townsville 72 5722 • Underwood 341 0844 • SA • Adelaide City 232 1200 • Darlington 298 8977 • Enfield 260 6088 • Salisbury 281 1593 • WA • Cannington 451 8666 • Fremantle 335 9733 • North Perth 328 6944 • Perth City 481 3261 • TAS • Hobart 31 0800 • NT • Stuart Park 81 1977

YOU'RE INVITED

To come and browse through our range of proven kits by

JAYCAR

NOW AVAILABLE IN

ADELAIDE

KITS FOR ALL OCCASIONS

Amplifiers, Tuners, Equalisers, Mixers, Decoders, Speakers, Test Equipment, Modems, Video Convertors, Musicolour, Model Railway, Dimmers, Chargers, Alarms, Power Supply, Auto, Robotics, Crossovers, Public Address, Strobes, Detectors, Synthesisers.

Save now and impress your friends

Discover how easy it is to build a quality kit of your choosing for half the cost of a similar commercial unit.

Please come to
ELECTRONIC DISCOUNTERS

305 Morphett St.
Adelaide, SA 5000
(08) 212-1799

50 and 25 years ago...

"Electronics Australia" is one of the longest running technical publications in the world. We started as "Wireless Weekly" in August 1922 and became "Radio and Hobbies in Australia" in April 1939. The title was changed to "Radio, Television and Hobbies" in February 1955 and finally, to "Electronics Australia" in April 1965. Below we feature some items from past issues.

Wireless Weekly

November 1936

Electric String Pick-Up: at the suggestion of the Philadelphia Symphony Orchestra, the Brush Development Company worked out an efficient amplification device to be applied to stringed musical instruments. The volume derived from one bass viola under such an arrangement is comparable to ten times the volume produced by a complete section of double basses in the orchestra.

The assembly consists of two small plates of piezoelectric crystals enclosed in a tiny case. The plate containing the crystal is attached to any part of the instrument with adhesive tape.

Women Can't Fly: (by a flying instructor) most women who take up flying do it out of sheer bravado. On the question of teaching women to fly, the average woman is a fairly apt pupil, up to the landing stage. But her judgment, particularly for approaches and landings, is very poor indeed. It takes a long time to get the principles of the two into her head.

Any time, I would sooner teach a man to fly, because although it takes a little longer, the ultimate result is certainly much more gratifying.

Largest Radio Network: the National Broadcasting Corporation of America which will celebrate its tenth anniversary this year is the largest broadcasting network in the world and the innovator of the system of sponsored broadcasting.

The programs broadcast by the NBC over a period of a year number approximately 40,000. Over half a million artists take part in more than 14,000 programme hours. Gigantic fees are paid to those artists, fees which can never be paid by any other broadcasting company.

RADIO. TELEVISION and HOBBIES

November 1961

Commercial Satellites: following the initial successes with satellite communication, British and American engineers plan to cooperate closely to evaluate the technique and possibly develop it to the point where it becomes a major medium of international communication.

Rural TV: the Postmaster-General recently announced dates for the opening of the 13 national TV stations in rural areas. They are at Canberra, Newcastle, Wollongong, Orange, Richmond-Tweed, Bendigo, Ballarat, Latrobe Valley, Goulburn Valley, Darling Downs, Rockhampton, Townsville and Launceston.

European Satellite: The announcement that the German Government is willing in principle to participate in a European organisation for the development of space vehicle launchers, as proposed by the United Kingdom and French Governments, has focussed attention on the British Blue Streak first stage launcher.

Although the part that satellites and the mastery of space will play in the future cannot be wholly foreseen, the rewards to be gained from such applications as satellite communication systems are obviously great indeed.

Colour VCR: (caption) the equipment pictured above has been adapted for full colour recording — the first time this has been achieved with a single-head machine. It was demonstrated in Tokyo by the Tokyo Shibaura Electric Company. The unit is claimed to be simple to operate and adjust and is free of many peculiarities encountered with the four head system of recording.

NOVEMBER CROSSWORD


ACROSS

1. Labour-saving form of slave labour. (10,5)
8. Caused a circuit fault. (7)
10. Radio base. (7)
11. Typical antenna site. (4)
12. Video output. (5)
13. Deliberately interferes with radio transmissions. (4)
16. Adhesive label. (7)
18. Record cover. (6)
20. Basic unit of 12 across. (3)

22. Part of a horn speaker. (6)
24. Electrochemical layer. (7)
28. Units of work in CGS system. (4)
29. Levels of application. (5)
30. Thirteenth word of phonetic alphabet. (4)
33. To power two. (7)
34. Data taken from a meter. (7)
35. Device used by a model-train enthusiast. (5,10)

DOWN

1. Add component into a circuit. (6)
2. Fault in a recording. (4-3)
3. Takes an examination. (4)
4. Allocate (frequency, etc). (6)
5. Authority in the recording industry. (1,1,1,1)
6. Type of electronic device, the bucket ———. (7)
7. Heavy light element! (8)
9. Controlled meter needle movement. (6)
14. Said of a system based on eight. (5)



SOLUTION FOR OCTOBER

D	E	R	A	T	E	D	S	E	T	T	I	N	G
I	E	A	W	T	U	N	O						
R	E	C	E	I	V	E	A	M	R	A	D	I	O
E	O	L	L	N	N	I	D						
C	O	R	D	B	L	A	D	E	W	A	T	T	
T	D	A	S	A	T	I							
F	I	E	L	D	G	R	E	E	N	C	A	P	
A	N	L	P	D	T	O	S						
P	E	G	B	O	A	R	D	H	I	L	L	S	
P	Y	I	H	A	L	D							
L	O	C	K	O	N	O	F	D	E	C	I		
E	L	D	T	B	K	C	O						
T	W	O	I	R	E	A	L	E	R	T	E	D	
O	U	A	R	N	Y	O	E						
N	O	D	U	L	E	S	D	I	S	A	R	M	S


15. A computer language. (5)
17. Common form of ferrite. (3)
19. These cause responses measured with strain gauges. (8)
21. Alter keyboard instrument to produce different keys. (6)
23. Again measure wire size. (7)
25. Current in a light globe surges in the ——— stage. (7)
26. Place for radio broadcasting. (6)
27. Circuit tester. (6)
31. State-wide network of power cables. (4)
32. Metric prefix. (4)

Allen-Bradley MOD POT® - Now you can have the best when you want it.

Because the Allen-Bradley Mod Pot, which has a world-wide reputation for consistent quality and performance, is assembled right here in Australia at our newly-established Mod Pot assembly centre. The entire standard Mod Pot range is now available for extra fast delivery to anywhere in Australia - Allen-Bradley, the company you can rely on.

FEATURES:

- Hot moulded Carbon.
- Cermet.
- Conductive Plastic.
- Single or Concentric shafts.
- Push/Pull or Rotary switches.
- PC Pin Type or Lug terminals optional.
- Vernier Drives, 4 or 16 turns.



The most versatile standard potentiometer available today - mix and match the amazing Mod Pot Modules for over 1 billion possible control combinations.



These pre-engineered, pre-tested modules form 1, 2, 3 or 4 control sections - one family of variable resistors to solve your unique control problems.

Call your Allen-Bradley Electronic Components Sales Centre today, and you'll be amazed at how fast we will deliver.

Allen-Bradley, 75 years of cost effective, innovative electronic component manufacturing.




ALLEN-BRADLEY
A ROCKWELL INTERNATIONAL COMPANY

Design excellence and quality in the best tradition.

VIC. 37 Chapman Street, Blackburn, 3130. Ph. 899 0335
N.S.W. 22 Parramatta Road, Lidcombe, 2141. Ph. 648 2652
QLD. 1925 Logan Road, Upper Mt. Gravatt, 4122. Ph. 343 7900
W.A. P.O. Box 23, Subiaco, 6008. Ph. 387 1702
S.A. K. D. Fisher, P.O. Box 170, St. Marys 5042. Ph. 277 3288

Compact Disc Reviews by RON COOPER



TCHAIKOVSKY

Romeo and Juliet
The Nutcracker Suite
Berlin Philharmonic conducted by
Herbert von Karajan.
Deutsche Grammophon CD 410 873-2
DDD 1983
Playing time: 42 min 20 sec.

PERFORMANCE										
1	2	3	4	5	6	7	8	9	10	
SOUND QUALITY										
1	2	3	4	5	6	7	8	9	10	

The Fantasy Overture Romeo and Juliet is one of Tchaikovsky's early spectacular orchestral works and was composed in 1869 to a basic plan suggested by Balakirev to whom the work was dedicated. It was an immediate success with its powerful and dramatic melodies and has become a concert favourite.

The Nutcracker Suite would clearly be Tchaikovsky's most popular and well-known composition, although if you read my review of Swan Lake in the August issue you will expect me to advise against this disc because it is not the complete version — and I will; but this is different.


The Nutcracker Suite was the only set of pieces, of the three ballets put together by the composer to form a concert work in itself. The suites from Swan Lake and the Sleeping Beauty are not Tchaikovsky's arrangements. Hence, this disc does really contain two complete Tchaikovsky works.

However, I still feel the complete Nutcracker is still the only one to buy!

While this is a late recording and has virtually no background noise, it still reflects the tendency of many DGG recordings to favour the strings and subdue the woodwind and brass.

The acoustics are quite good and exhibit the moderate amount of natural reverberation expected from a large hall.

The players need no introduction and clearly show their skills but I did not like Karajan's tempos. The fiery Romeo and Juliet was much too sluggish and lacking the sparkle of some previous recordings while the Nutcracker was really a little too rushed, though with the skill of these performers it did not appear to suffer in detail. (R.L.C.)



BEETHOVEN

Piano Concerto No.2, B flat major.
Piano Concerto No.4, G major.
Vladimir Ashkenazy piano.
The Vienna Philharmonic conducted by
Zubin Mehta.
Decca CD 411 901-2
Playing time: 65 min 34 sec.

PERFORMANCE										
1	2	3	4	5	6	7	8	9	10	
SOUND QUALITY										
1	2	3	4	5	6	7	8	9	10	

Just before the turn of the seventeenth century Beethoven had a dual career as a pianist and composer. Working hard on his piano technique, he travelled extensively and is known to have performed his own concertos on six occasions in Vien-

na, three in Prague, one in Pressburg and possibly one in Berlin.

However, from 1800 onward the insidious process of deafness began to take its toll, and he never actually performed his fifth concerto. By 1816 he was almost completely deaf and the thrill of physically performing in front of an audience was fast becoming a theoretical memory.

This disc offers excellent value for money with two concertos and long playing time.

The recorded sound of the piano is quite magnificent, although I prefer Van Cliburn's interpretation of the fourth. Nor was I fully at ease with the orchestral accompaniment which I felt could have been more articulate.

It is a very bright recording and the miking appears to favour the strings, to the detriment of the wonderful woodwind parts in these works, particularly in the fourth.

As ever though, the CD format is superb with its quiet background. As a bonus, this disc comes with detailed notes on the works, and on the use of cadenzas by Beethoven. (R.L.C.)

STRAVINSKY DEBUSSY

The Firebird Suite (1910)
Afternoon of a Faun
The Los Angeles Philharmonic Orches-
tra conducted by Erich Leinsdorf.
Sheffield lab CD-24. AAD 1985
Playing time: 38 min 12 sec.

PERFORMANCE										
1	2	3	4	5	6	7	8	9	10	
SOUND QUALITY										
1	2	3	4	5	6	7	8	9	10	

The Firebird ballet was written in 1909-10 and the first performance was on June 25, 1910 under the baton of Gabriel Pierne and amongst the audience, and one of the first to congratulate the composer, was Claude Debussy.

The work was conceived by Diaghilev and after unsuccessful attempts by Liadov and Tcherpnin they were finally given to 'the young Igor', who rose to the occasion.

Debussy's Prélude à L'Après-Midi



d'un Faune was written after the latest work of the symbolist poet Mallarmé. Composed under the influence of Wagner, it is a somewhat abstract work in which nothing is unequivocally stated.

I was very interested to review this disc, being familiar with the Sheffield Lab's superb direct-cut LPs of some years ago, such as Lincoln Mayorga Volume III and the King James Version (Harry James).

Sheffield go into much detail (three pages of pizzaz) discussing the musical, technical and human problems of direct recording. On Leinsdorf they say "He has gone up the mountain and bashed it all out with God, or his surrogate." Now really what is this band of hifi nuts coming too? True, Leinsdorf and the orchestra do a fine job but let's leave it at that.

They describe the magic of their technical genius with: "This live performance was recorded with a single-point, stereo microphone using tube electronics designed and built by Sheffield Lab. This microphone technique was employed to optimally capture the natural acoustic perspective of the orchestra's performance."

This may be true but this natural perspective just sounds as though you are sitting in a boomy barn some 20 metres from the orchestra with background tape hiss continuo. I don't really care by what process modern technology delivers the goods, it is the final audible result that counts.

If it was from a popular company I would say this disc was so-so, but this is promoted as direct from the master by Sheffield Lab and sells for \$35.95!

For all their tube electronics and analog recordings the result is noisy and should be fixed. You don't ask an artist to paint on a dirty canvas.

I have just received another version

of the Firebird from Telarc which promises to be much better. I hope to bring it to you next month. (R.L.C.)

TIM FINN

Big Canoe
Virgin Records CDV2369 DDD
Playing time: 52 min 3 sec.

PERFORMANCE

1 2 3 4 5 6 7 8 9 10

SOUND QUALITY

1 2 3 4 5 6 7 8 9 10

This is Tim Finn's second album since the break-up of the band Split Enz. It bears witness to both his New Zealand origins and his ability to produce consistently catchy as well as thoughtful lyrics and tunes.

The title track, "Big Canoe" is perhaps the most evocative of the 'homeland'. The lyrics have connotations of a Maori legend, and the tune has a Polynesian percussion sound to it that would not have been out of place in the musical "South Pacific".

It's a catchy, emotional song helped along by its anthem-like chorus. I couldn't help enjoying the nationalist feeling which it produces through the use of a full-sounding orchestral strings arrangement and strong choir-like backing vocals.

"No Thunder - No Fire - No Rain" exhibits a political feeling for which New Zealand is well known, and seemed to me an indictment of the Bhopal disaster in India. The lyrics and the sounds of Indian percussion, especially the Tabla drums, help to conjure up this image.

Three other tracks apart from these struck me as (dare I say it) top 40 material. "Spiritual Hunger", which has been released as a single, features the talents of ex-Swinger Phil Jud. "Don't Bury My Heart" - another full sounding piece, is reminiscent of Jeff Lyn's use of strings in ELO. And "Hyacinth" is notable for the harp and sitar in the last stages.

With twelve songs in all, this is a CD to suit any mood, ranging from good background pop like "Searching the Streets" and "Hole in my Heart" to the goose-bumpy thoughtfulness of "No Thunder - No Fire - No Rain", and a smattering of boppy brass and sax songs, like "Timmy", which were just made for dancing.

My only criticism is of the sound quality on some of the brass arrangements. On headphones they sounded distorted, but this was not noticeable during casual listening via my loudspeakers. (L.U.)

Hundreds of other items not listed — Send 40c postage stamp for list

L.E. CHAPMAN

122 PITT ROAD, NTH CURL CURL
MAIL ORDERS: BOX 156, DEE WHY, NSW. 2099.
TELEPHONE 93-1848.

SUPER SPECIAL BSR GRAMO

MOTOR AND PICKUP 240V
3 speed 33-45-78
includes cartridge and stylus turnover
\$15

P&P NSW \$2.75 INTERSTATE \$4.20 WA, NT \$5.20

SUPER SPECIAL FM STEREO KITS

World famous make. Sets of 3 modules includes FM Tuner, Decoder and IF detector. Circuit diagram supplied.

ONLY \$22
P.P. \$1.90

BSR BELT SUPER SPECIAL DRIVE

Record player 2 speed 33 and 45 RPM 11 inch turntable pickup arm counter balanced cuing facility. Ceramic cartridge, diamond stylus works off 240V 9V or 12V

\$39
P.P. \$5.50

SPECIAL BALANCE METERS CENTRE ZERO

\$2
PP \$1

SPECIAL DUAL VU METERS

\$3
pp \$1

TOUCH MICRO SWITCHES 4 for \$1

MICRO SWITCHES
5A 250 volt 50c.

IF's 455kHz
For valve radios \$1 ea.

OSCILLATOR COILS
75c

TAG STRIPS
Mixed 10 for \$1

MIXED SWITCHES
12 for \$4.50

MIXED RESISTORS
100 for \$2 all handy values

SHIELDED CABLE
Single strand.
25 metres for \$2.50

TOGGLE SWITCHES
4 for \$1

TRANSISTOR EARPIECE PLUG & LEAD 4 for \$1

STICK RECTIFIERS
TV 20 SC \$1 each

CAR RADIO SUPPRESSORS
4 for \$1

SLIDE POTS
1 1/2 Meg DUAL \$1
1 Meg dual \$1
2 Meg dual \$2
250K dual \$1
1K dual \$1

TRANSISTORS
AD 161-162 \$1 pair
AD 149 \$2 pair

VALVES
EF86 \$5

VALVE SOCKETS
7 pin 4 for \$1
9 pin 4 for \$1
OCTAL 4 for \$1

5 MIXED ROTARY SWITCHES
\$2.50

CHROME 1/4 PUSH ON KNOBS
10 for \$1

SLIDE POT KNOBS
10 for \$1

MIXED CAPACITORS
Fresh stock 100 for \$2


TV COLOUR CRYSTALS
4433 — 619kHz \$2

VALVES:
6 B05 \$5, 6 B08 \$5
6 BL8 \$4

SPARK GAPS
10 for \$1

THERMISTERS
4 for \$1

postage stamp for list — Hundreds of other items not listed — Send 40c postage stamp for list



Information centre

PC birdies won't stop

I recently built the PC Birdies project (May 1981) but am unable to get it working properly. I followed the instructions to the letter but instead of using the 74C14 IC, I used the equivalent 40106 from National Semiconductor.

When I switched it on for the first time, all I heard was a continuous high pitched whistle with a very fast trilling. I thought that the chirp oscillator may need adjusting so I changed the 47k resistor to a series of resistors totalling around 150k and found that the sound now resembled that of a starling.

I would like to know how to make the proper sound as I am getting quite frustrated with this circuit but would like to see it through to completion if I could. (J.M., Christchurch, NZ).

■ No problem, J.M. Just use the 74C14 IC specified in the original article. The 40106 has quite different hysteresis voltages and this is why your circuit is generating higher frequencies.

Problem with AM stereo decoder

I would like your advice about the AM Stereo Decoder (EA, October 1984) that I assembled from a kit and installed in the Playmaster AM/FM Tuner described in November 1978.

Adjusting the slug in coil L1 has no effect on the voltage on pin 19 of the IC, which remains steady at 3.7V, and the voltage on pin 10 remains too high at about 6.5V. Tuning in a station has no effect on these readings, and the pilot LED does not light up.

The output voltage of the LM317 is correct at 8.3V. I have replaced the three capacitors connected to L1, and the coil itself as I had a suitable former in my junk box, but these changes had no effect.

Reception of FM by the tuner is, of course, not altered, but AM reception is now very weak with a loud superimposed hum and is not stereophonic. (K.K., East Brighton, Vic).

■ The 6.5V reading at pin 10 is quite OK. It should simply be greater than 4.3V to

indicate that the VCO is in lock. Similarly, the 3.7V at pin 19 indicates that the oscillator is operating correctly.

Your problem is probably due to the IF signal level on pin 3 of the MC13020P being incorrect. To set the correct level, monitor the DC voltage on pin 4 and adjust the series resistor to pin 3 until the meter reads about 2.5V.

Having said all that, our experience with the 1978 Playmaster AM/FM Tuner is that it is not a good candidate for stereo conversion. Its local oscillator is not sufficiently stable, and its tuning is quite critical.

Problem with 50V/5A power supply

I recently built the 50V/5A switchmode power supply as featured in your magazine some time ago (June 1983).

Unfortunately, on two occasions the output transistor has blown when a load has been switched in. When this happens, the output voltage jumps immediately to 50V and the overload lamp comes on. Coupled with this has been overheating of the 120 ohm 0.5W resistor in series with the potentiometer.

I would be grateful for any assistance you may be able to give to cure this problem. (G.W., Winston Hills, NSW).

■ The BD139 transistor (Q1) has probably been installed back-to-front. Note that the package outline drawing on the circuit diagram shows the base and emitter leads transposed. The same error was repeated in the MK.II version published in May 1985 and was only recently brought to our attention.

Crystal oscillator won't start

I have a problem with your Digital Frequency Meter described in December 1981.

The crystal oscillator will not start when the unit is switched on cold. On a warm day there is no problem. Applying heat to the crystal area with a hair dryer also causes the oscillator to run. Use of freezer spray in the same area causes the oscillator to stop.


I tried reducing the 22M resistor to 10M as advised in previous correspond-

ence but no improvement. I also changed the 10MHz crystal and the 39pF capacitor and the result is still the same - the oscillator will not run when cold. (G.B., Merewether, NSW).

■ We suggest that you first check the output from the +5V regulator. If this is on the low side, it could be the cause of your problem.

However, it seems more likely that the ICM7216A counter chip is at fault. We don't recommend that you replace it though - it sells for about \$70, so the exercise would be rather expensive.

Instead, we suggest that you try feeding the 7216A with an external crystal oscillator. To do this, remove all components across pins 25 and 26 of the 7216A and feed the external timebase signal directly to pin 25.



Although we haven't tried it, the accompanying circuit should make a satisfactory 10MHz crystal oscillator. It is based on a single low-cost 74LS04 TTL chip.

Modifying the Playmaster 60/60

I have read with interest the series of articles describing the Playmaster 60/60 stereo amplifier and am impressed with its specifications and constructional simplicity. It appears that this amplifier may form the basis for updating my present unit.

At present, however, I operate a pair of loudspeakers with electronic cross-overs. A replacement amplifier needs the facility to make input and output connections between the pre and main power amplifiers.

In view of the above, would you please advise whether and how:

(1) preamp outputs and power amplifier inputs may be provided;

(2) a second power amplifier may be constructed on the 60/60 PCB - ie, without the controls, preamp etc;

(3) the original 60/60 power supply may be used for the additional power amplifier or whether the power supply should be duplicated. (G.B., Dalkeith, WA).

■ We elected not to provide separate preamplifier outputs and power amplifier inputs on the Playmaster 60/60 for two reasons: to simplify construction and to minimise cost. However, it should be possible to break the signal chain at the wiper on the balance control to provide these facilities.

Note that the necessary connections between the balance control and the extra sockets would have to be run using shielded cable.

It is perfectly feasible to construct separate power amplifier stages on another PCB. Just leave out the circuitry for the tone controls and the input preamplifier stages. It will, however, be necessary to duplicate the power supply.

Back-up for 300VA inverter

Recently I built, for a neighbour of ours, the EA 300VA inverter. This is functioning correctly and he seems happy with its performance.

This same neighbour normally runs his house from a diesel generating set (also charging household batteries). He has asked me to find out if it would be possible to run his house (in the event of breakdown in his main system) from his Lincoln electric welding unit which puts out 240VDC, by eliminating the transformer in the inverter and substituting upgraded power transistors (240V).

I realise this sounds a little rough and ready but it is intended for emergency use, as we are a long way from the mains power grid and he is not financial enough to afford the cost of a backup generator of the regular type.

Any help you may be able to give will be greatly appreciated. (R.D., Nimmitabel, NSW.)

■ Your proposition is an interesting one and one that might work in a pinch. There are several points to be considered though.

First, the regulation of a welder may not be good enough to run household appliances without the possibility of damage from over-voltage. Similarly, the output of the welder's generator (or is it an alternator?) may have large DC spikes from the commutator which could cause problems. In theory, many household appliances could be run from 240VDC. Heaters, lights and appliances with universal

motors will all run from DC. However, other appliances containing transformers or induction motors would not run.

If you wanted to use the welder's DC output to generate 240VAC at 50Hz, you would not use the inverter circuitry. Instead, you would require a DC to AC converter which would need a set of four high voltage transistors (or maybe transistors in parallel to obtain the necessary

current rating) in a bridge configuration.

The transistors could be driven with a sinewave or in pulse width modulation together with a filter to obtain a sinewave output.

Unfortunately though, having set out the theory, we are not in a position to help you put it into practice. A more practical standby may be to hire or purchase a small petrol powered generator.

Notes and Errata

FENCEMASTER ELECTRIC FENCE (October 1986, 3/MS-): The 470k resistor connected to the anode of PUT Q3 should be replaced by a 1M resistor to ensure reliable cycling.

240V LAMP SAVER (June 1986, File 2/PC/45): the parts layout diagram shows two resistors transposed. The 100k resistor connected to the base of Q1 (in the right hand corner) should be 1M while the 1M resistor next to D5 should be 100k. The circuit diagram is correct.

Note that the circuit will still work as shown, although the soft start characteristic will be altered slightly.

Constructors should also note that the

circuit will not work correctly with a 1W zener diode. The 18V/400mW zener specified must be used.

EXTRA CHANNELS FOR THE DSE EXPLORER (September 1986, File 2/TR/63): the circuit diagram shows pins 3 and 7 of the 4008B transposed with pins 8 and 9. The parts layout diagram is correct.


PLAYMASTER 60/60 STEREO AMPLIFIER (May-July 1986, File 1/SA/75): some readers have reported overheating of the output transistors and the heatsink. This problem is due to the fact that retailers are supplying a steel chassis whereas the prototype used a black anodised aluminium chassis which had much better heatsinking characteristics. In addition,

ANOTHER BRILLIANT RELEASE FROM VIFA!



\$449
PAIR

VIFA EA 60/60
KIT SPEAKERS.



The value and the sound get better and better!

As you probably know, the value of kit speakers has never been greater than it is today. Our falling dollar, together with the rate of import duty, freight costs and other handling charges make fully imported loudspeakers almost a super luxury item. On the other hand, kit speakers can offer the same - and in most cases better - drivers and cross-overs and cost far, far less and sound far, far superior.

A perfect example of the sound of excellence.

The new Vifa loudspeaker kit has been designed to completely outperform any similarly priced speakers. This is a 2-way design incorporating drivers which give a deeper, more natural bass response and 19mm soft-dome ferro fluid cooled tweeters which provide clear, uncoloured sound reproduction.

VIFA drivers are used in such fine speakers as MISSION, ROGERS, BANG & OLUFSEN,

MONITOR AUDIO, HAYBROOK just to mention a few. Some of these speakers cost well over \$1000 a pair.

The dividing network is of the highest quality and produce no inherent sound characteristics of their own; they simply act as passive devices which accurately distribute the frequency range between both drivers in each speaker.

The ideal Bookshelf Speakers.

The fully enclosed acoustic suspension cabinets are easily assembled and are perfect for bookshelf use or on speaker stands. All you need are normal household tools and a couple of hours enjoyable application and you've built yourself the finest pair of speakers in their class.

For further information and the name of your nearest Vifa stockist, please contact the Sole Australian Distributor:

SCAN AUDIO PTY. LTD.

52 Crown St.,

Richmond 3122.


Phone (03) 429 2199.

vifa

the ventilation slots in the kit versions are smaller than those of the prototype.

The cure is simple and effective. To eliminate the possibility of thermal runaway of the output transistors, the VBE multiplier transistor (Q12) in each channel should be replaced by an MJ340 transistor. This will give vastly improved thermal tracking and will keep the quiescent current virtually constant with increasing temperature.

The new transistor should be bolted to the heatsink using a mica washers for insulation and with heatsink compound smeared on all mating surfaces. Note that the base and collector leads of the MJ340 must be crossed over to suit the hole locations left by the original BC547. The accompanying diagram shows the details.



Finally, to compensate for the lower VBE of the MJ340, the 470 ohm resistor between the base and collector of Q12 should be increased to 1k.

Preamplifier

continued from page 69

phono output to the disc input plus a tuner, CD and auxiliary unit (if available) to their respective inputs. A tape player can be connected to the tape in the tape out terminals.

The output left and right terminals connect to the inputs of a power amplifier or to the tape monitor input of an integrated amplifier. The amplifier is powered using the mains socket at the rear of the IR preamplifier.

For best results, press the normal switch and set the volume indication on the level set display to mid setting. Now set the volume control of your integrated amplifier to normal listening level. The volume can now be adjusted with the IR Remote Preamplifier controls.

Note that the VR1 and VR201 trim pots adjust the output level of the preamplifier. This can be set to give sufficient sensitivity for your amplifier.

SCREECHER CAR BURGLAR ALARM (August 1986, File 3/AU/49): due to an oversight, an incorrect PCB artwork was sent to some PCB manufacturers. This incorrect artwork can be quickly recognised by inspection of the i1 and i2 terminal labels, which are transposed (ie, i2 will be nearest the bottom of the artwork).


Although the error was soon discovered and the faulty artwork withdrawn, some readers may have obtained the faulty PCB. This can be modified by cutting the copper tracks with a razor blade and installing wire links on the underside of the PCB as appropriate.

The necessary modifications are as follows: Q3's emitter must be connected to

the base of Q2 instead of to the emitter; a 220 ohm resistor must be connected between V+ and Q3's base; one side of the wire link should go to V+ instead of to the 0.1uF ceramic capacitor adjacent to D9; and the 0.1uF capacitor lead should go to the cathode of D9.

To further complicate matters, the replacement artwork (and the artwork published in the magazine) have a track missing between the emitter of Q2 and the adjacent end of the 220 ohm resistor. These two pads should be joined using a wire link. The parts layout diagram on page 29 was correct.


To assist readers, the parts layout diagram and a corrected PCB pattern are reprinted below.




Parts layout for the Screecher Car Burglar Alarm.

CONVERT YOUR TV TO A COMPUTER MONITOR (August 1986, File 2/CC/95): the main circuit diagram

(Fig.1) was cropped such that R202 is not shown. The accompanying diagram shows the position of R202.



AN ASTONISHING NEW SOUND COMES TO CD



**Clarity,
transparency,
imaging,
openness...**

Shure Ultra D6000 explodes the myth that all CD players sound pretty much the same. It ushers in a new generation of sound purity that transcends the whole notion of audio "reproduction" and brings the sense of the actual reality of a musical performance. It is the best and most natural music source available at any price.




**Compensates
for imperfect
discs...**

Its advanced laser system uses three beams instead of one: one reads the disc while the other two give micro-precise guidance to the reader beam—overcomes vibrations and disc imperfections.


**PURELY
PERFECT**

**The only
5-year
laser
warranty**

The LONGLIFE™ laser tracking system is engineered for a minimum of 8000 hours of service. (Replacing lasers on "bargain" CD units is prohibitively expensive.)



ULTRA COMPACT DISC PLAYER



AUDIO ENGINEERS PTY. LTD
342 Kent Street, Sydney, NSW 2000
Ph: (02) 29-6731

AUDIO ENGINEERS (QLD) **MARKETEC PTY. LTD.**
Cnr. Jane & Buchanan Sts, 51 Scarborough Beach Rd,
West End, Qld 4101 North Perth, WA 6000
Ph: (07) 44-8947 Ph: (09) 042-1119

AUDIO ENGINEERS (VIC)
Ph: (03) 850-4329


WHERE CAN YOU FIND THIS RANGE OF DISPLAY TECHNOLOGY??

L.C.D.'s




- * Single or Multiline Displays
- * Single 5V supply, parallel ASCII input
- * Some units Backlit using EL panels
- * Extended temperature range from -30°C to +85°C on certain models

VACUUM FLUORESCENT



- * 14 Segment or 5x7 Dot Matrix versions
- * Single 5V supply
- * Character heights from 5.1mm to a large 15.0mm
- * Certain Models with Extended Temperature from -40°C to +85°C

DC PLASMA



- * Interactive Models
 - * Multiline Displays to 12 lines x 40 characters
- Also EL Panels, Numeric LED's and LCD's, Dot Matrix LED's



MEASURING UP TO YOUR NEEDS

DAVIDSON PTY. LTD. Inc. Vic.

17 Roberna Street, Moorabbin Vic. 3189
Ph: (03) 555 7277 Telex: AA 34745 DAVCOM
Suite 22, 10 Help Street, Chatswood NSW 2067. Ph: (02) 411 5017

W.A. Henco Engineering (09) 381 4477
S.A. Graphic Electronic Indust. (08) 363 0277
Qld. Industrials (07) 349 2376
Act. MB & KJ Davidson (03) 555 7277
Tas. Imbros Pty. Ltd. (002) 34 9899

EA marketplace EA marketplace

ADVERTISING RATES FOR THIS PAGE

SMALL ADS: The minimum acceptable size of 2 centimetres x one column costs only \$40. Other sizes up to a maximum of 10 centimetres are rated at \$20 a centimetre. CLASSIFIEDS: \$4 for 40 letters. Just count the letters divide by 40 and multiply by \$4; ROUND UP TO NEAREST WHOLE NUMBER. CLOSING DATE: Ads may be accepted up to the 18th of the month two months prior to issue date. PAYMENT: Please enclose payment with your advertisement. Address your letter to THE ADVERTISING MANAGER, ELECTRONICS AUSTRALIA, PO BOX 227, WATERLOO, NSW 2017.

FOR SALE

5V 50A TRANSFORMER: Ex-comp. \$45.00. Brisbane 266-7388.

MODEM CHIP: AM 7910 \$27.50, P&P, \$1.00. Acetronics, Box 76, Yagoona 2199, N.S.W.

EX-ABC AUDIO TAPES: 1/4" wide on 10 1/2" Standard metal spool \$6.85. Robust metal spool \$7.85. 7" spool \$2.25. 5" spool \$1.25. Post extra. Also in stock 1/2", 1" and 2" tapes. Waltham Dan, 96 Oxford St., Darlinghurst, Sydney. Phone (02) 331-3360.

RESISTORS: 1/4W E12 Range, 1 1/2c each. Battery Clips, 12c each. Yellow Leds, 15c each. P&P, 80c. Steven Fox Enterprises, P.O. Box 4, South Bexley, N.S.W. 2207.

BUDGET 25+ \$1
HOBBY 50+ \$2
SERVICE 100+ \$3.50
PREMIER 500+ \$13.50

BC639ARX = PSU \$48.00
A43R MK II MANUPACK \$60
MTR1 MK2 TX 2 1/2 10 MHZ \$72
RX .5 30 MHZ

HANDY 100+ \$2
MASTER 500+ \$7.50
EXPERT 1% 100+ \$3.50
SCIENTIST 1/2% 100+ \$4.20

A.W.A. Volt OHMYST V.T.V.M. \$35
University MVA6 V.T.V.M. \$29
H.P. 400H-6 50IB \$87

15 80W — \$4.90
25 15W — \$1.80
20 mixed 5W+ \$2.20
50 mixed 5W+ \$4.90

RECO: SOLER POLLTS
PT309 CONG TIP \$11
STD. LONG TIP \$12
BIRKO 45W/12V IRON \$14

RACAL RA17 COM RX .5 30MH \$350
AVO BATTERY MEGGER 500 VOLT \$110

FREE STEINEL AC/DC CHECKER
WORTH \$15 — WITH
1ST 50 ORDERS
OVER
\$100

MACSERVICE

673
NORTH ROAD
CARNEGIE VIC 3163
(03) 578 8639

AMIDON FERROMAGNETIC CORES:

Large range for all receiver and transmitter applications. For data and price list and 105X220 SASE to: R.J. & U.S. Imports, P.O. Box 157, Mortdale, N.S.W. 2223. N.S.W: Geoff Wood Electronics, Lane Cove. Webb Electronics, Albury. A.C.T.: Electronic Components, Fyshwick Plaza. Vic: Truscott Electronics, Croydon. W.A.: Willis Trading Co., Perth.

NEW RADIO VALVES: For entertainment or industrial use. Waltham Dan, 96 Oxford St., Darlinghurst, Sydney, Phone (02) 331-3360.

MY \$39 8K TO 256K: CENTRONICS PARALLEL PRINTER BUFFER KIT now has an optional plug-in 75-19200 baud serial converter board @ \$18, and a printer shaver board @ \$12. For more info. send SAE to Don McKenzie, 29 Ellesmere Cres., Tullamarine 3043.

MAGAZINE: For VZ200/300 users. Includes Basic, Assembly Language, Hardware. S.A.E. to P.O. Box 154, Dural, N.S.W. 2158.

WANTED

27/3.5 MHz DICK SMITH TRANSVERTER: (E.A. April '76). Complete or parts. Box 21, Mena Creek 4871. Phone (070) 65-3160.

ENGRAVED PANEL: For E/A "DeHahet" receiver, also 1967 SSB transmitter. P. J. Weaver, Macquarie Private Hotel, Barton, A.C.T. 2600.

24 G.H.Z. SIGNAL GENERATOR & FREQUENCY COUNTER: Also want I.F.R. test unit, any condition. Phone (02) 524-4131 A.H.

WANTED: Instruction manual for Eico Oscilloscope Mod. 430. Phone (03) 848-7978.

RCS. RADIO PTY. LTD.

Established 1933
IS THE ONLY COMPANY
WHICH MANUFACTURES AND
SELLS EVERY PCB & FRONT PANEL
published in EA and ETI
651 Forest Road Bexley 2207
AUSTRALIA
RING (02) 587 3491 FOR INSTANT PRICES
24-HOUR TURNAROUND SERVICE

CHIPS PROGRAMMED

(BIPOLAR PROM, EPROM,
EEPROM, PAL, IFL &
VARIOUS MICROPROCESSORS
WITH 'ONBOARD' ROM)

PTIZAN

Computer
Services

P.O. Box 69
Belconnen ACT 2616
Australia

Phone (062) 58 6823

PRINTED CIRCUIT BOARDS

Minimum postage & packaging on all EA & ETI
Project PCBs.

Catalogue 1976-85 (inc components) \$1.50.
PCBs made to order — 48 hr prototype service.
Bankcard/Mastercard.

Acetronics PCBs

112 Robertson Rd, Bass Hill 2197
(02) 645 1241

... ELECTRICITY FROM THE SUN! ...

Solar Cells Australia Pty Ltd

From as little as \$8.00 per watt,
you can provide power for nearly
all electrical appliances.

- Stereos • Household Utensils
- Power Tools • Lighting

USING THE UNIQUE ARCO PV
PANELS

The largest supplier of solar
power in the world.

SOLAR CELLS AUSTRALIA P/L

Contact your closest agent:

ELANTE PTY LTD
382 Canterbury Road
Surrey Hills, Vic 3127
Tel: (03) 836-9966

G. F. TRADING
34 Reginald Street
Rocklea, Qld 4106
Tel: (07) 277-9688

SOLAR CELLS
97 Kew Street
Welshpool, WA 6106
Tel: (09) 361-7344

OPEN FOR BUSINESS: Monday to Friday 8.30 am to 5.00 pm.
Saturday Morning 8.30 am to 12.30 pm

A.C.E.
RADIO

**10B/3 KENNETH ROAD,
MANLY VALE, NSW 2093 TEL: 949 4871**

PROUD TO BE
AUSTRALIAN



ETONE SPEAKER SPECIALS

GENUINE FACTORY PRICES

Rugged top quality Aust made brand new bargains — all with factory warranty

Model	Size	Cone Type	Vi/Coil	Reson Hz	Freq Hz	Watts Rms	Price Ea or 2 for
4310	38cm	Straight surround	8 or 15 Ohms	45	40-6000	60	\$92.00 or \$180.00
4510	38cm	Straight surround	8 or 15 Ohms	45	40-6000	100	\$132.00 or \$258.00
4350	38cm	Hi-Fi	8 or 15 Ohms	30	30-4000	120	\$118.00 or \$233.00

Pack and Post for 1 speaker NSW/VIC \$8.75; Q/T \$13.50; NT/WA \$17.50; SA \$11.50
Pack and Post for 2 speakers NSW/VIC \$15.00; Q/T \$23.00; NT/WA \$30.00; SA \$20.00



TRIAC
TYPE 225D SENSITIVE GATE
400V. 10AMP
10 FOR \$17.50
OR \$1.95 EA P & P \$1.95

A AND R POWER TRANSFORMER

Primary Tapped from
200V to 250V 50Hz.

Secondary 0—20.
30.48V 2.5 Amps.

Size 95x80x85mm

\$11.95 ea P & P NSW/VIC \$5.50;
Q/T/NT, WA/SA \$8.00



★ NEW MODEL ★

50 WATT RMS SPEAKERS

ETONE FACTORY SCOOP

EVEN LOWER THAN FACTORY PRICE

A PAIR FOR \$54.95 OR \$31.95 EACH

RUGGED TOP QUALITY HI-FI WOOFER. 30cm 8 ohms • 90 DAYS FACTORY WARRANTY • FOAM POLY SURROUND • STURDY SUSPENSION FOR RICH REPRODUCTION • 3.5cm VOICE COIL • FERRITE MAGNET • FREQ. RESPONSE . . . 35-4500Hz RESONANCE 35Hz

P-P for 1 NSW \$6; VIC & SA \$7.50; QLD & TAS \$8; NT & WA \$9.50
P-P for 2 NSW \$8; VIC & SA \$9.50; QLD & TAS \$10.50; NT & WA \$11.50

★ NEW MODEL ★

MINI BRIDGE RECTIFIER W02

200 piv 1.5 AMP

10 FOR \$3.95
P-P \$1.95



IDC SOCKETS


50 way Gold-plated
with Strain Relief Clasp
\$5.00 ea or 2 for \$9.00 P & P \$1.95

INTERFACE CABLE

P & P \$1.95
70mm Long Terminated each
end with 50 way Gold-plated
strain relief IDC sockets \$12.50 ea.

10 WAY DIP SWITCH

10 FOR \$6.75
P & P \$1.95



NEW CMA MINI POWER CABLE

Moulded 3-pin plug 7.5A
Approved 3 metres
\$2.50 EACH P & P \$1.95

AEI BRIDGE RECTIFIER

150 piv. 10 amp.
\$1.95 ea
P & P \$1.35

or 10 for \$14.50

P & P NSW \$2.50,
Interstate \$3.50

DIODES 650piv 3 AMP

50 FOR \$9.50 P & P \$1.95



MODEL	SEC.V.	AMPS
JT266	0.18V	8A
JT248	0.10V	10A
JT249	8.58-0-8.5V & 15VCT	4A
JT274	0-9.5V	1A
	& 2X 0-12V	10A
JT320	36-0-36V	1A
		2A

C-CORE TRANSFORMERS • LOW NOISE • HIGH EFFICIENCY FOR THE COMPUTER • POWER SUPPLY • AND MANY MORE PROJECTS

ONE PRICE

\$33.95 ea


P & P NSW/VIC \$8.75; Q/T \$13.50;
1A NT/WA \$17.50; SA \$11.50 ea.

BOSCH RELAY 12 VOLT 30 AMP

FOR HORN OR
HEADLAMPS
\$4.25 P & P \$1.95



STEEL CABINET



LOUVERED SIDES • CABLE
ENTRY EACH END • GREY
METALLIC FINISH

\$9.95

P & P NSW/VIC \$4.50;
T/Q/SA/WA/NT \$5.50

TUNING CAPACITOR



\$6.75 EACH

P & P NSW \$2.50
Interstate \$3.25

3 gang. 60PF. 200PF AND 415PF
IDEAL for A.T.U., etc. Top quality. Ball bearings. 55x45x40mm.

KAUTT and BUX ROCKER SWITCH

30 x 10mm SLOT.
240VAC

4A \$1.55 ea. 10 for \$12.50
6A \$1.65 ea. 10 for \$13.50
P & P NSW \$1.95;
Interstate \$2.50



etone

THE PROFESSIONAL SOUND COMPANY

PRESENTS

THE ENTERTAINER SERIES

SPEAKER SYSTEMS

PHONE
FOR
PRICES!



STAGE SOUND REINFORCEMENT
BASS GUITAR

DISCO
WEDGE MONITORS

KEYBOARDS
SIDE-FILL

COMPACT
CARPET COVERED OR BLACK PAINTED PLY
INTEGRAL CROSSOVERS

PORTABLE

WIDE RANGE OF MODELS

METAL GRILLES
CANNON INPUTS

COMPUTER DESIGNED VENTED CABINETS

FOR POSTAL INSURANCE ADD: \$2.00 for parcel up to \$200.00 value plus
\$1.00 for each additional \$100.00 value.

WE BUY ELECTRONIC EQUIPMENT & COMPONENTS

WE BUY ELECTRONIC EQUIPMENT & COMPONENTS

Next month in

Electronics Australia

Low Distortion Audio Oscillator

Our latest audio oscillator is easy to build and covers from 10Hz to 100kHz over four ranges. It features selectable sine or square wave output, very low distortion, fast risetime, an optional level output meter, and a sync output for a CRO.

UHF Keyswitch for Burglar Alarms

Ever wished that you could switch your car burglar alarm on or off simply by pressing the button on a small hand-held control unit? This unit does just that. You can also use it to control your house burglar alarm or to eliminate wiring between the control box and its sensors.

Digital Sound Recorder

This audio recorder has no tape. Instead, it stores up to 15 seconds of audio in RAM (random access memory) for instant replay at the press of a button. It's just the shot for use with a shop display or as a novel doorbell.

**Note: although these articles have been prepared for publication, circumstances may change the final content.*

Electronics Australia Reader Service

"Electronics Australia" provides the following services:
BACK ISSUES: available only until stocks are exhausted. Price: \$4.00.
PHOTOSTAT COPIES: when back issues are exhausted, photocopies of articles can be supplied. Price: \$4 per project or \$8 where a project spreads over several issues.
PCB PATTERNS: high contrast, actual size transparencies for printed circuit boards and front panels are available. Price: \$5 for boards up to 100 square centimetres; \$10 for larger boards. Please specify positive or negative.
PROJECT QUERIES: advice on projects is limited to postal correspondence only, and to projects less than five years old. Price: \$5. Please note that we cannot undertake special research or advise on project modifications. Members of our technical staff are not available to discuss technical

problems by telephone.
OTHER QUERIES: technical queries outside the scope of "Replies by Post", or submitted without fee, may be answered in the "Information Centre" pages at the discretion of the Editor.
PAYMENT: must be negotiable in Australia and made payable to "Electronics Australia". Send cheque, money order or credit card number (American Express, Bankcard, or Mastercard), name and address (see form). All prices include postage within Australia and to New Zealand.
ADDRESS: send all correspondence to The Secretary, "Electronics Australia", PO Box 227, Waterloo, NSW 2017. Please note that we are unable to supply back issues, photocopies or PCB artwork material over the counter.

Back Issues

Photostat copies

Total price of magazines/photocopies, including postage and handling.

No off issues reg x \$4 = \$.....

Cheque/Money Order ☐ Please tick box to indicate method of payment:

*Please make payable to the Federal Publishing Company Pty Ltd.

Mastercard ☐ American Express ☐ Visa ☐ Bankcard ☐ Tick ☒:

Card Expiry Date

Credit Card No

Signature

(Unsigned Orders cannot be accepted)

NAME:

ADDRESS:

POSTCODE:

ADVERTISING INDEX

Ace Radio	129
Acetronics	128
Adilam	82
Allen Bradley	121
Altronics	21,22,23,24
Amtext	7
Audio Engineers	127
Australian Government RAAF	46,47
Australian Maritime College	113
B&JK Davidson	127
Bernie Lieberman	128
Bose	91
Bright Star Crystal	116
Cashmore Sound	49
Chapman LE	123
Conference Technology	OBC
David Reid	45
Dick Smith	55-62
	119
Disco World	108
Duet	115
Elante	128
Electronic Discounters	120
Elmeasco	IFC,40
Elija	83
Emona	111
Epson	107
Federal Publishing	86,87
Force Electronics	77
Geoff Wood	117
IEI	73
IRH Components	113
Icom	20
Jaycar	14,15,16
Laser Systems	109
Macro Dynamics	109
Neotronics	111
Philips Elcoma	85
Ptizan	128
RCS Design	72
RCS Radio	128
Ritronics	32,33,102,103,104
Scan Audio	125
Science World	9
Siemens	IBC
Stotts	13
TSA	73
Tennyson Graphics	112
Texas Instruments	94,95
TI Contest	99
Truscotts	109
VSI	88
Westinghouse	118

SIEMENS

SIPMOS saves grams, joules and bucks

Siemens new power transistors are a boon for designers.

By using SIPMOS[®] power transistors, you can develop systems with smaller, lighter power supplies. And which are more economical and reliable. Furthermore, SIPMOS transistors are extremely fast switching and easy to parallel, with no secondary breakdown. Most importantly, these advanced features increase the design possibilities for switch mode power supplies, asynchronous motor controls, audio amplifiers, DC convertors, proximity switches and inverters. Innovative SIPMOS components arise from discoveries at the very forefront of technology.

The range includes:

- ☐ P channel and N channel.
- ☐ Small signal transistors including surface mount types.
- ☐ FRED FETS with fast recovery reverse diode.
- ☐ SMART FETS.

And other superior SIPMOS components are currently being developed by Siemens higher technology.

For more information, contact your nearest Siemens office.



Siemens Ltd.

544 Church Street, Richmond, Vic.
Melbourne: (03) 420 7318 Sydney: (02) 436 8730
Brisbane: (07) 369 9666 Perth: (09) 362 0123

Distributors

Victoria: Promark Electronics (Vic) (03) 878 1255
Queensland: ECQ Electronics (07) 376 5677

New South Wales: Nexus Electronics Pty. Ltd.
(02) 439 5800
Promark Electronics Pty. Ltd. (02) 439 6477
South Australia: Auslec (08) 269 1688
Protronics Pty. Ltd. (08) 212 3111
Western Australia: Reserve Electronics
(09) 328 9755

Siemens. A higher technology

Cunningham Communications offer the new range of ELVOX Intercom Systems.

La linea Italiana

Elvox in Italy have been manufacturing communication systems for over fifty years and are a leading presence in the field of videointercoms in Europe. They now, through Cunningham Communications offer a whole new range of products to match demands for advanced technology and easy operation. Cunningham Communications are the sole distributor for Elvox products in Australia.



A versatile range of equipment.

- ① Audio kit-with external and indoor two way communications.
- ② Video intercom-wall mounted system recessed or flush.
- ③ Video-intercom desk type system.
- ④ Unlimited multi apartment central intercoms.
- ⑤ Close circuit television systems for individual applications.

Contact us now for further information and a free catalogue.



Cunningham Communications, Pty. Ltd.
100 Gladstone Street,
South Melbourne. 3205
Telephone (03) 690 9988
Telex 10718970